



E4 Educator v2.0

Tier 3 · Project 5 of 5

P05

Touch UI Controller

Walark Electronics · Fundrum Engineering · May 2026

★ The Final Project ★

P05 is the capstone of the entire E4 Educator curriculum. It brings every UI skill together: multi-screen touch navigation, animated transitions, modal dialogs, a number-entry keypad, MQTT-driven remote control, OTA updates, and a complete web management interface. A learner who builds this has the skills to create any embedded touch application.

Project overview

The Touch UI Controller is a general-purpose networked control panel. It hosts a five-screen touch interface: Dashboard (live sensor readings), Controls (MQTT output buttons and sliders), Settings (NVS settings editor), Network (WiFi/MQTT status and configuration), and About (firmware info and OTA trigger). It receives MQTT messages from other E4 devices and Node-RED, and publishes button events and slider values. It is intentionally a platform — the control functions are customisable via LittleFS config files.

New UI concepts:

Page manager with animated slide transitions · Tab bar navigation · Modal dialog overlay · On-screen numeric keypad · Toggle buttons with state · Slider control · Scrollable list widget · MQTT-driven display updates · JSON-configurable control layout

1 Project specification

1.1 Feature specification

ID	Feature	Detail
F01	Five-screen UI	Dashboard · Controls · Settings · Network · About. Tab bar at top for instant navigation.
F02	Touch tab bar	Five tab buttons across the full 240px header. Active tab highlighted. Tap to switch instantly.
F03	Animated transitions	Slide-left or slide-right animation when changing screens. 100ms, sprite-based, no flicker.
F04	Dashboard screen	Subscribes to e4/sensor/# MQTT topics. Displays up to 4 sensor tiles. Live update on message.
F05	Controls screen	Up to 6 configurable controls: toggle buttons, momentary buttons, sliders. Publish to MQTT on interact.
F06	Settings screen	Scrollable settings list. Tap to edit. On-screen numeric keypad for value entry. Saves to NVS.
F07	Network screen	WiFi SSID/IP/signal, MQTT broker/status, uptime, boot count. Reconnect button.
F08	About screen	FW version, build date, board name, uptime. OTA update button — opens /update in browser via QR hint.
F09	Modal dialog	Confirmation overlay for destructive actions (factory reset, delete log). YES/NO touch buttons.
F10	On-screen keypad	10-key numeric entry dialog triggered from Settings screen. Displays current and new value.
F11	MQTT subscribe	Subscribes to e4/sensor/# and e4/node/+/# for dashboard. Subscribes to e4/cmd/# for control feedback.
F12	JSON control config	data/controls.json defines button labels, topics, and types. Edit file and reflash filesystem to reconfigure.
F13	NVS settings	All user preferences persisted. Factory reset via modal confirmation, not accidental button press.
F14	OTA updates	ElegantOTA via /update. About screen shows IP and URL. Confirms update via MQTT e4/firmware.

1.2 Screen inventory

Screen	Tab label	Primary content
SCREEN_DASH	DASH	4 MQTT sensor tiles. Subscribes to e4/sensor/temperature, humidity, light, probe. Auto-updates.
SCREEN_CTRL	CTRL	6 configurable controls from controls.json. Toggle buttons with visual state. Slider for value.
SCREEN_SETT	SETT	Scrollable settings list. Brightness, temp/humid alerts, log interval. Numeric keypad entry.
SCREEN_NET	NET	WiFi SSID, signal strength, IP address. MQTT broker, port, connection status. Reconnect button.
SCREEN_ABOUT	INFO	FW version, build date, uptime, boot count. OTA URL. Factory reset (modal confirm).

2 UI architecture

2.1 Page manager

The page manager owns screen transitions. When the active screen changes, it runs an animated slide before making the new screen active. All screens implement the same interface: `draw()`, `update()`, `handleTouch()`.

```
// PageManager.h — E4 P05 Touch UI Controller
#pragma once
#include <Arduino.h>
#include <TFT_eSPI.h>

extern TFT_eSPI tft;
extern TFT_eSprite spr;

#define SCREEN_W 240
#define SCREEN_H 280 // Content area below tab bar
#define TAB_H 40
#define ANIM_MS 100 // Transition duration
#define ANIM_STEPS 8 // Frames in animation

// All screens implement this interface
class Screen {
public:
    virtual void draw() = 0; // Full redraw
    virtual void update() = 0; // Partial update (called every loop)
    virtual void handleTouch(uint16_t tx, uint16_t ty) = 0;
    virtual const char* tabLabel() = 0;
    virtual ~Screen() {}
};

class PageManager {
public:
    Screen* screens[5];
    int activeIdx = 0;
    int numScreens = 0;

    void addScreen(Screen* s) {
        if (numScreens < 5) screens[numScreens++] = s;
    }

    void navigateTo(int idx) {
        if (idx == activeIdx || idx < 0 || idx >= numScreens) return;
        bool slideLeft = (idx > activeIdx);
        activeIdx = idx;
        animateTransition(slideLeft);
        drawTabBar();
        screens[activeIdx]->draw();
    }

    void drawTabBar() {
        tft.fillRect(0, 0, SCREEN_W, TAB_H, 0x0319);
        int tw = SCREEN_W / numScreens;
```

```

    for (int i = 0; i < numScreens; i++) {
        bool active = (i == activeIdx);
        uint16_t bg = active ? 0xFFFF : 0x0319;
        uint16_t fg = active ? 0x0319 : 0xC618;
        tft.fillRect(i*tw, 0, tw-1, TAB_H, bg);
        tft.setTextColor(fg, bg);
        tft.setTextSize(1);
        int lw = strlen(screens[i]->tabLabel()) * 6;
        tft.setCursor(i*tw + (tw-lw)/2, 15);
        tft.print(screens[i]->tabLabel());
    }
}

void handleTouch(uint16_t tx, uint16_t ty, bool touched) {
    if (!touched) return;
    if (ty < TAB_H) {
        // Tab bar tap
        int tw = SCREEN_W / numScreens;
        int idx = tx / tw;
        navigateTo(idx);
    } else {
        // Pass to active screen (offset Y by tab bar)
        screens[activeIdx]->handleTouch(tx, ty - TAB_H);
    }
}

void update() {
    screens[activeIdx]->update();
}

private:
void animateTransition(bool slideLeft) {
    // Capture current content into a snapshot
    // Slide it off-screen while new screen slides in
    // Uses two sprites: outgoing and incoming
    // Simplified version — just clear content area
    tft.fillRect(0, TAB_H, SCREEN_W, SCREEN_H, 0x0000);
    delay(ANIM_MS / 2); // Brief black flash = minimal animation
    // Full sprite-based slide: see Section 2.2
}

};

PageManager pageMgr;

```

★ Key point

The Screen interface enforces a consistent structure across all five screens. `draw()` does a full redraw from scratch (called on navigation). `update()` handles incremental updates each loop pass — for example, updating a sensor value without redrawing the entire screen. `handleTouch()` receives coordinates relative to the content area (tab bar Y already subtracted).

2.2 Sprite-based slide transition

A full sprite-based slide animation captures both screens as sprites and scrolls them horizontally in `ANIM_STEPS` frames:

```
// Full slide animation (replace animateTransition stub above)
void animateTransition(bool slideLeft) {
    // Create two sprites: outgoing and incoming
    TFT_eSprite outSprite = TFT_eSprite(&tft);
    TFT_eSprite inSprite = TFT_eSprite(&tft);
    outSprite.setColorDepth(16); outSprite.createSprite(SCREEN_W, SCREEN_H);
    inSprite.setColorDepth(16); inSprite.createSprite(SCREEN_W, SCREEN_H);

    // Render outgoing (current) screen into outSprite
    // Render incoming (new) screen into inSprite
    // (Simplified: both just fill for demo -
    // production: redirect screen draw calls to sprite)
    outSprite.fillRect(0x0319);
    inSprite.fillRect(0x0000);
    screens[activeIdx]->draw(); // Already drawn to TFT

    int stepPx = SCREEN_W / ANIM_STEPS;
    for (int step = 1; step <= ANIM_STEPS; step++) {
        int offset = step * stepPx;
        int outX = slideLeft ? -offset : offset;
        int inX = slideLeft ? SCREEN_W - offset : -SCREEN_W + offset;
        outSprite.pushSprite(outX, TAB_H);
        inSprite.pushSprite(inX, TAB_H);
        delay(ANIM_MS / ANIM_STEPS);
    }
    outSprite.deleteSprite();
    inSprite.deleteSprite();
}
```

3 Dashboard screen — MQTT sensor tiles

The Dashboard screen shows up to four sensor tiles, each subscribed to an MQTT topic. When the master MQTT broker receives a new value on the topic, the corresponding tile updates immediately without redrawing the whole screen.

```
// DashScreen.h
#pragma once
#include "PageManager.h"

struct SensorTile {
    const char* label;
    const char* topic;
    const char* unit;
    char        value[16];
    uint16_t    colour;
    bool        updated;
};

class DashScreen : public Screen {
public:
    SensorTile tiles[4] = {
        { "AIR TEMP",  "e4/sensor/temperature", "\u00B0C", "--", 0x07E0, false },
        { "HUMIDITY",  "e4/sensor/humidity",    "%",    "--", 0x2E97, false },
        { "LIGHT",     "e4/sensor/light",       "%",    "--", 0xFD20, false },
        { "PROBE",     "e4/sensor/probe",       "\u00B0C", "--", 0x79CF, false },
    };

    const char* tabLabel() override { return "DASH"; }

    void onMqttMessage(const char* topic, const char* value) {
        for (int i = 0; i < 4; i++) {
            if (strcmp(topic, tiles[i].topic) == 0) {
                strncpy(tiles[i].value, value, 15);
                tiles[i].updated = true;
            }
        }
    }

    void draw() override {
        tft.fillRect(0, TAB_H, SCREEN_W, SCREEN_H, 0x0000);
        for (int i = 0; i < 4; i++) drawTile(i, true);
    }

    void update() override {
        for (int i = 0; i < 4; i++) {
            if (tiles[i].updated) {
                tiles[i].updated = false;
                drawTile(i, false); // Partial update
            }
        }
    }

    void handleTouch(uint16_t tx, uint16_t ty) override {}
}
```

```
// Dashboard is read-only – no touch actions

private:
// 2x2 tile grid
int tileX(int i) { return (i % 2) * 120 + 4; }
int tileY(int i) { return (i / 2) * 130 + TAB_H + 4; }

void drawTile(int idx, bool fullDraw) {
    SensorTile& t = tiles[idx];
    int x = tileX(idx); int y = tileY(idx);
    int w = 112; int h = 122;

    if (fullDraw) {
        tft.fillRoundRect(x, y, w, h, 8, 0x162040);
        tft.drawRoundRect(x, y, w, h, 8, 0x30363D);
        tft.setTextColor(0x8B94AA, 0x162040);
        tft.setTextSize(1);
        tft.setCursor(x+8, y+8);
        tft.print(t.label);
    }

    // Value area – always update
    tft.fillRect(x+4, y+24, w-8, 60, 0x162040);
    tft.setTextColor(t.colour, 0x162040);
    tft.setTextSize(3);
    tft.setCursor(x+8, y+30);
    tft.print(t.value);
    tft.setTextSize(2);
    tft.setCursor(x+8, y+65);
    tft.setTextColor(0x8B94AA, 0x162040);
    tft.print(t.unit);
}

};

DashScreen dashScreen;
```


4 Controls screen — JSON-configurable buttons and sliders

The Controls screen reads its layout from data/controls.json on LittleFS. This allows the control panel to be reconfigured without reflashing firmware — only the filesystem image needs updating.

4.1 data/controls.json format

```
{
  "controls": [
    {
      "type": "toggle",
      "label": "LED RED",
      "topic": "e4/cmd/led/red",
      "onValue": "1",
      "offValue": "0",
      "colour": "0xF800"
    },
    {
      "type": "toggle",
      "label": "LED GREEN",
      "topic": "e4/cmd/led/green",
      "onValue": "1",
      "offValue": "0",
      "colour": "0x07E0"
    },
    {
      "type": "momentary",
      "label": "ALERT",
      "topic": "e4/cmd/alert",
      "value": "on",
      "colour": "0xFD20"
    },
    {
      "type": "momentary",
      "label": "SILENCE",
      "topic": "e4/cmd/alert",
      "value": "off",
      "colour": "0xC618"
    },
    {
      "type": "slider",
      "label": "BRIGHTNESS",
      "topic": "e4/cmd/brightness",
      "minVal": 0,
      "maxVal": 255,
      "colour": "0x2E97"
    },
    {
      "type": "slider",
      "label": "VOLUME",
      "topic": "e4/cmd/volume",
      "minVal": 0,
      "maxVal": 100,
      "colour": "0xFD20"
    }
  ]
}
```

```

    }
  ]
}

```

4.2 ControlScreen implementation

```

// CtrlScreen.h (abbreviated)
#pragma once
#include "PageManager.h"
#include <ArduinoJson.h>
#include <LittleFS.h>

enum CtrlType { CTRL_TOGGLE, CTRL_MOMENTARY, CTRL_SLIDER };

struct Control {
  CtrlType type;
  char    label[16];
  char    topic[48];
  char    onVal[8];
  char    offVal[8];
  uint16_t colour;
  int     minVal, maxVal;
  bool    state;      // Toggle on/off
  int     sliderVal;  // Slider position
};

#define MAX_CONTROLS 6

class CtrlScreen : public Screen {
public:
  Control controls[MAX_CONTROLS];
  int     numControls = 0;

  const char* tabLabel() override { return "CTRL"; }

  bool loadFromJSON() {
    File f = LittleFS.open("/controls.json", "r");
    if (!f) { Serial.println("controls.json not found."); return false; }
    StaticJsonDocument<1024> doc;
    if (deserializeJson(doc, f) != DeserializationError::Ok) {
      f.close(); return false;
    }
    f.close();

    JsonArray arr = doc["controls"];
    numControls = 0;
    for (JsonObject obj : arr) {
      if (numControls >= MAX_CONTROLS) break;
      Control& c = controls[numControls];
      String type = obj["type"] | "toggle";
      c.type = (type == "slider") ? CTRL_SLIDER :
               (type == "momentary") ? CTRL_MOMENTARY : CTRL_TOGGLE;
      strncpy(c.label, obj["label"] | "BTN", 15);
    }
  }
};

```

```

        strncpy(c.topic, obj["topic"] | "e4/cmd", 47);
        strncpy(c.onVal, obj["onValue"] | "1", 7);
        strncpy(c.offVal, obj["offValue"] | "0", 7);
        c.colour = (uint16_t) strtoul(obj["colour"] | "0xFFFF", nullptr, 16);
        c.minVal = obj["minVal"] | 0;
        c.maxVal = obj["maxVal"] | 100;
        c.state = false;
        c.sliderVal = c.minVal;
        numControls++;
    }
    Serial.printf("Loaded %d controls.\n", numControls);
    return true;
}

void draw() override {
    tft.fillRect(0, TAB_H, SCREEN_W, SCREEN_H, 0x0000);
    for (int i = 0; i < numControls; i++) drawControl(i);
}

void handleTouch(uint16_t tx, uint16_t ty) override;
// defined below

void update() override {}

private:
    // 2x3 grid: 2 columns, 3 rows, 80px tall each
    int ctrlX(int i) { return (i % 2) * 120 + 4; }
    int ctrlY(int i) { return TAB_H + (i / 2) * 88 + 4; }

    void drawControl(int idx) {
        Control& c = controls[idx];
        int x = ctrlX(idx); int y = ctrlY(idx);
        int w = 112; int h = 80;

        if (c.type == CTRL_SLIDER) {
            // Slider: label + horizontal track + thumb
            tft.fillRoundRect(x, y, w, h, 6, 0x162040);
            tft.setTextColor(0xC618, 0x162040);
            tft.setTextSize(1); tft.setCursor(x+4, y+4);
            tft.print(c.label);
            tft.setTextSize(1); tft.setCursor(x+4, y+16);
            tft.printf("%d", c.sliderVal);
            // Track
            int trackX = x+8; int trackY = y+40;
            int trackW = w-16;
            tft.drawRect(trackX, trackY, trackW, 10, 0x30363D);
            int thumbX = trackX + map(c.sliderVal,
                                    c.minVal, c.maxVal, 0, trackW-8);
            tft.fillRect(thumbX, trackY, 8, 10, c.colour);
        } else {
            // Button: filled when state ON
            bool on = (c.type == CTRL_TOGGLE) && c.state;
            uint16_t bg = on ? c.colour : 0x162040;
            uint16_t fg = on ? 0x000000 : c.colour;

```

```

        tft.fillRoundRect(x, y, w, h, 8, bg);
        tft.drawRoundRect(x, y, w, h, 8, c.colour);
        tft.setTextColor(fg, bg);
        tft.setTextSize(2);
        int lw = strlen(c.label) * 12;
        tft.setCursor(x + (w-lw)/2, y + (h-16)/2);
        tft.print(c.label);
    }
}
};

void CtrlScreen::handleTouch(uint16_t tx, uint16_t ty) {
    for (int i = 0; i < numControls; i++) {
        Control& c = controls[i];
        int x = ctrlX(i) - 4; int y = ctrlY(i) - TAB_H;
        if (tx < x || tx > x+120 || ty < y || ty > y+88) continue;

        if (c.type == CTRL_TOGGLE) {
            c.state = !c.state;
            mqtt.publish(c.topic, c.state ? c.onVal : c.offVal, false);
            drawControl(i);
        } else if (c.type == CTRL_MOMENTARY) {
            mqtt.publish(c.topic, c.onVal, false);
            // Flash feedback
            c.state = true; drawControl(i);
            delay(120);
            c.state = false; drawControl(i);
        } else if (c.type == CTRL_SLIDER) {
            // Map touch X to slider value
            int trackX = ctrlX(i) + 8;
            int trackW = 112 - 16;
            int newVal = map(constrain(tx - trackX, 0, trackW),
                           0, trackW, c.minVal, c.maxVal);
            c.sliderVal = newVal;
            char buf[8]; sprintf(buf, "%d", newVal);
            mqtt.publish(c.topic, buf, false);
            drawControl(i);
        }
    }
}

CtrlScreen ctrlScreen;

```

5 On-screen numeric keypad

The numeric keypad is a modal overlay drawn on top of the current screen. It is triggered from the Settings screen when a value tile is tapped, and returns the entered value to a callback function.

```
// NumericKeypad.h — modal numeric entry overlay
#pragma once
#include <Arduino.h>
#include <TFT_eSPI.h>

extern TFT_eSPI tft;

class NumericKeypad {
public:
    typedef void (*Callback)(int value);

    bool    active    = false;
    int     current   = 0;    // Existing value (shown as hint)
    int     entered   = 0;    // Value being entered
    int     digits    = 0;
    Callback callback = nullptr;

    void show(int existingVal, Callback cb) {
        current = existingVal;
        entered = 0; digits = 0;
        callback = cb;
        active = true;
        drawKeypad();
    }

    void handleTouch(uint16_t tx, uint16_t ty) {
        if (!active) return;
        // Overlay starts at Y=60, keys in 4x3 grid
        if (ty < 60 || ty > 310) return;
        int row = (ty - 100) / 52;
        int col = tx / 80;
        if (row < 0 || row > 3 || col < 0 || col > 2) return;

        int keys[4][3] = {{1,2,3},{4,5,6},{7,8,9},{-1,0,-2}};
        // -1 = CLR, -2 = OK
        int key = keys[row][col];

        if (key == -1) { // CLR
            entered = 0; digits = 0;
        } else if (key == -2) { // OK
            if (callback) callback(entered);
            active = false;
            tft.fillRect(0, ZONE_CONTENT_Y, SCR_W, ZONE_CONTENT_H, 0x0000);
            return;
        } else if (digits < 5) {
            entered = entered * 10 + key;
            digits++;
        }
        drawKeypad();
    }
};
```

```

    }

private:
    void drawKeypad() {
        // Semi-transparent overlay background
        tft.fillRect(10, 60, 220, 260, 10, 0x162040);
        tft.drawRoundRect(10, 60, 220, 260, 10, 0x2E86AB);

        // Title and current value
        tft.setTextColor(0xC618, 0x162040);
        tft.setTextSize(1); tft.setCursor(20, 72);
        tft.printf("Current: %d", current);

        // New value display
        tft.setTextColor(0xFFFF, 0x162040);
        tft.setTextSize(3); tft.setCursor(20, 90);
        tft.printf("> %d", entered);

        // Key grid
        const char* labels[] = {"1","2","3","4","5","6","7","8","9","CLR","0","OK"};
        uint16_t btnCols[] = {
            0x18C3,0x18C3,0x18C3,0x18C3,0x18C3,0x18C3,
            0x18C3,0x18C3,0x18C3,0xF800,0x18C3,0x07E0
        };
        for (int i = 0; i < 12; i++) {
            int x = 14 + (i % 3) * 74;
            int y = 130 + (i / 3) * 48;
            tft.fillRect(x, y, 64, 40, 6, btnCols[i]);
            tft.setTextColor(0xFFFF, btnCols[i]);
            tft.setTextSize(2);
            int lw = strlen(labels[i]) * 12;
            tft.setCursor(x + (64-lw)/2, y+12);
            tft.print(labels[i]);
        }
    }
};

NumericKeypad numKeypad;

```

6 Settings, Network, and About screens

6.1 Settings screen

The Settings screen shows a scrollable list of NVS settings. Tapping a row opens the numeric keypad. On confirmation, the new value is saved to NVS and applied immediately.

```
// SettScreen.h (abbreviated)
#pragma once
#include "PageManager.h"
#include "NumericKeypad.h"
#include "Settings.h"

extern SettingsManager settings;
extern NumericKeypad numKeypad;

class SettScreen : public Screen {
public:
    const char* tabLabel() override { return "SETT"; }

    struct SettItem { const char* label; const char* unit; int value; };

    SettItem items[5] = {
        { "Brightness",    "/255", 200 },
        { "Temp alert",    "\u00B0C", 28 },
        { "Humid alert",   "%",    70 },
        { "Log interval",  "s",     5 },
        { "Gain",          "x",     1 },
    };

    void draw() override {
        tft.fillRect(0, TAB_H, SCREEN_W, SCREEN_H, 0x0000);
        loadValues();
        for (int i = 0; i < 5; i++) drawItem(i, false);
    }

    void handleTouch(uint16_t tx, uint16_t ty) override {
        int idx = ty / 52;
        if (idx < 0 || idx >= 5) return;
        int existing = items[idx].value;
        numKeypad.show(existing, [](int newVal) {
            // Apply: update settings + save
            // (Full implementation uses captured idx)
            settings.save();
        });
    }

    void update() override {
        if (numKeypad.active)
            numKeypad.handleTouch(0, 0); // handled in main loop
    }

private:
```

```

void loadValues() {
    items[0].value = settings.s.brightness;
    items[1].value = (int)settings.s.tempAlert;
    items[2].value = (int)settings.s.humidAlert;
    items[3].value = (int)(settings.s.logInterval / 1000);
}

void drawItem(int idx, bool highlight) {
    int y = TAB_H + idx * 52;
    uint16_t bg = highlight ? 0x0A29 : 0x0D1117;
    tft.fillRect(0, y, SCREEN_W, 50, bg);
    tft.drawFastHLine(0, y+50, SCREEN_W, 0x30363D);
    tft.setTextColor(0xC618, bg);
    tft.setTextSize(1); tft.setCursor(8, y+8);
    tft.print(items[idx].label);
    tft.setTextColor(0xFFFF, bg);
    tft.setTextSize(2); tft.setCursor(8, y+24);
    tft.printf("%d %s", items[idx].value, items[idx].unit);
}
};

```

6.2 Network screen

```

// NetScreen.h (abbreviated)
class NetScreen : public Screen {
public:
    const char* tabLabel() override { return "NET"; }

    void draw() override {
        tft.fillRect(0, TAB_H, SCREEN_W, SCREEN_H, 0x0000);
        refresh();
    }

    void update() override {
        static unsigned long lastRefresh = 0;
        if (millis() - lastRefresh > 2000) {
            lastRefresh = millis(); refresh();
        }
    }

    void handleTouch(uint16_t tx, uint16_t ty) override {
        // RECONNECT button at Y 220
        if (ty > 200 && ty < 250) {
            WiFi.reconnect();
            Serial.println("Manual reconnect triggered.");
        }
    }

private:
    void refresh() {
        int y = TAB_H + 8;
        tft.setTextSize(1);
    }
};

```



```

    auto row = [&](const char* lbl, const String& val, uint16_t col) {
        tft.setTextColor(0x8B94AA, 0x0000);
        tft.setCursor(8, y); tft.print(lbl);
        tft.setTextColor(col, 0x0000);
        tft.setCursor(100, y); tft.print(val);
        y += 20;
    };

    bool wok = WiFi.status() == WL_CONNECTED;
    bool mok = mqtt.connected();
    row("WiFi SSID:", WiFi.SSID(), wok ? 0x07E0 : 0xF800);
    row("IP:", wok ? WiFi.localIP().toString() : "---",
        0xFFFF);
    row("Signal:", wok ? String(WiFi.RSSI())+" dBm" : "---",
        0x79CF);

    y += 8;
    row("MQTT broker:", mqttBroker, mok ? 0x07E0 : 0xFFE0);
    row("MQTT status:", mok ? "Connected" : "Disconnected",
        mok ? 0x07E0 : 0xF800);

    y += 8;
    row("Uptime:", String(millis()/1000) + "s", 0xC618);
    row("Boot #:",
        String(settings.s.bootCount), 0xC618);

    // Reconnect button
    tft.fillRect(8, y+20, 100, 36, 6, 0x0319);
    tft.drawRoundRect(8, y+20, 100, 36, 6, 0x2E86AB);
    tft.setTextColor(0xFFFF, 0x0319);
    tft.setTextSize(1); tft.setCursor(22, y+31);
    tft.print("RECONNECT");
}
};

```

6.3 About screen with modal factory reset

```

// AboutScreen.h (abbreviated)
class AboutScreen : public Screen {
public:
    const char* tabLabel() override { return "INFO"; }
    bool showResetModal = false;

    void draw() override {
        tft.fillRect(0, TAB_H, SCREEN_W, SCREEN_H, 0x0000);
        int y = TAB_H + 12;
        tft.setTextColor(0xC618, 0x0000); tft.setTextSize(1);

        auto line = [&](const char* l, const String& v) {
            tft.setCursor(8, y); tft.print(l);
            tft.setTextColor(0xFFFF, 0x0000);
            tft.setCursor(110, y); tft.print(v); y += 22;
            tft.setTextColor(0xC618, 0x0000);
        };
    }
};

```

```

    line("Firmware:", FW_VERSION);
    line("Build date:", FW_DATE);
    line("Board:", "E4 Educator v2.0");
    line("Uptime:", String(millis()/1000) + "s");

    tft.setTextColor(0x2E97, 0x0000);
    tft.setCursor(8, y); y += 22;
    if (WiFi.status() == WL_CONNECTED)
        tft.printf("OTA: http://%s/update",
                   WiFi.localIP().toString().c_str());
    else
        tft.print("OTA: connect WiFi first");

    // Factory reset button
    tft.fillRect(8, y+10, 140, 36, 6, 0x300A0A);
    tft.drawRoundRect(8, y+10, 140, 36, 6, 0xF800);
    tft.setTextColor(0xF800, 0x300A0A);
    tft.setTextSize(1); tft.setCursor(22, y+21);
    tft.print("FACTORY RESET");
}

void handleTouch(uint16_t tx, uint16_t ty) override {
    if (showResetModal) {
        // YES button
        if (tx > 20 && tx < 100 && ty > 180 && ty < 220) {
            settings.reset(); ESP.restart();
        }
        // NO button
        if (tx > 140 && tx < 220 && ty > 180 && ty < 220) {
            showResetModal = false;
            draw();
        }
        return;
    }
    // Factory reset button area (approx)
    if (ty > 180 && ty < 220 && tx < 150) {
        showResetModal = true;
        drawModal();
    }
}

void update() override {}

private:
void drawModal() {
    tft.fillRect(20, TAB_H+60, 200, 160, 10, 0x162040);
    tft.drawRoundRect(20, TAB_H+60, 200, 160, 10, 0xF800);
    tft.setTextColor(0xFFFF, 0x162040);
    tft.setTextSize(2); tft.setCursor(35, TAB_H+80);
    tft.print("Factory reset?");
    tft.setTextSize(1); tft.setCursor(30, TAB_H+110);
    tft.print("All settings will be");
    tft.setCursor(30, TAB_H+125);
    tft.print("cleared. Reboot follows.");
}

```

```
// YES
tft.fillRoundRect(30, TAB_H+150, 70, 36, 6, 0xF800);
tft.setTextColor(0xFFFF, 0xF800);
tft.setTextSize(2); tft.setCursor(44, TAB_H+161);
tft.print("YES");
// NO
tft.fillRoundRect(140, TAB_H+150, 70, 36, 6, 0x18C3);
tft.setTextColor(0xFFFF, 0x18C3);
tft.setCursor(158, TAB_H+161);
tft.print("NO");
}
};
```

7 main.cpp — wiring it all together

```
#include <Arduino.h>
#include <esp_ota_ops.h>
#include "PageManager.h"
#include "DashScreen.h"
#include "CtrlScreen.h"
#include "SettScreen.h"
#include "NetScreen.h"
#include "AboutScreen.h"
#include "NumericKeypad.h"
#include "Network.h"
#include "Settings.h"
#include "Button.h"

TFT_eSPI    tft;
TFT_eSprite spr = TFT_eSprite(&tft);
Button      nextBtn(BTN_NEXT);
Button      entBtn(BTN_ENT);
SettingsManager settings;

DashScreen  dashScreen;
CtrlScreen  ctrlScreen;
SettScreen  settScreen;
NetScreen   netScreen;
AboutScreen aboutScreen;

bool otaValid    = false;
bool webStarted  = false;

// MQTT message handler — route to dashboard
void mqttCallback(char* topic, byte* payload, unsigned int len) {
    char val[32]; val[min((int)len, 31)] = 0;
    memcpy(val, payload, min((int)len, 31));
    dashScreen.onMqttMessage(topic, val);
    // Also handle e4/cmd/brightness etc. for self-control
}

void setup() {
    Serial.begin(115200);
    Serial.printf("P05 Touch UI  FW:%s\n", FW_VERSION);

    settings.load();

    // LEDs
    pinMode(LED_GREEN, OUTPUT); digitalWrite(LED_GREEN, LOW);
    pinMode(LED_RED,   OUTPUT); digitalWrite(LED_RED,   LOW);
    pinMode(LED_BLUE,  OUTPUT); digitalWrite(LED_BLUE,  LOW);

    // TFT
    pinMode(TFT_BL, OUTPUT); digitalWrite(TFT_BL, LOW);
    tft.init(); tft.setRotation(3); tft.fillScreen(0x0000); // Landscape 320x240
    ledcSetup(0, 5000, 8); ledcAttachPin(TFT_BL, 0);
```

```
    ledcWrite(0, settings.s.brightness);

    spr.setColorDepth(16); spr.createSprite(320, 165);

    nextBtn.begin(); entBtn.begin();

    // Touch calibration
    Preferences p; p.begin("touch", true);
    uint16_t cal[5];
    if (p.getBytesLength("cal") == sizeof(cal)) {
        p.getBytes("cal", cal, sizeof(cal)); tft.setTouch(cal);
    }
    p.end();

    // Load control config from LittleFS
    if (LittleFS.begin(true)) {
        ctrlScreen.loadFromJSON();
    }

    // Register screens
    pageMgr.addScreen(&dashScreen);
    pageMgr.addScreen(&ctrlScreen);
    pageMgr.addScreen(&settScreen);
    pageMgr.addScreen(&netScreen);
    pageMgr.addScreen(&aboutScreen);

    // Network
    initNetwork();
    mqtt.setCallback(mqttCallback);

    // Draw initial UI
    pageMgr.drawTabBar();
    pageMgr.screens[0]->draw();

    digitalWrite(LED_GREEN, HIGH);
    Serial.println("P05 Touch UI ready.");
}

void loop() {
    unsigned long now = millis();

    wifiUpdate(now); mqttUpdate(now); ElegantOTA.loop();

    if (wifiReady() && !webStarted) {
        setupWebServer();
        mqtt.subscribe("e4/sensor/#");
        mqtt.subscribe("e4/node/+/temperature");
        webStarted = true;
    }

    Button::Event nextEv = nextBtn.read();
    Button::Event entEv = entBtn.read();
}
```

```
// NEXT cycles screens
if (nextEv == Button::SHORT_PRESS)
    pageMgr.navigateTo((pageMgr.activeIdx + 1) % pageMgr.numScreens);

// Touch handling
uint16_t tx, ty;
bool touched = tft.getTouch(&tx, &ty);
if (touched) {
    if (numKeypad.active) {
        numKeypad.handleTouch(tx, ty);
    } else {
        static unsigned long lastTap = 0;
        if (now - lastTap > 300) {
            lastTap = now;
            pageMgr.handleTouch(tx, ty, touched);
        }
    }
}

pageMgr.update();

if (!otaValid && now > 10000) {
    esp_ota_mark_app_valid_cancel_rollback();
    otaValid = true;
}
}
```

8 Commissioning checklist

☐	Step
☐	Upload firmware (Ctrl+Alt+U). Upload filesystem (Upload Filesystem Image).
☐	On boot: confirm tab bar visible with DASH · CTRL · SETT · NET · INFO tabs.
☐	Tap DASH: confirm four sensor tiles visible, all showing "--" (no data yet).
☐	Tap CTRL: confirm six control buttons/sliders loaded from controls.json.
☐	Tap SETT: confirm five settings rows with labels and current values.
☐	Tap NET: confirm WiFi SSID, IP address visible after WiFi connects.
☐	Tap INFO: confirm FW_VERSION, build date, and OTA URL visible.
☐	Tap a setting row in SETT. Confirm numeric keypad overlay appears.
☐	Enter a new value on keypad. Tap OK. Confirm value updates in list.
☐	Power cycle. Confirm changed value persists in SETT screen.
☐	Tap a toggle button in CTRL. Confirm button highlights. Check MQTT Explorer for published message.
☐	Tap ALERT momentary button. Confirm brief highlight and MQTT publish.
☐	Drag slider in CTRL. Confirm value updates and MQTT publishes on drag.
☐	With P01 or P02 running on another E4: confirm DASH screen updates sensor tiles via MQTT.
☐	Tap INFO → FACTORY RESET. Confirm modal dialog appears with YES/NO.
☐	Tap NO. Confirm dialog dismisses and settings intact.
☐	Test animated transition: tap between tabs. Confirm brief slide animation.
☐	Test OTA: build new firmware, navigate to OTA URL on About screen, upload.

9 The E4 Educator curriculum — complete

Completing P05 marks the end of the E4 Educator v2.0 curriculum. The table below is a consolidated record of everything covered across all 16 tutorials and 5 projects.

T/P	Topic	Skills gained
T01	PlatformIO & the E4	Toolchain, build_flags, millis() timing, Serial debug
T02	GPIO & build_flags	All GPIO modes, ADC1 rule, LEDC PWM, boot-sensitive pins
T03	Buttons & debounce	Contact bounce, Button.h, short/long press state machine
T04	I2C fundamentals	Bus protocol, scanner, AHT20, multi-device, Wire.begin()
T05	OLED display	SSD1306, buffer model, zone layout, multi-page navigation
T06	One-wire & analog	DS18B20, non-blocking state machine, LDR, averaging
T07	Audio output	TonePlayer.h, DAC waveforms, PWM transistor, Tier 1 capstone
T08	TFT & sprites	ILI9341, RGB565, sprite pipeline, zone layout, colour palette

T09	Touch input	XPT2046, calibration, TouchZone.h, SPI coexistence
T10	SD card & file I/O	TFT-first rule, FAT32, CSV logging, BMP splash, config files
T11	NVS persistence	Preferences, 15-char key rule, Settings.h, factory reset
T12	WiFi & MQTT	Non-blocking state machine, PubSubClient, LWT, Node-RED
T13	LittleFS	Partition, web server, smooth fonts, ArduinoJson
T14	OTA updates	ElegantOTA, progress bar, versioning, rollback
T15	ESP-NOW	MAC addresses, SensorPacket.h, star network, MQTT bridge
T16	I2S & MEMS mic	ICS43434, I2S config, FFT, BANDSCOPE, event detection
P01	Environmental Monitor	All Tier 1+2 skills integrated. Multi-module architecture. AHT20 + DS18B20 + LDR.
P02	Data Logger	DS3231 RTC + NTP, BMP280 pressure trend, daily log rotation, Chart.js web graph, CSV download
P03	Wireless Sensor Network	ESP-NOW star network, deep sleep nodes, battery monitor, 4-card TFT, per-node SD logging
P04	BANDSCOPE	Dual-core FreeRTOS, four display modes, octave bands, event detection engine, MQTT telemetry
P05	Touch UI Controller	Page manager, animated transitions, JSON-configurable controls, numeric keypad, modal dialogs

★ E4 Educator v2.0 — Curriculum Complete ★

16 tutorials · 5 integrated projects · 5 reusable toolkit files · 1 reference card

A learner who has completed this curriculum can design, build, and deploy professional-grade ESP32 firmware. They understand peripheral hardware, wireless protocols, real-time display systems, data persistence, over-the-air updates, and multi-sensor network architectures.

Walark Electronics · Fundrum Engineering · Christchurch, New Zealand · May 2026

10 Extending the project

- Add a colour theme selector: store a theme index in NVS, reload the colour palette on boot. Create three themes — Dark (default), Light, and High Contrast.
- Add a chart screen: a sixth tab showing a live scrolling line graph of one MQTT topic. Use the same sprite-rendering approach as the spectrum display in P04.
- Add a keyboard screen for SSID/password entry: a full QWERTY touch keyboard for network provisioning via the touch screen, eliminating the need for a serial connection for first-time WiFi setup.
- Add a macro system: define sequences of MQTT publishes as macros in controls.json. A single button tap triggers multiple topic publishes in sequence with optional delays.
- Add a voice-activated mode using the MEMS microphone from T16: clap once to wake the display from dim, clap twice to publish a configurable MQTT event.
- Integrate P03 as a sub-panel: add a fifth tab showing the P03 wireless sensor network node grid, making P05 a unified control panel for an entire E4 installation.

E4 Educator v2.0 · P05: Touch UI Controller · Walark Electronics · Fundrum Engineering · May 2026