

# CRC 8 AUTOSTAR

Paulo Pinho nº71734



universidade  
de aveiro

# CRC-8-ENCODER

		r^0	r^1	r^2	r^3	r^4	r^5	r^6	r^7
0	x^8	1	1	1	1		1		
1	x^9		1	1	1	1		1	
2	x^10			1	1	1	1		1
3	x^11	1	1	1		1		1	
4	x^12		1	1	1		1		1
5	x^13	1	1			1	1	1	
6	x^14		1	1			1	1	1
7	x^15	1	1				1	1	1
8	x^16	1			1		1	1	1
9	x^17	1		1	1	1	1	1	1
10	x^18	1		1		1		1	1
11	x^19	1		1					1
12	x^20	1		1			1		
13	x^21		1		1			1	
14	x^22			1		1			1
15	x^23	1	1	1					
					3_XOR4:1		3_XOR2:1		
					2_XOR4:1		2_XOR2:1		
							2_XOR2:1		
							2_XOR2:1		

$$\text{CRC} = \text{Mod}[(M(x) * x^n) / B(x)]$$

M(x) is the message polynomial, B(x) is the generator polynomial and n is the degree of polynomial B(x)

$$B(x) = x^8 + x^5 + x^3 + x^2 + x + 1$$

In a worst case scenario we would need 64 xors so the color coded groupings were reused to minimize the amount of xors needed.

# CRC-8-Checker

We can confirm the correctness of the message sent by comparing the CRC Checksum of the sent message with the one calculated from the message received. If they don't match there has been an error in the message transmission.

There is a clk, reset, data inputs and an error output, this error will be displayed 1 cycle after the last bit introduced which is  $r(0)$  "the least significant bit of the correct checksum"