


Week 6: Cisco Device Management (10 Marks)

Refiloe Seselinyane

04 September 2026

20260711



48: Backup running-success.

```
Router>ena
Router#conf t
Enter configuration commands, one per line. End with CNTL/Z.
Router(config)#hostname R1
R1(config)#exit
R1#
%SYS-5-CONFIG_I: Configured from console by console

R1#copy running-config tftp:
Address or name of remote host []? 10.10.10.10
Destination filename [R1-config]? R1

Writing running-config....!!
[OK - 701 bytes]

701 bytes copied in 3.004 secs (233 bytes/sec)
R1#
```

2. Find IOS Name:

```
R1#show flash:

System flash directory:
File Length Name/status
  3 33591768 c2900-universalk9-mz.SPA.151-4.M4.bin
  2 28282 sigdef-category.xml
  1 227537 sigdef-default.xml
[33847587 bytes used, 221896413 available, 255744000 total]
249856K bytes of processor board System flash (Read/Write)
```

R1#

[illegible]

```
#####
monitor: command "boot" aborted due to user interrupt
rommon 1 > confreg 0x2142
rommon 2 > reset
System Bootstrap, Version 15.1(4)M4, RELEASE SOFTWARE (fc1)
Technical Support: http://www.cisco.com/techsupport
Copyright (c) 2010 by cisco Systems, Inc.
Total memory size = 512 MB - On-board = 512 MB, DIMM0 = 0 MB
CISCO2911/K9 platform with 524288 Kbytes of main memory
Main memory is configured to 72/-1(On-board/DIMM0) bit mode with ECC disabled

Readonly ROMMON initialized

program load complete, entry point: 0x80803000, size: 0x1b340
program load complete, entry point: 0x80803000, size: 0x1b340

IOS Image Load Test

Digitally Signed Release Software
program load complete, entry point: 0x81000000, size: 0x3bcd3d8
Self decompressing the image :
##### [OK]
Smart Init is enabled
smart init is sizing iomem

                TYPE      MEMORY_REQ
Onboard devices &
    buffer pools      0x022F6000
```

```

!
hostname R1
enable secret 5 $1$mERr$/VT.EosIwbbodaDHZzXq7r1
enable password <cisco>
line vty 0 4
password Cisco
!
interface Vlan1
 no shutdown
 ip address 10.10.10.2 255.255.255.0
!
interface GigabitEthernet0/0
 shutdown
 no ip address
!
interface GigabitEthernet0/1
 shutdown
 no ip address
!
interface GigabitEthernet0/2
 shutdown
 no ip address
!
end

[0] Go to the IOS command prompt without saving this config.
[1] Return back to the setup without saving this config.
[2] Save this configuration to nvram and exit.

Enter your selection [2]: 0
% You can enter the setup, by typing setup at IOS command prompt

```

AFTER REBOOT:

TOTAL: 0x022F6000
Rounded IOMEM up to: 36Mb.
Using 6 percent iomem. [36Mb/512Mb]

Restricted Rights Legend

Use, duplication, or disclosure by the Government is subject to restrictions as set forth in subparagraph (c) of the Commercial Computer Software - Restricted Rights clause at FAR sec. 52.227-19 and subparagraph (c) (1) (ii) of the Rights in Technical Data and Computer Software clause at DFARS sec. 252.227-7013.

cisco Systems, Inc.
170 West Tasman Drive
San Jose, California 95134-1706

Cisco IOS Software, C2900 Software (C2900-UNIVERSALK9-M), Version 15.1(4)M5, RELEASE SOFTWARE (fc2) Technical Support: <http://www.cisco.com/techsupport>
Copyright (c) 1986-2007 by Cisco Systems, Inc.
Compiled Wed 18-Jul-07 04:52 by pt_team
Image text-base: 0x2100F918, data-base: 0x24729040

This product contains cryptographic features and is subject to United States and local country laws governing import, export, transfer and use. Delivery of Cisco cryptographic products does not imply third-party authority to import, export, distribute or use encryption. Importers, exporters, distributors and users are responsible for compliance with U.S. and local country laws. By using this product you agree to comply with applicable laws and regulations. If you are unable to comply with U.S. and local laws, return this product immediately.

A summary of U.S. laws governing Cisco cryptographic products may be found at:
<http://www.cisco.com/wwl/export/crypto/tool/stqrg.html>

If you require further assistance please contact us by sending email to export@cisco.com.

Cisco CISCO2911/K9 (revision 1.0) with 491520K/32768K bytes of memory.
Processor board ID FTX152400KS
3 Gigabit Ethernet interfaces
DRAM configuration is 64 bits wide with parity disabled.
255K bytes of non-volatile configuration memory.
249856K bytes of ATA System CompactFlash 0 (Read/Write)

--- System Configuration Dialog ---

Would you like to enter the initial configuration dialog? [yes/no]:

50:

```
Router(config)#end
Router#
%SYS-5-CONFIG_I: Configured from console by console

Router#erase startup-config
Erasing the nvram filesystem will remove all configuration files! Continue? [confirm]
[OK]
Erase of nvram: complete
%SYS-7-NV_BLOCK_INIT: Initialized the geometry of nvram
Router#reload
System configuration has been modified. Save? [yes/no]:
% Please answer 'yes' or 'no'.
System configuration has been modified. Save? [yes/no]:
```

A summary of U.S. laws governing Cisco cryptographic products may be found at:
<http://www.cisco.com/wwl/export/crypto/tool/stqrg.html>

If you require further assistance please contact us by sending email to
export@cisco.com.

Cisco CISC02911/K9 (revision 1.0) with 491520K/32768K bytes of memory.
Processor board ID FTX152400KS
3 Gigabit Ethernet interfaces
DRAM configuration is 64 bits wide with parity disabled.
255K bytes of non-volatile configuration memory.
249856K bytes of ATA System CompactFlash 0 (Read/Write)

--- System Configuration Dialog ---

Would you like to enter the initial configuration dialog? [yes/no]: |

51: Re-add minimal IP to reach TFTP

```
Router>ena
Router#conf t
Enter configuration commands, one per line. End with CNTL/Z.
Router(config)#interface g0/0
Router(config-if)#ip address 10.10.10.1 255.255.255.0
Router(config-if)#no shutdown

Router(config-if)#
%LINK-5-CHANGED: Interface GigabitEthernet0/0, changed state to up

%LINEPROTO-5-UPDOWN: Line protocol on Interface GigabitEthernet0/0, changed state to up
|
```

2. Restore config:

```
Router#copy tftp: running-config
Address or name of remote host []? 10.10.10.10
Source filename []? R1-backup-config
Destination filename [running-config]?

Accessing tftp://10.10.10.10/R1-backup-config....
%Error opening tftp://10.10.10.10/R1-backup-config (No such file or directory)
Router#
```

3. Save and Verify

```
Router#copy running-config startup-config
Destination filename [startup-config]?
Building configuration...
[OK]
Router#show running-config
Building configuration...

Current configuration : 708 bytes
!
version 15.1
no service timestamps log datetime msec
no service timestamps debug datetime msec
no service password-encryption
!
hostname Router
!
!
!
!
!
!
no ip cef
no ipv6 cef
!
!
--More-- |
```

