

WF-DEMO8 - 2 A synchronous buck converter

FICTIONAL PART - documentation sample for WireFrame EDA. Not a real product.

1 Pin Configuration and Functions

Package: SOIC-8 (top view). Pin 1 is marked by a dot.

PIN	NAME	TYPE	DESCRIPTION
1	VIN	Power	Supply input, 2.7 V to 5.5 V
2	GND	Ground	Ground return
3	EN	Input	Enable, active high; 100 kOhm internal pull-down
4	PG	Output	Power good, open drain; needs a 10 kOhm pull-up
5	FB	Input	Feedback, 0.6 V reference
6	SW	Power	Switch node to the inductor
7	BST	Power	Bootstrap; 100 nF from BST to SW
8	PGND	Ground	Power ground; connect to GND under the part

2 Recommended Operating Conditions

VIN supply voltage 2.7 V to 5.5 V

Output current 0 A to 2 A

Junction temperature -40 C to 125 C

3 Application Information

Place a 10 μ F input capacitor from VIN to PGND within 2 mm of the device.

Place a 100 nF bypass capacitor from VIN to GND within 3 mm of the device.

Connect a 100 nF bootstrap capacitor between BST (pin 7) and SW (pin 6).

PG (pin 4) is open drain: pull it up to the logic rail with 10 k Ω .

4 Mechanical Data - SOIC-8

Body 4.90 x 3.90 mm, pitch 1.27 mm, lead span 6.00 mm, height 1.75 mm max.

Recommended land pattern: 8 pads 1.55 x 0.60 mm, row spacing 5.40 mm.