

DATA ACQUISITION

PHX-DAQ 24

4-channel 24-bit sensor and temperature datalogger

Ethernet-connected logger for strain gauges, load cells, pressure transducers and other bridge-type sensors.



Illustration. Actual product appearance may vary.

KEY FEATURES

- **4 independent 24-bit inputs**, one converter per channel, for bridge-type sensors
- **Programmable gain 1× to 128×**, set per channel
- **4 temperature inputs** for NTC probes, for on-site temperature compensation
- **1 to 100 Hz** selectable output rate per channel
- **Ethernet 10/100** with Modbus TCP and a continuous data stream
- **Automatic discovery** on the network; DHCP or static IP
- **Built-in Wi-Fi access point** for on-site setup
- **Authenticated** configuration and firmware updates
- **Network firmware updates** with automatic rollback
- **Self-reporting health**: uptime and restart counters
- **24 V DC** supply with input protection

COMPATIBLE SENSORS

Strain gauges ($\frac{1}{4}$, $\frac{1}{2}$, full bridge)

Load cells

Pressure transducers

Force & torque sensors

Other mV-level bridge sensors

NTC temperature probes

TYPICAL APPLICATIONS

Bridges & flyovers

Dams & barrages

Buildings & towers


Tunnels & metro

Pile & load testing

Industrial weighing

Complete solution. Every unit is used with **PHX-Sense Studio**, our Windows console for discovery, live plots, calibration and CSV recording.

SYSTEM OVERVIEW



TECHNICAL SPECIFICATIONS

SENSOR INPUTS (BRIDGE-TYPE)

Channels	4, differential, independent
Resolution	24-bit analog-to-digital converter, one per channel
Programmable gain	1, 2, 4, 8, 16, 32, 64, 128 (set per channel)
Full-scale input	$\pm(1 \div \text{gain}) \times \text{excitation voltage}$. Example: $\pm 7.8 \text{ mV/V}$ at 128 $\times$ gain
Sensor excitation	3.3 V DC per channel, ratiometric measurement: excitation drift and cable voltage drop cancel out. 350 Ω bridges recommended
Sensor configurations	Quarter, half and full bridge. Completion resistors are fitted externally, at the sensor
Noise / accuracy	TBC (characterisation in progress)

TEMPERATURE INPUTS

Channels / sensor	4 $\times$ NTC thermistor, 10 k Ω at 25 $^{\circ}\text{C}$, $\beta = 3950$ (waterproof probes recommended)
Update rate	About 1 Hz per channel. A disconnected probe is reported as "no probe", not as a false reading
Range / accuracy	TBC

SAMPLING AND DATA

Output rate	1 to 100 Hz per channel, selectable (default 100 Hz). Each channel can be enabled or disabled
Data delivery	Continuous TCP data stream (one active stream client at a time) and Modbus TCP register access. Samples are sequence-numbered so a receiver can detect missing data

COMMUNICATIONS

Network	10/100 Mbit/s Ethernet, RJ45. Modbus TCP (port 502), TCP data stream (port 5000), automatic network discovery. DHCP or static IP
Wi-Fi	Built-in 2.4 GHz access point (WPA2) for commissioning and as a fallback when Ethernet is unavailable
Firmware update	Over the network from PHX-Sense Studio. The unit returns to the previous firmware automatically if an update does not complete correctly
Configuration security	Settings, restart, factory reset and firmware update require authentication. Measurement data is readable without authentication

POWER, ENVIRONMENTAL AND MECHANICAL

Supply	24 V DC nominal (12 to 28 V DC), screw terminal. Fused, reverse-polarity and surge protected
Power consumption	Typically under 3 W at 24 V with all channels streaming
Operating temperature	0 to +50 $^{\circ}\text{C}$
Enclosure	Aluminium enclosure recommended (see page 3). IP65 when installed in an IP65-rated enclosure with cable glands
Dimensions / weight	Depends on the enclosure supplied. TBC
Status LED	Blue: Ethernet connected. Green: access point active. Three quick blinks then a pause: ready. Single slow blink: data streaming. Slow red: no network

Values are design values for Rev A and may be refined after production testing. TBC: to be confirmed.

CONNECTIONS AND WIRING

SENSOR CONNECTOR (ONE PER CHANNEL)


6-position pluggable screw terminal, 5.08 mm pitch. Four identical connectors, CH1 to CH4.

Pin	Function
1	Excitation + (E+)
2	Excitation – (E–)
3	Signal + (S+)
4	Signal – (S–)
5	Temperature probe, lead 1
6	Temperature probe, lead 2 (no polarity)

OTHER CONNECTORS

Power	2-position pluggable screw terminal, 24 V DC
Network	RJ45, 10/100 Ethernet

BRIDGE SENSOR CONNECTION



WIRING NOTES

- **Full-bridge sensors** (load cells, pressure and force transducers) connect directly to pins 1 to 4.
- **Quarter- and half-bridge strain gauges** need bridge completion resistors. Fit them in a junction box close to the gauge and run the completed bridge to pins 1 to 4. Keeping completion at the sensor removes cable-resistance errors on long runs.
- Use **shielded, twisted-pair cable** and connect the shield at the logger end only.
- **Temperature probes** are two-wire, with no polarity. Waterproof probes are recommended for outdoor locations.
- Sensors must be suitable for a **3.3 V excitation**. Output in mV/V is unchanged, but the absolute signal is smaller than with a 5 V or 10 V supply, and the gain setting compensates for this.
- Do not connect sensor excitation lines to any external supply.

RECOMMENDED ENCLOSURE

Use an aluminium enclosure (IP65 or better) with cable glands. It shields the millivolt-level sensor signals from electrical noise, spreads heat from the power stage and protects the unit on site.

- Mount the board on insulated standoffs. Do not let it touch the metal.
- Connect the enclosure to protective earth according to site practice.
- Bring every cable in through a gland. Ethernet, power and sensor cables included.
- A metal box blocks the built-in Wi-Fi. Commission over Ethernet, or fit an external antenna.

COMMISSIONING STEPS

1. Wire the sensors and probes to the sensor connectors with the power off.
2. Connect the Ethernet cable, then apply 24 V DC. The status LED turns blue when the network link is up.
3. Start PHX-Sense Studio on a PC on the same network. The unit appears automatically in the Devices list.
4. Set the unit name, sample rate, gains and channel calibration, then start recording.
5. Set a site-specific access key under *Network setup* before leaving the unit in service.

PHX-SENSE STUDIO

Windows console supplied with every PHX-DAQ 24 for setup, monitoring and recording. Requires Windows 10 or 11 (64-bit) and a network connection to the logger.

- Automatic discovery of every logger on the network
- Connect to one unit or many, each with its own settings
- Live multi-channel plots and numeric readouts
- Per-channel names, units, calibration and zero (tare)
- Selectable digital filters
- Recording to CSV, one file per module, with session notes and event markers
- Sample rate, gain and channel selection per unit
- Network setup and site access key
- Firmware update with progress and automatic rollback
- Unit health view: uptime and restart history

INTEGRATION WITH YOUR SYSTEMS

PHX-DAQ 24 exposes its measurements over standard **Modbus TCP** so it can be read by SCADA systems, PLCs and custom software. A continuous TCP data stream is available for high-rate acquisition.

- The Modbus register map and stream format are provided in an **integration guide** issued to qualified partners on request.
- Measurement and status data can be read by any Modbus TCP client. Changing settings requires authentication.
- Only one client can hold the data stream at a time. Additional clients can read measurements through Modbus TCP.

NETWORK SECURITY GUIDANCE

- Install the logger on a **trusted, private network or VLAN**. Do not expose it directly to the internet.
- Measurement data is readable by any device on the same network segment. Use network segmentation where data confidentiality matters.
- Set a **site-specific access key** at commissioning and store it securely. Contact Phoenixtek if a key is lost.
- Change the Wi-Fi access-point password if the access point is left enabled.
- Keep firmware up to date. Phoenixtek issues updates through PHX-Sense Studio.

ORDERING INFORMATION

Part	PHX-DAQ 24 — 4-channel sensor and temperature datalogger, with PHX-Sense Studio
Accessories	NTC temperature probes, bridge-completion junction boxes, shielded cable, 24 V DC power supply. Available on request
Support	Integration guide, calibration guidance and pilot deployments

PHOENIXTEK SOLUTIONS

Request a demo or a pilot deployment

www.phoenixtek.in
info@phoenixtek.in

Specifications are subject to change without notice. PHX-DAQ 24 and PHX-Sense Studio are products of Phoenixtek Solutions. Document DS-PHXDAQ24, Rev A, September 2026.