MILITARY SPECIFICATION

POWER SUPPLY: 9333063

This amendment forma a part of MIL-P-50346A (AR), dated 28 September 1984, and is approved for use by the US Army Armament, Munitions, and chemical Command, and is available for use by all Departments and Agencies of the Department of Defense.

PAGE 5

3.4.2, Circuit breakers: Delete "(5A)" and substitute "(2A)".

3.5.1: Delete in its entirety and substitute the following:

"3.5.1 115 V, 400 Hz ON-OFF switch S1. With 115 ± 10 volts, 400 Hz power connected to J1-A and B, 24 Vdc switch (S3) in OFF position, and circuit breaker CB1 closed, 115 V, 400 Hz switch S1 shall serve to change indicator DS1 from OFF to ON and the reverse, and to cause 115 ± 10 volts, 400 Hz power to be applied to J2-A and L in accordance with indicator DS1."

3.5.2: Delete in its entirety and substitute the following:

"3.5.2 +24 Vdc ON-OFF switch S3. With 115 ± 10 volts, 400 Hz power connected to J1-A and B, +24 volts dc power connected to J1-D (+) and E (RET), TEST MODE switch S2 in OFF position, terminals J2-H and S shorted, and circuit breakers CB1, CB2 and CB4 closed, +24 Vdc switch S3 shall serve to change indicator DS2 from OFF illuminated to ON illuminated and the reverse, and to cause +24 volts dc power to be applied to points specified on the schematic drawing, in accordance with indicator DS2. Indicator 115 V, 400 Hz (DSI) shall track DS2 indicator."



DISTRIBUTION STATEMENT A. Approved for public release; distribution is unlimited.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

PAGE 5 (Cont'd.)

3.5.3, Power SUP 1 voltages: Delete following subparagraph:

"With power applied as in 3.5.2, CB2 and CB4 closed, S3 ON, TEST MODE switch S2 in any position except FC CONSOLE, terminals J2-K and S shorted, . . ."

and substitute:

"With +24 volts dc power connected to J1-D (+) and E(RET), CB2 and CB4 closed, S3 ON, TEST MODE switch S2 in OFF position, terminals J2-H and S shorted, ..."

PAGE 6

Table I, Converter voltages. Delete requirements under column "Reading on Volts Meter (M1)" and substitute the following:

| |
|---|
| 0 to 1 |
| 24 ± 2 |
| 6 ± 1 |
| 15 ± 1 |
| 15 ± 1 |
| 23 ± 1 |
| 23 ± 1 |
| 29 ± 1 |
| 33 ± 1 |
| 33 ± 1 |

3.5.4, Dc voltage outputs: Delete following subparagraph:

"With power applied as in 3.5.2, CB2, CB3, CB4 closed, S3 ON, J2-K and S shorted, and TEST MODE switch S2 in any position except FC CONSOLE, . . ."

and substitute:

"With power applied as in 3.5.3, CB2, CB3, and CB4 closed, S3 ON, J2-H and S shorted, and TEST MODE switch S2 in OFF position, . .."



Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

PAGE 7

3.5.5, Power control voltage: Delete first line of paragraph "With power applied as in 3.5.2 ...." and substitute "With power applied as in 3.5.3 . ..."

3.5.6, FC control voltages: Delete first line of paragraph "With power applied as in 3.5.2 ...." and substitute "With power applied as in 3.5.3 . ..."

PAGE 8

3.5.7, 10 KV Voltage divider: Delete following subparagraph:

"... in MICROWAVE/KLYSTRON PWR SUP position, and 10 KV DC . . . . output current shall increase by 100 MA ± 10%."

and substitute:

"... in MICROWAVE/KLYSTRON PWR SUP POSITION, TP11 and COM (TP6) shorted, and 10 KVdc . . . . output current shall be 19MA ± 10%."

PAGE 11

Table VII, Inspection equipment list. Delete item No. 4 description "0 to 15 KV DC at 300 Ma" and substitute "O to 15 KV DC at 30 MA".

PAGE 13

4.7.2.2.1, 115V, 400 Hz circuit breaker (CB1): Delete following subparagraph:

"Connect J2-K to J2-S. Put TEST MODE switch S2 in any position except FC CONSOLE. Close 115V, 400 Hz circuit breaker CB1 and 24 Vdc CONTROL CKT circuit breaker CB4 by depressing their pushbuttons so white bands are concealed. Connect 115 volts ac, 400 Hz, and +24 volts dc input power from power supplies, items 1 and 2 to connector J1 ...."

and substitute:

"Close 115 V, 400 Hz circuit breaker CB1 by depressing pushbutton so white band is concealed. Connect 115 volts ac, 400 Hz input power from power supply, item 1 to connector J1 . . . ."



Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

PAGE 13 (Cont'd.)

4.7.2.2.2, PWR SUP 1 circuit breaker (CB2): Delete following subparagraph:

"Connect J2-K to J2-S. Put TEST MODE switch S2 in any position except FC CONSOLE. . . . . Either ON or OFF legend indicator DS3 . . . ."

and substitute:

"Connect J2-H to J2-S. Place TEST MODE switch S2 in OFF position. . . . . Either ON or OFF legend indicator DS2 ...."

4.7.2.2.3, Tester CKT circuit breaker (CB3): Delete following subparagraph:

"Connect J2-K to J2-S. Put TEST MODE switch S2 in any position except FC CONSOLE. Close PWR SUP 1 circuit-breaker CB2 and 24 Vdc CONTROL CKT circuit breaker CB4 by depressing their pushbuttons so white bands are concealed. Close TESTER CKT circuit breaker CB3 by depressing pushbutton so white band is concealed. Connect +24 volts dc ...."

and substitute:

"Connect J2-H to J2-S. Place TEST MODE switch S2 in OFF position. Close PWR SUP 1 circuit breaker CB2, TESTER CKT circuit breaker CB3, and 24 Vdc CONTROL CKT circuit breaker CB4 by depressing their pushbuttons so white bands are concealed. Connect +24 volts dc ...."

PAGE 15

4.7.2.2.3, Tester CKT circuit breaker (CB3): Delete following subparagraph:

".... (ON legend of DS3 illuminated) ...."

and substitute:

".... (ON legend of DS2 illuminated) ...."



Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

4.7.2.2.4, Control CKT circuit breaker (CB4): Delete following subparagraph:

"Connect J2-K to J2-S. Turn TEST MODE switch S2 to the PWR SUP/SERVO position. Close CONTROL CKT circuit breaker CB4 by depressing pushbutton so white band is concealed . . . . If indicator DS3 reads OFF, push switch S3 so that DS3 . . . . between J2-N(+) and J2-C(RET) . . . . ON legend of DS3 shall . . . . DS3 shall light."

and substitute:

"Connect J2-H to J2-S. Turn TEST MODE switch S2 to the PWR SUP/SERVO position. Close PWR SUP 1 circuit breaker CB2 and CONTROL CKT circuit breaker CB4 by depressing their pushbuttons so white bands are concealed . . . . If indicator DS2 reads OFF, push switch S3 so that DS2 . . . . between J2-N(+) and J2-B(RET) .... ON legend of DS2 shall . . . . DS2 shall light."

4.7.3, Performance, under "circuit breaker column": Delete "115V 400 Hz (10A)" and substitute "115V 400 Hz (2A)".

4.7.3, Performance, under "position column": Delete "OFF (full ccw)" and substitute "OFF".

4.7.3.1, 115V, 400 Hz ON-OFF switch S1: Delete following subparagraph:

"Connect input power from power supplies, items 1 and 2, to connector J1 in accordance with Figure 1. Put TEST MODE switch S2 in any position except FC CONSOLE. Connect J2-K to J2-S. Close 115V, 400 Hz circuit breaker CB1 and CONTROL CKT circuit breaker CB4 by depressing their pushbuttons so white bands are concealed. Either ON or OFF . ..."

and substitute:

"Connect input power from power supplies, items 1 and 2, to connector J1 in accordance with Figure 1. Close 115 V, 400 Hz circuit breaker CB1 by depressing pushbutton so white band is concealed. Depress 24 Vdc switch (S3) so OFF legend of DS2 is illuminated. Either ON or OFF ...."



Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

4.7.3.2, +24 Vdc ON-OFF switch S3: Delete following subparagraph:

"Connect +24 volts dc from power supply, item 2 to J1 in accordance with Figure 1. Put TEST MODE switch S2 in any position except FC CONSOLE. Connect J2-K to J2-S. Close PWR SUP 1 and CONTROL CKT circuit breakers (CB2 and CB4) by depressing pushbuttons so white bands are concealed .... +24 Vdc indicator DS3 shall .... Leave indicator DS3 reading ON .... DS1 tracks DS3 indicator."

and substitute:

"Connect input power from power supplies, items 1 and 2, to J1 connector in accordance with Figure 1. Place TEST MODE switch S2 to OFF position. Connect J2-H to J2-S. Close PWR SUP 1, 115 V 400 Hz, and CONTROL CKT circuit breakers (CB1, CB2 and CB4) by depressing their pushbuttons so white bands are concealed .... +24 Vdc indicator DS2 shall .... Leave indicator DS2 reading ON .... DS1 tracks DS2 indicator."

4.7.3.3, Converter voltagesand metering: Delete following subparagraph:

"After completing 4.7.3.2, turn ...."

and substitute:

"Connect input power from power supply, item 2, to J1 connector in accordance with Figure 1. With CB2 and CB4 closed, DS2 reading ON, J2-H and S shorted, and TEST MODE switch S2 in OFF position, turn ....".

4.7.3.4, Dc output voltages: Delete following subparagraph:

"With input power applied as in 4.7.3.1, CB2, CB3, and CB4 closed, DS3 reading ON, J2-K and S shorted, and TEST MODE switch S2 in any position except FC CONSOLE< ...."

and substitute:

"With input power applied as in 4.7.3.3, CB2, CB3, and CB4 closed, DS2 reading ON, J2-H and S shorted, and TEST MODE switch S2 in OFF position, ....".



Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

4.7.3.5, Power control voltage: Delete following subparagraph:

"... Connect power as in 4.7.3.1 ...."

and substitute:

"... Connect power as in 4.7.3.3 ....".

4.7.3.6, FC control voltages: Delete following subparagraph:

"Apply power as in 4.7.3.2 ...."

and substitute:

"Apply power as in 4.7.3.3 ...."

4.7.3.7, 10 KV voltage divider: Delete following subparagraph:

"MICROWAVE/KLYSTRON PWR SUP position, and close .... 9.1V at TP9(+) ...."

and substitute:

"MICROWAVE/KLYSTRON PWR SUP position, connect TP11 to COM (TP6), and close .... 9.1 ± .45 V at TP9(+) ....".

Custodian:
Army-AR

Preparing activity:
Army-AR

(Project 4931-A259)



Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.

# STANDARDIZATION DOCUMENT IMPROVEMENT PROPOSAL

INSTRUCTIONS

1. The preparing activity must complete blocks 1, 2, 3, and 8. In block 1, both the document number and revisi letter should be given.
2. The submitter of this form must complete blocks 4, 5, 6, and 7.
3. The preparing activity must provide a reply within 30 days from receipt of the form.

NOTE: This form may not be used to request copies of documents, nor to request waivers, or clarification of requirements on current contracts. Comments submitted on this form do not constitute or imply authorization waive any portion of the referenced document(s) or to amend contractual requirements.

| I RECOMMEND A CHANGE: | 1. DOCUMENT NUMBER | 2. DOCUMENT DATE (YYMMDD) |
|---|---|---|
| 3. DOCUMENT TITLE | | |

4. NATURE OF CHANGE *(Identify paragraph number and include proposed rewrite, if possible. Attach extra sheets if needed.)*

5. REASON FOR RECOMMENDATION

6. SUBMITTER

| a. NAME (Last, First, Middle Initial) | b. ORGANIZATION |
|---|---|
| c. ADDRESS (Include Zip Code) | d. TELEPHONE (Include Area Code)<br>(1) Commercial<br>(2) AUTOVON<br>(If applicable) |
| | 7. DATE SUBMITTED (YYMMDD) |

8. PREPARING ACTIVITY

| a. NAME | b. TELEPHONE (Include Area Code)<br>(1) Commercial (2) AUTOVON |
|---|---|
| c. ADDRESS (Include Zip Code) | IF YOU DO NOT RECEIVE A REPLY WITHIN 45 DAYS, CONTACT:<br>Defense Quality and Standardization Office<br>5203 Leesburg Pike, Suite 1403, Falls Church, VA 22041-3466<br>Telephone (703) 756-2340 AUTOVON 289-2340 |



Source: https://assist.dla.mil -- Downloaded: 202640-22T20:22Z
Check the source to verify that this is the current version before use.

Source: https://assist.dla.mil -- Downloaded: 2026-10-22T20:22Z
Check the source to verify that this is the current version before use.