

SN6200-LD Engineering Sample

Release Notes

October 8, 2026

Table of Contents

SN6200-LD Engineering Sample..... 1

 Supported Platforms 1

 SN6200-LD Supported Port Speeds 1

 Package Content 1

 New Features..... 2

 Unsupported Features..... 2

 Network Port Connectivity Matrix 2

 Service Port Connectivity Matrix 3

 Verified Cables..... 3

 NVIDIA DSX Air..... 3

 Install BMC..... 4

 Show BMC Commands 5

 Liquid Cooling Leakage Telemetry..... 6

 Open Issues..... 6

 Legal Notices and 3rd Party Licenses 7

SN6200-LD Engineering Sample

This document provides information about the SN6200-LD engineering sample for Cumulus Linux 5.18.

Important:

- > The SN6200-LD engineering sample requires Cumulus Linux release 5.18.6200. For information about Cumulus Linux 5.18, refer to the [Cumulus Linux 5.18 User Guide](#).
- > Future upgrades from the SN6200-LD engineering sample will be binary upgrades using ONIE.

Supported Platforms

The SN6200-LD engineering sample supports the following platforms:

Model Number	Part Number	Description
SN6200-LD	920-9N60F-00LI-GC0	NVIDIA Spectrum-6 based 800GbE Ethernet switch with Cumulus Linux Authentication, Rack Scale, 32xOSFP, 1xQSFP112, 256x200G Cable Cartridge, 48VDC Busbar, 8-Cores CPU, Secure-boot, Liquid-Cooling, Rail Kit

SN6200-LD Supported Port Speeds

Speed [GbE]	Auto-Negotiation	Force			Cables/Modules	Cable Length [m]
		RS FEC	FC FEC	NO FEC		
200G PAM4: 800G 400G 200G	✓	✓	X	X	Optic	Up to 100
					Copper	1
100G (service port)	✓	✓	X	X	Optic	Up to 100

- > PAM4 is the system default.
- > When connecting NVIDIA-to-NVIDIA in PAM4, make sure Auto-negotiation is enabled.
- > 100 Gbps serdes lane speed is not supported

Package Content

NVIDIA has validated this release with the following component versions:

NVIDIA CONFIDENTIAL

Package	Version
SDK	4.10.1526-002
Kernel	6.1.123-1
MFT	4.36.0.1037
Hardware management	7.0070.1133
NetQ	5.2.1
FRR	10.0.3
NVUE Core	1.14.0.77
UMF	91.1.14.14
BMC	88.0060.2422

New Features

-

Unsupported Features

The Spectrum-6 engineering sample does not support:

- > Optimized image upgrade
- > Package upgrade
- > ISSU upgrade
- > Fast reboot
- > Precision Time Protocol (PTP)

Network Port Connectivity Matrix

Supported Speeds	Connectivity	Cable PN	Cable Type and Description	Lengths (m)
800G_R4 to 200G_R1	SN6200-LD ↔ SN6200-LD/ ConnectX-9	980-9IAU1-00X M00	DR4 Optic module, OSFP flat	Up to 100
800G_R4 to 200G_R1	SN6200-LD ↔ SN6200-LD	980-9IAM6-00X 001	ACC copper, OSFP flat	1, 2, 3

When connecting to ConnectX-9 using cable PN 980-9IAU1-00XM00, ensure that the adapter is running firmware version 82.49.10xx or later and apply the configuration setting `mlxconfig -d /dev/mst/mt4133_pciconf0 set MODULE_MAX_POWER_OVERRIDE_M0=0x96`.

Service Port Connectivity Matrix

Supported Speeds	Connectivity	Cable PN	Cable Type and Description	Lengths (m)
100G_R1	SN6200-LD	980-9I068-00NM00 (MMS1X00-NS400)	DR4 Optic module, QSFP112 flat	Up to 100

Verified Cables

Speed	Part Number	Description
1600GbE	980-9IAU1-00XM00	NVIDIA twin port transceiver, 2xDR4, 1600Gbps, OSFP, 2xMPO(APC), 1310nm SMF, up to 500m, RHS, FRO, Gen2, Ethernet Only
1600GbE	980-9IAM6-00X001	NVIDIA Active copper cable, 1600Gbps to 1600Gbps, OSFP, 1.1m, RHS to RHS
1600GbE	980-9IAM6-00X002	NVIDIA Active copper cable, 1600Gbps to 1600Gbps, OSFP, 2m, RHS to RHS
1600GbE	980-9IAM6-00X003	NVIDIA Active copper cable, 1600Gbps to 1600Gbps, OSFP, 3m, RHS to RHS

NVIDIA DSX Air

NVIDIA DSX Air only supports 256 ports (the physical switch supports 512 ports).

Install BMC

The Spectrum-6 switch requires you to download and install the Baseboard Management Controller (BMC) onto the switch.

BMC is a specialized microcontroller designed to deliver out-of-band remote monitoring and management for servers and switches. Operating independently from the main CPU and operating system, the BMC enables administrative control even when the switch is powered down or unresponsive. It streamlines server and switch management while enhancing network efficiency, reliability, and security through automation of critical tasks.

To download the BMC package, run the `nv action fetch platform firmware <firmware-name> <remote-url-to-package>` command:

```
cumulus@switch:~$ nv action fetch platform firmware BMC <remote-url-to-BMC-package>
Action executing ...
Firmware downloaded successfully. File:
/tmp/firmware_downloads/sw_bmc_arm_chameleon5_chameleon_bu_kernel-001.fwpkg. SHA256:
19439f4a6695473386a9bb5f2fe253126825c0336890cd0e7366c7a10bda97c0
Action succeeded
```

To install the BMC package, run the `nv action install platform firmware <firmware-name> files <downloaded-file-name>` command:

```
cumulus@switch:~$ nv action install platform firmware BMC files <downloaded-file-name>
The operation will install the firmware.
Type [y] to install the firmware.
Type [N] to abort.
Do you want to continue? [y/N] y
Action executing ...
Firmware installation completed for bmc. Version: unknown
Action succeeded
```

If you prefer not to reboot the switch after BMC installation completes, add the `skip-reboot` command option; for example, `nv action install platform firmware BMC files <downloaded-file-name> skip-reboot`.

Show BMC Commands

Use the following commands to show information about the installed BMC package and switch environment leakage.

Command	Description
<code>nv show platform inventory</code>	Shows the model, serial number, operational state, and type of each component on the switch.
<code>nv show platform inventory BMC</code>	Shows the BMC firmware model, serial number, operational state, and type.
<code>nv show platform firmware BMC</code>	Shows the BMC firmware part number and name.
<code>nv show platform firmware BMC files</code>	Shows the available BMC firmware files.
<code>nv show platform environment leakage</code> <code>nv show platform environment leakage -o json</code>	Shows the switch environment leakage (low-current signals).

The following example shows the BMC model, serial number, operational state, and type.

```
cumulus@switch:~$ nv show platform inventory BMC
                        operational
-----
state                ok
hardware-version      chameleon_bu_kernel_leak-002
model                 Baseboard Management Controller
serial                MT2538600R0B
type                  bmc
```

The following examples show the switch environment leakage:

```
cumulus@switch:~$ nv show platform environment leakage
Name      State
-----
leakage1   normal
leakage2   normal
```

```
cumulus@switch:~$ nv show platform environment leakage -o json
{
  "leakage1": {
    "state": "normal"
  },
  "leakage2": {
    "state": "normal"
  }
}
```

Liquid Cooling Leakage Telemetry

Liquid-cooled NVIDIA switches contain leakage sensors that detect coolant leaks. These sensors are critical for data center safety as an undetected leak can cause equipment damage, fire risk, or unplanned downtime.

This feature adds leakage sensor data to the gNMI and OTEL telemetry pipeline, enabling remote monitoring systems, such as Prometheus, Grafana, and gNMI collectors, to subscribe to real-time leakage status and trigger automated alerts.

Open Issues

ID	Description

Legal Notices and 3rd Party Licenses

Product	Version	Legal Notices and 3rd Party Licenses
SDK	4.10.1526	> 3rd Party Unify Notice > 3rd Party Notice > License
MFT	4.36.0-1037	> 3rd Party Notice—Linux > License—Linux

Notice

This document is provided for information purposes only and shall not be regarded as a warranty of a certain functionality, condition, or quality of a product. NVIDIA Corporation ("NVIDIA") makes no representations or warranties, expressed or implied, as to the accuracy or completeness of the information contained in this document and assumes no responsibility for any errors contained herein. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This document is not a commitment to develop, release, or deliver any Material (defined below), code, or functionality. NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and any other changes to this document, at any time without notice.

Customer should obtain the latest relevant information before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer ("Terms of Sale"). NVIDIA hereby expressly objects to applying any customer general terms and conditions with regards to the purchase of the NVIDIA product referenced in this document. No contractual obligations are formed either directly or indirectly by this document.

NVIDIA products are not designed, authorized, or warranted to be suitable for use in medical, military, aircraft, space, or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death, or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk.

NVIDIA makes no representation or warranty that products based on this document will be suitable for any specified use. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to evaluate and determine the applicability of any information contained in this document, ensure the product is suitable and fit for the application planned by customer, and perform the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this document. NVIDIA accepts no liability related to any default, damage, costs, or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this document or (ii) customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this document. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA.

Reproduction of information in this document is permissible only if approved in advance by NVIDIA in writing, reproduced without alteration and in full compliance with all applicable export laws and regulations, and accompanied by all associated conditions, limitations, and notices.

THIS DOCUMENT AND ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. TO THE EXTENT NOT PROHIBITED BY LAW, IN NO EVENT WILL NVIDIA BE LIABLE FOR ANY DAMAGES, INCLUDING WITHOUT LIMITATION ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE, OR CONSEQUENTIAL DAMAGES, HOWEVER CAUSED AND REGARDLESS OF THE THEORY OF LIABILITY, ARISING OUT OF ANY USE OF THIS DOCUMENT, EVEN IF NVIDIA HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customers for the products described herein shall be limited in accordance with the Terms of Sale for the product.

Trademarks

NVIDIA, the NVIDIA logo, are trademarks and/or registered trademarks of NVIDIA Corporation in the U.S. and other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

VESA DisplayPort

DisplayPort and DisplayPort Compliance Logo, DisplayPort Compliance Logo for Dual-mode Sources, and DisplayPort Compliance Logo for Active Cables are trademarks owned by the Video Electronics Standards Association in the United States and other countries.

HDMI

HDMI, the HDMI logo, and High-Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC.

Arm

Arm, AMBA, and Arm Powered are registered trademarks of Arm Limited. Cortex, MPCore, and Mali are trademarks of Arm Limited. All other brands or product names are the property of their respective holders. "Arm" is used to represent Arm Holdings plc; its operating company Arm Limited; and the regional subsidiaries Arm Inc.; Arm KK; Arm Korea Limited.; Arm Taiwan Limited; Arm France SAS; Arm Consulting (Shanghai) Co. Ltd.; Arm Germany GmbH; Arm Embedded Technologies Pvt. Ltd.; Arm Norway, AS, and Arm Sweden AB.

OpenCL

OpenCL is a trademark of Apple Inc. used under license to the Khronos Group Inc.

Copyright

© 2024 NVIDIA Corporation. All rights reserved.

