CPE 381: Fundamentals of Signals and Systems for Computer Engineers

05 Fourier Transform

Fall 2026

Rahul Bhadani

Outline

1. Fourier Transform of an Aperiodic Signal

2. Properties of Fourier Transform

3. Spectral Representation

4. Filtering



Fourier Transform of an Aperiodic Signal

Aperiodic Signal

- Aperiodic signal can be thought of as a periodic signal with infinite fundamental frequency.
- In practice, there are no periodic signals, but they are nice mathematical tools.

$$x(t) = \lim_{T_0 \to \infty} \tilde{x}(t)$$

From Fourier Series to Fourier Transform

Consider

$$\tilde{x}(t) = \sum_{n=-\infty}^{\infty} X_n e^{jn\Omega_0 t}, \quad \Omega_0 = \frac{2\pi}{T_0}$$

and its Fourier coefficient is

$$X_n = \frac{1}{T_0} \int_{-T_0/2}^{T_0/2} \tilde{x}(t) e^{-jn\Omega_0 t} dt$$

In the limiting case $T_0 \to \infty$, $X_n \to 0$, so to avoid it, $X(\Omega_n) = T_0 X_n$, and $\Omega_n = n\Omega_0$ are the harmonic frequencies. That is to say:

$$X_n T_0 = \int_{-T_0/2}^{T_0/2} \tilde{x}(t) e^{-j\Omega_n t} dt$$

From Fourier Series to Fourier Transform

Rewriting $\Omega_0 = \Delta\Omega = \dfrac{2\pi}{T_0}$

$$\tilde{x}(t) = \sum_{n=-\infty}^{\infty} X(\Omega_n) e^{j\Omega_n t} = \sum_{n=-\infty}^{\infty} X(\Omega_n) e^{j\Omega_n t} \frac{\Delta\Omega}{2\pi}$$

$$X(\Omega_n) = \int_{-T_0/2}^{T_0/2} \tilde{x}(t) e^{-j\Omega_n t} dt$$

As $T_0 \to \infty$, $\Delta\Omega \to d\Omega$ and sum becomes integral. Thus $\Omega_n = n\Omega_0 = n\Delta\Omega \to \Omega$.

Fourier Transform

Hence, in the limiting case, $T_0 \to \infty$,

Fourier Transform

$$X(\Omega) = \int_{-\infty}^{\infty} x(t) e^{-j\Omega t} dt$$

Inverse Fourier Transform

$$x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(\Omega) e^{j\Omega t} d\Omega$$

Obtaining Fourier Transform

- If $x(t)$ is periodic, its Fourier transform is obtained using the signal's Fourier series.
- For some functions, e.g. the integral is not well-defined, or has discontinuities then the integration formula cannot be used for calculating the Fourier transform. We will use properties of Fourier transform in such a case.

It appears that almost nothing has a Fourier transform—nothing except practical communication signals. No signal amplitude goes to infinity and no signal lasts forever; therefore, no practical signal can have an infinite area under it, and hence all have Fourier transforms.

- E. Craig

Frequency Content with Fourier Transform

- The Fourier transform measures the frequency content of a signal.
- Time-domain vs Frequency-domain: The characterization in one domain provides information that is not clearly available in the other.



Properties of Fourier Transform

Linearity

$$\mathcal{F}[\alpha x(t) + \beta y(t)] = \alpha \mathcal{F}[x(t)] + \beta \mathcal{F}[y(t)] = \alpha X(\Omega) + \beta Y(\Omega)$$

Fourier Transform of an Impulse Function

$$x(t) = \delta(t)$$
$$X(\Omega) = \int_{-\infty}^{\infty} \delta(t) e^{-j\Omega t} dt = e^{-j0} = \int_{-\infty}^{\infty} \delta(t) dt = 1, \quad -\infty < \Omega < \infty \tag{1}$$

Hence, if the delta function has finite support as seen, then its Fourier transform has infinite support in frequency.

It means $\delta(t)$ changes so much in a very short time that its FT has all possible frequency components.

Example

Fourier Transform

Find the Fourier transform of (i) $u(t)$, (iii) $p(t) = u(t) - u(t-1)$

Blank space for calculation

Duality Property

Inverse Fourier Transform:

$$x(t) = \frac{1}{2\pi}\int_{-\infty}^{\infty} X(\rho)e^{j\rho t}d\rho$$

Replacing t with $-\Omega$,

$$2\pi x(-\Omega) = \int_{-\infty}^{\infty} X(\rho)e^{-j\rho\Omega}d\rho = \int_{-\infty}^{\infty} X(t)e^{-j\Omega t}dt = \mathcal{F}[X(t)]$$

after replacing ρ with t as they are dummy variables. Hence

$$X(t) \Leftrightarrow 2\pi x(-\Omega)$$

Fourier Transform of a Constant Signal

$$x(t) = A, \quad -\infty < t < \infty \tag{2}$$

As, it is a constant, natural $\Omega = 0$ is the frequency. We cannot find its frequency in the usual way it is not absolutely integrable. Then we can the **duality property**.

$$\begin{aligned} \delta(t) &\Leftrightarrow 1 \\ A\delta(t) &\Leftrightarrow A \\ A &\Leftrightarrow 2\pi A\delta(-\Omega) = 2\pi A\delta(\Omega) \end{aligned} \tag{3}$$

Notice the last step because δ is an even function.

Fourier Transform of Shifted Delta and Cosines

Shifted Delta

$$\delta(t-b)+\delta(t+b) \Leftrightarrow e^{-jb\Omega}+e^{jb\Omega}=2\cos(b\Omega) \tag{4}$$

Cosine

We use duality property:

$$2\cos(bt) \Leftrightarrow 2\pi[\delta(\Omega-b)+\delta(\Omega+b)]$$
$$\cos(bt) \Leftrightarrow \pi[\delta(\Omega-b)+\delta(\Omega+b)] \tag{5}$$

Example

Use duality to find the Fourier transform of $x(t) = 10\text{sinc}(0.5t)$.

Blank space for calculation

Blank space for calculation

Blank space for calculation

Time Frequency Inverse Proportionality


Support of $X(\Omega)$ is inversely proportional to the support of $x(t)$. If $x(t)$ has Fourier transform $X(\Omega)$, and $\alpha \neq 0$, a real number, then
$x(\alpha t)$

- is a contracted signal when $\alpha > 1$
- , is a contracted and reflected signal when $\alpha < -1$
- is an expanded signal when $0 < \alpha < 1$
- is an expanded and reflected signal when $-1 < \alpha < 0$
- reflect signal when $\alpha = -1$

and,

$$x(\alpha t) \leftrightarrow \frac{1}{|\alpha|} X(\frac{\Omega}{\alpha})$$

Inverse Proportionality of Time and Frequency: Example 1



Notice that the wider the pulse the more concentrated in frequency its Fourier transform. Code: https://github.com/rahulbhadani/CPE381_FA26/blob/main/Code/Ch05_fourier_transform_rect.m

Inverse proportionality of time and frequency: Example 2

Consider a pulse $x(t) = u(t) - u(t-1)$. Find its Fourier transform, and the Fourier Transform of $x(2t)$.

Inverse proportionality of time and frequency: Example 2

Blank space for calculation


Inverse proportionality of time and frequency: Example 2

Blank space for calculation

Inverse proportionality of time and frequency: Example 2

Blank space for calculation

Inverse proportionality of time and frequency: Example 2



$x(t)$ has finite support, while $X(\Omega)$ has infinite support.

Code: `https://github.com/rahulbhadani/CPE381_FA26/blob/main/Code/Ch05_FourierTransform_Rect_Expanded.m`

Example 3

Apply the reflection property to find the Fourier transform of $x(t) = e^{-a|t|}$, $a > 0$.

Example 3

Blank space for calculation


Example 3

Blank space for calculation

Example 3

Blank space for calculation

Example 3



From this plot, we see that its energy is concentrated mostly in low frequencies, hence the signal is called **low-pass**.

Code: https://github.com/rahulbhadani/CPE381_FA26/blob/main/Code/Ch05_FourierTransform_Exp_Abs.m



Spectral Representation

Modulation

$$\mathcal{F}[x(t)e^{j\Omega_0 t}] = \int_{-\infty}^{\infty}[x(t)e^{j\Omega_0 t}]e^{-j\Omega t}dt = \int x(t)e^{j(\Omega-\Omega_0)t}]dt = X(\Omega-\Omega_0)$$

Then applying frequency shifting property to $x(t)\cos(\Omega_0 t)$, we have

$$x(t)\cos(\Omega_0 t) \Leftrightarrow 0.5[X(\Omega-\Omega_0)+X(\Omega-\Omega_0)]$$

Here, $x(t)$ is the main signal, called the **message**, $\cos(\Omega_0 t)$ is called the **carrier**, and $x(t)\cos(\Omega_0 t)$ is the **modulated signal**.
The scheme discussed is called Amplitude Modulation

Why Amplitude Modulation?

- Music signals are audible at up to 22 KHz, while speech signals are at 100 Hz - 5 KHz. They are relatively low frequency.
- The length of an antenna that is used to radiate the signal is a quarter of a wavelength, given by

$$\lambda = \frac{c}{f}\ meter$$

  $c = 3 \times 10^8 m/s$ is the speed of light, and f is the frequency in Hz of the signal to be radiated.
- Assuming $f = 30$ KHz, normal for music and speech with some noise, the $\lambda \approx 10$ km, hence antenna size would be 2.5 km. A very giant antenna.
- Choosing an appropriate modulation frequency helps in reducing the size of the antenna.

Fourier Transform of Periodic Signals

If the function is periodic, we know that it can be represented as a Fourier series, i.e.

$$x(t) = \sum_{k=-\infty}^{\infty} X_k e^{j\Omega_k t}$$

where

$$X_k = \frac{1}{T}\int_{-\infty}^{\infty} x(t) e^{-j\Omega_k t} dt$$

From the linearity and frequency-shifting property, we can write

$$X(\Omega) = \sum_k \mathcal{F}[X_k e^{j\Omega_k t}] = \sum_k 2\pi X_k \delta(\Omega - \Omega_k)$$

$\Omega_k = k\Omega_0$.

Example 4

Consider a periodic signal $x(t)$ with a period $x_1(t) = r(t) - 2r(t-0.5) + r(t-1)$. Its fundamental frequency is $\Omega_0 = 2\pi$. Determine its Fourier transform analytically and using MATLAB.

Example 4

Blank space for calculation

Example 4

Blank space for calculation

Parseval's Energy Relationship

$$E_x = \int_{-\infty}^{\infty} |x(t)|^2 dt = \int_{-\infty}^{\infty} x(t)x^*(t)dt = \int_{-\infty}^{\infty} x(t)\left[\frac{1}{2\pi}\int_{-\infty}^{\infty} X^*(\Omega)e^{-j\Omega t}d\Omega\right]dt$$
$$= \frac{1}{2\pi}\int_{-\infty}^{\infty} X^*(\Omega)\left[\int_{-\infty}^{\infty} x(t)e^{-j\Omega t}dt\right]d\Omega = \frac{1}{2\pi}\int_{-\infty}^{\infty} |X(\Omega)|^2 d\Omega \quad (6)$$

Thus $|X(\Omega)|^2$ is an energy density—indicating the amount of energy at each of the frequencies. The plot $|X(\Omega)|^2$ vs. frequency is called the energy spectrum of $x(t)$, and displays how the energy of the signal is distributed over frequency.

Example 5: Pulse Signal and its Energy

Consider $p(t) = u(t+1) - u(t-1)$, use its Fourier transform $P(\Omega)$ and Parseval's energy relation to show that

$$\int_{-\infty}^{\infty} \left(\frac{\sin(\Omega)}{\Omega} \right)^2 d\Omega = \pi$$

Example 5: Pulse Signal and its Energy

Blank space for calculation

Example 5: Pulse Signal and its Energy

Blank space for calculation

Spectral Representation

- Magnitude spectrum: $|X(\Omega)|$ vs Ω: even function
- Phase spectrum: $\angle X(\Omega)$ vs Ω: odd function
- Energy/Power spectrum: $|X(\Omega)|^2$ vs Ω: even function



Filtering

Frequency Response

$H(j\Omega)$ (or $H(\Omega)$) is the frequency response of the system. Thus,

$$y(t) = \frac{1}{2\pi}\int_{-\infty}^{\infty}[X(\Omega)H(\Omega)]e^{j\Omega t}d\Omega = \frac{1}{2\pi}\int_{-\infty}^{\infty}[Y(\Omega)]e^{j\Omega t}d\Omega$$

Thus $Y(\Omega) = X(\Omega)H(\Omega)$ For a periodic signal $X(\Omega) = \sum_{k=-\infty}^{\infty} 2\pi X_k \delta(\Omega - \Omega_k)$,

$$Y(\Omega) = X(\Omega)H(\Omega) = \sum_{k=-\infty}^{\infty} 2\pi X_k H(\Omega_k)\delta(\Omega - \Omega_k)$$

Thus Fourier coefficient of the output $y(t)$ is $Y_k = X_k H(\Omega_k)$.

Filtering

In practice $s(t) = x(t) + \eta(t)$, where η is the noise. We want to get rid of noise. So we design a special system called **Filters** that will by assuming that noise has certain frequencies, and filters will remove those frequencies.
The problem of filtering is finding the frequency response $H(\Omega)$ of the filter.

Example 6: From Full-wave Rectifier to DC Source

Let $x(t) = |\cos(\pi t)|$ is a full-wave rectifier be an input to a filter $H(\Omega)$, and the output is a DC signal. What should $H(\Omega)$ look like?

Example 6: From Full-wave Rectifier to DC Source

Blank space for calculation

Example 6: From Full-wave Rectifier to DC Source

Blank space for calculation

Example 6: From Full-wave Rectifier to DC Source

Blank space for calculation

Low Pass Filters

Ideal Low Pass Filter

A filter that keeps low frequencies is called a low-pass filter. The magnitude response of an ideal low-pass filter is

$$|H_{\ell p}(\Omega)| = \begin{cases} 1, & -\Omega_1 \leq \Omega \leq \Omega_1 \\ 0, & \text{otherwise} \end{cases} \tag{7}$$

and the frequency response is $\angle H_{\ell p}(\Omega) = -\alpha\Omega$ which is a linear phase.

- Ω_1 is called cut-off frequency.

Band-pass Filter

Ideal Band-pass Filter

Keeps a band of frequencies

Magnitude Response:

$$|H_{bp}(\Omega)| = \begin{cases} 1, & \Omega_1 \leq \Omega \leq \Omega_2 \text{ and } -\Omega_2 \leq \Omega \leq -\Omega_1 \\ 0, & \text{otherwise} \end{cases} \tag{8}$$

Its phase is also linear in the pass band.

High-pass Filter

Ideal High-pass Filter

Keeps only high frequencies
Magnitude Response:

$$|H_{hp}(\Omega)| = \begin{cases} 1, & \Omega \geq \Omega_2 \text{ and } -\Omega \leq -\Omega_2 \\ 0, & \text{otherwise} \end{cases} \tag{9}$$

Its phase is also linear in the pass band.

An ideal multi-band filter can be obtained by a combination of low, high, and band-pass filter.

Band-stop Filter (Band-eliminating Filter)

Ideal High-pass Filter


Removes a range of frequencies

Magnitude Response:

$$|H_{be}(\Omega)| = 1 - |H_{bp}(\Omega)| \tag{10}$$


Its phase is also linear in the pass band.


Magnitude Response of Filter



Filtering a Real Signal I

Consider a data file that contains a timestamp and speed in *km/h*. We will convert it to **m/s** first.






Filtering a Real Signal II

```
csv_file = '../Data/vel.csv';
data = readtable(csv_file);
data.Time = data.Time - data.Time(1);
% Convert the velocity data to m/s
velocity_ms = data.Message * 1000 / 3600;
```

Compute Fourier Transform using FFT and Plot Magnitude Spectrum, we plot the magnitude spectrum in Decibel (20*log10) for clarity.

Filtering a Real Signal III




Filtering a Real Signal IV

```
% Compute the Fourier transform of the velocity data
fs = 1 / mean(diff(data.Time));  % sampling frequency
velocity_fft = fft(velocity_ms);

% Plot the magnitude spectrum
f = figure;
f.Position = [ 810         819        1320         419];
plot((0:length(velocity_fft)-1) * fs / length(velocity_fft), 20*log10(abs(velocity_fft)));
```

Filtering a Real Signal V



Filtering a Real Signal VI

```
% Compute the Fourier transform of the velocity data
fs = 1 / mean(diff(data.Time));  % sampling frequency
velocity_fft = fft(velocity_ms);

% Plot the phase spectrum
f = figure;
f.Position = [ 810         819        1320         419];
plot((0:length(velocity_fft)-1) * fs / length(velocity_fft), angle(velocity_fft));
```

Now, we design a filter

Filtering a Real Signal VII


```
cutoff_freq = 5;  % Hz
order = 4;

% Normalize the cutoff frequency to the Nyquist frequency
% Design the low-pass filter
[b, a] = butter(order, cutoff_freq / (fs/2), 'low')


% Apply the filter to the velocity data
velocity_filtered = filter(b, a, velocity_ms);
```

b = [0.0003, 0.0013, 0.0019, 0.0013, 0.0003]
a = [1.0000, -3.2380, 3.9911, -2.2127, 0.4647]


Filtering a Real Signal VIII



Filtering a Real Signal IX



Filtering a Real Signal X



Full code at https://github.com/rahulbhadani/CPE381_FA26/blob/main/Code/Ch05_speed_fourier.m

Time-shift Properties

$$x(t \pm t_0) \Leftrightarrow X(\Omega)e^{\pm j\Omega t_0}$$

Differentiation Property

$$\frac{d^N x(t)}{dt^N} \Leftrightarrow (j\Omega)^N X(\Omega)$$

Integration Property

$$\int_{-\infty}^{t} x(\sigma)d\sigma \Leftrightarrow \frac{X(\Omega)}{j\Omega} + \pi X(0)\delta(\Omega)$$

where $X(0) = \int_{-\infty}^{\infty} x(t)dt$

Integration Property

Blank space for calculation

Integration Property

Blank space for calculation

Integration Property

Blank space for calculation

Example 7: Fourier Transform of Triangular Pulse

$$x(t) = r(t) - 2r(t-1) + r(t-2)$$

Find the Fourier transform of $x(t)$ using the derivative property.

Example 7: Fourier Transform of Triangular Pulse

Blank space for calculation

Fourier Optics

https://www.youtube.com/watch?v=EGYVquku8r4