

TUSCAN 2K MONITOR

TCL Z80 ASSEMBLER PAGE 0007

ADDR	CODE	SIMT	SOURCE	STATEMENT	
F951	FE04	0350	CP	EOT	
F953	2813	0351	JR	Z,US80	;EOT
F955	FE0A	0352	CP	LF	
F957	28E9	0353	JR	Z,VDUDEL	;LF, WAIT FOR OPERATION
F959	FE1B	0354	CP	ESC	
F95B	28E5	0355	JR	Z,VDUDEL	;SCROLL
F95D	3A4100	0356	LD	A,(CURPOS)	;SEE IF LINE WRAP ROUND
F960	3C	0357	INC	A	
F961	FE40	0358	CP	64	;IE 64 CHARS ON ROW
F963	28D9	0359	JR	Z,CHAR0	;YES, WAIT FOR AUTO CRLF
F965	324100	0360	LD	(CURPOS),A	;ELSE UPDATE CURSOR POSITION
F968	3A0300	0361	LD	A,(IOBYTE)	;SEE IF 2MHZ OR 4MHZ
F96B	E630	0362	AND	30H	;GET CON BITS
F96D	FE20	0363	CP	20H	;TEST FOR 4MHZ
F96F	20D4	0364	JR	NZ,RESTRI	;2MHZ, NO MORE DELAY
F971	3E08	0365	LD	A,8	;WAIT ABOUT 40US
F973	3D	0366	US40: DEC	A	
F974	20ED	0367	JR	NZ,US40	
F976	18CD	0368	JR	RESTRI	;RESTORE REGS
		0369			
F978	F5	0370	DBMS: PUSH	AF	; (B)MS DELAY ROUTINE
F979	3A0300	0371	DLMS: LD	A,(IOBYTE)	;DELAY COUNT IS DEPENDANT ON
F97C	E630	0372	AND	30H	;PROCESSOR SPEED
F97E	FE20	0373	CP	20H	;TEST FOR 4MHZ
F980	3EF6	0374	LD	A,246	;DELAY COUNT FOR 4MHZ (1 WAIT)
F982	2802	0375	JR	Z,DLOOP	;IS 4MHZ
F984	3E79	0376	LD	A,121	;DELAY COUNT FOR 2MHZ (NO WAIT)
F986	3D	0377	DLOOP: DEC	A	
F987	20FD	0378	JR	NZ,DLOOP	
F989	10EE	0379	DJNZ	DLMS	;REPEAT (B) TIMES
F98B	F1	0380	POP	AF	
F98C	C9	0381	RET		
		0382			
F98D	DB06	0383	RSSTK: IN	A,(RSHS)	;GET HANDSHAKE BIT
F98F	E601	0384	AND	1H	
F991	28FA	0385	JR	Z,RSSTK	;WAIT FOR NOT BUSY
F993	DB00	0386	IN	A,(RSS)	;GET UART STATUS
F995	E610	0387	AND	10H	;TBMT?
F997	28F4	0388	JR	Z,RSSTK	;NO
F999	79	0389	LD	A,C	;GET CHAR
F99A	D300	0390	OUT	(RSDO),A	;SEND IT
F99C	C1	0391	POP	BC	
F99D	C9	0392	RET		
		0393			
F99E	CD00D4	0394	MMSTK: CALL	MMOUT	
F9A1	C1	0395	POP	BC	
F9A2	C9	0396	RET		
		0397			
		0398			;LIST - ROUTINE TO OUTPUT A CHARACTER TO THE LIST DEVICE
		0399			;INPUTS - A= CHARACTER TO BE PRINTED
		0400			;OUTPUTS - NONE
		0401			;DESTROYS - FLAGS
		0402			
F9A3	C5	0403	LIST: PUSH	BC	
F9A4	4F	0404	LD	C,A	
F9A5	3A0300	0405	LD	A,(IOBYTE)	;SEE WHICH PRINTER TO USE
F9A8	E6C0	0406	AND	0C0H	;GET PRINTER BITS
F9AA	28E1	0407	JR	Z,RSSTK	;RS232