

TUSCAN 2K MONITOR
ADDR CODE

SIMT SOURCE STATEMENT

TCL Z80 ASSEMBLER PAGE 0021

```

1162 ; DISPLACED OP CODE
1163 ;
1164 ;AN INACTIVE BREAKPOINT HAS THE HIGH ORDER ADDRESS FIELD
1165 ;SET TO THE START OF THE MONITOR (0F8H). THIS ELIMINATES
1166 ;THE NEED TO TEST FOR ACTIVE BREAKPOINTS WHEN THEY ARE SET.
1167 ;
1168 CLRBP: CALL PARAM ;GET ADDRESS IF PRESENT
1169 LD B,NBP ;CTR OF ENTRIES
1170 LD IX,BPTAB ;PTR TO TABLE
1171 JR C,CLRAL ;NO ADDR,CLEAR ALL BPTS
1172 CLRSRC: LD E,(IX) ;PICK UP ADDR FROM TABLE
1173 LD D,(IX+1) ;INTO DE
1174 CALL DPCMP ;SEE IF ADDR TO DELETE
1175 JR Z,CLEAR ;YES
1176 INC IX ;ELSE MOVE ON TO NEXT ENTRY
1177 INC IX
1178 INC IX
1179 DJNZ CLRSRC ;IF IT EXISTS
1180 ;
1181 LSTBPT: LD B,NBP ;ELSE LIST ACTIVE BPTS
1182 LD DE,BPTAB
1183 LSTB: LD A,(DE) ;GET ADDR TO HL
1184 LD L,A
1185 INC DE
1186 LD A,(DE)
1187 LD H,A
1188 INC DE
1189 INC DE
1190 CP MONPAG ;ACTIVE?
1191 JR Z,LASTB ;NO,SO DONE
1192 CALL PRTHLSP ;PRINT ADDR
1193 DJNZ LSTB ;LIST NEXT
1194 LASTB: JP CRLF
1195 ;
1196 CLEAR: DEC B ;CTR OF ENTRIES TO MOVE
1197 LD A,B
1198 ADD A,A ;NEED TO MOVE B*3
1199 ADD A,B
1200 LD C,A ;BC=CTR
1201 LD B,0
1202 PUSH IX
1203 POP DE ;DE = ADDR OF FREE ENTRY
1204 JR Z,NOMOVE ;IF BC=0 NO NEED TO MOVE
1205 LD H,D ;HL=ADDR OF NEXT ENTRY
1206 LD L,E
1207 INC HL
1208 INC HL
1209 INC HL
1210 LDIR ;MOV TABLE DOWN ONE ENTRY
1211 NOMOVE: LD A,MONPAG ;RESET LAST BPT IN TABLE
1212 INC DE
1213 LD (DE),A ;BY SETTING PAGE ADDR
1214 JR LSTBPT ;LIST ACTIVE BPTS
1215 ;
1216 CLRAL: INC IX ;PTR TO TABLE (HI ADDR BYTE)
1217 LD DE,3 ;LENGTH OF ENTRY
1218 LD A,MONPAG ;INACTIVE FLAG,B=f OF ENTRIES
1219 CLRBPN:LD (IX),A ;RESET BREAKPOINT

```