

TUSCAN 2K MONITOR TCL Z80 ASSEMBLER PAGE 0022

ADDR	CODE	STMT	SOURCE STATEMENT
FD55	DD19	1220	ADD IX,DE ;MOVE PTR TO NEXT
FD57	10F9	1221	DJNZ CLRBP
FD59	C9	1222	RET
		1223	;
		1224	SETBPT - FUNCTION TO SET A BREAKPOINT. THE COMMAND FORMAT
		1225	IS :
		1226	BNNN WHERE NNN IS THE ADDRESS OF THE
		1227	BREAKPOINT TO BE SET.
		1228	B LISTS ALL BREAKPOINTS CURRENTLY
		1229	ACTIVE.
		1230	BREAKPOINTS ARE LISTED ON ONE LINE AS HEX ADDRESSES SEPARATED
		1231	BY SPACES.
		1232	;
FD5A	CDF4FB	1233	SETBPT: CALL PARAM ;GET ADDR TO SET (IF ANY)
FD5D	38BB	1234	JR C,LSTBPT ;NONE SO LIST ALL BPTS
FD5F	DD214F00	1235	LD IX,BPTAB ;PTR TO TABLE
FD63	0608	1236	LD B,NBP ;CTR OF ENTRIES
FD65	DD5E00	1237	SETB: LD E,(IX) ;GET TABLE ADDR TO DE
FD68	DD5601	1238	LD D,(IX+1)
FD6B	7A	1239	LD A,D ;SEE IF FOUND A
FD6C	FEF8	1240	CP MONPAG ;FREE ENTRY
FD6E	2815	1241	JR Z,SETIT ;YES,SET BPT
FD70	CD24FB	1242	CALL DPCMP ;SEE IF ALREADY SET
FD73	28A5	1243	JR Z,LSTBPT ;YES,DON'T BOTHER AGAIN
FD75	DD23	1244	INC IX ;BUMP PTR TO NEXT ENTRY
FD77	DD23	1245	INC IX
FD79	DD23	1246	INC IX
FD7B	10E8	1247	DJNZ SETB
FD7D	11C5FF	1248	LD DE,ALLSET ;CAN'T SET ANY MORE
FD80	CDADFA	1249	CALL BUFFCR ;SINCE TABLE IS FULL
FD83	1895	1250	JR LSTBPT ;LIST BPTS ACTIVE
		1251	;
FD85	DD7500	1252	SETIT: LD (IX),L ;STORE BPT ADDR
FD88	DD7401	1253	LD (IX+1),H ;IN TABLE
FD8B	188D	1254	JR LSTBPT ;THEN LIST ALL
		1255	;
		1256	FILL -FUNCTION TO FILL AN AREA OF MEMORY WITH A BYTE
		1257	THE COMMAND FORMAT IS :
		1258	FS,F,B WHERE S IS THE START ADDR
		1259	F IS THE FINNISH ADDR
		1260	AND B IS THE BYTE VALUE
		1261	;
FD8D	CD53FC	1262	FILL: CALL PCHECK ;GET PARAMETERS 1 & 2
FD90	FE2C	1263	CP ;3RD PARAMETER THERE?
FD92	C2DEFB	1264	FERR: JP NZ,PARER ;NO,ERROR
FD95	CDF4FB	1265	CALL PARAM ;GET IT
FD98	7D	1266	LD A,L ;USE AS FILL BYTE
FD99	2A4A00	1267	LD HL,(PAR1) ;GET START ADDR
FD9C	EB	1268	EX DE,HL ;INTO DE
FD9D	2A4C00	1269	LD HL,(PAR2) ;END ADDR TO HL
FDA0	12	1270	FILLM: LD (DE),A ;PUT BYTE INTO MEMORY
FDA1	CD24FB	1271	CALL DPCMP ;AT END YET?
FDA4	13	1272	INC DE
FDA5	20F9	1273	JR NZ,FILLM ;NOT YET
FDA7	C9	1274	RET
		1275	;
		1276	ASCII - FUNCTION TO INSERT ASCII CODES DIRECTLY INTO MEMORY
		1277	COMMAND FORMAT IS :