

## **Dataset collected from the accelerometers from Samsung Galaxy S smartphone**

### **Experiment and data collection information**

According to

<http://archive.ics.uci.edu/ml/datasets/Human+Activity+Recognition+Using+Smartphones>,

The experiments have been carried out with a group of 30 volunteers within an age bracket of 19-48 years. Each person performed six activities (WALKING, WALKING\_UPSTAIRS, WALKING\_DOWNSTAIRS, SITTING, STANDING, LAYING) wearing a smartphone (Samsung Galaxy S II) on the waist. Using its embedded accelerometer and gyroscope, we captured 3-axial linear acceleration and 3-axial angular velocity at a constant rate of 50Hz. The experiments have been video-recorded to label the data manually.

For each record in the dataset it is provided:

- Triaxial acceleration from the accelerometer (total acceleration) and the estimated body acceleration.
- Triaxial Angular velocity from the gyroscope.
- A 561-feature vector with time and frequency domain variables.
- Its activity label.
- An identifier of the subject who carried out the experiment.
- The value in each column other than subject and activity labels was averaged for each subject and activity.

### **Fields explanation**

Using the features info document from

<https://d396qusza40orc.cloudfront.net/getdata%2Fprojectfiles%2FUCI%20HAR%20Dataset.zip>,

the features selected for this database come from the accelerometer and gyroscope 3-axial raw signals tAcc-XYZ and tGyro-XYZ. These time domain signals (prefix 't' to denote time) were captured at a constant rate of 50 Hz. Then they were filtered using a median filter and a 3rd order low pass Butterworth filter with a corner frequency of 20 Hz to remove noise. Similarly, the acceleration signal was then separated into body and gravity acceleration signals (tBodyAcc-XYZ and tGravityAcc-XYZ) using another low pass Butterworth filter with a corner frequency of 0.3 Hz.

Subsequently, the body linear acceleration and angular velocity were derived in time to obtain Jerk signals (tBodyAccJerk-XYZ and tBodyGyroJerk-XYZ). Also the magnitude of these three-dimensional signals were calculated using the Euclidean norm (tBodyAccMag, tGravityAccMag, tBodyAccJerkMag, tBodyGyroMag, tBodyGyroJerkMag).

Finally a Fast Fourier Transform (FFT) was applied to some of these signals producing fBodyAcc-XYZ, fBodyAccJerk-XYZ, fBodyGyro-XYZ, fBodyAccJerkMag, fBodyGyroMag, fBodyGyroJerkMag. (Note the 'f' to indicate frequency domain signals).

These signals were used to estimate variables of the feature vector for each pattern:

'-XYZ' is used to denote 3-axial signals in the X, Y and Z directions.

tBodyAcc-XYZ

tGravityAcc-XYZ

tBodyAccJerk-XYZ

tBodyGyro-XYZ

tBodyGyroJerk-XYZ

tBodyAccMag

tGravityAccMag

tBodyAccJerkMag

tBodyGyroMag

tBodyGyroJerkMag

fBodyAcc-XYZ

fBodyAccJerk-XYZ

fBodyGyro-XYZ

fBodyAccMag

fBodyAccJerkMag

fBodyGyroMag

fBodyGyroJerkMag

The set of variables that were estimated from these signals are:

mean(): Mean value

std(): Standard deviation