

Active Noise Control of Speech in Headphones using Linear Prediction

Christian Claumarch, Kasper Kiis Jensen^{**}, Maxime Démurger,
Mikkel Krogh Simonsen, Oliver Palmhøj Jokumsen^{*}
Acoustics and Audio Technology Group 761

Introduction Active Noise Control (ANC) is a widely used technique in consumer headphones for attenuating noise. ANC is useful for attenuation of periodic noise e.g. machinery but has limited ability to attenuate quasiperiodic noise e.g. speech (50 Hz – 4000 Hz). This paper therefore focuses on improving attenuation of speech. Feedforward ANC systems are widely used, where an FIR-filter is adapted by a Filtered- x Least Mean Squares (FXLMS)-algorithm. The main problem when implementing ANC is delays in converters. A tested $\Sigma\Delta$ -converter has a delay of 225 μs – 900 μs . A Linear Prediction (LP) method combined with multirate processing is proposed to compensate for the introduced conversion delays.

Methods and Proposals A signal sampled at 192 kHz decimated to 48 kHz requires prediction of 10 samples. Cascaded Wiener filtering is therefore used to predict 10 samples \approx 225 μs at 48 kHz. The predicted signal is filtered using a control filter with adaptive coefficients. The optimization algorithm adapting the coefficients is an FXLMS algorithm [1]. The combined feedforward LP FXLMS consists of two blocks, the LP and the FXLMS which can function individually.

Speech is characterized as a quasiperiodic signal, which can be split into two main classes; voiced and unvoiced. Voiced sounds are characterized by a strong periodicity, with the fundamental frequency referred to as the pitch frequency (50 Hz – 500 Hz). Unvoiced sounds are characterized as stochastic. Speech is a non-stationary signal and can only be assumed Wide Sense Stationary (WSS) for periods of 20 ms – 30 ms [2]. These characteristics of speech allow for prediction of short time intervals.

Simulation Results The combined feedforward LP FXLMS system is found by simulation to have a 34 dB larger attenuation, when the delay is 10 samples, compared the system without LP. At frequencies above 400 Hz the attenuation of the feedforward FXLMS system drops, whereas the feedforward LP FXLMS system's attenuation is maintained above 20 dB up to 4000 Hz.

Discussion When listening to the output of the two ANC systems the difference in attenuation is clearly distinguishable. This shows that the concept of LP combined with FXLMS yields higher attenuation of speech in simulation. No real time implementation is attempted because the computational cost of the proposed LP is $>50,000$ instructions per sample. However Wiener filtering is used in speech encoding therefore real time implementation is possible.

References

- [1] Colin Hansen and Scott Snyder and Xiaojun Qiu and Laura Brooks and Danielle Moreau : *Active Control of Noise and Vibration*, CRC Press 2nd Edition 2012
- [2] Wai C. Chu: *Speech Coding Algorithms*, Wiley 1st Edition 2013