GATE ASSIGNMENT 4

Dishank Jain
AI20BTECH11011

Download latex-tikz codes from

https://github.com/Dishank422/EE3900/blob/main/Gate−Assignment4/latex_code.tex

1 EC 1999 Q.2.1

The Fourier representation of an impulse train represented by $s(t) = \sum_{n=-\infty}^{\infty} \delta(t - nT_0)$ is given by

(a) $\frac{1}{T_0} \sum_{n=-\infty}^{\infty} \exp\left(-\frac{j2\pi nt}{T_0}\right)$

(b) $\frac{1}{T_0} \sum_{n=-\infty}^{\infty} \exp\left(-\frac{j\pi nt}{T_0}\right)$

(c) $\frac{1}{T_0} \sum_{n=-\infty}^{\infty} \exp\left(\frac{j\pi nt}{T_0}\right)$

(d) $\frac{1}{T_0} \sum_{n=-\infty}^{\infty} \exp\left(\frac{j2\pi nt}{T_0}\right)$

2 Solution

Lemma 2.1. *Any periodic signal x(t) with period T_0 can be written as*

$$x(t) = \sum_{n=-\infty}^{\infty} a_n \exp\left(\frac{j2\pi nt}{T_0}\right) \tag{2.0.1}$$

where, a_n is given by

$$a_n = \frac{1}{T_0} \int_{T_0} x(t) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt \tag{2.0.2}$$

Proof. We shall verify equation 2.0.2.

$$a_n = \frac{1}{T_0} \int_{T_0} x(t) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt \tag{2.0.3}$$

$$= \frac{1}{T_0} \int_{T_0} \left(\sum_{m=-\infty}^{\infty} a_m \exp\left(\frac{j2\pi mt}{T_0}\right)\right) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt \tag{2.0.4}$$

$$= \frac{1}{T_0} \sum_{m=-\infty}^{\infty} \int_{T_0} a_m \left(\exp\frac{j2\pi mt}{T_0}\right) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt \tag{2.0.5}$$

When $m = n$,

$$\int_{T_0} a_m \exp\left(\frac{j2\pi mt}{T_0}\right) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt = \int_{T_0} a_n \tag{2.0.6}$$

$$= T_0 a_n \tag{2.0.7}$$

When $m \neq n$,

$$\int_{T_0} a_m \exp\left(\frac{j2\pi mt}{T_0}\right) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt \tag{2.0.8}$$

$$= a_m \int_{T_0} \exp\left(\frac{j2\pi(m-n)t}{T_0}\right) dt \tag{2.0.9}$$

Since $\exp\left(\frac{j2\pi(m-n)t}{T_0}\right)$ is periodic with period $\frac{T_0}{m-n}$, it's integral over any time interval of length $\frac{T_0}{m-n}$ or any integral multiple of $\frac{T_0}{m-n}$ will be 0. Therefore, when $m \neq n$,

$$\int_{T_0} a_m \exp\left(\frac{j2\pi mt}{T_0}\right) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt = 0 \tag{2.0.10}$$

Continuing from equation 2.0.5,

$$a_n = \frac{1}{T_0} \sum_{m=-\infty}^{\infty} \int_{T_0} a_m \exp\left(\frac{j2\pi mt}{T_0}\right) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt \tag{2.0.11}$$

$$= \frac{1}{T_0}(T_0 a_n) = a_n \tag{2.0.12}$$

□

We observe that $s(t)$ is periodic with period T_0. Thus it's Fourier representation as a sum of complex exponents is given by

$$s(t) = \sum_{n=-\infty}^{\infty} a_n \exp\left(\frac{j2\pi nt}{T_0}\right) \tag{2.0.13}$$

where, a_n can be calculated as

$$a_n = \frac{1}{T_0} \int_{-\frac{T_0}{2}}^{\frac{T_0}{2}} s(t) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt \tag{2.0.14}$$

Between $-\frac{T_0}{2}$ and $\frac{T_0}{2}$, we can say that $s(t) = \delta(t)$.

$$\implies a_n = \frac{1}{T_0} \int_{-\frac{T_0}{2}}^{\frac{T_0}{2}} \delta(t) \exp\left(-\frac{j2\pi nt}{T_0}\right) dt \quad (2.0.15)$$

$$= \frac{1}{T_0} \quad (2.0.16)$$

$$\implies s(t) = \frac{1}{T_0} \sum_{n=-\infty}^{\infty} \exp\left(\frac{j2\pi nt}{T_0}\right) \quad (2.0.17)$$

Therefore option (d) is the correct option.