

Register [DaveW DitronIX]	Register ID	Description	Area	Function	IPEM S3-AI E36 Hex	HA/ESPHome Platform Phase
0x00	SoftReset	Software Reset	Status Registers E36		0x0000	
0x01	SysStatus0	System Status0	Status Registers E36	GetSysStatus0	0x0000	
0x02	SysStatus1	System Status1	Status Registers E36	GetSysStatus1	0x0000	
0x03	FuncEn0	Function Enable0	Status Registers E36		0x0000	
0x04	FuncEn1	Function Enable1	Status Registers E36		0x0000	
0x07	ZXConfig	Zero-Crossing Config	Status Registers		0x0001	
0x08	SagTh	Voltage Sag Th	Status Registers	vSagTh	0x0001	
0x09	PhaseLossTh	Voltage Phase Losing Th	Status Registers		0x0000	
0x0A	INWarnTh0	N Current Line Th	Status Registers		0xFFFF	
0x0A	INWarnTh	Neutral Current (Calculated) Warning Threshold	Status Registers E36			
0x0B	INWarnTh1	Voltage ADC Th	Status Registers E36		0xFFFF	
0x0C	THDNUTH	Voltage THD Th	Status Registers E36		0xFFFF	
0x0D	THDNITH	Current THD Th	Status Registers E36		0xFFFF	
0x0E	DMACtrl	DMA Int. Control	Status Registers E36	FreqLoThresh	0x7E44	
0x0F	LastSPIData	Last Read/Write SPI Value	Status Registers E36		0x7E44	
0x10	DetectCtrl	Current Detect Controller	Low Power Registers		x	
0x11	DetectTh1	Channel CT1 Current Threshold in Detection Mode	Low Power Registers		x	phase_a
0x12	DetectTh2	Channel CT2 Current Threshold in Detection Mode	Low Power Registers		x	phase_b
0x13	DetectTh3	Channel CT3 Current Threshold in Detection Mode	Low Power Registers		x	phase_c
0x14	PMOffsetCT1	Ioffset for Phase A in Partial Measurment Mode	Low Power Registers		x	phase_a
0x15	PMOffsetCT2	Ioffset for Phase B in Partial Measurment Mode	Low Power Registers		x	phase_b
0x16	PMOffsetCT3	Ioffset for Phase C in Partial Measurment Mode	Low Power Registers		x	phase_c
0x17	PMPGA	OGAgain Configuration in in Partial Measurment Mode	Low Power Registers		x	
0x18	PMIRMSCT1	irms for Phase A in Partial Measurment Mode	Low Power Registers		x	phase_a
0x19	PMIRMSCT2	irms fDetectTh3r Phase B in Partial Measurment Mode	Low Power Registers		x	phase_b
0x1A	PMIRMSCT3	irms for Phase C in Partial Measurment Mode	Low Power Registers		x	phase_c
0x1B	PMConfig	Measure Configuraition in Partial Measurement Mode	Low Power Registers		x	
0x1C	PMAvgSamples	Number of 8k samples to be averages in RMS/mean computation	Low Power Registers		x	
0x1D	PMIRMSLSB	LSB bits of PMRRrms (A/B/C)	Low Power Registers		x	
0x30	ConfigStart	Configuration Start	Configuration Registers E36		0x5678	
0x31	PLConstH	High Word of PL_Constant	Configuration Registers		0x861	
0x32	PLConstL	Low Word of PL_Constant	Configuration Registers		0xC468	
0x33	MMode0	Metering Mode Config. Mains Frequency	Configuration Registers	lineFreq	0x185	line_frequency
0x34	MMode1	Metering Mode Config. PGA Gain Configuration for Current Channels	Configuration Registers	pgagain	0x555	gain_pga
0x35	PStartTh	Startup Power Th (P)	Configuration Registers		0x0000	
0x36	QStartTh	Startup Power Th (Q)	Configuration Registers		0x0000	
0x37	SStartTh	Startup Power Th (S)	Configuration Registers		0x0000	
0x38	PPhaseTh	Startup Power Accum Th (P)	Configuration Registers		0x0000	
0x39	QPhaseTh	Startup Power Accum Th (Q)	Configuration Registers		0x0000	
0x3A	SPhaseTh	Startup Power Accum Th (S)	Configuration Registers		0x0000	
0x3B	CSZero	Checksum 0	Configuration Registers E36		0x41C5	
0x40	CalStart	Cal Start	Calibration Registers E36		0x5678	
0x41	PoffsetCT1	CT1 Line Power Offset (P)	Calibration Registers		0x0000	phase_a
0x42	QoffsetCT1	CT1 Line Power Offset (Q)	Calibration Registers		0x0000	phase_a
0x43	PoffsetCT2	CT2 Line Power Offset (P)	Calibration Registers		0x0000	phase_b
0x44	QoffsetCT2	CT2 Line Power Offset (Q)	Calibration Registers		0x0000	phase_b
0x45	PoffsetCT3	CT3 Line Power Offset (P)	Calibration Registers		0x0000	phase_c
0x46	QoffsetCT3	CT3 Line Power Offset (Q)	Calibration Registers		0x0000	phase_c
0x47	PQGainCT1	CT1 Line Calibration Gain	Calibration Registers		0x0000	phase_a
0x48	PhiCT1	CT1 Line Calibration Angle	Calibration Registers		0x0000	phase_a
0x49	PQGainCT2	CT2 Line Calibration Gain	Calibration Registers		0x0000	phase_b
0x4A	PhiCT2	CT2 Line Calibration Angle	Calibration Registers		0x0000	phase_b
0x4B	PQGainCT3	CT3 Line Calibration Gain	Calibration Registers		0x0000	phase_c
0x4C	PhiCT3	CT3 Line Calibration Angle	Calibration Registers		0x0000	phase_c
0x4D	CSOne	Checksum 1	Calibration Registers E36		0x0000	
0x50	HaRMStart	Harmonic Cal Start	Fundamental Harmonic Energy Calibration Registers E36		0x5678	
0x51	PoffsetCT1F	CT1 Fund Power Offset (P)	Fundamental Harmonic Energy Calibration Registers		0x0000	phase_a
0x52	PoffsetCT2F	CT2 Fund Power Offset (P)	Fundamental Harmonic Energy Calibration Registers		0x0000	phase_b
0x53	PoffsetCT3F	CT3 Fund Power Offset (P)	Fundamental Harmonic Energy Calibration Registers		0x0000	phase_c
0x54	PGainCT1F	CT1 Fund Power Gain (P)	Fundamental Harmonic Energy Calibration Registers		0x0000	phase_a
0x55	PGainCT2F	CT2 Fund Power Gain (P)	Fundamental Harmonic Energy Calibration Registers		0x0000	phase_b
0x56	PGainCT3F	CT3 Fund Power Gain (P)	Fundamental Harmonic Energy Calibration Registers		0x0000	phase_c
0x57	CSTwo	Checksum 2	Fundamental Harmonic Energy Calibration Registers E36		0x0000	
0x60	AdjStart	Measurement Cal Start	Measurement Calibration Registers E36		0x5678	
0x61	UGainCT1	CT1 Voltage RMS Gain	Measurement Calibration Registers	_uGainCT1	0x4EE8	phase_a
0x62	IGainCT1	CT1 Current RMS Gain	Measurement Calibration Registers	_iGainCT1	0x82DC	phase_a
0x63	UoffsetCT1	CT1 Voltage Offset	Measurement Calibration Registers		0x0000	phase_a
0x64	IoffsetCT1	CT1 Current Offset	Measurement Calibration Registers		0x0000	phase_a
0x65	UGainCT2	CT2 Voltage RMS Gain	Measurement Calibration Registers	_uGainCT2	0x4EE8	phase_b
0x66	IGainCT2	CT2 Current RMS Gain	Measurement Calibration Registers	_iGainCT2	0x82DC	phase_b
0x67	UoffsetCT2	CT2 Voltage Offset	Measurement Calibration Registers		0x0000	phase_b
0x68	IoffsetCT2	CT2 Current Offset	Measurement Calibration Registers		0x0000	phase_b
0x69	UGainCT3	CT3 Voltage RMS Gain	Measurement Calibration Registers	_uGainCT3	0x4EE8	phase_c
0x6A	IGainCT3	CT3 Current RMS Gain	Measurement Calibration Registers	_iGainCT3	0x82DC	phase_c
0x6B	UoffsetCT3	CT3 Voltage Offset	Measurement Calibration Registers		0x0000	phase_c
0x6C	IoffsetCT3	CT3 Current Offset	Measurement Calibration Registers		0x0000	phase_c
0x6D	IgainN	N Current Gain	Measurement Calibration Registers E36		0xFD7F	phase_n
0x6E	IoffsetN	N Current Offset	Measurement Calibration Registers E36		0x0000	phase_n
0x6F	CSThree	Checksum 3	Measurement Calibration Registers E36		0x7A38	
0x80	APenergyT	Total Forward Active	Energy Registers	GetImportEnergy	x	
0x81	APenergyCT1	CT1 Forward Active	Energy Registers		x	phase_a
0x82	APenergyCT2	CT2 Forward Active	Energy Registers		x	phase_b
0x83	APenergyCT3	CT3 Forward Active	Energy Registers		x	phase_c
0x84	ANenergyT	Total Reverse Active	Energy Registers	GetExportEnergy	x	
0x85	ANenergyCT1	CT1 Reverse Active	Energy Registers	GetExportEnergy	x	phase_a

0x86	ANergyCT2	CT2 Reverse Active	Energy Registers	GetExportEnergy	x	phase_b
0x87	ANergyCT3	CT3 Reverse Active	Energy Registers	GetExportEnergy	x	phase_c
0x88	RPnergyT	Total Forward Reactive	Energy Registers	GetImportReactiveEnergy	x	
0x89	RPnergyCT1	CT1 Forward Reactive	Energy Registers	GetImportReactiveEnergy	x	phase_a
0x8A	RPnergyCT2	CT2 Forward Reactive	Energy Registers	GetImportReactiveEnergy	x	phase_b
0x8B	RPnergyCT3	CT3 Forward Reactive	Energy Registers	GetImportReactiveEnergy	x	phase_c
0x8C	RNergyT	Total Reverse Reactive	Energy Registers	GetExportReactiveEnergy	x	
0x8D	RNergyCT1	CT1 Reverse Reactive	Energy Registers	GetExportReactiveEnergy	x	phase_a
0x8E	RNergyCT2	CT2 Reverse Reactive	Energy Registers	GetExportReactiveEnergy	x	phase_b
0x8F	RNergyCT3	CT3 Reverse Reactive	Energy Registers	GetExportReactiveEnergy	x	phase_c
0x90	SAnergyT	Total Apparent Energy	Energy Registers	GetImportApparentEnergy	x	
0x91	SenergyCT1	CT1 Apparent Energy	Energy Registers	GetImportApparentEnergy	x	phase_a
0x92	SenergyCT2	CT2 Apparent Energy	Energy Registers	GetImportApparentEnergy	x	phase_b
0x93	SenergyCT3	CT3 Apparent Energy	Energy Registers	GetImportApparentEnergy	x	phase_c
0x94	SVnergyT	Total Apparent Energy (Arit)	Energy Registers E36		x	
0x95	EnStatus0	Metering Status 0	Energy Registers E36	GetMeterStatus0	0x0000	
0x96	EnStatus1	Metering Status 1	Energy Registers E36	GetMeterStatus1	0x0000	
0x98	SVmeanT	Total Apparent Energy (Vect)	Energy Registers E36		x	
0x99	SVmeanTLsb	LSB of Vector Sum	Energy Registers E36		x	
0xA0	APnergyTF	Total Forward Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	
0xA1	APnergyCT1F	CT1 Forward Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_a
0xA2	APnergyCT2F	CT2 Forward Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_b
0xA3	APnergyCT3F	CT3 Forward Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_c
0xA4	ANergyTF	Total Reverse Fund Energy	Fundamental Harmonic Energy Calibration Registers		x	
0xA5	ANergyCT1F	CT1 Reverse Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_a
0xA6	ANergyCT2F	CT2 Reverse Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_b
0xA7	ANergyCT3F	CT3 Reverse Fund. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_c
0xA8	APnergyTH	Total Forward Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	
0xA9	APnergyCT1H	CT1 Forward Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_a
0xAA	APnergyCT2H	CT2 Forward Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_b
0xAB	APnergyCT3H	CT3 Forward Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_c
0xAC	ANergyTH	Total Reverse Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	
0xAD	ANergyCT1H	CT1 Reverse Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_a
0xAE	ANergyCT2H	CT2 Reverse Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_b
0xAF	ANergyCT3H	CT3 Reverse Harm. Energy	Fundamental Harmonic Energy Calibration Registers		x	phase_c
0xB0	PmeanT	Total Mean Power (P)	Power & Power Factor Registers		x	
0xB1	PmeanCT1	CT1 Mean Power (P)	Power & Power Factor Registers		x	phase_a
0xB2	PmeanCT2	CT2 Mean Power (P)	Power & Power Factor Registers		x	phase_b
0xB3	PmeanCT3	CT3 Mean Power (P)	Power & Power Factor Registers		x	phase_c
0xB4	QmeanT	Total Mean Power (Q)	Power & Power Factor Registers		x	
0xB5	QmeanCT1	CT1 Mean Power (Q)	Power & Power Factor Registers	GetReactivePowerCT	x	phase_a
0xB6	QmeanCT2	CT2 Mean Power (Q)	Power & Power Factor Registers	GetReactivePowerCT	x	phase_b
0xB7	QmeanCT3	CT3 Mean Power (Q)	Power & Power Factor Registers	GetReactivePowerCT	x	phase_c
0xB8	SmeanT	Total Mean Power (S)	Power & Power Factor Registers		x	
0xB9	SmeanCT1	CT1 Mean Power (S)	Power & Power Factor Registers	GetApparentPowerCT	x	phase_a
0xBA	SmeanCT2	CT2 Mean Power (S)	Power & Power Factor Registers	GetApparentPowerCT	x	phase_b
0xBB	SmeanCT3	CT3 Mean Power (S)	Power & Power Factor Registers	GetApparentPowerCT	x	phase_c
0xBC	PFmeanT	Mean Power Factor	Power & Power Factor Registers		x	
0xBD	PFmeanCT1	CT1 Power Factor	Power & Power Factor Registers	GetPowerFactorCT	x	phase_a
0xBE	PFmeanCT2	CT2 Power Factor	Power & Power Factor Registers	GetPowerFactorCT	x	phase_b
0xBF	PFmeanCT3	CT3 Power Factor	Power & Power Factor Registers	GetPowerFactorCT	x	phase_c
0xC0	PmeanTLsb	Lower Word (Tot. Act. Power)	Power & Power Factor Registers		x	
0xC1	PmeanCT1LSB	Lower Word (CT1 Act. Power)	Power & Power Factor Registers		x	phase_a
0xC2	PmeanCT2LSB	Lower Word (CT2 Act. Power)	Power & Power Factor Registers		x	phase_b
0xC3	PmeanCT3LSB	Lower Word (CT3 Act. Power)	Power & Power Factor Registers		x	phase_c
0xC4	QmeanTLsb	Lower Word (Tot. React. Power)	Power & Power Factor Registers		x	
0xC5	QmeanCT1LSB	Lower Word (CT1 React. Power)	Power & Power Factor Registers		x	phase_a
0xC6	QmeanCT2LSB	Lower Word (CT2 React. Power)	Power & Power Factor Registers		x	phase_b
0xC7	QmeanCT3LSB	Lower Word (CT3 React. Power)	Power & Power Factor Registers		x	phase_c
0xC8	SAmeanTLsb	Lower Word (Tot. App. Power)	Power & Power Factor Registers		x	
0xC9	SmeanCT1LSB	Lower Word (CT1 App. Power)	Power & Power Factor Registers		x	phase_a
0xCA	SmeanCT2LSB	Lower Word (CT2 App. Power)	Power & Power Factor Registers		x	phase_b
0xCB	SmeanCT3LSB	Lower Word (CT3 App. Power)	Power & Power Factor Registers		x	phase_c
0xD0	PmeanTF	Total Active Fund. Power	Funamental & Harmonic Power & V/I RMS Registers		x	
0xD1	PmeanCT1F	CT1 Active Fund. Power	Funamental & Harmonic Power & V/I RMS Registers		x	phase_a
0xD2	PmeanCT2F	CT2 Active Fund. Power	Funamental & Harmonic Power & V/I RMS Registers		x	phase_b
0xD3	PmeanCT3F	CT3 Active Fund. Power	Funamental & Harmonic Power & V/I RMS Registers		x	phase_c
0xD4	PmeanTH	Total Active Harm. Power	Funamental & Harmonic Power & V/I RMS Registers		x	
0xD5	PmeanCT1H	CT1 Active Harm. Power	Funamental & Harmonic Power & V/I RMS Registers		x	phase_a
0xD6	PmeanCT2H	CT2 Active Harm. Power	Funamental & Harmonic Power & V/I RMS Registers		x	phase_b
0xD7	PmeanCT3H	CT3 Active Harm. Power	Funamental & Harmonic Power & V/I RMS Registers		x	phase_c
0xD9	URMSCT1	CT1 RMS Voltage	Funamental & Harmonic Power & V/I RMS Registers		x	phase_a
0xDA	URMSCT2	CT2 RMS Voltage	Funamental & Harmonic Power & V/I RMS Registers		x	phase_b
0xDB	URMSCT3	CT3 RMS Voltage	Funamental & Harmonic Power & V/I RMS Registers		x	phase_c
0xDC	IRMSN	Calculated N RMS Current	Funamental & Harmonic Power & V/I RMS Registers		x	
0xDD	IRMSCT1	CT1 RMS Current	Funamental & Harmonic Power & V/I RMS Registers		x	phase_a
0xDE	IRMSCT2	CT2 RMS Current	Funamental & Harmonic Power & V/I RMS Registers		x	phase_b
0xDF	IRMSCT3	CT3 RMS Current	Funamental & Harmonic Power & V/I RMS Registers		x	phase_c
0xE0	PmeanTFLsb	Lower Word (Tot. Act. Fund. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	
0xE1	PmeanCT1FLSB	Lower Word (CT1 Act. Fund. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_a
0xE2	PmeanCT2FLSB	Lower Word (CT2 Act. Fund. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_b
0xE3	PmeanCT3FLSB	Lower Word (CT3 Act. Fund. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_c
0xE4	PmeanTHLSB	Lower Word (Tot. Act. Harm. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	
0xE5	PmeanCT1HLSB	Lower Word (CT1 Act. Harm. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_a
0xE6	PmeanCT2HLSB	Lower Word (CT2 Act. Harm. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_b
0xE7	PmeanCT3HLSB	Lower Word (CT3 Act. Harm. Power)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_c
0xE9	URMSCT1LSB	Lower Word (CT1 RMS Voltage)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_a
0xEA	URMSCT2LSB	Lower Word (CT2 RMS Voltage)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_b
0xEB	URMSCT3LSB	Lower Word (CT3 RMS Voltage)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_c
0xED	IRMSCT1LSB	Lower Word (CT1 RMS Current)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_a

0xE0	IRMSCT2LSB	Lower Word (CT2 RMS Current)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_b
0xEF	IRMSCT3LSB	Lower Word (CT3 RMS Current)	Funamental & Harmonic Power & V/I RMS Registers		x	phase_c
0xF1	THDNUCT1	CT1 Voltage THD+N	Peak Frequency Angle and Temperature Registers E36	GetVHarmCT	x	phase_a
0xF2	THDNUCT2	CT2 Voltage THD+N	Peak Frequency Angle and Temperature Registers E36	GetVHarmCT	x	phase_b
0xF3	THDNUCT3	CT3 Voltage THD+N	Peak Frequency Angle and Temperature Registers E36	GetVHarmCT	x	phase_c
0xF4	Reserved	Reserved Register			x	
0xF5	THDNICT1	CT1 Current THD+N	Peak Frequency Angle and Temperature Registers E36	GetCHarmCT	x	phase_a
0xF6	THDNICT2	CT2 Current THD+N	Peak Frequency Angle and Temperature Registers E36	GetCHarmCT	x	phase_b
0xF7	THDNICT3	V Current THD+N	Peak Frequency Angle and Temperature Registers E36	GetCHarmCT	x	phase_c
0xF8	Freq	Frequency	Peak Frequency Angle and Temperature Registers		x	frequency
0xF9	PAngleCT1	CT1 Mean Phase Angle	Peak Frequency Angle and Temperature Registers	GetPhaseCT	x	phase_a
0xFA	PAngleCT2	CT2 Mean Phase Angle	Peak Frequency Angle and Temperature Registers	GetPhaseCT	x	phase_b
0xFB	PAngleCT3	CT3 Mean Phase Angle	Peak Frequency Angle and Temperature Registers	GetPhaseCT	x	phase_c
0xFC	Temp	Measured Temperature	Peak Frequency Angle and Temperature Registers	GetTemperature	x	chip_temperature
0xFD	UangleCT1	CT1 Voltage Phase Angle	Peak Frequency Angle and Temperature Registers		x	phase_a
0xFE	UangleCT2	CT2 Voltage Phase Angle	Peak Frequency Angle and Temperature Registers		x	phase_b
0xFF	UangleCT3	CT3 Voltage Phase Angle	Peak Frequency Angle and Temperature Registers		x	phase_c
0x100	AI HR2	phase A, Current, Harmonic Ratio for 2-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x101	AI HR3	phase A, Current, Harmonic Ratio for 3-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x102	AI HR4	phase A, Current, Harmonic Ratio for 4-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x103	AI HR5	phase A, Current, Harmonic Ratio for 5-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x104	AI HR6	phase A, Current, Harmonic Ratio for 6-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x105	AI HR7	phase A, Current, Harmonic Ratio for 7-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x106	AI HR8	phase A, Current, Harmonic Ratio for 8-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x107	AI HR9	phase A, Current, Harmonic Ratio for 9-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x108	AI HR10	phase A, Current, Harmonic Ratio for 10-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x109	AI HR11	phase A, Current, Harmonic Ratio for 11-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x10A	AI HR12	phase A, Current, Harmonic Ratio for 12-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x10B	AI HR13	phase A, Current, Harmonic Ratio for 13-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x10C	AI HR14	phase A, Current, Harmonic Ratio for 14-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x10D	AI HR15	phase A, Current, Harmonic Ratio for 15-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x10E	AI HR16	phase A, Current, Harmonic Ratio for 16-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x10F	AI HR17	phase A, Current, Harmonic Ratio for 17-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x110	AI HR18	phase A, Current, Harmonic Ratio for 18-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x111	AI HR19	phase A, Current, Harmonic Ratio for 19-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x112	AI HR20	phase A, Current, Harmonic Ratio for 20-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x113	AI HR21	phase A, Current, Harmonic Ratio for 21-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x114	AI HR22	phase A, Current, Harmonic Ratio for 22-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x115	AI HR23	phase A, Current, Harmonic Ratio for 23-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x116	AI HR24	phase A, Current, Harmonic Ratio for 24-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x117	AI HR25	phase A, Current, Harmonic Ratio for 25-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x118	AI HR26	phase A, Current, Harmonic Ratio for 26-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x119	AI HR27	phase A, Current, Harmonic Ratio for 27-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x11A	AI HR28	phase A, Current, Harmonic Ratio for 28-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x11B	AI HR29	phase A, Current, Harmonic Ratio for 29-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x11C	AI HR30	phase A, Current, Harmonic Ratio for 30-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x11D	AI HR31	phase A, Current, Harmonic Ratio for 31-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x11E	AI HR32	phase A, Current, Harmonic Ratio for 32-th order component	Harmonic Fourier Analysis Results Registers		x	phase_a
0x11F	AI THD	phase A, Current, Total Harmonic Distortion Ratio	Harmonic Fourier Analysis Results Registers		x	phase_a
0x120	BI HR2	phase B, Current, Harmonic Ratio for 2-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x121	BI HR3	phase B, Current, Harmonic Ratio for 3-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x122	BI HR4	phase B, Current, Harmonic Ratio for 4-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x123	BI HR5	phase B, Current, Harmonic Ratio for 5-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x124	BI HR6	phase B, Current, Harmonic Ratio for 6-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x125	BI HR7	phase B, Current, Harmonic Ratio for 7-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x126	BI HR8	phase B, Current, Harmonic Ratio for 8-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x127	BI HR9	phase B, Current, Harmonic Ratio for 9-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x128	BI HR10	phase B, Current, Harmonic Ratio for 10-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x129	BI HR11	phase B, Current, Harmonic Ratio for 11-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x12A	BI HR12	phase B, Current, Harmonic Ratio for 12-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x12B	BI HR13	phase B, Current, Harmonic Ratio for 13-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x12C	BI HR14	phase B, Current, Harmonic Ratio for 14-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x12D	BI HR15	phase B, Current, Harmonic Ratio for 15-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x12E	BI HR16	phase B, Current, Harmonic Ratio for 16-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x12F	BI HR17	phase B, Current, Harmonic Ratio for 17-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x130	BI HR18	phase B, Current, Harmonic Ratio for 18-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x131	BI HR19	phase B, Current, Harmonic Ratio for 19-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x132	BI HR20	phase B, Current, Harmonic Ratio for 20-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x133	BI HR21	phase B, Current, Harmonic Ratio for 21-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x134	BI HR22	phase B, Current, Harmonic Ratio for 22-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x135	BI HR23	phase B, Current, Harmonic Ratio for 23-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x136	BI HR24	phase B, Current, Harmonic Ratio for 24-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x137	BI HR25	phase B, Current, Harmonic Ratio for 25-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x138	BI HR26	phase B, Current, Harmonic Ratio for 26-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x139	BI HR27	phase B, Current, Harmonic Ratio for 27-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x13A	BI HR28	phase B, Current, Harmonic Ratio for 28-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x13B	BI HR29	phase B, Current, Harmonic Ratio for 29-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x13C	BI HR30	phase B, Current, Harmonic Ratio for 30-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x13D	BI HR31	phase B, Current, Harmonic Ratio for 31-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x13E	BI HR32	phase B, Current, Harmonic Ratio for 32-th order component	Harmonic Fourier Analysis Results Registers		x	phase_b
0x13F	BI THD	phase B, Current, Total Harmonic Distortion Ratio	Harmonic Fourier Analysis Results Registers		x	phase_b
0x140	CI HR2	phase C, Current, Harmonic Ratio for 2-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x141	CI HR3	phase C, Current, Harmonic Ratio for 3-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x142	CI HR4	phase C, Current, Harmonic Ratio for 4-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x143	CI HR5	phase C, Current, Harmonic Ratio for 5-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x144	CI HR6	phase C, Current, Harmonic Ratio for 6-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x145	CI HR7	phase C, Current, Harmonic Ratio for 7-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x146	CI HR8	phase C, Current, Harmonic Ratio for 8-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x147	CI HR9	phase C, Current, Harmonic Ratio for 9-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x148	CI HR10	phase C, Current, Harmonic Ratio for 10-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c

[illegible]

0x1A3	CV_HR5	phase C, Voltage, Harmonic Ratio for 5-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1A4	CV_HR6	phase C, Voltage, Harmonic Ratio for 6-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1A5	CV_HR7	phase C, Voltage, Harmonic Ratio for 7-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1A6	CV_HR8	phase C, Voltage, Harmonic Ratio for 8-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1A7	CV_HR9	phase C, Voltage, Harmonic Ratio for 9-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1A8	CV_HR10	phase C, Voltage, Harmonic Ratio for 10-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1A9	CV_HR11	phase C, Voltage, Harmonic Ratio for 11-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1AA	CV_HR12	phase C, Voltage, Harmonic Ratio for 12-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1AB	CV_HR13	phase C, Voltage, Harmonic Ratio for 13-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1AC	CV_HR14	phase C, Voltage, Harmonic Ratio for 14-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1AD	CV_HR15	phase C, Voltage, Harmonic Ratio for 15-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1AE	CV_HR16	phase C, Voltage, Harmonic Ratio for 16-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1AF	CV_HR17	phase C, Voltage, Harmonic Ratio for 17-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B0	CV_HR18	phase C, Voltage, Harmonic Ratio for 18-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B1	CV_HR19	phase C, Voltage, Harmonic Ratio for 19-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B2	CV_HR20	phase C, Voltage, Harmonic Ratio for 20-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B3	CV_HR21	phase C, Voltage, Harmonic Ratio for 21-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B4	CV_HR22	phase C, Voltage, Harmonic Ratio for 22-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B5	CV_HR23	phase C, Voltage, Harmonic Ratio for 23-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B6	CV_HR24	phase C, Voltage, Harmonic Ratio for 24-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B7	CV_HR25	phase C, Voltage, Harmonic Ratio for 25-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B8	CV_HR26	phase C, Voltage, Harmonic Ratio for 26-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1B9	CV_HR27	phase C, Voltage, Harmonic Ratio for 27-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1BA	CV_HR28	phase C, Voltage, Harmonic Ratio for 28-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1BB	CV_HR29	phase C, Voltage, Harmonic Ratio for 29-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1BC	CV_HR30	phase C, Voltage, Harmonic Ratio for 30-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1BD	CV_HR31	phase C, Voltage, Harmonic Ratio for 31-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1BE	CV_HR32	phase C, Voltage, Harmonic Ratio for 32-th order component	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1BF	CV_THD	phase C, Voltage, Total Harmonic Distortion Ratio	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1C0	AI_FUND	phase A, Current, Fundamental component value	Harmonic Fourier Analysis Results Registers		x	phase_a
0x1C1	AV_FUND	phase A, Voltage, Fundamental component value	Harmonic Fourier Analysis Results Registers		x	phase_a
0x1C2	BI_FUND	Phase B, Current, Fundamental component value	Harmonic Fourier Analysis Results Registers		x	phase_b
0x1C3	BV_FUND	Phase B, Voltage, Fundamental component value	Harmonic Fourier Analysis Results Registers		x	phase_b
0x1C4	CI_FUND	Phase C, Current, Fundamental component value	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1C5	CV_FUND	Phase C, Voltage, Fundamental component value	Harmonic Fourier Analysis Results Registers		x	phase_c
0x1D0	DFT_SCALE	DFT Scale Configuration	Harmonic Fourier Analysis Results Registers		x	
0x1D1	DFT_CTRL	DFT Control Configuration	Harmonic Fourier Analysis Results Registers		x	