rooDial
Quick Installation Guide

- Download and install balenaEtcher from here: https://www.balena.io/etcher
- Download SD card image "rooExtend_v1.0.zip" from here:
  https://drive.google.com/drive/folders/1c72vVpuuVlIWJpB8flVAZlHXmW2KNd1k?usp=sharing
- Flash the image to the SD card.
- Enter the SD card into the RaspberryPi zero w.
- Power on RaspberryPi zero w and wait for apry. 1.5 minutes.
- Look for the WiFi created by RaspberryPi with name "rooExtend" and connect to it.
  Password is: 1234567890
- Open your Browser and go to http://rooExtend.local.
  If you get trouble with that go to http://10.0.0.5
- In the list of available WiFis displayed, your WiFi should show up.
  If not setup your WiFi to transmit at 2.4GHz. RaspberryPi cannot operate with 5GHz!
- Select your Wifi, enter the password and country and connect to it.
- Aprx. three minutes later you should be connected, and your Browser shall show the connected
  WiFi in green.
- The LED at the RaspberryPi should flash regularly. This means RaspberryPi is connected to roon.
  If it blinks make shure a roon core is available in your network!
- Open roon now (e.g. on your tablet or PC) and navigate to Settings→Extensions and look for the
  rooDial extension.
- Press the associated button to activate it.
  You now see the status line in red showing "unpaired" and "unlicensed".
- Get the Surface Dial
  - Enter batteries in the Surface Dial
  - Press the little button near the batteries until a light on the opposite side of the
    batteries begins to flash.
  - Wait until flashing stops.
  - Now the status line displays "Paired".
  - After a while when the Surface Dial is connected it should see "Connected" in the status
    line.
- Twist the Surface Dial and you will see a (L) or a (R). If you press the surface Dial the status line
  shows a (P). This means all is up and properly working.
- Goto https://sellcodes.com/7oWuMUUF and buy a license. You can buy a lifelong or a yearly
  recurring license. After Purchase the License number will show up. **SAVE IT**!
- Enter the license number in the settings dialog of the rooDial extension, select the license action
  "License" and save the settings.
- Have fun 😊