

# DRISHYAM

From Footage to Action

## User Flow Document

Key Journeys, Success & Failure Paths

Document ID: DRISHYAM-FLOW-001

Version: 1.0 | 13 September 2026

Confidential – For Development Use Only

## 1. First-Time Org Admin Setup

Start → Sign up / Accept invite → Create Organization → Create first Site → Add Camera (RTSP URL + test) → Configure detection classes & zones → Invite Operator → Go Live.

**Success:** Camera shows Online, test detection fires (or simulated), Operator receives invite.

**Failure paths:** Invalid RTSP → clear error + retry. Invite email fails → show resend. Zone drawing invalid → validation message.

## 2. Operator Daily Alert Handling

Login → Dashboard (alert feed + live grid) → New Critical alert appears (sound/badge) → Open alert → Play evidence clip → Decide:

- Real threat → Acknowledge → Escalate or Resolve after action → Optional note.
- False positive → Mark FP → Optional reason → Alert closed, feedback recorded.

**Edge cases:** Multiple simultaneous alerts → priority by severity + time. Clip not yet available → show “processing” + retry. Network drop → queue action and sync later.

## 3. Camera Offline Handling

Edge or backend detects no frames / heartbeat timeout → Camera status = offline → Health event created → Optional notification to SiteManager → When stream returns → status = online, event logged.

## 4. Multi-Site Manager View

Login as SiteManager → See only assigned sites → Filter alerts by site → Configure cameras only within scope → Cannot invite OrgAdmins or change org settings.

## 5. Mobile Alert Path

Push notification received → Tap → App opens alert detail (clip + metadata) → Acknowledge / Resolve / FP with one tap → Optional short note → Returns to feed.

## 6. Failure & Recovery Patterns

- API 401 → redirect to login / refresh token flow.
- API 403 → show “You don’t have permission” and stay on current page.
- Clip load failure → retry button + fallback thumbnail.
- WebSocket disconnect → auto-reconnect with exponential backoff + missed-alert poll on reconnect.
- Empty states: No cameras → CTA to add camera. No alerts → “All clear” illustration.