

capacitor-plugin-epson-epos

A capacitorjs plugin for Epson Pos Printer

Android

- ePos SDK: V2.29.0.a
- Only tested with TM_T20III Ethernet / TM_T20 USB

Roadmap

- Add iOS support

Install

```
npm install capacitor-plugin-epson-epos
npx cap sync
```

API

- `requestPermission()`
- `startDiscovery(...)`
- `stopDiscovery()`
- `print(...)`
- `finalizePrinter()`
- [Interfaces](#)
- [Type Aliases](#)

`requestPermission()`

```
requestPermission() => Promise<{ success: boolean; }>
```

Returns: `Promise<{ success: boolean; }>`

`startDiscovery(...)`

```
startDiscovery(options: DiscoveryOptions) => Promise<DiscoveryResult>
```

Param	Type
<code>options</code>	DiscoveryOptions

Returns: `Promise<DiscoveryResult>`

`stopDiscovery()`

```
stopDiscovery() => Promise<{ message: string; }>
```

Returns: `Promise<{ message: string; }>`

`print(...)`

```
print(options: PrintOptions) => Promise<{ success: boolean; }>
```

Param	Type
<code>options</code>	<code>PrintOptions</code>

Returns: `Promise<{ success: boolean; }>`

`finalizePrinter()`

```
finalizePrinter() => Promise<{ message: string; }>
```

Returns: `Promise<{ message: string; }>`

Interfaces

DiscoveryResult

Prop	Type
<code>printers</code>	<code>DiscoveryResultPrinter[]</code>

DiscoveryResultPrinter

Prop	Type
<code>PrinterName</code>	<code>string</code>
<code>Target</code>	<code>string</code>

DiscoveryOptions

Prop	Type	Default
timeout	number	10000 default value 10 seconds
broadcast	string	'255.255.255.255'
portType	EpsonEposPortType	'ALL'

PrintOptions

Prop	Type	Default
target	string	
instructions	PrintInstruction[]	
modelCode	EpsonEposPrinterSerie	
langCode	string	'ANK'

PrintInstruction

Prop	Type	Description
addHPosition	number	Integer from 0 to 65535
addLineSpace	number	Integer from 0 to 255
addFeedLine	number	Integer from 0 to 255
addFeedUnit	number	Integer from 0 to 255
addTextAlign	TextAlign	
addText	PrintText	
addTextStyle	PrintTextStyle	
addBase64Image	PrintBase64Image	
addBarcode	PrintBarcode	
addTextSize	[number, number]	
addHLine	PrintHorizontalLine	
addVLineBegin	PrintVerticalLine	
addVLineEnd	Pick<PrintVerticalLine, 'lineId'>	
addCut	Cut	
addPulse	PrintWithPulse	
addCommand	BinaryType	
addFeedPosition	FeedPosition	

Prop	Type	Description
addLayout	PrintLayout	

PrintText

Prop	Type
value	string
size	[number, number]
align	TextAlign
style	PrintTextStyle

PrintTextStyle

Prop	Type	Default
reverse	boolean	false
ul	boolean	false
em	boolean	false

PrintBase64Image

Prop	Type	Description
value	string	value Base64 image string
x	number	
y	number	
width	number	
height	number	

PrintBarcode

Prop	Type	Default
value	string	
type	BarcodeType	CODE_39
font	BarcodeFont	FONT_A
hri	BarcodeHri	HRI_BELOW
width	number	2 Integer from 2 to 6
height	number	100 Integer from 1 to 255

PrintHorizontalLine

Prop	Type
position	[number, number]
lineStyle	LineStyle

PrintVerticalLine

Prop	Type
position	number
lineStyle	LineStyle
lineId	number[]

PrintWithPulse

Prop	Type	Default
drawer	DrawerPin	2pin
time	PulseTime	100

PrintLayout

Prop	Type
type	LayoutType
width	number
height	number
marginTop	number
marginBottom	number
offsetCut	number
offsetLabel	number

Type Aliases

EpsonEposPortType

'ALL' | 'TCP' | 'BLUETOOTH' | 'USB'

TextAlign

'left' | 'right' | 'center'

BarcodeType

Types representing the allowed barcode types.

```
'UPC_A' | 'UPC_E' | 'EAN13' | 'JAN13' | 'EAN8' | 'JAN8' | 'ITF' | 'CODA_BAR' |  
'CODE_39' | 'CODE_93' | 'CODE_128' | 'CODE_128_AUTO' | 'GS1_128' |  
'GS1_DATA_BAR_OMNIDIRECTIONAL' | 'GS1_DATA_BAR_TRUNCATED' |  
'GS1_DATA_BAR_LIMITED' | 'GS1_DATA_BAR_EXPANDED'
```

BarcodeFont

Types representing the allowed barcode fonts.

```
'FONT_A' | 'FONT_B' | 'FONT_C' | 'FONT_D' | 'FONT_E'
```

BarcodeHri

Types representing the allowed barcode HRI (Human Readable Interpretation) positions.

```
'HRI_NONE' | 'HRI_ABOVE' | 'HRI_BELOW' | 'HRI_BOTH'
```

LineStyle

```
'thin' | 'medium' | 'thick' | 'thin_double' | 'medium_double' | 'thick_double'
```

Pick

From T, pick a set of properties whose keys are in the union K

```
{ [P in K]: T[P]; }
```

Cut

```
'cut_feed' | 'cut_no_feed' | 'cut_reserve' | 'full_cut_feed' |  
'full_cut_no_feed' | 'full_cut_reserve'
```

DrawerPin

```
'2pin' | '5pin'
```

PulseTime

```
'pulse_100' | 'pulse_200' | 'pulse_300' | 'pulse_300' | 'pulse_400' |  
'pulse_500'
```

FeedPosition

```
'peeling' | 'cutting' | 'current_tof' | 'next_tof'
```

LayoutType

'receipt' | 'receipt_bm' | 'label' | 'label_bm'

EpsonEposPrinterSerie

'TM_M10' | 'TM_M30' | 'TM_P20' | 'TM_P60' | 'TM_P60II' | 'TM_P80' | 'TM_T20' |
'TM_T60' | 'TM_T70' | 'TM_T81' | 'TM_T82' | 'TM_T83' | 'TM_T83III' | 'TM_T88' |
'TM_T90' | 'TM_T90KP' | 'TM_T100' | 'TM_U220' | 'TM_U330' | 'TM_L90' |
'TM_H6000' | 'TM_M30II' | 'TS_100' | 'TM_M50' | 'TM_T88VII' | 'TM_L90LFC' |
'EU_M30' | 'TM_L100' | 'TM_P20II' | 'TM_P80II' | 'TM_M30III' | 'TM_M50II' |
'TM_M55' | 'TM_U220II'