







File: Motor_Control.kicad_sch
M1: PWM PA6, DIR PB0, ENC PA15/PB3 (TIM3/TIM2)
M2: PWM PA7, DIR PB2, ENC PA8/PA9 (TIM3/TIM1)

MCU GPIO Breakout


File: GPIO_Breakout.kicad_sch
J8-J10: 2.54 mm headers for every spare STM32 pin.
Connected by global labels, so the block has no sheet pins.




File: Pi5_Interface.kicad_sch
J13 Pi UART (R12/R13 100R)
J14 Pi power via F2 isolation fuse

IMU Interface

File: IMU_Interface.kicad_sch
J11 I2C: SDA PB7, SCL PB6 (I2C1)
J12: INT PC4, RST PC5 (via R34/R35)
Global labels - no sheet pins




Input protection (J2 battery)
Reverse polarity: no P-FET - relies on the keyed XT30 (J2).
Why: the XT30 housing cannot be mated reversed, and this avoids an extra series part (and its heat) in the 4-8 A input path.
Not covered: a harness crimped backwards at the battery M8 lugs.
Mitigation: meter-check harness polarity (+ to J2 pin 2) before first power-up and after any harness rework.
C36: 220 uF 35 V bulk on +12V near J2.




File: Buck_5V_2A.kicad_sch
12 V to 5 V / 2 A buck - U3 (TPS54202)
Buck 12V-5V 6A PI



File: Buck_5V_6A.kicad_sch
12 V to 5 V / 6 A buck - U2 (TPSM63606)
Output is the +5V, 6A PI net (feeds the Pi via F2/J14)



File: Buck_5V_6A_AUX.kicad_sch



File: LDO_3V3.kicad_sch
3.3 V / 1 A LDO - U4
STM32 VDD and analog filter input supplied from +3V3


Delivery robot senior design - MCU core
Derived from ST NUCLEO-64 MB1136 rev C-04, sheets 2-3

Sheet: /
File: delivery_robot_1.kicad_sch
Title: STM32F091RC core - ready for peripherals

Size: A3	Date: 2026-09-24	Rev: 1.0
KiCad E.D.A. 10.0.6		Id: 1/11

5 V to 3.3 V LDO supply

Reusable sheet: VIN_5V input, VOUT_3V3 output, common GND



VOUT nominal = $0.8 \times (1 + 35.7k / 11.5k) = 3.284 \text{ V}$ (E96 values)
1 A is the TOTAL output budget for STM32 + IMU + other 3.3 V loads.

C2: require $\geq 4.7\mu\text{F}$ EFFECTIVE capacitance; selected part modeled at 8.8uF.
EN tied to IN. C3 sets noise reduction / soft start; C4 bypasses R1.

Layout: capacitors close to U1; EP pad 9 to GND copper and thermal vias.
Heat at 1 A: about 1.7 W at 5 V input; verify junction temperature on final PCB.

5 V motor / encoder supply branches BEFORE this sheet.
Adafruit BNO085 breakout: 3.3 V rail to VIN; 3Vo is an output, leave separate.
Bare BNO085: connect 3.3 V to VDD and VDDIO with its specified decoupling.

5 V to 3.3 V, 1 A total rail capacity

Senior Design


Sheet: /LDO Power/
File: LDO_3V3.kicad_sch

Title: LDO power supply – reusable sheet

Size: A4	Date: 2026–10–05	Rev: 1.0
KiCad E.D.A. 10.0.6		Id: 2/11

12 V – 5 V, 6A Buck Convertor

12 V to 5 V buck converter – TPSM63606 (U2)



Reusable sheet: VIN_12V input, VOUT_5V output, common GND
VOUT set by R4/R5 divider on FB; RT = R2; EN tied to VIN.
RBOOT shorted to CBOOT; SW left unconnected (inductor is inside the module).

12 V to 5 V buck, TPSM63606 (U2), 6 A rail

Senior Design

Sheet: /Buck 12V-5V 6A PI/

File: Buck_5V_6A.kicad_sch

Title: Buck converter – reusable sheet

Size: A4

Date: 2026-10-06


Rev: 1.0

KiCad E.D.A. 10.0.6

Id: 3/11

12 V – 5 V, 2A Buck Converter

12 V to 5 V buck converter – TPS54202 (U3)



Reusable sheet: VIN_12V input, VOUT_5V output, common GND

12 V to 5 V buck, TPS54202 (U3), 2 A rail
Senior Design

Sheet: /Buck 12V–5V 2A/
File: Buck_5V_2A.kicad_sch

Title: Buck converter – reusable sheet

Size: A4 Date: 2026–10–06


KiCad E.D.A. 10.0.6

Rev: 1.0

Id: 4/11

12 V – 5 V, 6A Buck Convertor

12 V to 5 V buck converter – TPSM63606 (U5)



Reusable sheet: VIN_12V input, VOUT_5V output, common GND.
VOUT set by R15/R16 divider on FB; RT = R14; EN tied to VIN.
RBOOT shorted to CBOOT; SW left unconnected (inductor is inside the module).

12 V to 5 V buck, TPSM63606 (U5), 6 A rail

Senior Design

Sheet: /Buck 12V-5V 6A AUX/

File: Buck_5V_6A_AUX.kicad_sch

Title: Buck converter – reusable sheet



Size: A4

Date: 2026-10-06

Rev: 1.0

KiCad E.D.A. 10.0.6

Id: 5/11




Senior Design

Sheet: /Pi 5 Interface/
File: Pi5_Interface.kicad_sch

Title: Raspberry Pi 5 interface – UART and power


Size: A4	Date: 2026-10-07	Rev: 1.0
KiCad E.D.A. 10.0.6		Id: 6/11



Senior Design


Sheet: /MCU GPIO Breakout/		
File: GPIO_Breakout.kicad_sch		
Title: STM32 GPIO breakout headers		
Size: A4	Date: 2026-10-07	Rev: 1.0
KiCad E.D.A. 10.0.6		Id: 7/11

Power rail indicators – one green LED per rail
(Lite-On LTST-C190KGKT, 0603, Vf 2.0 V typ)



LED current ~2–2.7 mA: $R = (V_{rail} - 2.0\text{ V}) / I$. +12V uses 4.75k for the 10.8–14.6 V battery range.
All resistors 0805; worst-case dissipation 34 mW (R17 at 14.6 V).

Debug LEDs – STM32 GPIO, active high (Lite-On LTST-C190KSKT yellow, 0603)



PA5 LED_USER: heartbeat
PB12 LED_PI_LINK: PI UART activity
PB13 LED_IMU: IMU data-ready
PB14 LED_MOTOR: motor running / fault
681R: $(3.3 - 2.1) / 681 = 1.8\text{ mA per pin}$




Senior Design

Sheet: /Power Indicators/
File: Power_Indicators.kicad_sch

Title: Power rail and debug indicator LEDs

Size: A4	Date: 2026-10-07	Rev: 1.0
KiCad E.D.A. 10.0.6	Id: 8/11	

Motor control – Cytron MDD20A dual-channel driver + two 37D encoder motors



STM32F091 PIN ASSIGNMENT

series	R	connector
MOTOR1_PWM	PA6 TIM3_CH1 R26 100R	J6 pin 1 → MDD20A PWM1
MOTOR1_DIR	PB0 GPIO R27 100R	J6 pin 2 → MDD20A DIR1
ENC1_A	PA15 TIM2_CH1 R28 100R	J7 pin 2 ← encoder A (yellow)
ENC1_B	PB3 TIM2_CH2 R29 100R	J7 pin 3 ← encoder B (white)
MOTOR2_PWM	PA7 TIM3_CH2 R30 100R	J16 pin 1 → MDD20A PWM2
MOTOR2_DIR	PB2 GPIO R31 100R	J16 pin 2 → MDD20A DIR2
ENC2_A	PA8 TIM1_CH1 R32 100R	J15 pin 2 ← encoder A (yellow)
ENC2_B	PA9 TIM1_CH2 R33 100R	J15 pin 3 ← encoder B (white)

Timers: TIM3 = both PWMs (≤ 20 kHz for MDD20A); TIM2 = encoder 1, TIM1 = encoder 2.
 ESD: USBL6-4SC6 arrays on motor 1 only – U6 on J6 PWM/DIR (VBUS +3V3), U7 on J7 encoder A/B (VBUS +5V 2A). Encoders powered from +5V, 2A;
 A/B pins must be 5 V tolerant (FT). Battery and motor leads wire directly to the MDD20A.

Senior Design


Sheet: /Motor Control/
 File: Motor_Control.kicad_sch

Title: Motor control – MDD20A driver and encoders

Size: A4 Date: 2026-10-08
 KiCad E.D.A. 10.0.6

Rev: 1.1
 Id: 9/11

Power test points



J5: one 2.54 mm header for every rail, ordered by voltage
1 GND
2 +3V3
3 +3.3VA (MCU analog)
4 +5V, 2A
5 +5V, 6A AUX
6 +12V (after F1)



TP3: GND loop for the scope ground clip.
+5V, 6A PI is on TP1 (PI 5 Interface sheet),
used in the PI bring-up check.

Senior Design		
Sheet: /Test Points/		
File: Test_Points.kicad_sch		
Title: Power test points		
Size: A4	Date: 2026-10-08	Rev: 1.1
KiCad E.D.A. 10.0.6		Id: 10/11

