EXERCISE 7.3

Solve the following problems by using Factor Theorem :

(1) Show that $\begin{vmatrix} x & a & a \\ a & x & a \\ a & a & x \end{vmatrix} = (x-a)^2(x+2a)$.

(2) Show that $\begin{vmatrix} b+c & a-c & a-b \\ b-c & c+a & b-a \\ c-b & c-a & a+b \end{vmatrix} = 8abc$.

(3) Solve $\begin{vmatrix} x+a & b & c \\ a & x+b & c \\ a & b & x+c \end{vmatrix} = 0.$

(4) Show that $\begin{vmatrix} b+c & a & a^2 \\ c+a & b & b^2 \\ a+b & c & c^2 \end{vmatrix} = (a+b+c)\ (a-b)\ (b-c)\ (c-a)$.

(5) Solve $\begin{vmatrix} 4-x & 4+x & 4+x \\ 4+x & 4-x & 4+x \\ 4+x & 4+x & 4-x \end{vmatrix} = 0$.

(6) Show that $\begin{vmatrix} 1 & 1 & 1 \\ x & y & z \\ x^2 & y^2 & z^2 \end{vmatrix} = (x-y)(y-z)(z-x)$.



7.3.4 Product of Determinants

While multiplying two matrices "row-by-column" rule alone can be followed. The process of interchanging the rows and columns will not affect the value of the determinant (by Property 1). Therefore we can also adopt the following procedures for multiplication of two determinants.

(i) Row by column multiplication rule
(ii) Row by row multiplication rule
(iii) Column by column multiplication rule
(iv) Column by row multiplication rule

Note 7.11

(i) If A and B are square matrices of the same order n, then $|AB| = |A|\,|B|$ holds.
(ii) In matrices, although $AB \neq BA$ in general, we do have $|AB| = |BA|$ always.

Example 7.27

Verify that $|AB| = |A|\,|B|$ if $A = \begin{bmatrix} \cos\theta & -\sin\theta \\ \sin\theta & \cos\theta \end{bmatrix}$ and $B = \begin{bmatrix} \cos\theta & \sin\theta \\ -\sin\theta & \cos\theta \end{bmatrix}$.

Solution

$$AB = \begin{bmatrix} \cos\theta & -\sin\theta \\ \sin\theta & \cos\theta \end{bmatrix} \begin{bmatrix} \cos\theta & \sin\theta \\ -\sin\theta & \cos\theta \end{bmatrix}.$$

07_11th-Maths-Vol2-Unit7.indd 34 16-12-2022 10:59:54