

ASSIGNMENT 3


Due 1:15 p.m. Sep 26, 2014

Before we delve into IA-32 programming, let us “peel open” a computer and look at its internal structure. In this assignment you will be introduced machine-language, a set of instructions executed by the CPU. To make this an especially valuable experience, you will be also asked to build a computer (through the technique of software-based *simulation*) on which you can execute your machine-language programs.

Part I: Machine Language Programming

In Part II of this assignment you will be asked to create a computer called the VSM (Very Simple Machine). The VSM runs programs written in the only language it directly understands—that is, VSM Language, or VSML for short.

The VSM Instruction Set Architecture. The VSM contains an *accumulator* – a special register in which information is put before the VSM uses that information in calculations or examines it in various ways. All information in the VSM is handled in terms of machine instructions, each of which is an unsigned 2-byte number (defined as *word* in the VSM) comprised of the *op-code* and the *operand*:



The bit pattern appearing in the op-code field indicates which of the elementary operations, such as READ or ADD, is requested by the instruction. The bit patterns found in the operand field provide more detailed information about the operation specified by the op-code. For example, in the case of an ADD operation, the information in the operand field indicates which memory location contains the data to be added to the Accumulator. The middle bit distinguishes between operands that are memory addresses and operands that are numbers. When the bit is set to 1, the operand represents a number.

A simple set of machine instructions for the VSM are listed in the table below:


Op-code	Mnemonic	Function
0000	EOC	End of code section
0001	LOAD	Load a word at a specific location in memory (or a number) into the accumulator.
0010	STORE	Store a word in the accumulator into a specific location in memory.
0011	READ	Read a word from the standard input into a specific location in memory.
0100	WRITE	Write a word at a specific location in memory to the standard output.
0101	ADD	Add a word at a specific location in memory (or a number) to the word in the accumulator, leaving the sum in the accumulator.
0110	SUB	Subtract a word at a specific location in memory (or a number) from the word in the accumulator, leaving the difference in the accumulator.
0111	MUL	Multiply the word in the accumulator by a word at a specific location in memory (or a number), leaving the product in the accumulator.
1000	DIV	Divide the word in the accumulator by a word at a specific location in memory (or a number), leaving the quotient in the accumulator.
1001	JUMP	Branch to a specific location in memory.
1010	JNEG	Branch to a specific location in memory if the accumulator is negative.
1011	JZERO	Branch to a specific location in memory if the accumulator is zero.
1100	HALT	Halt—i.e., the program has completed its task. This instruction writes the “*** Terminating VSM ***” message to the standard output.
1101	NOP	Undefined
1110	NOP	Undefined
1111	NOP	Undefined

The middle bit can be used only with the LOAD and four arithmetic operations (ADD, SUB, MUL, DIV). Here are some examples:

0001100000001010	<i>load 10 into accumulator</i>
0110100000000001	<i>decrement the word in the accumulator by 1</i>

The end of instructions of VSML programs must be indicated by the op-code 0, followed by the input data required by the program.

The VSM Memory Layout. The VSM supports a memory system comprised of 2,048 bytes (why?), partitioned into the *code* and *data* sections:



Before running a VSML program, it must be loaded into memory. The first instruction of every VSML program is always placed in location 0, the beginning of the code section. The data required by the program must be stored in the data section which begins at memory location 1024.

EXAMPLE 1: The following VSML program (**sum.vsm**) reads two numbers (x and y) from the standard input, and computes and prints their sum (z). In this example, $30 = 10 + 20$ will be output.

<u>Location</u>	<u>Instruction</u>	<u>Comment</u>
00	0011010000000000	<i>read x</i>
02	0011010000000010	<i>read y</i>
04	0001010000000000	<i>load x</i>
06	0101010000000010	<i>add y</i>
08	0010010000000100	<i>store z</i>
10	0100010000000100	<i>write z</i>
12	1100000000000000	<i>halt</i>
	0000000000000000	<i>end of code</i>
	0000000000001010	<i>10</i>
	00000000000010100	<i>20</i>

EXAMPLE 2: The following VSML program (**max.vsm**) reads two numbers (x and y) from the standard, and determines and prints the larger value. In this example, 13 will be output.

<u>Location</u>	<u>Instruction</u>	<u>Comment</u>
00	0011010000000000	<i>read x</i>
02	0011010000000010	<i>read y</i>
04	0001010000000000	<i>load x</i>
06	0110010000000010	<i>subtract y</i>
08	1010000000001110	<i>branch negative to 14</i>
10	0100010000000000	<i>write x</i>
12	1100000000000000	<i>halt</i>
14	0100010000000010	<i>write y</i>
16	1100000000000000	<i>halt</i>
	0000000000000000	<i>end of code</i>
	0000000000000111	<i>7</i>
	0000000000001101	<i>13</i>

To Do: Write a VSML program (**score.vsm**) which will read ten quiz scores and print the sum and the average of the best nine scores, that is, the lowest score is dropped.

Part II: The VSM Simulator

In this part you're going to build your own computer. You won't be soldering components together. Rather, you'll use the powerful technique of software-based simulation to create a software model of the VSM. Your VSM simulator will turn the computer you are using into a VSM, and you will actually be able to run, test and debug the VSML programs.

When you run your VSM simulator, it should begin by printing the message:

```
*** Initializing VSM ***
```

followed by the output from an input VSML program and terminate the simulator by displaying the message:

```
*** Terminating VSM ***
```

The program then displays the names and contents of each register as well as the contents of memory. Such a printout is often called a *computer dump*. A dump after executing a VSM program would show the actual values of instructions and data values at the moment execution terminated. To help you program your dump function, a sample dump format is shown below:

```
REGISTERS:
accumulator          0x0000
instructionCounter    0x0000
instructionRegister    0x0000

opCode                0x0
operand               0x0000

CODE:
  0  1  2  3  4  5  6  7  8  9
0000 00 00 00 00 00 00 00 00 00 00
0010 00 00 00 00 00 00 00 00 00 00
0020 00 00 00 00 00 00 00 00 00 00
0030 00 00 00 00 00 00 00 00 00 00
0040 00 00 00 00 00 00 00 00 00 00
0050 00 00 00 00 00 00 00 00 00 00
0060 00 00 00 00 00 00 00 00 00 00
0070 00 00 00 00 00 00 00 00 00 00
0080 00 00 00 00 00 00 00 00 00 00
0090 00 00 00 00 00 00 00 00 00 00
...

DATA:
  0  1  2  3  4  5  6  7  8  9
1024 00 00 00 00 00 00 00 00 00 00
1034 00 00 00 00 00 00 00 00 00 00
1044 00 00 00 00 00 00 00 00 00 00
1054 00 00 00 00 00 00 00 00 00 00
1064 00 00 00 00 00 00 00 00 00 00
1074 00 00 00 00 00 00 00 00 00 00
1084 00 00 00 00 00 00 00 00 00 00
1094 00 00 00 00 00 00 00 00 00 00
1104 00 00 00 00 00 00 00 00 00 00
1114 00 00 00 00 00 00 00 00 00 00
...
```

Here, **accumulator** represents the accumulator register. **instructionCounter** keeps track of the location in memory that contains the instruction being executed. **instructionRegister** contains the next instruction to be executed. You should not execute instructions directly from memory. Rather, you should transfer the next instruction to be executed from memory to **instructionRegister**. **opCode** indicates the operation currently being performed. **operand** represents the memory location on which the current

instruction operates. For the memory dump, only the first 100 bytes of the code section and the data section should be displayed in hexadecimal without the prefix **0x**.

To Do: Write a C program (**vsm.c**) which will simulate the VSM. Run your VSML programs from Part I using your simulator, namely, **sum.vsml**, **max.vsml**, and **score.vsml**. Your simulator should check for various types of errors, including:

- Illegal op-code
- Illegal memory reference (instruction and data)
- Division by zero

When a fatal error is detected, your simulator should print an error message such as:

```
*** Attempt to divide by zero ***  
*** VSM execution abnormally terminated ***
```

and should print a full computer dump.

The input VSML programs to your simulator should consist of one or more strings of sixteen 0's and 1's, each on a separate line. The **scanf()** function supports both octal and hexadecimal conversions, but, unfortunately, it does not support binary conversion of the input. So, you will need to write a C program (**binstr2hex.c**) which will read binary strings from the standard input and displays their hexadecimal equivalent to the standard output. For example, the following code is the hexadecimal equivalent to **sum.vsml** converted by **binstr2hex**:

```
3400  
3402  
1400  
5402  
2404  
4404  
C000  
0000  
000A  
0014
```

With this converter in place, your simulator should expect as input VSML programs entirely written in hexadecimal.

Part III: Extra Features

Add the following features to your VSM simulator for extra credits:

1. Allow the simulator to perform remainder calculations. This requires an additional VSML instruction.
2. Modify the simulator to handle string input.
3. Modify the simulator to handle string output.

Programming Notes

1. Compile your program with:

```
$ gcc -o binstr2hex binstr2hex.c  
$ gcc -o vsm vsm.c
```

2. Run your simulator with:

```
$ ./binstr2hex < prog.vsml | ./vsm
```

where **prog.vsml** is a VSML program. Note that we use a Unix pipe (**|**) to “feed” the output from **binstr2hex** to the simulator.

Handin

Upload **binstr2hex.c**, **vsm.c** and **score.vsm** to the course website. If you decide to implement any of extra features in your VSM simulator, submit your VSML programs with the names **extra1.vsm**, **extra2.vsm**, and **extra3.vsm**.

Grading

VSM Simulator	20 points
Converter	10 points
VSML Programs	
sum.vsm	5 points
max.vsm	5 points
score.vsm	10 points
Extra credits	15 points

Your program will be graded based on the following criteria:

1. Correctness – produces the correct result that is consistent with I/O specifications.
2. Design – employs a good modular design, function prototypes.
3. Efficiency – contains no redundant coding, efficient use of memory.
4. Style – uses meaningful names for identifiers, readable code, documentation.