hochschule aschaffenburg
university of applied sciences

Commands for EV3-API

Initialization:

command	explanation
#include <ev3.h>	including Header
InitEV3();	Initialization of all EV3-Functions
FreeEV3();	Closing of all EV3-Functions

Display:

command	explanation
bool **LcdClean();**	Erase Display
LcdPrintf(<Color>,<Text>,…);	Working like printf()

Help:

parameter	type	explanation	value
<Color>	char	Color of text	1: black text 0: wihteteext with black background
<Text>	char*	Pointer to text	e.g. “Hello EV3“

Break:

command	explanation
void **Wait(<Zeit_ms>);**	Break code for a given time

Help:

parameter	type	explanation	value
<Zeit_ms>	unsigned long	time in ms possible to use the given macros or type directly the value	MS_1…10 :1 10…100 :10 50…500 :50 100…900 :100 SEC_1…10 :1 5…20 :5 30 MIN_1

Inputs (Sensoren):

Commands:

command	explanation
int **setAllSensorMode(<Mode>, <Mode>,<Mode>,<Mode>);**	Allocate of the sensor types of all 4 ports in the correct order (IN_1, IN_2, IN_3, IN_4)
int **readSensor(<Input>);**	Readout of the actual sensor data
int **setIRBeaconCH(<Input>, <Channel>);**	Set Channel of the Beacon for Readout (default: Ch. 1)

Help:

parameter	type	explanation	value
<Input>	int	Input-Ports	IN_1, IN_2, IN_3, IN_4
<Mode>	char	Name und Mode of the connected Sensors	See next table
<Channel>	int	Channel of the Beacon. Needed for: IR_SEEK and IR_REMOTE	BEACON_CH_1, BEACON_CH_2, BEACON_CH_3, BEACON_CH_4

Sensor type:

Sensor	<Mode>	explanation	return value
No Sensor	NO_SEN	No sensor to the port connected	-1
Touch sensor	TOUCH_PRESS	Return of state (2 states possible)	Not pressed: 0 pressed: 1
Light sensor	COL_REFLECT	Return of the reflected light intensities in %	0 to 100
	COL_AMBIENT	Return of room light intensities in %	0 to 100
	COL_COLOR	Return of color	0: transparent 1: black 2: blue 3: green 4: yellow 5: red 6: white 7: brown
Sonar sensor	US_DIST_MM	Return of distance in mm	0 to 2550
Gyroscope	GYRO_ANG	Return of angle in °	-180 to 180
	GYRO_RATE	Return of gear rate in °/s	-440 to 440
EV3 Infrared	IR_PROX	Return of distance in % (up to 70cm)	0 (Near) to 100 (Far)
	IR_SEEK	Position of the Beacon	-25 to 25
	IR_REMOTE	Controlling EV3 with Beacon	BEACON_OFF BEACON_UP_LEFT BEACON_DOWN_LEFT BEACON_UP_RIGHT BEACON_DOWN_RIGHT BEACON_UP BEACON_DIAG_UP_LEFT

			BEACON_DIAG_UP_RIGHT BEACON_DOWN BEACON_ON BEACON_LEFT BEACON_RIGHT
NXT Infrared	NXT_IR_SEEKER		1 to 9
NXT Temperature	NXT_TEMP_C	Temperature in °C	-55 to 128
	NXT_TEMP_F	Temperature in °F	-67 to 262

Outputs (Motoren):

Controlling:

command	explanation
void **OnFwdReg(<Output>, <Speed>);**	Forwards/backwards with given speed
void **OnRevReg(<Output>, <Speed>);**	
void **OnFwdSync(<Output>, <Speed>);**	synchronized forwards/backwards with given speed (only working with two motors)
void **OnRevSync(<Output>, <Speed>);**	
void **Off(<Output>);**	Switch off motors
void **RotateMotor(<Output>, <Speed>, <Angle>);**	Rotate with given speed for a defined angle (Code stops till the angle is reached)

Reading out:

command	explanation
int **MotorRotationCount(<Output>);**	Rotation angle of the motors in °
void **ResetRotationCount(<Output>);**	Reset of rotation angle
char **MotorPower(<Output>);**	Actual motor speed

Help:

parameter	type	explanation	value
<Output>	int	Output-ports	OUT_A, OUT_B, OUT_C, OUT_D, OUT_AB, OUT_AC, OUT_AD, OUT_BC, OUT_BD, OUT_CD, OUT_ABC, OUT_BCD, OUT_ABCD, OUT_ALL
<Speed>	char	speed	0 to 100
<Angle>	int	angle in °	

Buttons und LED:

Functions for LED:

command	explanation
void **SetLedPattern(<Pattern>);**	Changing color of LED behind buttons
void **SetLedWarning (<Value>);**	Activate/deactivate of warning. LED color cannot be changed while warning is set.

Functions for buttons:

command	explanation
word **ButtonWaitForAnyPress(<Zeit>);**	Waiting for button press for given time
bool **ButtonIsUp(<Button>);**	Check if button is pressed or not (1: true, 0: false)
bool **ButtonIsDown(<Button>);**	
void **ButtonWaitForPress(<Button>);**	Waiting till a specific button is pressed
void **ButtonWaitForPressAndRelease(<Button>);**	Waiting till a specific button is pressed and released

Help:

parameter	type	explanation	value
<Pattern>	byte	Color and modus of LED	LED_BLACK (0) LED_GREEN (1) LED_RED (2) LED_ORANGE (3) LED_GREEN_FLASH (4) LED_RED_FLASH (5) LED_ORANGE_FLASH (6) LED_GREEN_PULSE (7) LED_RED_PULSE (8) LED_ORANGE_PULSE (9)
<Value>	bool	Activate or deactivate	0: deactivate 1: activate
<Zeit>	uint	time in ms	0: for endless waiting
<Button>	byte	Name of button	BTNEXIT, BTNRIGHT, BTNLEFT, BTNCENTER, BTNUP, BTNDOWN