API Reference

Matrox ConvertIP REST API Programming Reference

API Version: 1.5.08

This REST API allows you to configure Matrox ConvertIP devices.

By downloading or using this file, you are explicitly agreeing to the
Matrox Video Software License Agreement available at the following URL:
https://video.matrox.com/software-license-agreement

COPYRIGHT © 2025 Matrox Graphics Inc. All rights reserved. Matrox is a trademark of Matrox Graphics Inc.

Index

1. API 7

1.1 GET /api/version 7

2. ANCILLARY 8

2.1 GET /device/settings/streams/anc/{index} 8

2.2 POST /device/settings/streams/anc/{index} 8

2.3 GET /device/settings/streams/anc/{index}/manual 9

2.4 POST /device/settings/streams/anc/{index}/manual 10

3. AUDIO 12

3.1 GET /audio/configuration 12

3.2 POST /audio/configuration 12

3.3 POST /device/settings/streams/audiosdp/{index} 13

3.4 GET /device/settings/streams/audio/{index} 14

3.5 POST /device/settings/streams/audio/{index} 14

3.6 GET /device/settings/streams/audio/{index}/manual 15

3.7 POST /device/settings/streams/audio/{index}/manual 16

4. CERTIFICATES 18

4.1 GET /certificates/manufacturer/{type}/{name} 18

4.2 GET /certificates/customer/{type}/{name} 18

4.3 POST /certificates/customer/{type}/{name} 19

4.4 DELETE /certificates/customer/{type}/{name} 19

4.5 GET /certificates/trusted/{type}/cacert/alt/{index} 20

4.6 POST /certificates/trusted/{type}/cacert/alt/{index} 21

4.7 DELETE /certificates/trusted/{type}/cacert/alt/{index} 21

5. DEVICE 22

5.1 GET /device/caps 22

5.2 GET /device/information 23

5.3 GET /device/sku 25

5.4 POST /device/sku 26

5.5 POST /device/reboot 27

5.6 POST /device/locate 27

5.7 GET /device/settings/networks/{index} 28

5.8 POST /device/settings/networks/{index} 29

5.9 GET /device/settings/networks/{index}/capture 30

5.10 POST /device/settings/networks/{index}/capture 30

5.11 GET /device/settings/streams/auto/{index} 31

5.12 POST /device/settings/streams/auto/{index} 32

5.13 POST /device/settings/streams/ancsdp/{index} 33

5.14 GET /device/settings/streams/master 34

5.15 POST /device/settings/streams/master 34

5.16 GET /device/settings/multiview 35
5.17 POST /device/settings/multiview 36
5.18 GET /device/settings/other 36
5.19 POST /device/settings/other 37
5.20 GET /device/settings/save 38
5.21 POST /device/settings/restore 46
5.22 POST /device/settings/reset 54

6. DIAGNOSTICS 56
6.1 GET /device/settings/diag/control 56
6.2 POST /device/settings/diag/control 56
6.3 GET /device/settings/diag/data 57
6.4 POST /device/settings/diag/cleardata 58
6.5 POST /device/update 59

7. EDID 60
7.1 GET /device/settings/video/in/hdmi/edid/passthrough/header 60
7.2 GET /device/settings/video/in/hdmi/edid/passthrough/resolutions 60
7.3 GET /device/settings/video/in/hdmi/edid/passthrough/ 61
7.4 GET /device/settings/video/in/hdmi/edid/custom/{index} 62
7.5 POST /device/settings/video/in/hdmi/edid/custom/{index} 62
7.6 GET /device/settings/video/out/hdmi/edid/monitor/header 63
7.7 GET /device/settings/video/out/hdmi/edid/monitor/resolutions 64
7.8 GET /device/settings/video/out/hdmi/edid/monitor/ 65
7.9 GET /device/settings/video/out/hdmi/edid/custom/{index} 65
7.10 POST /device/settings/video/out/hdmi/edid/custom/{index} 66

8. HDCP 67
8.1 GET /device/settings/hdmi/hdcp 67
8.2 POST /device/settings/hdmi/hdcp 67

9. LOGS 69
9.1 GET /device/log/critical 69
9.2 GET /device/log/standard 69
9.3 POST /device/standard/clear 69
9.4 GET /device/log/detail 70
9.5 POST /device/detail/clear 71
9.6 GET /device/log/network 71
9.7 GET /device/log/ptp 72

10. NMOS 73
10.1 GET /device/settings/nmos/interface 73
10.2 POST /device/settings/nmos/interface 74
10.3 GET /device/settings/nmos/registerserver 74
10.4 POST /device/settings/nmos/registerserver 75
10.5 GET /device/settings/nmos/receivers/video/{index} 76

10.6 POST /device/settings/nmos/receivers/video/{index} 77
10.7 GET /device/settings/nmos/receivers/audio/{index} 78
10.8 POST /device/settings/nmos/receivers/audio/{index} 79
10.9 GET /device/settings/nmos/receivers/ANC/{index} 79
10.10 POST /device/settings/nmos/receivers/ANC/{index} 80
10.11 GET /device/settings/nmos/senders/video/{index} 81
10.12 POST /device/settings/nmos/senders/video/{index} 82
10.13 GET /device/settings/nmos/senders/audio/{index} 82
10.14 POST /device/settings/nmos/senders/audio/{index} 83
10.15 GET /device/settings/nmos/senders/ANC/{index} 84
10.16 POST /device/settings/nmos/senders/ANC/{index} 85

11. PTP 86
11.1 GET /device/status/ptp 86
11.2 GET /device/settings/ptp 86
11.3 POST /device/settings/ptp 87

12. RS-232 89
12.1 POST /serial/sendString 89

13. STATUS 90
13.1 GET /device/status/networks/{index} 90
13.2 GET /device/status 90

14. TIME 94
14.1 GET /device/settings/time 94
14.2 POST /device/settings/time 94

15. USER 96
15.1 POST /user/login 96
15.2 POST /user/logout 96
15.3 GET /user/profile 97
15.4 POST /user/profile 98
15.5 GET /user/profile/all 98
15.6 PUT /user/password 99
15.7 POST /user/register 99
15.8 POST /user/delete 100

16. VIDEO 101
16.1 GET /device/settings/video/passthrough 101
16.2 POST /device/settings/video/passthrough 101
16.3 GET /device/settings/video/in/mode 102
16.4 POST /device/settings/video/in/mode 103
16.5 GET /device/settings/video/out/mode 103
16.6 POST /device/settings/video/out/mode 104
16.7 GET /device/settings/streams/video/{index} 106

16.8 POST /device/settings/streams/video/{index} 107
16.9 GET /device/settings/streams/video/{index}/manual 108
16.10 POST /device/settings/streams/video/{index}/manual 109
16.11 POST /device/settings/streams/videosdp/{index} 110

Security and Authentication

Security Schemes

KEY	Type	Description
cookieAuth	apiKey	
DefaultAdminAuth	http, bearer	
AdminAuth	http, bearer	
UserAuth	http, bearer	

API

1. API

1.1 GET /api/version

Get the REST API version

Retrieves the current REST API version.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
  version  string  Rest Api version
}
```

2. ANCILLARY

2.1 GET /device/settings/streams/anc/{index}

Get ancillary stream settings

Retrieves configuration for the specified ANC stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
ONE OF
OPTION 1 {
   enable*  boolean  Indicates whether this stream or feature is enabled.
   nmosId   string   NMOS identifier associated with this resource.
}
OPTION 2 {
   enable*  boolean  Indicates whether this stream or feature is enabled.
   nmosId   string   NMOS identifier associated with this resource.
   sdpUrl*  string   URL pointing to the SDP file describing this stream.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
   status   string
   code     integer
   message  string
}
```

2.2 POST /device/settings/streams/anc/{index}

Set ANC stream settings

Applies configuration changes to the specified ANC stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
```

TX ancillary stream settings

```
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

```
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

2.3 GET /device/settings/streams/anc/{index}/manual

Get ancillary stream manual settings

Retrieves advanced manual settings for the specified ANC stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

ONE OF

OPTION 1 {

```
  packetTime              number   Packetization time in microseconds for the stream.
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*    boolean
  isIPMXEnabled           boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*             number   Source UDP port used for the primary stream leg.
  dstIpAddress*           string   Destination IP address used for the primary stream leg.
  dstUdpPort*             number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*        number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*         number   RTP payload type value assigned to the stream.
```

```
    rtpTimeToLive*            number   Time-to-live applied to packets on the primary RTP stream.
    redundancySrcUdpPort*     number   Source UDP port used for the redundant leg.
    redundancyDstIpAddress*   string   Destination IP address used for the redundant leg.
    redundancyDstUdpPort*     number   Destination UDP port used for the redundant leg.
  }
  OPTION 2{
    isIPv6Enabled*            boolean  Indicates whether IPv6 addressing is enabled for this stream.
    isRedundancyEnabled*      boolean  Indicates whether redundant streaming is active for this resource.
    srcIpAddress*             string   Source IP address used for the primary stream leg.
    dstIpAddress*             string   Destination IP address used for the primary stream leg.
    dstUdpPort*               number   Destination UDP port used for the primary stream leg.
    rtpSyncSourceId           number   RTP synchronization source identifier (SSRC).
    rtpPayloadType*           number   RTP payload type value assigned to the stream.
    rtpTimeToLive             number   Time-to-live applied to packets on the primary RTP stream.
    redundancySrcIpAddress*   string   Source IP address used for the redundant leg.
    redundancyDstIpAddress*   string   Destination IP address used for the redundant leg.
    redundancyDstUdpPort*     number   Destination UDP port used for the redundant leg.
    linkOffsetDelay           number   Additional latency in microseconds applied to align the redundant link.
  }
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

2.4 POST /device/settings/streams/anc/{index}/manual

Set ancillary stream manual settings

Applies advanced manual settings to the specified ANC stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
TX ancillary stream advanced settings
  packetTime                number   Packetization time in microseconds for the stream.
  isIPv6Enabled*            boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*      boolean
  isIPMXEnabled             boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*               number   Source UDP port used for the primary stream leg.
  dstIpAddress*             string   Destination IP address used for the primary stream leg.
  dstUdpPort*               number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*          number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*           number   RTP payload type value assigned to the stream.
  rtpTimeToLive*            number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcUdpPort*     number   Source UDP port used for the redundant leg.
  redundancyDstIpAddress*   string   Destination IP address used for the redundant leg.
```

```
  redundancyDstUdpPort*    number    Destination UDP port used for the redundant leg.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string    Status on error.
  code     integer   A non-null value indicates that the service encountered an error while processing the request.
  message  string    A human friendly error message.
}
```

3. AUDIO

3.1 GET /audio/configuration

Get audio volume and mute settings

Retrieve the current volume levels and mute state for audio output.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Represents the device audio volume and mute settings.
  rightVolume* integer between 0 and 127
                       Right channel output volume level.
  leftVolume*  integer between 0 and 127
                       Left channel output volume level.
  muteEnabled* boolean Indicates whether audio output is muted.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

3.2 POST /audio/configuration

Set audio volume and mute settings

Update the volume levels and mute state for audio output.

Request

Request Body - application/json

```
{
Represents the device audio volume and mute settings.
  rightVolume* integer between 0 and 127
                       Right channel output volume level.
  leftVolume*  integer between 0 and 127
                       Left channel output volume level.
  muteEnabled* boolean Indicates whether audio output is muted.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

3.3 POST /device/settings/streams/audiosdp/{index}

Update audio settings from SDP file

Updates the specified audio stream by importing parameters from an SDP file.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
Object containing SDP file
  sdpContent* string  SDP file content
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

```
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

3.4 GET /device/settings/streams/audio/{index}

Get audio stream settings

Retrieves configuration for the specified audio stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
ONE OF
OPTION 1{
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
}
OPTION 2{
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
  sdpUrl*  string   URL pointing to the SDP file describing this stream.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

3.5 POST /device/settings/streams/audio/{index}

Set audio stream settings

Applies configuration changes to the specified audio stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
TX audio stream settings
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

3.6 GET /device/settings/streams/audio/{index}/manual

Get audio stream manual settings

Retrieves advanced manual settings for the specified audio stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
ONE OF
OPTION 1 {
  packetTime              number   Packetization time in microseconds for the stream.
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*    boolean
  isIPMXEnabled           boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*             number   Source UDP port used for the primary stream leg.
  dstIpAddress*           string   Destination IP address used for the primary stream leg.
  dstUdpPort*             number   Destination UDP port used for the primary stream leg.
                                   RTP synchronization source identifier (SSRC).
```

```
    rtpSyncSourceId*          number
    rtpPayloadType*           number   RTP payload type value assigned to the stream.
    rtpTimeToLive*            number   Time-to-live applied to packets on the primary RTP stream.
    redundancySrcUdpPort*     number   Source UDP port used for the redundant leg.
    redundancyDstIpAddress*   string   Destination IP address used for the redundant leg.
    redundancyDstUdpPort*     number   Destination UDP port used for the redundant leg.
  }
  OPTION 2{
    isIPv6Enabled*            boolean  Indicates whether IPv6 addressing is enabled for this stream.
    audioFormat* {
    Defines an audio format supported by the device.
      format*      enum     Allowed:PCM_16, PCM_20, PCM_24, NPCM
                            Audio encoding format identifier.
      sampleRate*  number   Configured audio sample rate in hertz.
      nbChannels*  number   Number of audio channels supported.
    }
    packetTime                number   Packetization time in microseconds for the stream.
    isRedundancyEnabled*      boolean  Indicates whether redundant streaming is active for this resource.
    srcIpAddress*             string   Source IP address used for the primary stream leg.
    dstIpAddress*             string   Destination IP address used for the primary stream leg.
    dstUdpPort*               number   Destination UDP port used for the primary stream leg.
    rtpSyncSourceId           number   RTP synchronization source identifier (SSRC).
    rtpPayloadType*           number   RTP payload type value assigned to the stream.
    rtpTimeToLive             number   Time-to-live applied to packets on the primary RTP stream.
    redundancySrcIpAddress*   string   Source IP address used for the redundant leg.
    redundancyDstIpAddress*   string   Destination IP address used for the redundant leg.
    redundancyDstUdpPort*     number   Destination UDP port used for the redundant leg.
    linkOffsetDelay           number   Additional latency in microseconds applied to align the redundant link.
  }
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

3.7 POST /device/settings/streams/audio/{index}/manual

Set audio stream manual settings

Applies advanced manual settings to the specified audio stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
TX audio stream advanced settings
  packetTime          number   Packetization time in microseconds for the stream.
  isIPv6Enabled*      boolean  Indicates whether IPv6 addressing is enabled for this stream.
```

```
  isRedundancyEnabled*     boolean
  isIPMXEnabled            boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*              number   Source UDP port used for the primary stream leg.
  dstIpAddress*            string   Destination IP address used for the primary stream leg.
  dstUdpPort*              number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*         number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*          number   RTP payload type value assigned to the stream.
  rtpTimeToLive*           number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcUdpPort*    number   Source UDP port used for the redundant leg.
  redundancyDstIpAddress*  string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*    number   Destination UDP port used for the redundant leg.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

```
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

4. CERTIFICATES

4.1 GET /certificates/manufacturer/{type}/{name}

Download manufacturer-issued certificate asset

Retrieves a manufacturer-provisioned certificate, key, or CA bundle for archival or validation.

Request

PATH PARAMETERS

Name	Type	Description
*type	enum **Allowed:** rsa, ecdsa	Certificate family to target (RSA or ECDSA).
*name	enum **Allowed:** servercert, clientcert, cacert	Named manufacturer certificate asset to access.

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

4.2 GET /certificates/customer/{type}/{name}

Download customer-supplied certificate asset

Retrieves the stored customer-supplied certificate, key, or CA bundle for the requested slot.

Request

PATH PARAMETERS

Name	Type	Description

Name	Type	Description
*type	enum **Allowed:** rsa, ecdsa	Certificate family to target (RSA or ECDSA).
*name	enum **Allowed:** servercert, clientcert, cacert	Named customer certificate asset to access.

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

4.3 POST /certificates/customer/{type}/{name}

Upload customer certificate or key

Uploads or replaces a customer-provided certificate, key, or CA bundle on the device.

Request

PATH PARAMETERS

Name	Type	Description
*type	enum **Allowed:** rsa, ecdsa	Certificate family to target (RSA or ECDSA).
*name	enum **Allowed:** serverprivatekey, servercert, clientprivatekey, clientcert, cacert	Named customer certificate asset to create or replace.

Response

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

4.4 DELETE /certificates/customer/{type}/{name}

Remove customer certificate or key

Removes the selected customer-supplied certificate, key, or CA bundle from the device.

Request

PATH PARAMETERS

Name	Type	Description
*type	enum **Allowed:** rsa, ecdsa	Certificate family to target (RSA or ECDSA).
*name	enum **Allowed:** serverprivatekey, servercert, clientprivatekey, clientcert, cacert	Named customer certificate asset to remove.

Response

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

4.5 GET /certificates/trusted/{type}/cacert/alt/{index}

Download alternate trusted CA certificate

Retrieves an alternate trusted CA certificate from the device trust store.

Request

PATH PARAMETERS

Name	Type	Description
*type	enum **Allowed:** rsa, ecdsa	Certificate family to target (RSA or ECDSA).
*index	integer	Alternate trust-store slot index to retrieve.

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

4.6 POST /certificates/trusted/{type}/cacert/alt/{index}

Upload alternate trusted CA certificate

Uploads or replaces an alternate trusted CA certificate in the device trust store.

Request

PATH PARAMETERS

Name	Type	Description
*type	enum **Allowed:** rsa, ecdsa	Certificate family to target (RSA or ECDSA).
*index	integer	Alternate trust-store slot index to update.

Response

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

4.7 DELETE /certificates/trusted/{type}/cacert/alt/{index}

Delete alternate trusted CA certificate

Deletes an alternate trusted CA certificate from the device trust store.

Request

PATH PARAMETERS

Name	Type	Description
*type	enum **Allowed:** rsa, ecdsa	Certificate family to target (RSA or ECDSA).
*index	integer	Alternate trust-store slot index to clear.

Response

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5. DEVICE

5.1 GET /device/caps

Get device capabilities

Returns the device capability profile, including feature flags, licenses, and interface counts.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
  hostname*                    string   Device hostname reported by the ConvertIP unit.
  isGolden*                    boolean  Indicates whether the unit is running the golden recovery firmware image.
  isSafeMode*                  boolean  Indicates whether the device is operating in safe mode.
  isRX*                        boolean  Indicates whether the device is configured with receiver capabilities.
  isTX*                        boolean  Indicates whether the device is configured with transmitter capabilities.
  isRXSupported*               boolean  Indicates whether receiver functionality is supported.
  isTXSupported*               boolean  Indicates whether transmitter functionality is supported.
  isMultiviewLicenseInstalled* boolean  Indicates whether a multiview license is installed.
  isJpegxsLicenseInstalled*    boolean  Indicates whether a JPEG XS license is installed.
  isMultiviewSupported*        boolean  Indicates whether the device supports multiview processing.
  isHdcpSupported*             boolean  Indicates whether the device supports HDCP content protection.
  isUncompressedSupported*     boolean  Indicates whether the device supports uncompressed streaming.
  isCompressionSupported*      boolean  Indicates whether the device supports compressed streaming.
  isJpegxsSupported*           boolean  Indicates whether JPEG XS streaming is supported.
  isRedundancySupported*       boolean  Indicates whether the device supports redundant streaming.
  isIPv6Supported*             boolean  Indicates whether the device supports IPv6 networking.
  isMultiviewAvailable*        boolean  Indicates whether multiview can currently be enabled.
  isUncompressedAvailable*     boolean  Indicates whether uncompressed streaming can currently be enabled.
  isCompressionAvailable*      boolean  Indicates whether compressed streaming can currently be used.
  isRedundancyAvailable*       boolean  Indicates whether redundancy can currently be enabled.
  isIPv6Available*             boolean  Indicates whether IPv6 can currently be used.
  is12BitAvailable             boolean  Indicates whether 12-bit video processing is currently available.
  controlNetworkCount*         number   Number of control network interfaces exposed by the unit.
  mediaNetworkSpeed*           enum     Allowed:2G5, 10G, 25G
                                        Link speed of the media network interfaces.
  mediaNetworkCount*           number   Number of media network interfaces available.
  connectorType*               enum     Allowed:hdmi, sdi
                                        Physical network  connectors fitted to the device
  videoInCount*                number   Number of video input connectors available.
  videoOutCount*               number   Number of video output connectors available.
  rxVideoStreamCount*          number   Number of video receive streams supported.
  rxAudioStreamCount*          number   Number of audio receive streams supported.
  rxAncillaryStreamCount*      number   Number of ancillary receive streams supported.
  txVideoStreamCount*          number   Number of video transmit streams supported.
  txAudioStreamCount*          number   Number of audio transmit streams supported.
  txAncillaryStreamCount*      number   Number of ancillary transmit streams supported.
  isAnalogAudioSupported*      boolean  Indicates whether the hardware includes analog audio support.
  isRS232Supported*            boolean  Indicates whether the device supports RS-232 control.
  isOEM*                       boolean  Indicates whether the firmware is running in OEM mode.
```

```
  isSDM*                    boolean   Indicates whether the device is built on the Intel SDM form factor.
  isEncoder*                boolean   Indicates whether the device is operating with encoder capabilities.
  isDecoder*                boolean   Indicates whether the device is operating with decoder capabilities.
  isDeveloperMode           boolean   Indicates whether developer mode is active.
}
```

Status Code - 400: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.2 GET /device/information

Get device information

Retrieve device and firmware details for the current unit.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
  serialNumber*        string      Serial number
  SKUName              undefined   Product name
  SKU
    ONE OF
    prop0
    enum
    Allowed: fpga2110_hdbt_colibri_combo_rj45_1_2G5_rx,
    fpga2110_hdbt_jpegxs_combo_rj45_1_2G5_rx,
    fpga2110_hdbt_unc_colibri_combo_sfp_10G_rx, fpga2110_hdbt_unc_combo_sfp_10_25G_rx,
    fpga2110_hdbt_unc_jpegxs_combo_sfp_10G_rx,
    fpga2110_hdmi_colibri_combo_rj45_1_2G5_rx, fpga2110_hdmi_colibri_rj45_1_2G5_rx,
    fpga2110_hdmi_jpegxs_combo_rj45_1_2G5_rx, fpga2110_hdmi_jpegxs_rj45_1_2G5_rx,
    fpga2110_hdmi_unc_colibri_sfp_10G_rx, fpga2110_hdmi_unc_jpegxs_sfp_10G_rx,
    fpga2110_hdmi_unc_sfp_10_25G_rx, fpga2110_hdmi_unc_sfp_10_25G_colorlight_rx,
    fpga2110_sdi_colibri_rj45_1_2G5_rx, fpga2110_sdi_jpegxs_rj45_1_2G5_rx,
    fpga2110_sdi_unc_colibri_sfp_10G_rx, fpga2110_sdi_unc_jpegxs_sfp_10G_rx,
    fpga2110_sdi_unc_sfp_10_25G_rx, fpga2110_sdi_colibri_combo_rj45_1_2G5_rx,
    fpga2110_sdi_jpegxs_combo_rj45_1_2G5_rx, fpga2110_hdmi_colibri_rj45_1_2G5_sdm_rx,
    fpga2110_hdmi_jpegxs_rj45_1_2G5_sdm_rx,
    fpga2110_hdmi_unc_colibri_sfp_10_25G_sdm_rx,
    fpga2110_hdmi_unc_jpegxs_sfp_10_25G_sdm_rx,
    fpga2110_nobb_unc_colibri_sfp_10_25G_gw_dec,
    fpga2110_nobb_unc_jpegxs_sfp_10_25G_gw_dec
    SKU 1
    prop1
    enum
```

		Allowed: fpga2110_hdbt_colibri_combo_rj45_1_2G5_tx, fpga2110_hdbt_jpegxs_combo_rj45_1_2G5_tx, fpga2110_hdbt_unc_colibri_combo_sfp_10G_tx, fpga2110_hdbt_unc_combo_sfp_10_25G_tx, fpga2110_hdbt_unc_jpegxs_combo_sfp_10G_tx, fpga2110_hdmi_colibri_combo_rj45_1_2G5_tx, fpga2110_hdmi_colibri_rj45_1_2G5_tx, fpga2110_hdmi_jpegxs_combo_rj45_1_2G5_tx, fpga2110_hdmi_jpegxs_rj45_1_2G5_tx, fpga2110_hdmi_unc_colibri_sfp_10G_tx, fpga2110_hdmi_unc_jpegxs_sfp_10G_tx, fpga2110_hdmi_unc_sfp_10_25G_tx, fpga2110_hdmi_unc_sfp_10_25G_colorlight_rx, fpga2110_sdi_colibri_rj45_1_2G5_tx, fpga2110_sdi_jpegxs_rj45_1_2G5_tx, fpga2110_sdi_unc_colibri_sfp_10G_tx, fpga2110_sdi_unc_jpegxs_sfp_10G_tx, fpga2110_sdi_unc_sfp_10_25G_tx, fpga2110_sdi_colibri_combo_rj45_1_2G5_tx, fpga2110_sdi_jpegxs_combo_rj45_1_2G5_tx, fpga2110_nobb_unc_colibri_sfp_10_25G_gw_enc, fpga2110_nobb_unc_jpegxs_sfp_10_25G_gw_enc SKU 2
SKU1	enum	**Allowed:** fpga2110_hdbt_colibri_combo_rj45_1_2G5_rx, fpga2110_hdbt_jpegxs_combo_rj45_1_2G5_rx, fpga2110_hdbt_unc_colibri_combo_sfp_10G_rx, fpga2110_hdbt_unc_combo_sfp_10_25G_rx, fpga2110_hdbt_unc_jpegxs_combo_sfp_10G_rx, fpga2110_hdmi_colibri_combo_rj45_1_2G5_rx, fpga2110_hdmi_colibri_rj45_1_2G5_rx, fpga2110_hdmi_jpegxs_combo_rj45_1_2G5_rx, fpga2110_hdmi_jpegxs_rj45_1_2G5_rx, fpga2110_hdmi_unc_colibri_sfp_10G_rx, fpga2110_hdmi_unc_jpegxs_sfp_10G_rx, fpga2110_hdmi_unc_sfp_10_25G_rx, fpga2110_hdmi_unc_sfp_10_25G_colorlight_rx, fpga2110_sdi_colibri_rj45_1_2G5_rx, fpga2110_sdi_jpegxs_rj45_1_2G5_rx, fpga2110_sdi_unc_colibri_sfp_10G_rx, fpga2110_sdi_unc_jpegxs_sfp_10G_rx, fpga2110_sdi_unc_sfp_10_25G_rx, fpga2110_sdi_colibri_combo_rj45_1_2G5_rx, fpga2110_sdi_jpegxs_combo_rj45_1_2G5_rx, fpga2110_hdmi_colibri_rj45_1_2G5_sdm_rx, fpga2110_hdmi_jpegxs_rj45_1_2G5_sdm_rx, fpga2110_hdmi_unc_colibri_sfp_10_25G_sdm_rx, fpga2110_hdmi_unc_jpegxs_sfp_10_25G_sdm_rx, fpga2110_nobb_unc_colibri_sfp_10_25G_gw_dec, fpga2110_nobb_unc_jpegxs_sfp_10_25G_gw_dec SKU 1
SKU2	enum	**Allowed:** fpga2110_hdbt_colibri_combo_rj45_1_2G5_tx, fpga2110_hdbt_jpegxs_combo_rj45_1_2G5_tx, fpga2110_hdbt_unc_colibri_combo_sfp_10G_tx, fpga2110_hdbt_unc_combo_sfp_10_25G_tx, fpga2110_hdbt_unc_jpegxs_combo_sfp_10G_tx, fpga2110_hdmi_colibri_combo_rj45_1_2G5_tx, fpga2110_hdmi_colibri_rj45_1_2G5_tx, fpga2110_hdmi_jpegxs_combo_rj45_1_2G5_tx, fpga2110_hdmi_jpegxs_rj45_1_2G5_tx, fpga2110_hdmi_unc_colibri_sfp_10G_tx, fpga2110_hdmi_unc_jpegxs_sfp_10G_tx, fpga2110_hdmi_unc_sfp_10_25G_tx, fpga2110_hdmi_unc_sfp_10_25G_colorlight_rx, fpga2110_sdi_colibri_rj45_1_2G5_tx, fpga2110_sdi_jpegxs_rj45_1_2G5_tx,

```
                                    fpga2110_sdi_unc_colibri_sfp_10G_tx,
                                    fpga2110_sdi_unc_jpegxs_sfp_10G_tx,
                                    fpga2110_sdi_unc_sfp_10_25G_tx,
                                    fpga2110_sdi_colibri_combo_rj45_1_2G5_tx,
                                    fpga2110_sdi_jpegxs_combo_rj45_1_2G5_tx,
                                    fpga2110_nobb_unc_colibri_sfp_10_25G_gw_enc,
                                    fpga2110_nobb_unc_jpegxs_sfp_10_25G_gw_enc
                                    SKU 2
  FPGAVersion          string       FPGA version
  softwareVersion*     string       Main partition version
  maintenanceVersion*  string       Maintenance partition version
  hardwareRevision*    string       Hardware revision
  manufactureDate*     string       Manufacturer date
  networks* [{
  Array of object:
    state*        enum     Allowed:undefined, disconnected, autonegociation, RJ45 100M,
                           RJ45 1G, RJ45 2.5G, SFP 10G, SFP 25G
                           Current operational state reported for the resource.
    MACAddress    string   Hardware MAC address for the network interface.
    IPv4Address   string   Current IPv4 address configured for the interface.
    ipv6Address*  string   Configured IPv6 address for the interface.
  }]
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.3 GET /device/sku

Get device SKU

Returns the SKU identifier currently programmed on the device.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
SKU
  label*  string  User-visible label for the resource.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
```

```
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

5.4 POST /device/sku

Switch device SKU

For SDM devices, switches between SFP and RJ45 mode. For all other devices, switches between RX and TX mode. You must reboot your device for the changes to take effect.

Request

Request Body - application/json

```
{
Placeholder object used when no additional data is required.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

5.5 POST /device/reboot

Reboot device

Reboots the device.

Request

Request Body - application/json

```
{
Options that control how the device reboots.
  maintenanceMode boolean  Reboots the device into maintenance mode when true.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

5.6 POST /device/locate

Locate device

Activate the device locator function. This causes all LEDs to flash, making the device easier to locate.

Request

Request Body - application/json

```
{
Payload for enabling or disabling the device locator indicator.
  enable boolean  Indicates whether this stream or feature is enabled.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
```

```
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.7 GET /device/settings/networks/{index}

Get network settings

Retrieves network interface configuration for the specified interface.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	LAN index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Network settings
  ipv4Mode*          enum      Allowed:dhcp, static
                               DHCP or static
  ipv4Address*       string    IPv4 Address
  ipv4Netmask*       string    IPv4 Netmask
  ipv4Gateway*       string    IPv4 Gateway
  ipv4DnsServers*    [string]
  ipv4SearchDomain*  string    IPv4 Search Domain
  ipv4MDNS*          boolean   IPv4 mDNS
  ipv4LLMNR*         boolean   IPv4 LLMNR
  ipv4VLAN*          boolean   IPv4 VLAN (Network Control VLAN tags all management packets)
  ipv4VLANid*        integer   IPv4 VLAN identifier (VID). Valid range is between 0 and 4095.
  ipv6Mode*          enum      Allowed:dhcp, static
                               DHCP or static
  ipv6Address*       string    IPv6 Address
  ipv6PrefixLen*     string    IPv6 Prefix Length
  ipv6Gateway*       string    IPv6 Gateway
  ipv6DnsServers*    string    IPv6 DNS Servers
  ipv6SearchDomain*  string    IPv6 Search Domain
  ipv6MDNS*          boolean   IPv6 mDNS
  ipv6LLMNR*         boolean   IPv6 LLMNR
  ipv6VLAN*          boolean   IPv6 VLAN (Network Control VLAN tags all management packets)
  ipv6VLANid*        integer   IPv6 VLAN identifier (VID). Valid range is between 0 and 4095.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

5.8 POST /device/settings/networks/{index}

Set network settings

Updates the network settings. You must reboot the device for the changes to take effect.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	LAN index

Request Body - application/json

```
{
Network settings
  ipv4Mode*          enum      Allowed:dhcp, static
                               DHCP or static
  ipv4Address*       string    IPv4 Address
  ipv4Netmask*       string    IPv4 Netmask
  ipv4Gateway*       string    IPv4 Gateway
  ipv4DnsServers*    [string]
  ipv4SearchDomain*  string    IPv4 Search Domain
  ipv4MDNS*          boolean   IPv4 mDNS
  ipv4LLMNR*         boolean   IPv4 LLMNR
  ipv4VLAN*          boolean   IPv4 VLAN (Network Control VLAN tags all management packets)
  ipv4VLANid*        integer   IPv4 VLAN identifier (VID). Valid range is between 0 and 4095.
  ipv6Mode*          enum      Allowed:dhcp, static
                               DHCP or static
  ipv6Address*       string    IPv6 Address
  ipv6PrefixLen*     string    IPv6 Prefix Length
  ipv6Gateway*       string    IPv6 Gateway
  ipv6DnsServers*    string    IPv6 DNS Servers
  ipv6SearchDomain*  string    IPv6 Search Domain
  ipv6MDNS*          boolean   IPv6 mDNS
  ipv6LLMNR*         boolean   IPv6 LLMNR
  ipv6VLAN*          boolean   IPv6 VLAN (Network Control VLAN tags all management packets)
  ipv6VLANid*        integer   IPv6 VLAN identifier (VID). Valid range is between 0 and 4095.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
```

```
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.9 GET /device/settings/networks/{index}/capture

Get network packet capture settings

Retrieves the network capture settings for the specified interface. Packets that are not not the main payload video/audio/anc can be captured using this feature.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	LAN index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Network capture packet settings
  isEnabled*  boolean  Indicates whether the feature is enabled.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

5.10 POST /device/settings/networks/{index}/capture

Set network packet capture settings

Updates the network capture settings for the specified interface. Packets that are not not the main payload video/audio/anc can be captured using this feature.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	LAN index

Request Body - application/json

```
{
Network capture packet settings
  isEnabled*  boolean  Indicates whether the feature is enabled.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.11 GET /device/settings/streams/auto/{index}

Get automatic mode settings

Retrieves the automatic stream configuration preferences. Available only on Rx devices

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Automatic mode settings
  interface*   enum     Allowed:lan0, lan1, lan2
                        Network interface to use
  isIPv6*      boolean  Indicates whether the connection uses IPv6 or IPv4.
  isSecured*   boolean  Indicates whether HTTPS is required.
```

```
  selectPrivateKey*    enum      Allowed:ManufacturerRsaServerPrivateKey,
                                 ManufacturerEcdsaServerPrivateKey,
                                 CustomerRsaServerPrivateKey,
                                 CustomerEcdsaServerPrivateKey
                                 Select the private key and certificate to use.
  isClientServerRole* boolean    Indicates whether the auto mode expects a client or server role.
  name*               string     Friendly name assigned to the configuration.
  ipAddress*          string     IP address associated with the auto mode peer.
  port*               integer    between 0 and  65535
                                 Port number on which to connect
  videoSender*        string     NMOS UUID of the video sender
  audioSender*        string     NMOS UUID of the audio sender
  ancSender*          string     NMOS UUID of the ancillary sender
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - 404: HTTP/1.0 404 Not Found

5.12 POST /device/settings/streams/auto/{index}

Set automatic mode settings

Updates the automatic stream configuration preferences. Available only on Rx devices

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
Automatic mode settings
  interface*          enum      Allowed:lan0, lan1, lan2
                                Network interface to use
  isIPv6*             boolean   Indicates whether the connection uses IPv6 or IPv4.
  isSecured*          boolean   Indicates whether HTTPS is required.
  selectPrivateKey*   enum      Allowed:ManufacturerRsaServerPrivateKey,
                                ManufacturerEcdsaServerPrivateKey,
                                CustomerRsaServerPrivateKey,
                                CustomerEcdsaServerPrivateKey
                                Select the private key and certificate to use.
  isClientServerRole* boolean   Indicates whether the auto mode expects a client or server role.
  name*               string    Friendly name assigned to the configuration.
  ipAddress*          string    IP address associated with the auto mode peer.
  port*               integer   between 0 and  65535
                                Port number on which to connect
  videoSender*        string    NMOS UUID of the video sender
  audioSender*        string    NMOS UUID of the audio sender
```

```
  ancSender*          string   NMOS UUID of the ancillary sender
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.13 POST /device/settings/streams/ancsdp/{index}

Update ANC settings from SDP file

Updates the specified ANC stream by importing parameters from an SDP file.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
Object containing SDP file
  sdpContent* string  SDP file content
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.14 GET /device/settings/streams/master

Get the stream's master switch settings

Retrieves master stream behavior settings shared by all stream.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
The master switch to activate/deactivate stream settings on a particular product SKU.
  enable*              boolean  DEFAULT:true
                                Enable the stream settings
  isRedundancyEnabled  boolean  Indicates whether redundant streaming is active for this stream.
  connectionMode       enum     Allowed:manual, sdp, quickConnect
                                Connection mode used for this stream (manual, SDP url or quick connect.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

5.15 POST /device/settings/streams/master

Set the stream's master switch settings

Updates the master stream behavior settings shared by all stream.

Request

Request Body - application/json

```
{
The master switch to activate/deactivate stream settings on a particular product SKU.
  enable*              boolean  DEFAULT:true
                                Enable the stream settings
  isRedundancyEnabled  boolean  Indicates whether redundant streaming is active for this stream.
  connectionMode       enum     Allowed:manual, sdp, quickConnect
                                Connection mode used for this stream (manual, SDP url or quick connect.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

5.16 GET /device/settings/multiview

Get multiview settings

Retrieves configuration for the multiview renderer. This feature is currently not operational. Refer to the "MultiviewSettings" section in the output file generated by /device/settings/save for more information. Available only on Rx devices

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
The multiview switch to enable or disable multiview on a particular product SKU, and to set the multiview mode (PiP, Quad, Triple...).
  enable*                 boolean  Enable multiview
  multiviewConfiguration  number   DEFAULT:0
                                   Identifier of the multiview layout profile.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

5.17 POST /device/settings/multiview

Set the multiview settings

Updates configuration for the multiview renderer.Available only on Rx devices

Request

Request Body - application/json

```
{
```

The multiview switch to enable or disable multiview on a particular product SKU, and to set the multiview mode (PiP, Quad, Triple...).

enable*	boolean	Enable multiview
multiviewConfiguration	number	DEFAULT:0 Identifier of the multiview layout profile.

```
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

status	string	Status on error.
code	integer	A non-null value indicates that the service encountered an error while processing the request.
message	string	A human friendly error message.

```
}
```

5.18 GET /device/settings/other

Get other settings

Retrieve miscellaneous device settings such as IGMP version, button lock state, test signal configuration, and more.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
```

Other settings

igmpVersion*	enum	Allowed:none, v2, v3 IGMP version (RX only)
areButtonsLocked*	boolean	Indicates whether the buttons are locked or not.

```
  selectPrivateKey*          enum      Allowed:ManufacturerRsaServerPrivateKey,
                                       ManufacturerEcdsaServerPrivateKey,
                                       CustomerRsaServerPrivateKey,
                                       CustomerEcdsaServerPrivateKey
                                       Select the private key and the certificate to use.
  isClientServerRole*        boolean   Indicates whether the client certificates must be validated or not.
  isTestSignalEnabled*       boolean   Enable test signal
  testSignalMode             enum      Allowed:video, audioVideo
                                       Test pattern mode applied to the video output.
  isWatchdogEnabled*         boolean   Enable the watchdog
  clampToLimitedRange*       boolean   Enforce legal values for limited range
  troubleshootingControl*    number    Diagnostic control mode applied to the device.
  daisyChainingPosition*     number    Relative position of the unit when devices are daisy chained.
  groupName                  string    DEFAULT:IP OUT/IN
                                       Group name to customize urn:x-nmos:tag with.
  groupNameRx                string    DEFAULT:IP IN
                                       Group name to customize urn:x-nmos:tag with of the receiver on a gateway.
  groupNameTx                string    DEFAULT:IP OUT
                                       Group name to customize urn:x-nmos:tag with of the sender on a gateway.
  sapInterval*               number    between 0 and 300000
                                       DEFAULT:0
                                       SAP announcement interval in milliseconds. `0` disables the service. `1` enables the
                                       service with a default interval.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

5.19 POST /device/settings/other

Set other settings

Update miscellaneous device settings. You must reboot your device for the changes to take effect.

Request

Request Body - application/json

```
{
Other settings
  igmpVersion*               enum      Allowed:none, v2, v3
                                       IGMP version (RX only)
  areButtonsLocked*          boolean   Indicates whether the buttons are locked or not.
  selectPrivateKey*          enum      Allowed:ManufacturerRsaServerPrivateKey,
                                       ManufacturerEcdsaServerPrivateKey,
                                       CustomerRsaServerPrivateKey,
                                       CustomerEcdsaServerPrivateKey
                                       Select the private key and the certificate to use.
  isClientServerRole*        boolean   Indicates whether the client certificates must be validated or not.
  isTestSignalEnabled*       boolean   Enable test signal
  testSignalMode             enum      Allowed:video, audioVideo
                                       Test pattern mode applied to the video output.
  isWatchdogEnabled*         boolean   Enable the watchdog
  clampToLimitedRange*       boolean   Enforce legal values for limited range
```

```
  troubleshootingControl*  number   Diagnostic control mode applied to the device.
  daisyChainingPosition*   number   Relative position of the unit when devices are daisy chained.
  groupName                string     DEFAULT:IP OUT/IN
                                      Group name to customize urn:x-nmos:tag with.
  groupNameRx              string     DEFAULT:IP IN
                                      Group name to customize urn:x-nmos:tag with of the receiver on a gateway.
  groupNameTx              string     DEFAULT:IP OUT
                                      Group name to customize urn:x-nmos:tag with of the sender on a gateway.
  sapInterval*             number     between 0 and  300000
                                      DEFAULT:0
                                      SAP announcement interval in milliseconds. `0` disables the service. `1` enables the
                                      service with a default interval.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.20 GET /device/settings/save

Save settings to a file.

Exports the full user configuration payload.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
RX and TX user settings
  timeSettings* {
  Time settings
    mode*          enum     Allowed:NtpServer, DeviceTime, SystemTime
                            Time synchronization mode
```

```
  interface*     enum     Allowed:lan0, lan1, lan2
                          Network interface used for time synchronization
  isIPv6*        boolean  Indicates whether the connection is IPv6 or IPv4.
  ntpServer*     string   NTP server (IPv4 address, IPv6 address, or host name).
  timestamp_s*   integer  Timestamp in seconds (SystemTime mode; not preserved after reboot).
  timestamp_ns*  integer  Timestamp in nanoseconds (SystemTime mode; not preserved after reboot).
}
ptpSettings {
PTP settings
  isEnabled*            boolean  Indicates whether the PTP service is enabled or not.
  mode*                 enum     Allowed:follower, bmc
                                 PTP mode
  isIPv6*               boolean  Indicates whether the connection is IPv6 or IPv4.
  domain*               integer  between 0 and  127
                                 Domain number
  logSyncInterval*      integer  between -1 and  1
                                 PTP sync message interval expressed as a power-of-two value.
  logAnnounceInterval*  integer  between 0 and  4
                                 PTP announce message interval expressed as a power-of-two value.
  logDelayReqInterval*  integer  between 0 and  5
                                 PTP delay request interval expressed as a power-of-two value.
  isDelayReqEnabled*    boolean  Indicates whether PTP delay request messages are transmitted.
  priority1             integer  between 0 and  255
                                 PTP priority1 value advertised by the device.
  priority2             integer  between 0 and  255
                                 PTP priority2 value advertised by the device.
}
pepSettings {
  encrypt  boolean  Enable or disable PEP on all device stream. Valid and required only for tx devices. If true, a PSK with the
                    matching `key_id` must be present ont device or set in `pskInfo`. "Returned only for tx devices."
  key_id   string   Identifier for the media encryption key id. "Returned only for tx devices."
  pskInfo [{
  Array of object:
    key_id  string   Identifier for the key.
    length  integer  Length of the key.
    psk     string   Pre-shared key (PSK) value.
  }]
}
videoInSettings* {
Video in settings
  isEdidOverrideEnabled*  boolean  Enable EDID override
  selectEdid*             enum     Allowed:passthrough, custom0, base
                                   EDID mode
  noSignalOption*         enum     Allowed:message, nooutput, bitmap
                                   Signal behavior to use when no source is detected.
  syncType                enum     Allowed:ipmx, 2110, blackburst
                                   Synchronization reference type.
  isAudioSourceEmbedded*  boolean  Indicates whether audio should be sourced from the embedded input.
}
monitorSettings* {
Video out settings
  selectResolution*       enum     Allowed:stream, edidpreference, force
                                   Selection of resolution
  resolution* {
  Resolution
    isPresent        boolean  Indicates whether the referenced signal is present.
    width*           integer  Width
    height*          integer  Height
```

```
    refreshRateNum*  integer  Refresh rate numerator
    refreshRateDen*  integer  Refresh rate denominator
    scan*            enum     Allowed:progressive, interlaced
                              Interlaced or progressive
  }
  selectPixelFormat*      enum     Allowed:stream, edidpreference, force
                                   Selection of pixel format
  pixelFormat*            enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420,
                                   yuv_8_422, yuv_10_422, yuv_12_422, yuv_8_444,
                                   yuv_10_444, yuv_12_444, rgb_8, rgb_10, rgb_12
                                   Enumeration of pixel formats
  colorSpace*             enum     Allowed:bt601, bt709, bt2020
                                   Enumeration of color spaces
  isEdidOverrideEnabled*  boolean  Enable EDID override
  selectEdid*             enum     Allowed:custom0
                                   mode
  noSignalOption*         enum     Allowed:message, nooutput, bitmap, blank, lastframe
                                   Signal behavior to use when no source is detected.
  syncType                enum     Allowed:ipmx, 2110, blackburst
                                   Synchronization reference type.
  syncOffset              number   Output sync offset in microseconds.
}
networkSettings0* {
Network settings
  ipv4Mode*          enum     Allowed:dhcp, static
                              DHCP or static
  ipv4Address*       string   IPv4 Address
  ipv4Netmask*       string   IPv4 Netmask
  ipv4Gateway*       string   IPv4 Gateway
  ipv4DnsServers*    [string]
  ipv4SearchDomain*  string   IPv4 Search Domain
  ipv4MDNS*          boolean  IPv4 mDNS
  ipv4LLMNR*         boolean  IPv4 LLMNR
  ipv4VLAN*          boolean  IPv4 VLAN (Network Control VLAN tags all management packets)
  ipv4VLANid*        integer  IPv4 VLAN identifier (VID). Valid range is between 0 and 4095.
  ipv6Mode*          enum     Allowed:dhcp, static
                              DHCP or static
  ipv6Address*       string   IPv6 Address
  ipv6PrefixLen*     string   IPv6 Prefix Length
  ipv6Gateway*       string   IPv6 Gateway
  ipv6DnsServers*    string   IPv6 DNS Servers
  ipv6SearchDomain*  string   IPv6 Search Domain
  ipv6MDNS*          boolean  IPv6 mDNS
  ipv6LLMNR*         boolean  IPv6 LLMNR
  ipv6VLAN*          boolean  IPv6 VLAN (Network Control VLAN tags all management packets)
  ipv6VLANid*        integer  IPv6 VLAN identifier (VID). Valid range is between 0 and 4095.
}
networkSettings1* {
Network settings
  ipv4Mode*          enum     Allowed:dhcp, static
                              DHCP or static
  ipv4Address*       string   IPv4 Address
  ipv4Netmask*       string   IPv4 Netmask
  ipv4Gateway*       string   IPv4 Gateway
  ipv4DnsServers*    [string]
  ipv4SearchDomain*  string   IPv4 Search Domain
  ipv4MDNS*          boolean  IPv4 mDNS
  ipv4LLMNR*         boolean  IPv4 LLMNR
```

ipv4VLAN*	boolean	IPv4 VLAN (Network Control VLAN tags all management packets)
ipv4VLANid*	integer	IPv4 VLAN identifier (VID). Valid range is between 0 and 4095.
ipv6Mode*	enum	**Allowed:** dhcp, static DHCP or static
ipv6Address*	string	IPv6 Address
ipv6PrefixLen*	string	IPv6 Prefix Length
ipv6Gateway*	string	IPv6 Gateway
ipv6DnsServers*	string	IPv6 DNS Servers
ipv6SearchDomain*	string	IPv6 Search Domain
ipv6MDNS*	boolean	IPv6 mDNS
ipv6LLMNR*	boolean	IPv6 LLMNR
ipv6VLAN*	boolean	IPv6 VLAN (Network Control VLAN tags all management packets)
ipv6VLANid*	integer	IPv6 VLAN identifier (VID). Valid range is between 0 and 4095.

}

networkSettings2* {

Network settings

ipv4Mode*	enum	**Allowed:** dhcp, static DHCP or static
ipv4Address*	string	IPv4 Address
ipv4Netmask*	string	IPv4 Netmask
ipv4Gateway*	string	IPv4 Gateway
ipv4DnsServers*	[string]	
ipv4SearchDomain*	string	IPv4 Search Domain
ipv4MDNS*	boolean	IPv4 mDNS
ipv4LLMNR*	boolean	IPv4 LLMNR
ipv4VLAN*	boolean	IPv4 VLAN (Network Control VLAN tags all management packets)
ipv4VLANid*	integer	IPv4 VLAN identifier (VID). Valid range is between 0 and 4095.
ipv6Mode*	enum	**Allowed:** dhcp, static DHCP or static
ipv6Address*	string	IPv6 Address
ipv6PrefixLen*	string	IPv6 Prefix Length
ipv6Gateway*	string	IPv6 Gateway
ipv6DnsServers*	string	IPv6 DNS Servers
ipv6SearchDomain*	string	IPv6 Search Domain
ipv6MDNS*	boolean	IPv6 mDNS
ipv6LLMNR*	boolean	IPv6 LLMNR
ipv6VLAN*	boolean	IPv6 VLAN (Network Control VLAN tags all management packets)
ipv6VLANid*	integer	IPv6 VLAN identifier (VID). Valid range is between 0 and 4095.

}

nmosInterface* {

NMOS interface settings

isEnabled*	boolean	Indicates whether the NMOS server is enabled.
interface*	enum	**Allowed:** lan0, lan1, lan2, auto Interface
isIPv6*	boolean	Indicates whether the connection uses IPv6 or IPv4.
port*	integer	between 0 and 65535 Port number on which the server listens.
isSecured*	boolean	Indicates whether HTTPS is required.
selectPrivateKey*	enum	**Allowed:** ManufacturerRsaServerPrivateKey, ManufacturerEcdsaServerPrivateKey, CustomerRsaServerPrivateKey, CustomerEcdsaServerPrivateKey Select the private key and certificate to use.
isClientServerRole*	boolean	Indicates whether the client certificates must be validated or not.
nodeName*	string	NMOS node name
nodeDescription*	string	NMOS node description
deviceName*	string	NMOS device name
deviceDescription*	string	NMOS device description

```
  heartbeatRepeatPeriod* number   Time interval before sending a heartbeat to the NMOS server.
}
nmosRegisterServer* {
Server settings
  isEnabled*          boolean  Indicates whether the server is enabled or not.
  mode*               enum     Allowed:disabled, dns_mdns, dns, mdns, manual
                               Operating mode for this configuration.
  name                string   Name used for certificate validation.
  host*               string   IPv4 address, IPv6 address, or hostname.
  isIPv6*             boolean  Indicates whether the connection uses IPv6 or IPv4.
  port*               integer  between 0 and  65535
                               Server port
  apiVersion*         enum     Allowed:v1.2, v1.3
                               API version
  isSecured*          boolean  Indicates whether HTTPS is required.
  selectPrivateKey*   enum     Allowed:ManufacturerRsaServerPrivateKey,
                               ManufacturerEcdsaServerPrivateKey,
                               CustomerRsaServerPrivateKey,
                               CustomerEcdsaServerPrivateKey
                               Select the private key and the cerficate to use.
  isClientServerRole* boolean  Indicates whether the client certificate will be validated by the server.
}
rxVideoStream0* {
RX video stream settings
  enable* boolean  Indicates whether this stream or feature is enabled.
  nmosId  string   NMOS identifier associated with this resource.
  sdpUrl* string   URL pointing to the SDP file describing this stream.
}
rxVideoStreamManual0* {
RX video stream advanced settings
  resolution* {
  Resolution
    isPresent       boolean  Indicates whether the referenced signal is present.
    width*          integer  Width
    height*         integer  Height
    refreshRateNum* integer  Refresh rate numerator
    refreshRateDen* integer  Refresh rate denominator
    scan*           enum     Allowed:progressive, interlaced
                             Interlaced or progressive
  }
  pixelFormat*            enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420,
                                   yuv_8_422, yuv_10_422, yuv_12_422, yuv_8_444,
                                   yuv_10_444, yuv_12_444, rgb_8, rgb_10, rgb_12
                                   Enumeration of pixel formats
  colorSpace*             enum     Allowed:bt601, bt709, bt2020
                                   Enumeration of color spaces
  colorTcs                enum     Allowed:undefined, sdr, pq, hlg
                                   Enumeration of color transfer characteristic systems
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isCompressionEnabled*   boolean  DEFAULT:true
                                   Indicates whether compression is active for the current stream configuration.
  isRedundancyEnabled*    boolean  Indicates whether redundant streaming is active for this resource.
  isIPMXEnabled*          boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcIpAddress*           string   Source IP address used for the primary stream leg.
  dstIpAddress*           string   Destination IP address used for the primary stream leg.
  dstUdpPort*             number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*        number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*         number   RTP payload type value assigned to the stream.
```

```
  rtpTimeToLive*           number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcIpAddress*  string   Source IP address used for the redundant leg.
  redundancyDstIpAddress*  string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*    number   Destination UDP port used for the redundant leg.
  linkOffsetDelay          number   Additional latency in microseconds applied to align the redundant link.
}
txVideoStream0* {
TX video stream settings
  enable*                boolean  Indicates whether this stream or feature is enabled.
  nmosId                 string   NMOS identifier associated with this resource.
  selectResolution*      enum     Allowed:input, force
                                  Selection of resolution
  resolution* {
  Resolution
    isPresent        boolean  Indicates whether the referenced signal is present.
    width*           integer  Width
    height*          integer  Height
    refreshRateNum*  integer  Refresh rate numerator
    refreshRateDen*  integer  Refresh rate denominator
    scan*            enum     Allowed:progressive, interlaced
                              Interlaced or progressive
  }
  selectPixelFormat*     enum     Allowed:input, force
                                  Selection of pixel format
  pixelFormat*           enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420,
                                  yuv_8_422, yuv_10_422, yuv_12_422, yuv_8_444,
                                  yuv_10_444, yuv_12_444, rgb_8, rgb_10, rgb_12
                                  Enumeration of pixel formats
  colorSpace*            enum     Allowed:bt601, bt709, bt2020
                                  Enumeration of color spaces
  isCompressionEnabled*  boolean  DEFAULT:true
                                  Enable JPEG XS compression (TX only)
  intraFrameCompression  boolean  Enable intra-frame-only compression (TX only)
  bitRateUHD*            number   Target bitrate for resolutions larger than Full HD, in Mbps.
  bitRateHD*             number   Target bitrate for resolutions up to Full HD, in Mbps.
}
txVideoStreamManual0* {
TX video stream advanced settings
  isIPv6Enabled*           boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*     boolean  Indicates whether redundant streaming is active for this resource.
  isIPMXEnabled            boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*              number   Source UDP port used for the primary stream leg.
  dstIpAddress*            string   Destination IP address used for the primary stream leg.
  dstUdpPort*              number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*         number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*          number   RTP payload type value assigned to the stream.
  rtpTimeToLive*           number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcUdpPort*    number   Source UDP port used for the redundant leg.
  redundancyDstIpAddress*  string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*    number   Destination UDP port used for the redundant leg.
  payloadSize*             number   Payload size per packet in bytes.
}
rxAudioStream0* {
RX audio stream settings
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
  sdpUrl*  string   URL pointing to the SDP file describing this stream.
}
```

```
rxAudioStreamManual0* {
RX audio stream advanced settings
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  audioFormat* {
  Defines an audio format supported by the device.
    format*      enum    Allowed:PCM_16, PCM_20, PCM_24, NPCM
                         Audio encoding format identifier.
    sampleRate*  number  Configured audio sample rate in hertz.
    nbChannels*  number  Number of audio channels supported.
  }
  packetTime              number   Packetization time in microseconds for the stream.
  isRedundancyEnabled*    boolean  Indicates whether redundant streaming is active for this resource.
  srcIpAddress*           string   Source IP address used for the primary stream leg.
  dstIpAddress*           string   Destination IP address used for the primary stream leg.
  dstUdpPort*             number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId         number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*         number   RTP payload type value assigned to the stream.
  rtpTimeToLive           number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcIpAddress* string   Source IP address used for the redundant leg.
  redundancyDstIpAddress* string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*   number   Destination UDP port used for the redundant leg.
  linkOffsetDelay         number   Additional latency in microseconds applied to align the redundant link.
}
txAudioStream0* {
TX audio stream settings
  enable* boolean  Indicates whether this stream or feature is enabled.
  nmosId  string   NMOS identifier associated with this resource.
}
txAudioStreamManual0* {
TX audio stream advanced settings
  packetTime              number   Packetization time in microseconds for the stream.
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*    boolean
  isIPMXEnabled           boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*             number   Source UDP port used for the primary stream leg.
  dstIpAddress*           string   Destination IP address used for the primary stream leg.
  dstUdpPort*             number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*        number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*         number   RTP payload type value assigned to the stream.
  rtpTimeToLive*          number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcUdpPort*   number   Source UDP port used for the redundant leg.
  redundancyDstIpAddress* string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*   number   Destination UDP port used for the redundant leg.
}
rxAncStream0* {
RX ancillary stream settings
  enable* boolean  Indicates whether this stream or feature is enabled.
  nmosId  string   NMOS identifier associated with this resource.
  sdpUrl* string   URL pointing to the SDP file describing this stream.
}
rxAncStreamManual0* {
RX ancillary stream advanced settings
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*    boolean  Indicates whether redundant streaming is active for this resource.
  srcIpAddress*           string   Source IP address used for the primary stream leg.
  dstIpAddress*           string   Destination IP address used for the primary stream leg.
  dstUdpPort*             number   Destination UDP port used for the primary stream leg.
```

rtpSyncSourceId	number	RTP synchronization source identifier (SSRC).
rtpPayloadType*	number	RTP payload type value assigned to the stream.
rtpTimeToLive	number	Time-to-live applied to packets on the primary RTP stream.
redundancySrcIpAddress*	string	Source IP address used for the redundant leg.
redundancyDstIpAddress*	string	Destination IP address used for the redundant leg.
redundancyDstUdpPort*	number	Destination UDP port used for the redundant leg.
linkOffsetDelay	number	Additional latency in microseconds applied to align the redundant link.

}

txAncStream0* {

TX ancillary stream settings

enable*	boolean	Indicates whether this stream or feature is enabled.
nmosId	string	NMOS identifier associated with this resource.

}

txAncStreamManual0* {

TX ancillary stream advanced settings

packetTime	number	Packetization time in microseconds for the stream.
isIPv6Enabled*	boolean	Indicates whether IPv6 addressing is enabled for this stream.
isRedundancyEnabled*	boolean	
isIPMXEnabled	boolean	Indicates whether IPMX interoperability is enabled for the stream.
srcUdpPort*	number	Source UDP port used for the primary stream leg.
dstIpAddress*	string	Destination IP address used for the primary stream leg.
dstUdpPort*	number	Destination UDP port used for the primary stream leg.
rtpSyncSourceId*	number	RTP synchronization source identifier (SSRC).
rtpPayloadType*	number	RTP payload type value assigned to the stream.
rtpTimeToLive*	number	Time-to-live applied to packets on the primary RTP stream.
redundancySrcUdpPort*	number	Source UDP port used for the redundant leg.
redundancyDstIpAddress*	string	Destination IP address used for the redundant leg.
redundancyDstUdpPort*	number	Destination UDP port used for the redundant leg.

}

otherSettings* {

Other settings

igmpVersion*	enum	**Allowed:**none, v2, v3 IGMP version (RX only)
areButtonsLocked*	boolean	Indicates whether the buttons are locked or not.
selectPrivateKey*	enum	**Allowed:**ManufacturerRsaServerPrivateKey, ManufacturerEcdsaServerPrivateKey, CustomerRsaServerPrivateKey, CustomerEcdsaServerPrivateKey Select the private key and the certificate to use.
isClientServerRole*	boolean	Indicates whether the client certificates must be validated or not.
isTestSignalEnabled*	boolean	Enable test signal
testSignalMode	enum	**Allowed:**video, audioVideo Test pattern mode applied to the video output.
isWatchdogEnabled*	boolean	Enable the watchdog
clampToLimitedRange*	boolean	Enforce legal values for limited range
troubleshootingControl*	number	Diagnostic control mode applied to the device.
daisyChainingPosition*	number	Relative position of the unit when devices are daisy chained.
groupName	string	**DEFAULT:**IP OUT/IN Group name to customize urn:x-nmos:tag with.
groupNameRx	string	**DEFAULT:**IP IN Group name to customize urn:x-nmos:tag with of the receiver on a gateway.
groupNameTx	string	**DEFAULT:**IP OUT Group name to customize urn:x-nmos:tag with of the sender on a gateway.
sapInterval*	number	between 0 and 300000 **DEFAULT:**0 SAP announcement interval in milliseconds. `0` disables the service. `1` enables the service with a default interval.

}

```
    rxAutoSettings* {
    Automatic mode settings
      interface*            enum     Allowed:lan0, lan1, lan2
                                     Network interface to use
      isIPv6*               boolean  Indicates whether the connection uses IPv6 or IPv4.
      isSecured*            boolean  Indicates whether HTTPS is required.
      selectPrivateKey*     enum     Allowed:ManufacturerRsaServerPrivateKey,
                                     ManufacturerEcdsaServerPrivateKey,
                                     CustomerRsaServerPrivateKey,
                                     CustomerEcdsaServerPrivateKey
                                     Select the private key and certificate to use.
      isClientServerRole* boolean    Indicates whether the auto mode expects a client or server role.
      name*                 string   Friendly name assigned to the configuration.
      ipAddress*            string   IP address associated with the auto mode peer.
      port*                 integer  between 0 and  65535
                                     Port number on which to connect
      videoSender*          string   NMOS UUID of the video sender
      audioSender*          string   NMOS UUID of the audio sender
      ancSender*            string   NMOS UUID of the ancillary sender
    }
  }
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

5.21 POST /device/settings/restore

Restore the settings from a file

Restore device settings from a saved configuration file. You must reboot your device for the changes to take effect.

Request

Request Body - application/json

```
{
RX and TX user settings
  timeSettings* {
  Time settings
    mode*          enum     Allowed:NtpServer, DeviceTime, SystemTime
                            Time synchronization mode
    interface*     enum     Allowed:lan0, lan1, lan2
                            Network interface used for time synchronization
    isIPv6*        boolean  Indicates whether the connection is IPv6 or IPv4.
    ntpServer*     string   NTP server (IPv4 address, IPv6 address, or host name).
    timestamp_s*   integer  Timestamp in seconds (SystemTime mode; not preserved after reboot).
    timestamp_ns*  integer  Timestamp in nanoseconds (SystemTime mode; not preserved after reboot).
  }
  ptpSettings {
  PTP settings
    isEnabled*     boolean  Indicates whether the PTP service is enabled or not.
    mode*          enum     Allowed:follower, bmc
                            PTP mode
```

```
  isIPv6*               boolean  Indicates whether the connection is IPv6 or IPv4.
  domain*               integer  between 0 and  127
                                 Domain number
  logSyncInterval*      integer  between -1 and  1
                                 PTP sync message interval expressed as a power-of-two value.
  logAnnounceInterval*  integer  between 0 and  4
                                 PTP announce message interval expressed as a power-of-two value.
  logDelayReqInterval*  integer  between 0 and  5
                                 PTP delay request interval expressed as a power-of-two value.
  isDelayReqEnabled*    boolean  Indicates whether PTP delay request messages are transmitted.
  priority1             integer  between 0 and  255
                                 PTP priority1 value advertised by the device.
  priority2             integer  between 0 and  255
                                 PTP priority2 value advertised by the device.
}
pepSettings {
  encrypt  boolean  Enable or disable PEP on all device stream. Valid and required only for tx devices. If true, a PSK with the
                    matching `key_id` must be present ont device or set in `pskInfo`. "Returned only for tx devices."
  key_id   string   Identifier for the media encryption key id. "Returned only for tx devices."
  pskInfo [{
  Array of object:
    key_id  string   Identifier for the key.
    length  integer  Length of the key.
    psk     string   Pre-shared key (PSK) value.
  }]
}
videoInSettings* {
Video in settings
  isEdidOverrideEnabled* boolean  Enable EDID override
  selectEdid*            enum     Allowed:passthrough, custom0, base
                                  EDID mode
  noSignalOption*        enum     Allowed:message, nooutput, bitmap
                                  Signal behavior to use when no source is detected.
  syncType               enum     Allowed:ipmx, 2110, blackburst
                                  Synchronization reference type.
  isAudioSourceEmbedded* boolean  Indicates whether audio should be sourced from the embedded input.
}
monitorSettings* {
Video out settings
  selectResolution*      enum     Allowed:stream, edidpreference, force
                                  Selection of resolution
  resolution* {
  Resolution
    isPresent        boolean  Indicates whether the referenced signal is present.
    width*           integer  Width
    height*          integer  Height
    refreshRateNum*  integer  Refresh rate numerator
    refreshRateDen*  integer  Refresh rate denominator
    scan*            enum     Allowed:progressive, interlaced
                              Interlaced or progressive
  }
  selectPixelFormat*     enum     Allowed:stream, edidpreference, force
                                  Selection of pixel format
  pixelFormat*           enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                                  yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                                  yuv_12_444, rgb_8, rgb_10, rgb_12
                                  Enumeration of pixel formats
  colorSpace*            enum     Allowed:bt601, bt709, bt2020
```

		Enumeration of color spaces
isEdidOverrideEnabled*	boolean	Enable EDID override
selectEdid*	enum	**Allowed:**custom0
		mode
noSignalOption*	enum	**Allowed:**message, nooutput, bitmap, blank, lastframe
		Signal behavior to use when no source is detected.
syncType	enum	**Allowed:**ipmx, 2110, blackburst
		Synchronization reference type.
syncOffset	number	Output sync offset in microseconds.

}

networkSettings0* {

Network settings

ipv4Mode*	enum	**Allowed:**dhcp, static
		DHCP or static
ipv4Address*	string	IPv4 Address
ipv4Netmask*	string	IPv4 Netmask
ipv4Gateway*	string	IPv4 Gateway
ipv4DnsServers*	[string]	
ipv4SearchDomain*	string	IPv4 Search Domain
ipv4MDNS*	boolean	IPv4 mDNS
ipv4LLMNR*	boolean	IPv4 LLMNR
ipv4VLAN*	boolean	IPv4 VLAN (Network Control VLAN tags all management packets)
ipv4VLANid*	integer	IPv4 VLAN identifier (VID). Valid range is between 0 and 4095.
ipv6Mode*	enum	**Allowed:**dhcp, static
		DHCP or static
ipv6Address*	string	IPv6 Address
ipv6PrefixLen*	string	IPv6 Prefix Length
ipv6Gateway*	string	IPv6 Gateway
ipv6DnsServers*	string	IPv6 DNS Servers
ipv6SearchDomain*	string	IPv6 Search Domain
ipv6MDNS*	boolean	IPv6 mDNS
ipv6LLMNR*	boolean	IPv6 LLMNR
ipv6VLAN*	boolean	IPv6 VLAN (Network Control VLAN tags all management packets)
ipv6VLANid*	integer	IPv6 VLAN identifier (VID). Valid range is between 0 and 4095.

}

networkSettings1* {

Network settings

ipv4Mode*	enum	**Allowed:**dhcp, static
		DHCP or static
ipv4Address*	string	IPv4 Address
ipv4Netmask*	string	IPv4 Netmask
ipv4Gateway*	string	IPv4 Gateway
ipv4DnsServers*	[string]	
ipv4SearchDomain*	string	IPv4 Search Domain
ipv4MDNS*	boolean	IPv4 mDNS
ipv4LLMNR*	boolean	IPv4 LLMNR
ipv4VLAN*	boolean	IPv4 VLAN (Network Control VLAN tags all management packets)
ipv4VLANid*	integer	IPv4 VLAN identifier (VID). Valid range is between 0 and 4095.
ipv6Mode*	enum	**Allowed:**dhcp, static
		DHCP or static
ipv6Address*	string	IPv6 Address
ipv6PrefixLen*	string	IPv6 Prefix Length
ipv6Gateway*	string	IPv6 Gateway
ipv6DnsServers*	string	IPv6 DNS Servers
ipv6SearchDomain*	string	IPv6 Search Domain
ipv6MDNS*	boolean	IPv6 mDNS
ipv6LLMNR*	boolean	IPv6 LLMNR
ipv6VLAN*	boolean	IPv6 VLAN (Network Control VLAN tags all management packets)

```
  ipv6VLANid*        integer   IPv6 VLAN identifier (VID). Valid range is between 0 and 4095.
}
networkSettings2* {
Network settings
  ipv4Mode*          enum      Allowed:dhcp, static
                               DHCP or static
  ipv4Address*       string    IPv4 Address
  ipv4Netmask*       string    IPv4 Netmask
  ipv4Gateway*       string    IPv4 Gateway
  ipv4DnsServers*    [string]
  ipv4SearchDomain*  string    IPv4 Search Domain
  ipv4MDNS*          boolean   IPv4 mDNS
  ipv4LLMNR*         boolean   IPv4 LLMNR
  ipv4VLAN*          boolean   IPv4 VLAN (Network Control VLAN tags all management packets)
  ipv4VLANid*        integer   IPv4 VLAN identifier (VID). Valid range is between 0 and 4095.
  ipv6Mode*          enum      Allowed:dhcp, static
                               DHCP or static
  ipv6Address*       string    IPv6 Address
  ipv6PrefixLen*     string    IPv6 Prefix Length
  ipv6Gateway*       string    IPv6 Gateway
  ipv6DnsServers*    string    IPv6 DNS Servers
  ipv6SearchDomain*  string    IPv6 Search Domain
  ipv6MDNS*          boolean   IPv6 mDNS
  ipv6LLMNR*         boolean   IPv6 LLMNR
  ipv6VLAN*          boolean   IPv6 VLAN (Network Control VLAN tags all management packets)
  ipv6VLANid*        integer   IPv6 VLAN identifier (VID). Valid range is between 0 and 4095.
}
nmosInterface* {
NMOS interface settings
  isEnabled*             boolean   Indicates whether the NMOS server is enabled.
  interface*             enum      Allowed:lan0, lan1, lan2, auto
                                   Interface
  isIPv6*                boolean   Indicates whether the connection uses IPv6 or IPv4.
  port*                  integer   between 0 and  65535
                                   Port number on which the server listens.
  isSecured*             boolean   Indicates whether HTTPS is required.
  selectPrivateKey*      enum      Allowed:ManufacturerRsaServerPrivateKey,
                                   ManufacturerEcdsaServerPrivateKey,
                                   CustomerRsaServerPrivateKey,
                                   CustomerEcdsaServerPrivateKey
                                   Select the private key and certificate to use.
  isClientServerRole*    boolean   Indicates whether the client certificates must be validated or not.
  nodeName*              string    NMOS node name
  nodeDescription*       string    NMOS node description
  deviceName*            string    NMOS device name
  deviceDescription*     string    NMOS device description
  heartbeatRepeatPeriod* number    Time interval before sending a heartbeat to the NMOS server.
}
nmosRegisterServer* {
Server settings
  isEnabled*           boolean   Indicates whether the server is enabled or not.
  mode*                enum      Allowed:disabled, dns_mdns, dns, mdns, manual
                                 Operating mode for this configuration.
  name                 string    Name used for certificate validation.
  host*                string    IPv4 address, IPv6 address, or hostname.
  isIPv6*              boolean   Indicates whether the connection uses IPv6 or IPv4.
  port*                integer   between 0 and  65535
                                 Server port
```

```
  apiVersion*          enum     Allowed:v1.2, v1.3
                                API version
  isSecured*           boolean  Indicates whether HTTPS is required.
  selectPrivateKey*    enum     Allowed:ManufacturerRsaServerPrivateKey,
                                ManufacturerEcdsaServerPrivateKey,
                                CustomerRsaServerPrivateKey,
                                CustomerEcdsaServerPrivateKey
                                Select the private key and the cerficate to use.
  isClientServerRole* boolean   Indicates whether the client certificate will be validated by the server.
}
rxVideoStream0* {
RX video stream settings
  enable* boolean  Indicates whether this stream or feature is enabled.
  nmosId  string   NMOS identifier associated with this resource.
  sdpUrl* string   URL pointing to the SDP file describing this stream.
}
rxVideoStreamManual0* {
RX video stream advanced settings
  resolution* {
  Resolution
    isPresent       boolean  Indicates whether the referenced signal is present.
    width*          integer  Width
    height*         integer  Height
    refreshRateNum* integer  Refresh rate numerator
    refreshRateDen* integer  Refresh rate denominator
    scan*           enum     Allowed:progressive, interlaced
                             Interlaced or progressive
  }
  pixelFormat*            enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                                   yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                                   yuv_12_444, rgb_8, rgb_10, rgb_12
                                   Enumeration of pixel formats
  colorSpace*             enum     Allowed:bt601, bt709, bt2020
                                   Enumeration of color spaces
  colorTcs                enum     Allowed:undefined, sdr, pq, hlg
                                   Enumeration of color transfer characteristic systems
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isCompressionEnabled*   boolean  DEFAULT:true
                                   Indicates whether compression is active for the current stream configuration.
  isRedundancyEnabled*    boolean  Indicates whether redundant streaming is active for this resource.
  isIPMXEnabled*          boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcIpAddress*           string   Source IP address used for the primary stream leg.
  dstIpAddress*           string   Destination IP address used for the primary stream leg.
  dstUdpPort*             number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*        number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*         number   RTP payload type value assigned to the stream.
  rtpTimeToLive*          number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcIpAddress* string   Source IP address used for the redundant leg.
  redundancyDstIpAddress* string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*   number   Destination UDP port used for the redundant leg.
  linkOffsetDelay         number   Additional latency in microseconds applied to align the redundant link.
}
txVideoStream0* {
TX video stream settings
  enable*               boolean  Indicates whether this stream or feature is enabled.
  nmosId                string   NMOS identifier associated with this resource.
  selectResolution*     enum     Allowed:input, force
                                 Selection of resolution
```

```
  resolution* {
  Resolution
    isPresent        boolean  Indicates whether the referenced signal is present.
    width*           integer  Width
    height*          integer  Height
    refreshRateNum*  integer  Refresh rate numerator
    refreshRateDen*  integer  Refresh rate denominator
    scan*            enum     Allowed:progressive, interlaced
                              Interlaced or progressive
  }
  selectPixelFormat*     enum     Allowed:input, force
                                  Selection of pixel format
  pixelFormat*           enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                                  yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                                  yuv_12_444, rgb_8, rgb_10, rgb_12
                                  Enumeration of pixel formats
  colorSpace*            enum     Allowed:bt601, bt709, bt2020
                                  Enumeration of color spaces
  isCompressionEnabled*  boolean  DEFAULT:true
                                  Enable JPEG XS compression (TX only)
  intraFrameCompression  boolean  Enable intra-frame-only compression (TX only)
  bitRateUHD*            number   Target bitrate for resolutions larger than Full HD, in Mbps.
  bitRateHD*             number   Target bitrate for resolutions up to Full HD, in Mbps.
}
txVideoStreamManual0* {
TX video stream advanced settings
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*    boolean  Indicates whether redundant streaming is active for this resource.
  isIPMXEnabled           boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*             number   Source UDP port used for the primary stream leg.
  dstIpAddress*           string   Destination IP address used for the primary stream leg.
  dstUdpPort*             number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*        number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*         number   RTP payload type value assigned to the stream.
  rtpTimeToLive*          number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcUdpPort*   number   Source UDP port used for the redundant leg.
  redundancyDstIpAddress* string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*   number   Destination UDP port used for the redundant leg.
  payloadSize*            number   Payload size per packet in bytes.
}
rxAudioStream0* {
RX audio stream settings
  enable* boolean  Indicates whether this stream or feature is enabled.
  nmosId  string   NMOS identifier associated with this resource.
  sdpUrl* string   URL pointing to the SDP file describing this stream.
}
rxAudioStreamManual0* {
RX audio stream advanced settings
  isIPv6Enabled*          boolean  Indicates whether IPv6 addressing is enabled for this stream.
  audioFormat* {
  Defines an audio format supported by the device.
    format*      enum    Allowed:PCM_16, PCM_20, PCM_24, NPCM
                         Audio encoding format identifier.
    sampleRate*  number  Configured audio sample rate in hertz.
    nbChannels*  number  Number of audio channels supported.
  }
  packetTime              number   Packetization time in microseconds for the stream.
  isRedundancyEnabled*    boolean  Indicates whether redundant streaming is active for this resource.
```

```
  srcIpAddress*            string   Source IP address used for the primary stream leg.
  dstIpAddress*            string   Destination IP address used for the primary stream leg.
  dstUdpPort*              number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId          number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*          number   RTP payload type value assigned to the stream.
  rtpTimeToLive            number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcIpAddress*  string   Source IP address used for the redundant leg.
  redundancyDstIpAddress*  string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*    number   Destination UDP port used for the redundant leg.
  linkOffsetDelay          number   Additional latency in microseconds applied to align the redundant link.
}
txAudioStream0* {
TX audio stream settings
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
}
txAudioStreamManual0* {
TX audio stream advanced settings
  packetTime               number   Packetization time in microseconds for the stream.
  isIPv6Enabled*           boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*     boolean
  isIPMXEnabled            boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*              number   Source UDP port used for the primary stream leg.
  dstIpAddress*            string   Destination IP address used for the primary stream leg.
  dstUdpPort*              number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*         number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*          number   RTP payload type value assigned to the stream.
  rtpTimeToLive*           number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcUdpPort*    number   Source UDP port used for the redundant leg.
  redundancyDstIpAddress*  string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*    number   Destination UDP port used for the redundant leg.
}
rxAncStream0* {
RX ancillary stream settings
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
  sdpUrl*  string   URL pointing to the SDP file describing this stream.
}
rxAncStreamManual0* {
RX ancillary stream advanced settings
  isIPv6Enabled*           boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*     boolean  Indicates whether redundant streaming is active for this resource.
  srcIpAddress*            string   Source IP address used for the primary stream leg.
  dstIpAddress*            string   Destination IP address used for the primary stream leg.
  dstUdpPort*              number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId          number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*          number   RTP payload type value assigned to the stream.
  rtpTimeToLive            number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcIpAddress*  string   Source IP address used for the redundant leg.
  redundancyDstIpAddress*  string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*    number   Destination UDP port used for the redundant leg.
  linkOffsetDelay          number   Additional latency in microseconds applied to align the redundant link.
}
txAncStream0* {
TX ancillary stream settings
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
```

}

txAncStreamManual0* {

TX ancillary stream advanced settings

packetTime	number	Packetization time in microseconds for the stream.
isIPv6Enabled*	boolean	Indicates whether IPv6 addressing is enabled for this stream.
isRedundancyEnabled*	boolean	
isIPMXEnabled	boolean	Indicates whether IPMX interoperability is enabled for the stream.
srcUdpPort*	number	Source UDP port used for the primary stream leg.
dstIpAddress*	string	Destination IP address used for the primary stream leg.
dstUdpPort*	number	Destination UDP port used for the primary stream leg.
rtpSyncSourceId*	number	RTP synchronization source identifier (SSRC).
rtpPayloadType*	number	RTP payload type value assigned to the stream.
rtpTimeToLive*	number	Time-to-live applied to packets on the primary RTP stream.
redundancySrcUdpPort*	number	Source UDP port used for the redundant leg.
redundancyDstIpAddress*	string	Destination IP address used for the redundant leg.
redundancyDstUdpPort*	number	Destination UDP port used for the redundant leg.

}

otherSettings* {

Other settings

igmpVersion*	enum	**Allowed:**none, v2, v3 IGMP version (RX only)
areButtonsLocked*	boolean	Indicates whether the buttons are locked or not.
selectPrivateKey*	enum	**Allowed:**ManufacturerRsaServerPrivateKey, ManufacturerEcdsaServerPrivateKey, CustomerRsaServerPrivateKey, CustomerEcdsaServerPrivateKey Select the private key and the certificate to use.
isClientServerRole*	boolean	Indicates whether the client certificates must be validated or not.
isTestSignalEnabled*	boolean	Enable test signal
testSignalMode	enum	**Allowed:**video, audioVideo Test pattern mode applied to the video output.
isWatchdogEnabled*	boolean	Enable the watchdog
clampToLimitedRange*	boolean	Enforce legal values for limited range
troubleshootingControl*	number	Diagnostic control mode applied to the device.
daisyChainingPosition*	number	Relative position of the unit when devices are daisy chained.
groupName	string	**DEFAULT:**IP OUT/IN Group name to customize urn:x-nmos:tag with.
groupNameRx	string	**DEFAULT:**IP IN Group name to customize urn:x-nmos:tag with of the receiver on a gateway.
groupNameTx	string	**DEFAULT:**IP OUT Group name to customize urn:x-nmos:tag with of the sender on a gateway.
sapInterval*	number	between 0 and 300000 **DEFAULT:**0 SAP announcement interval in milliseconds. `0` disables the service. `1` enables the service with a default interval.

}

rxAutoSettings* {

Automatic mode settings

interface*	enum	**Allowed:**lan0, lan1, lan2 Network interface to use
isIPv6*	boolean	Indicates whether the connection uses IPv6 or IPv4.
isSecured*	boolean	Indicates whether HTTPS is required.
selectPrivateKey*	enum	**Allowed:**ManufacturerRsaServerPrivateKey, ManufacturerEcdsaServerPrivateKey, CustomerRsaServerPrivateKey, CustomerEcdsaServerPrivateKey Select the private key and certificate to use.
isClientServerRole*	boolean	Indicates whether the auto mode expects a client or server role.

```
    name*            string   Friendly name assigned to the configuration.
    ipAddress*       string   IP address associated with the auto mode peer.
    port*            integer  between 0 and  65535
                              Port number on which to connect
    videoSender*     string   NMOS UUID of the video sender
    audioSender*     string   NMOS UUID of the audio sender
    ancSender*       string   NMOS UUID of the ancillary sender
  }
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

5.22 POST /device/settings/reset

Reset the user configuration

Reset the device to default user configuration. You must reboot your device for the changes to take effect.

Request

Request Body - application/json

```
{
Mask-based request used to reset selected configuration blocks to factory defaults.
  resetMask* integer  Bit mask identifying which configuration blocks to reset.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

6. DIAGNOSTICS

6.1 GET /device/settings/diag/control

Get the diagnostic control settings (RX only)

Retrieve diagnostic control parameters for RX devices, including jitter expectations and IGMP behavior.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Diagnostic control settings
  diagStreamIndex*         integer  between 0 and  16
                                    Index of the stream for which diagnostic data is gathered.
  diagExpectedJitter*      integer  between 0 and  581348
                                    Maximum jitter threshold, in microseconds, expected before flagging a warning.
  pushIGMPReports*         boolean  Indicates whether the IGMP reports are automatically refreshed.
  captureRejectedPackets*  enum     Allowed:disabled, low, medium, high
                                    Indicates whether diagnostic captures include packets rejected by filters.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

6.2 POST /device/settings/diag/control

Set the diagnostic control settings (RX only)

Configure diagnostic parameters for RX devices, such as jitter threshold and IGMP report behavior.

Request

Request Body - application/json

```
{
Diagnostic control settings
  diagStreamIndex*         integer  between 0 and  16
                                    Index of the stream for which diagnostic data is gathered.
  diagExpectedJitter*      integer  between 0 and  581348
                                    Maximum jitter threshold, in microseconds, expected before flagging a warning.
  pushIGMPReports*         boolean  Indicates whether the IGMP reports are automatically refreshed.
  captureRejectedPackets*  enum     Allowed:disabled, low, medium, high
                                    Indicates whether diagnostic captures include packets rejected by filters.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

6.3 GET /device/settings/diag/data

Get the diagnostic data (RX only)

Retrieve diagnostic metrics from the RX device, including packet statistics, jitter, interface bitrate, and clock tracking status.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Diagnostic data
  missingPacketMain*        integer between 0 and 4294967295
                            Number of missing packets on the primary media port.
  missingPacketSec*         integer between 0 and 4294967295
                            Number of missing packets on the secondary media port.
  fecCorErr*                integer between 0 and 4294967295
                            Number of packets corrected by the FEC module.
  replay*                   integer between 0 and 4294967295
                            Number of replay events
  skip*                     integer between 0 and 4294967295
                            Number of skip events
  frameErr*                 integer between 0 and 4294967295
                            Number of times the stream decompression didn't complete in time.
  firstPacketToNextFrame*   integer between 0 and 4294967295
                            First packet of a frame to the first packet of the next frame (Video 0 only).
  firstPacketToLastPacket*  integer between 0 and 4294967295
                            First packet of a frame to the last packet of the same frame (Video 0 only).
  firstPacketVsRedundancy*  integer between 0 and 4294967295
                            First packet of a frame vs. first packet of redundancy path (Video 0 only).
  firstPacketWdmaVsVout*    integer between 0 and 4294967295
```

First packet at the input of WDMA2110 vs. the output of the video pipeline (Video 0 only).

```
  isFirstPacketOnPrimary*   boolean  DEFAULT:true
```

Indicates whether the primary or secondary path received the first packet.

```
  jitterValue*              integer  between 0 and  4294967295
```

Measured jitter value.

```
  isMacPacketDetected*      boolean  Indicates if packets match the MAC filter.
  isUdpPacketDetected*      boolean  Indicates if packets match the MAC/UDP filter.
  igmpQueryCounter0*        integer  DEFAULT:0
```

Number of IGMP queries on media port 0.

```
  igmpQueryCounter1*        integer  DEFAULT:0
```

Number of IGMP queries on media port 1.

```
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

6.4 POST /device/settings/diag/cleardata

Clear the diagnostic data

Clears all diagnostic data from the device.

Request

Request Body - application/json

```
{
```

Placeholder object used when no additional data is required.

```
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

```
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

6.5 POST /device/update

Update the device

Updates the device. You must reboot your device for the changes to take effect.

Request

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

```
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

7. EDID

7.1 GET /device/settings/video/in/hdmi/edid/passthrough/header

Get EDID header information

Retrieves the EDID header currently captured from the HDMI input when passthrough is active.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
EDID header information
  manufactureName*  string   Manufacturer name
  monitorName*      string   Monitor name
  productCode*      string   Product code
  serialNumber*     string   Serial number
  manufactureDate*  string   Manufacturer name
  version*          string   EDID structure version and revision
  isChecksumValid*  boolean  Indicates whether the EDID checksum is valid.
  isHeaderValid*    boolean  Indicates whether the EDID header is valid.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

7.2 GET /device/settings/video/in/hdmi/edid/passthrough/resolutions

Get EDID supported resolutions

Lists the supported resolutions from the passthrough EDID captured on the HDMI input.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
[{
Array of object: Resolution
  isPresent        boolean  Indicates whether the referenced signal is present.
  width*           integer  Width
  height*          integer  Height
  refreshRateNum*  integer  Refresh rate numerator
  refreshRateDen*  integer  Refresh rate denominator
  scan*            enum     Allowed:progressive, interlaced
                            Interlaced or progressive
}]
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

7.3 GET /device/settings/video/in/hdmi/edid/passthrough/

Get EDID binary

Retrieve the EDID binary data.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
```

```
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

7.4 GET /device/settings/video/in/hdmi/edid/custom/{index}

Get EDID binary

Retrieve the EDID binary from a custom slot.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Custom EDID slot index

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

7.5 POST /device/settings/video/in/hdmi/edid/custom/{index}

Set EDID binary

Upload a custom EDID binary to the specified slot.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Custom EDID slot index

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

7.6 GET /device/settings/video/out/hdmi/edid/monitor/header

Get EDID header information

Retrieves the EDID header reported by the connected monitor.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
EDID header information
  manufactureName*  string   Manufacturer name
  monitorName*      string   Monitor name
  productCode*      string   Product code
  serialNumber*     string   Serial number
  manufactureDate*  string   Manufacturer name
  version*          string   EDID structure version and revision
  isChecksumValid*  boolean  Indicates whether the EDID checksum is valid.
  isHeaderValid*    boolean  Indicates whether the EDID header is valid.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

7.7 GET /device/settings/video/out/hdmi/edid/monitor/resolutions

Get EDID supported resolutions

Lists the resolutions advertised by the connected monitor's EDID.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
[{
Array of object:  Resolution
  isPresent        boolean  Indicates whether the referenced signal is present.
  width*           integer  Width
  height*          integer  Height
  refreshRateNum*  integer  Refresh rate numerator
  refreshRateDen*  integer  Refresh rate denominator
  scan*            enum     Allowed:progressive, interlaced
                            Interlaced or progressive
}]
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
```

```
}
```

7.8 GET /device/settings/video/out/hdmi/edid/monitor/

Get EDID binary

Retrieve the EDID binary data from the connected monitor.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

7.9 GET /device/settings/video/out/hdmi/edid/custom/{index}

Get EDID binary

Retrieve the EDID binary from a specified custom slot.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Custom EDID slot index

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

7.10 POST /device/settings/video/out/hdmi/edid/custom/{index}

Set EDID binary

Upload a custom EDID binary to the specified slot.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Custom EDID slot index

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

---

8. HDCP

8.1 GET /device/settings/hdmi/hdcp

Get HDCP settings

Retrieves the HDCP configuration for the HDMI interface.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
RX and TX user settings
  enableHdcpSupport  boolean  Enable HDCP support
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

8.2 POST /device/settings/hdmi/hdcp

Set HDCP settings

Applies new HDCP settings to the HDMI interface.

Request

Request Body - application/json

```
{
RX and TX user settings
  enableHdcpSupport  boolean  Enable HDCP support
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

```
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

9. LOGS

9.1 GET /device/log/critical

Get the critical log

Downloads the critical event log captured by the device.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - text/encrypted

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

9.2 GET /device/log/standard

Get the standard log

Downloads the standard system log captured by the device.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - text/encrypted

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

9.3 POST /device/standard/clear

Clear the standard log

Clears the standard log.

Request

Request Body - application/json

```
{
Placeholder object used when no additional data is required.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

9.4 GET /device/log/detail

Get the detail log

Downloads the detailed diagnostic log captured by the device.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - text/encrypted

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

9.5 POST /device/detail/clear

Clear the detail log

Clears the detail log.

Request

Request Body - application/json

```
{
Placeholder object used when no additional data is required.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

9.6 GET /device/log/network

Get the last packet capture

Downloads the network log.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - text/encrypted

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

9.7 GET /device/log/ptp

Get the PTP log

Downloads the PTP clock synchronization log.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - text/encrypted

```
string
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

10. NMOS

10.1 GET /device/settings/nmos/interface

Get NMOS interface settings

Retrieves the NMOS network interface settings applied to the node.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
NMOS interface settings
  isEnabled*              boolean  Indicates whether the NMOS server is enabled.
  interface*              enum     Allowed:lan0, lan1, lan2, auto
                                   Interface
  isIPv6*                 boolean  Indicates whether the connection uses IPv6 or IPv4.
  port*                   integer  between 0 and  65535
                                   Port number on which the server listens.
  isSecured*              boolean  Indicates whether HTTPS is required.
  selectPrivateKey*       enum     Allowed:ManufacturerRsaServerPrivateKey,
                                   ManufacturerEcdsaServerPrivateKey,
                                   CustomerRsaServerPrivateKey,
                                   CustomerEcdsaServerPrivateKey
                                   Select the private key and certificate to use.
  isClientServerRole*     boolean  Indicates whether the client certificates must be validated or not.
  nodeName*               string   NMOS node name
  nodeDescription*        string   NMOS node description
  deviceName*             string   NMOS device name
  deviceDescription*      string   NMOS device description
  heartbeatRepeatPeriod*  number   Time interval before sending a heartbeat to the NMOS server.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.2 POST /device/settings/nmos/interface

Set NMOS interface settings

Updates the NMOS network interface configuration for the node.

Request

Request Body - application/json

```
{
NMOS interface settings
  isEnabled*              boolean  Indicates whether the NMOS server is enabled.
  interface*              enum     Allowed:lan0, lan1, lan2, auto
                                   Interface
  isIPv6*                 boolean  Indicates whether the connection uses IPv6 or IPv4.
  port*                   integer  between 0 and  65535
                                   Port number on which the server listens.
  isSecured*              boolean  Indicates whether HTTPS is required.
  selectPrivateKey*       enum     Allowed:ManufacturerRsaServerPrivateKey,
                                   ManufacturerEcdsaServerPrivateKey,
                                   CustomerRsaServerPrivateKey,
                                   CustomerEcdsaServerPrivateKey
                                   Select the private key and certificate to use.
  isClientServerRole*     boolean  Indicates whether the client certificates must be validated or not.
  nodeName*               string   NMOS node name
  nodeDescription*        string   NMOS node description
  deviceName*             string   NMOS device name
  deviceDescription*      string   NMOS device description
  heartbeatRepeatPeriod*  number   Time interval before sending a heartbeat to the NMOS server.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.3 GET /device/settings/nmos/registerserver

Get NMOS registration server settings

Retrieves the NMOS registration server configuration.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Server settings
  isEnabled*          boolean  Indicates whether the server is enabled or not.
  mode*               enum     Allowed:disabled, dns_mdns, dns, mdns, manual
                               Operating mode for this configuration.
  name                string   Name used for certificate validation.
  host*               string   IPv4 address, IPv6 address, or hostname.
  isIPv6*             boolean  Indicates whether the connection uses IPv6 or IPv4.
  port*               integer  between 0 and  65535
                               Server port
  apiVersion*         enum     Allowed:v1.2, v1.3
                               API version
  isSecured*          boolean  Indicates whether HTTPS is required.
  selectPrivateKey*   enum     Allowed:ManufacturerRsaServerPrivateKey,
                               ManufacturerEcdsaServerPrivateKey,
                               CustomerRsaServerPrivateKey,
                               CustomerEcdsaServerPrivateKey
                               Select the private key and the cerficate to use.
  isClientServerRole* boolean  Indicates whether the client certificate will be validated by the server.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.4 POST /device/settings/nmos/registerserver

Set NMOS registration server settings

Updates the NMOS registration server configuration.

Request

Request Body - application/json

```
{
Server settings
  isEnabled*          boolean  Indicates whether the server is enabled or not.
  mode*               enum     Allowed:disabled, dns_mdns, dns, mdns, manual
                               Operating mode for this configuration.
  name                string   Name used for certificate validation.
  host*               string   IPv4 address, IPv6 address, or hostname.
  isIPv6*             boolean  Indicates whether the connection uses IPv6 or IPv4.
  port*               integer  between 0 and  65535
                               Server port
  apiVersion*         enum     Allowed:v1.2, v1.3
                               API version
  isSecured*          boolean  Indicates whether HTTPS is required.
  selectPrivateKey*   enum     Allowed:ManufacturerRsaServerPrivateKey,
                               ManufacturerEcdsaServerPrivateKey,
                               CustomerRsaServerPrivateKey,
                               CustomerEcdsaServerPrivateKey
                               Select the private key and the cerficate to use.
  isClientServerRole* boolean  Indicates whether the client certificate will be validated by the server.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.5 GET /device/settings/nmos/receivers/video/{index}

Get NMOS video node description

Retrieves NMOS node identification metadata for the specified video receiver.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Video stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
NMOS sender or receiver node identification
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.6 POST /device/settings/nmos/receivers/video/{index}

Set NMOS video node description

Updates NMOS node identification metadata for the specified video receiver.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Video stream index

Request Body - application/json

```
{
NMOS sender or receiver node identification
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

10.7 GET /device/settings/nmos/receivers/audio/{index}

Get NMOS audio node description

Retrieves NMOS node identification metadata for the specified audio receiver.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Audio stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
NMOS sender or receiver node identification
  label*       string  User-visible label for the resource.
  description* string  Human-readable explanation associated with the status entry.
  groupHint0*  string  Top-level NMOS group hint tag applied to the node.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
```

```
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

10.8 POST /device/settings/nmos/receivers/audio/{index}

Set NMOS video node description

Updates NMOS node identification metadata for the specified audio receiver.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Audio stream index

Request Body - application/json

```
{
NMOS sender or receiver node identification
  label*       string  User-visible label for the resource.
  description* string  Human-readable explanation associated with the status entry.
  groupHint0*  string  Top-level NMOS group hint tag applied to the node.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

10.9 GET /device/settings/nmos/receivers/ANC/{index}

Get NMOS ancillary node description

Retrieves NMOS node identification metadata for the specified ANC receiver.

Request

PATH PARAMETERS

Name	Type	Description

Name	Type	Description
*index	integer	Ancillary stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
NMOS sender or receiver node identification
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.10 POST /device/settings/nmos/receivers/ANC/{index}

Set NMOS ancillary node description

Updates NMOS node identification metadata for the specified ANC receiver.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Ancillary stream index

Request Body - application/json

```
{
NMOS sender or receiver node identification
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status  string   Status on error.
  code    integer  A non-null value indicates that the service encountered an error while processing the request.
  message string   A human friendly error message.
}
```

10.11 GET /device/settings/nmos/senders/video/{index}

Get NMOS video node description

Retrieves NMOS node identification metadata for the specified video sender.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Video stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
NMOS sender or receiver node identification
  label*       string  User-visible label for the resource.
  description* string  Human-readable explanation associated with the status entry.
  groupHint0*  string  Top-level NMOS group hint tag applied to the node.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

Response status on error.

10.12 POST /device/settings/nmos/senders/video/{index}

Set NMOS video node description

Updates NMOS node identification metadata for the specified video sender.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Video stream index

Request Body - application/json

```
{
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

NMOS sender or receiver node identification

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

Response status on error.

10.13 GET /device/settings/nmos/senders/audio/{index}

Get NMOS audio node description

Retrieves NMOS node identification metadata for the specified audio sender.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Audio stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
NMOS sender or receiver node identification
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.14 POST /device/settings/nmos/senders/audio/{index}

Set NMOS video node description

Updates NMOS node identification metadata for the specified audio sender.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Audio stream index

Request Body - application/json

```
{
NMOS sender or receiver node identification
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.15 GET /device/settings/nmos/senders/ANC/{index}

Get NMOS ancillary node description

Retrieves NMOS node identification metadata for the specified ANC sender.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Ancillary stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
NMOS sender or receiver node identification
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

10.16 POST /device/settings/nmos/senders/ANC/{index}

Set NMOS ancillary node description

Updates NMOS node identification metadata for the specified ANC sender.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Ancillary stream index

Request Body - application/json

```
{
NMOS sender or receiver node identification
  label*        string  User-visible label for the resource.
  description*  string  Human-readable explanation associated with the status entry.
  groupHint0*   string  Top-level NMOS group hint tag applied to the node.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

---

11. PTP

11.1 GET /device/status/ptp

Get PTP client status

Retrieves current PTP clock status and synchronization metrics.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
PTP information
  ptpState*       enum     Allowed:Disabled, Leader, FollowerNoLeaderFound,
                           FollowerUnlocked, FollowerLocked, ChangeInProgress
                           Indicates the current state of the PTP client.
  clockIdentity*  string   Clock identity
  syncInterval*   integer  Sync interval
  rawOffset*      string   Raw offset
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

11.2 GET /device/settings/ptp

Get PTP settings

Retrieves the PTP configuration currently applied.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
PTP settings
  isEnabled*            boolean  Indicates whether the PTP service is enabled or not.
  mode*                 enum     Allowed:follower, bmc
                                 PTP mode
  isIPv6*               boolean  Indicates whether the connection is IPv6 or IPv4.
  domain*               integer  between 0 and 127
                                 Domain number
  logSyncInterval*      integer  between -1 and 1
                                 PTP sync message interval expressed as a power-of-two value.
  logAnnounceInterval*  integer  between 0 and 4
                                 PTP announce message interval expressed as a power-of-two value.
  logDelayReqInterval*  integer  between 0 and 5
                                 PTP delay request interval expressed as a power-of-two value.
  isDelayReqEnabled*    boolean  Indicates whether PTP delay request messages are transmitted.
  priority1             integer  between 0 and 255
                                 PTP priority1 value advertised by the device.
  priority2             integer  between 0 and 255
                                 PTP priority2 value advertised by the device.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

11.3 POST /device/settings/ptp

Set PTP settings

Updates the PTP settings. You must reboot the device for the changes to take effect.

Request

Request Body - application/json

```
{
PTP settings
  isEnabled*            boolean  Indicates whether the PTP service is enabled or not.
  mode*                 enum     Allowed:follower, bmc
                                 PTP mode
  isIPv6*               boolean  Indicates whether the connection is IPv6 or IPv4.
  domain*               integer  between 0 and 127
                                 Domain number
  logSyncInterval*      integer  between -1 and 1
                                 PTP sync message interval expressed as a power-of-two value.
  logAnnounceInterval*  integer  between 0 and 4
                                 PTP announce message interval expressed as a power-of-two value.
  logDelayReqInterval*  integer  between 0 and 5
                                 PTP delay request interval expressed as a power-of-two value.
  isDelayReqEnabled*    boolean  Indicates whether PTP delay request messages are transmitted.
  priority1             integer  between 0 and 255
                                 PTP priority1 value advertised by the device.
```

```
  priority2            integer  between 0 and  255
                                PTP priority2 value advertised by the device.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

12. RS-232

12.1 POST /serial/sendString

Send string on RS-232 port

Send a command string to the device through the RS-232 interface.

Request

Request Body - application/json

```
{
Payload describing an RS-232 command to transmit.
  string*  string  Message command to send to RS-232 serial device
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Response returned after issuing an RS-232 command.
  response*  string  Serial device response
}
```

Status Code - 400: Bad request – missing or invalid parameter

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

13. STATUS

13.1 GET /device/status/networks/{index}

Get network settings

Retrieves link state and addressing details for the specified network interface.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	LAN index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
  macAddress*         string   MAC address assigned to the network port.
  isIpv4DhcpAddress*  boolean  Indicates whether the IPv4 address was obtained via DHCP.
  ipv4Address*        string   Configured IPv4 address for the interface.
  ipv4SearchDomains*  string   Search domains applied to IPv4 name resolution.
  ipv4MDNS            boolean  Indicates whether mDNS is enabled for IPv4 on this interface.
  ipv4LLMNR           boolean  Indicates whether LLMNR is enabled for IPv4 on this interface.
  isIpv6DhcpAddress*  boolean  Indicates whether the IPv6 address was obtained via DHCP.
  ipv6Address*        string   Configured IPv6 address for the interface.
  ipv6SearchDomains*  string   Search domains applied to IPv6 name resolution.
  ipv6MDNS            boolean  Indicates whether mDNS is enabled for IPv6 on this interface.
  ipv6LLMNR           boolean  Indicates whether LLMNR is enabled for IPv6 on this interface.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

13.2 GET /device/status

Get device information

Retrieve the current operational status of the device, including temperature, network, video, and service states.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
  PTPState                        enum       Allowed:Disabled, Leader,
                                             FollowerNoLeaderFound,
                                             FollowerUnlocked, FollowerLocked,
                                             ChangeInProgress
                                             Indicates the current state of the PTP client.
  isNmosResourcesRegistered*      boolean    Indicates whether NMOS resources are registered with the
                                             registry.
  isPowerOverEthernetPresent*     boolean    Indicates whether the device is receiving Power over Ethernet.
  temperature*                    string     Temperature
  TemperatureLimit                string     Temperature limit
  isLoggedIn*                     boolean    Indicates whether a user session is currently authenticated.
  registryServer* {
  Server settings
    name*                 string   Server name
    host*                 string   IPv4 address, IPv6 address or host name.
    isIPv6*               boolean  Indicates whether the connection is IPv6 or IPv4.
    port*                 integer  between 0 and  65535
                                   Server port
    isSecured*            boolean  Indicates whether HTTPS is required.
    selectPrivateKey*     enum     Allowed:ManufacturerRsaServerPrivateKey,
                                   ManufacturerEcdsaServerPrivateKey,
                                   CustomerRsaServerPrivateKey,
                                   CustomerEcdsaServerPrivateKey
                                   Select the private key and the certificate to use.
    isClientServerRole*   boolean  Indicates whether the client certificate will be validated by the server.
    priority*             integer  between 0 and  65535
  }
  frameBuffer* {
  Current status of the video input or output signal, including format and presence information.
    isPresent       boolean   Indicates whether a valid video signal is currently detected.
    isCompressed    boolean   Specifies if the detected video signal is compressed (e.g., JPEG XS, PRO AV or
                              uncompressed.
    resolution* {
    Resolution
      isPresent        boolean  Indicates whether the referenced signal is present.
      width*           integer  Width
      height*          integer  Height
      refreshRateNum*  integer  Refresh rate numerator
      refreshRateDen*  integer  Refresh rate denominator
      scan*            enum     Allowed:progressive, interlaced
                                Interlaced or progressive
    }
    pixelFormat*   enum      Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                             yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                             yuv_12_444, rgb_8, rgb_10, rgb_12
                             Enumeration of pixel formats
```

```
  colorSpace*    enum      Allowed:bt601, bt709, bt2020
                           Enumeration of color spaces
}
videos* [{
Array of object: Current status of the video input or output signal, including format and presence information.
  isPresent      boolean   Indicates whether a valid video signal is currently detected.
  isCompressed   boolean   Specifies if the detected video signal is compressed (e.g., JPEG XS, PRO AV or
                           uncompressed.
  resolution* {
  Resolution
    isPresent        boolean Indicates whether the referenced signal is present.
    width*           integer Width
    height*          integer Height
    refreshRateNum*  integer Refresh rate numerator
    refreshRateDen*  integer Refresh rate denominator
    scan*            enum    Allowed:progressive, interlaced
                             Interlaced or progressive
  }
  pixelFormat*   enum      Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                           yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                           yuv_12_444, rgb_8, rgb_10, rgb_12
                           Enumeration of pixel formats
  colorSpace*    enum      Allowed:bt601, bt709, bt2020
                           Enumeration of color spaces
}]
audios* [{
Array of object:
  isPresent*    boolean    Indicates whether the referenced signal is present.
  audioFormat* {
  Defines an audio format supported by the device.
    format*      enum    Allowed:PCM_16, PCM_20, PCM_24, NPCM
                         Audio encoding format identifier.
    sampleRate*  number  Configured audio sample rate in hertz.
    nbChannels*  number  Number of audio channels supported.
  }
}]
networks* [{
Array of object:
  state*        enum    Allowed:undefined, disconnected, autonegociation, RJ45 100M,
                        RJ45 1G, RJ45 2.5G, SFP 10G, SFP 25G
                        Current operational state reported for the resource.
  MACAddress    string  Hardware MAC address for the network interface.
  IPv4Address   string  Current IPv4 address configured for the interface.
  ipv6Address*  string  Configured IPv6 address for the interface.
}]
videoStreams* [{
Array of object:
  state*         enum     Allowed:disabled, active, inactive
                          Current operational state reported for the resource.
  isCompressed   boolean  This field is added to distinguish compression between multiview streams.
  bitrateKbits*  integer  Measured stream bitrate in kilobits per second.
  bppX100        integer  Bits-per-pixel value multiplied by 100 for fractional precision.
  isMaxBpp       boolean  Indicates whether the stream operates at the maximum bits-per-pixel value.
}]
audioStreams* [{
Array of object:
  state*         enum     Allowed:disabled, active, inactive
                          Current operational state reported for the resource.
```

```
    isCompressed   boolean  This field is added to distinguish compression between multiview streams.
    bitrateKbits*  integer  Measured stream bitrate in kilobits per second.
    bppX100        integer  Bits-per-pixel value multiplied by 100 for fractional precision.
    isMaxBpp       boolean  Indicates whether the stream operates at the maximum bits-per-pixel value.
  }]
  ancillaryStreams* [{
  Array of object:
    state*         enum     Allowed:disabled, active, inactive
                            Current operational state reported for the resource.
    isCompressed   boolean  This field is added to distinguish compression between multiview streams.
    bitrateKbits*  integer  Measured stream bitrate in kilobits per second.
    bppX100        integer  Bits-per-pixel value multiplied by 100 for fractional precision.
    isMaxBpp       boolean  Indicates whether the stream operates at the maximum bits-per-pixel value.
  }]
  servicesStatus [{
  Array of object:
    id*            integer  Unique identifier of the status entry.
    timestamp*     integer  Timestamp when the status entry was generated.
    service*       string   Name of the reporting service.
    code*          integer  Device-specific status or error code reported by the service.
    param0*        integer  Service-specific numeric parameter 0.
    param1*        integer  Service-specific numeric parameter 1.
    paramStr*      string   Service-specific string parameter.
    description*   string   Human-readable explanation associated with the status entry.
  }]
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

14. TIME

14.1 GET /device/settings/time

Get time settings

Retrieves the device time synchronization configuration.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Time settings
  mode*          enum     Allowed:NtpServer, DeviceTime, SystemTime
                          Time synchronization mode
  interface*     enum     Allowed:lan0, lan1, lan2
                          Network interface used for time synchronization
  isIPv6*        boolean  Indicates whether the connection is IPv6 or IPv4.
  ntpServer*     string   NTP server (IPv4 address, IPv6 address, or host name).
  timestamp_s*   integer  Timestamp in seconds (SystemTime mode; not preserved after reboot).
  timestamp_ns*  integer  Timestamp in nanoseconds (SystemTime mode; not preserved after reboot).
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

14.2 POST /device/settings/time

Set time settings

Updates the device's time settings. You must reboot the device for changes to take effect.

Request

Request Body - application/json

```
{
Time settings
  mode*          enum     Allowed:NtpServer, DeviceTime, SystemTime
                          Time synchronization mode
  interface*     enum     Allowed:lan0, lan1, lan2
                          Network interface used for time synchronization
  isIPv6*        boolean  Indicates whether the connection is IPv6 or IPv4.
  ntpServer*     string   NTP server (IPv4 address, IPv6 address, or host name).
  timestamp_s*   integer  Timestamp in seconds (SystemTime mode; not preserved after reboot).
  timestamp_ns*  integer  Timestamp in nanoseconds (SystemTime mode; not preserved after reboot).
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

15. USER

15.1 POST /user/login

Log in to the system

Authenticates a user and starts a session.

Request

Request Body - application/json

{

User credentials required to authenticate with the API.

`username*`	`string`	Username
`password*`	`string`	Password
`closeExistingSessions`	`boolean`	Close existing sessions

}

Response

Status Code - 200: Successful operation

Response Model - application/json

{

Session tokens and metadata returned after a successful login.

`access_token*`	`string`	Access token
`authenticationMode*`	`enum`	**Allowed:** `Local` Authentication mode that granted the current session.
`email*`	`string`	Email
`expires_in*`	`string`	Expiration
`firstName*`	`string`	FirstName
`lastName*`	`string`	LastName
`refresh_token*`	`string`	Refresh token returned for session renewal.
`role*`	`enum`	**Allowed:** `defaultAdmin, admin, operator` Role
`username*`	`string`	Username

}

Status Code - 400: Invalid username or password

Status Code - default: Error response

Response Model - application/json

{

Response status on error.

`status`	`string`	Status on error.
`code`	`integer`	A non-null value indicates that the service encountered an error while processing the request.
`message`	`string`	A human friendly error message.

}

15.2 POST /user/logout

Log out the current user session

Terminate the active user session

Request

No request parameters

Response

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

15.3 GET /user/profile

Get user profile

Retrieve the profile details of the currently logged-in user.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
A complete user profile including identity and role.
  username*   string  Unique username of the user.
  firstName*  string  First name of the user.
  lastName*   string  Last name of the user.
  role*       enum    Allowed:defaultAdmin, admin, operator
                      The role assigned to a user, which determines their level of access.
}
```

Status Code - 400: Invalid username supplied

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - 404: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

15.4 POST /user/profile

Update user profile

Update the currently logged-in user's profile information.

Request

Request Body - application/json

```
{
```

Schema for creating a new user profile.

firstName*	string	First name of the new user.
lastName*	string	Last name of the new user.
username*	string	Desired unique username for the new user.
password*	string	Initial password for the new user. Must comply with password policy (minimum length, special characters, etc.).
role*	enum	**Allowed:** defaultAdmin, admin, operator The role assigned to a user, which determines their level of access.

```
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

status	string	Status on error.
code	integer	A non-null value indicates that the service encountered an error while processing the request.
message	string	A human friendly error message.

```
}
```

15.5 GET /user/profile/all

Get all user profiles

Retrieve a list of all configured user profiles on the device.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
[{
```

Array of object: A complete user profile including identity and role.

username*	string	Unique username of the user.
firstName*	string	First name of the user.
lastName*	string	Last name of the user.
role*	enum	**Allowed:** defaultAdmin, admin, operator The role assigned to a user, which determines their level of access.

```
}]
```

Status Code - 400: Invalid username supplied

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - 404: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

15.6 PUT /user/password

Change user password

Update the password for the currently authenticated user.

Request

Request Body - application/json

```
{
Schema for updating a user's password.
The request must include the username, the current password for authentication,  and the new password to be set.
  username*     string  Unique username of the account whose password is being changed.
  curPassword*  string  The current password for the user. Used to authenticate before allowing the change.
  newPassword*  string  The new password to set for the user. Must follow the system's password policy (e.g., minimum length, special
                        characters).
}
```

Response

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

15.7 POST /user/register

Register a user

Creates a new local user account with the supplied credentials and role assignments.

Request

Request Body - application/json

```
{
```

Schema for creating a new user profile.

```
  firstName*  string  First name of the new user.
  lastName*   string  Last name of the new user.
  username*   string  Desired unique username for the new user.
  password*   string  Initial password for the new user. Must comply with password policy (minimum length, special characters, etc.).
  role*       enum    Allowed:defaultAdmin, admin, operator
                      The role assigned to a user, which determines their level of access.
}
```

Response

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

15.8 POST /user/delete

Delete a user

Deletes the specified user account from the system.

Request

Request Body - application/json

```
{
Schema containing only a username, typically used for identifying a user.
  username*  string  Unique username of the user.
}
```

Response

Status Code - 400: Invalid username supplied

Status Code - 404: User not found

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

---

16. VIDEO

16.1 GET /device/settings/video/passthrough

Get video passthrough setting

Retrieve the current video passthrough setting. Indicates whether passthrough is enabled.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Settings that control HDMI video and audio passthrough behavior.
  enablePassthrough*  boolean  Indicates whether the passthrough feature is enabled or not.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

16.2 POST /device/settings/video/passthrough

Set video passthrough setting

Enable or disable video passthrough mode on the device.

Request

Request Body - application/json

```
{
Settings that control HDMI video and audio passthrough behavior.
  enablePassthrough*  boolean  Indicates whether the passthrough feature is enabled or not.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/octet-stream

```
string
```

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string    Status on error.
  code     integer   A non-null value indicates that the service encountered an error while processing the request.
  message  string    A human friendly error message.
}
```

16.3 GET /device/settings/video/in/mode

Get video input mode

Retrieves the current video input mode configuration.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Video in settings
  isEdidOverrideEnabled*  boolean  Enable EDID override
  selectEdid*             enum     Allowed:passthrough, custom0, base
                                   EDID mode
  noSignalOption*         enum     Allowed:message, nooutput, bitmap
                                   Signal behavior to use when no source is detected.
  syncType                enum     Allowed:ipmx, 2110, blackburst
                                   Synchronization reference type.
  isAudioSourceEmbedded*  boolean  Indicates whether audio should be sourced from the embedded input.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

16.4 POST /device/settings/video/in/mode

Set video input mode

Request

Request Body - application/json

```
{
Video in settings
  isEdidOverrideEnabled*  boolean  Enable EDID override
  selectEdid*             enum     Allowed:passthrough, custom0, base
                                   EDID mode
  noSignalOption*         enum     Allowed:message, nooutput, bitmap
                                   Signal behavior to use when no source is detected.
  syncType                enum     Allowed:ipmx, 2110, blackburst
                                   Synchronization reference type.
  isAudioSourceEmbedded*  boolean  Indicates whether audio should be sourced from the embedded input.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

16.5 GET /device/settings/video/out/mode

Get video output mode

Retrieves the current video output mode configuration.

Request

No request parameters

Response

Status Code - 200: Successful operation

Response Model - application/json

```
{
Video out settings
  selectResolution*       enum     Allowed:stream, edidpreference, force
                                   Selection of resolution
  resolution* {
  Resolution
    isPresent        boolean Indicates whether the referenced signal is present.
    width*           integer Width
    height*          integer Height
    refreshRateNum*  integer Refresh rate numerator
    refreshRateDen*  integer Refresh rate denominator
    scan*            enum    Allowed:progressive, interlaced
                             Interlaced or progressive
  }
  selectPixelFormat*      enum     Allowed:stream, edidpreference, force
                                   Selection of pixel format
  pixelFormat*            enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                                   yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                                   yuv_12_444, rgb_8, rgb_10, rgb_12
                                   Enumeration of pixel formats
  colorSpace*             enum     Allowed:bt601, bt709, bt2020
                                   Enumeration of color spaces
  isEdidOverrideEnabled* boolean   Enable EDID override
  selectEdid*             enum     Allowed:custom0
                                   mode
  noSignalOption*         enum     Allowed:message, nooutput, bitmap, blank, lastframe
                                   Signal behavior to use when no source is detected.
  syncType                enum     Allowed:ipmx, 2110, blackburst
                                   Synchronization reference type.
  syncOffset              number   Output sync offset in microseconds.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

16.6 POST /device/settings/video/out/mode

Set video output mode

Applies new video output mode settings.

Request

Request Body - application/json

```
{
Video out settings
  selectResolution*       enum     Allowed:stream, edidpreference, force
                                   Selection of resolution
  resolution* {
  Resolution
    isPresent        boolean  Indicates whether the referenced signal is present.
    width*           integer  Width
    height*          integer  Height
    refreshRateNum*  integer  Refresh rate numerator
    refreshRateDen*  integer  Refresh rate denominator
    scan*            enum     Allowed:progressive, interlaced
                              Interlaced or progressive
  }
  selectPixelFormat*      enum     Allowed:stream, edidpreference, force
                                   Selection of pixel format
  pixelFormat*            enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                                   yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                                   yuv_12_444, rgb_8, rgb_10, rgb_12
                                   Enumeration of pixel formats
  colorSpace*             enum     Allowed:bt601, bt709, bt2020
                                   Enumeration of color spaces
  isEdidOverrideEnabled* boolean   Enable EDID override
  selectEdid*             enum     Allowed:custom0
                                   mode
  noSignalOption*         enum     Allowed:message, nooutput, bitmap, blank, lastframe
                                   Signal behavior to use when no source is detected.
  syncType                enum     Allowed:ipmx, 2110, blackburst
                                   Synchronization reference type.
  syncOffset              number   Output sync offset in microseconds.
}
```

Response

Status Code - 200: Successful operation

Response Model - application/json

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

16.7 GET /device/settings/streams/video/{index}

Get video stream settings

Retrieves configuration for the specified video stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

```
ONE OF
OPTION 1 {
  enable*                boolean  Indicates whether this stream or feature is enabled.
  nmosId                 string   NMOS identifier associated with this resource.
  selectResolution*      enum     Allowed:input, force
                                  Selection of resolution
  resolution* {
  Resolution
    isPresent            boolean  Indicates whether the referenced signal is present.
    width*               integer  Width
    height*              integer  Height
    refreshRateNum*      integer  Refresh rate numerator
    refreshRateDen*      integer  Refresh rate denominator
    scan*                enum     Allowed:progressive, interlaced
                                  Interlaced or progressive
  }
  selectPixelFormat*     enum     Allowed:input, force
                                  Selection of pixel format
  pixelFormat*           enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                                  yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                                  yuv_12_444, rgb_8, rgb_10, rgb_12
                                  Enumeration of pixel formats
  colorSpace*            enum     Allowed:bt601, bt709, bt2020
                                  Enumeration of color spaces
  isCompressionEnabled*  boolean  DEFAULT:true
                                  Enable JPEG XS compression (TX only)
  intraFrameCompression  boolean  Enable intra-frame-only compression (TX only)
  bitRateUHD*            number   Target bitrate for resolutions larger than Full HD, in Mbps.
  bitRateHD*             number   Target bitrate for resolutions up to Full HD, in Mbps.
}
OPTION 2 {
  enable*  boolean  Indicates whether this stream or feature is enabled.
  nmosId   string   NMOS identifier associated with this resource.
  sdpUrl*  string   URL pointing to the SDP file describing this stream.
}
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
```

```
    code     integer
    message  string
  }
```

16.8 POST /device/settings/streams/video/{index}

Set video stream settings

Applies configuration changes to the specified video stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
TX video stream settings
  enable*                boolean  Indicates whether this stream or feature is enabled.
  nmosId                 string   NMOS identifier associated with this resource.
  selectResolution*      enum     Allowed:input, force
                                  Selection of resolution
  resolution* {
  Resolution
    isPresent        boolean  Indicates whether the referenced signal is present.
    width*           integer  Width
    height*          integer  Height
    refreshRateNum*  integer  Refresh rate numerator
    refreshRateDen*  integer  Refresh rate denominator
    scan*            enum     Allowed:progressive, interlaced
                              Interlaced or progressive
  }
  selectPixelFormat*     enum     Allowed:input, force
                                  Selection of pixel format
  pixelFormat*           enum     Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                                  yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                                  yuv_12_444, rgb_8, rgb_10, rgb_12
                                  Enumeration of pixel formats
  colorSpace*            enum     Allowed:bt601, bt709, bt2020
                                  Enumeration of color spaces
  isCompressionEnabled*  boolean  DEFAULT:true
                                  Enable JPEG XS compression (TX only)
  intraFrameCompression  boolean  Enable intra-frame-only compression (TX only)
  bitRateUHD*            number   Target bitrate for resolutions larger than Full HD, in Mbps.
  bitRateHD*             number   Target bitrate for resolutions up to Full HD, in Mbps.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
```

```
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```
Response status on error.

```
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

16.9 GET /device/settings/streams/video/{index}/manual

Get video stream manual settings

Retrieves advanced manual settings for the specified video stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Response

Status Code - 200: Successful operation

Response Model - application/json

ONE OF

OPTION 1 {

```
  isIPv6Enabled*           boolean  Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*     boolean  Indicates whether redundant streaming is active for this resource.
  isIPMXEnabled            boolean  Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*              number   Source UDP port used for the primary stream leg.
  dstIpAddress*            string   Destination IP address used for the primary stream leg.
  dstUdpPort*              number   Destination UDP port used for the primary stream leg.
  rtpSyncSourceId*         number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*          number   RTP payload type value assigned to the stream.
  rtpTimeToLive*           number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcUdpPort*    number   Source UDP port used for the redundant leg.
  redundancyDstIpAddress*  string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*    number   Destination UDP port used for the redundant leg.
  payloadSize*             number   Payload size per packet in bytes.
}
```

OPTION 2 {

```
  resolution* {
```
Resolution

```
    isPresent        boolean  Indicates whether the referenced signal is present.
    width*           integer  Width
    height*          integer  Height
    refreshRateNum*  integer  Refresh rate numerator
    refreshRateDen*  integer  Refresh rate denominator
    scan*            enum     Allowed:progressive, interlaced
```

Interlaced or progressive

```
    }
    pixelFormat*            enum      Allowed:yuv_8_420, yuv_10_420, yuv_12_420, yuv_8_422,
                                      yuv_10_422, yuv_12_422, yuv_8_444, yuv_10_444,
                                      yuv_12_444, rgb_8, rgb_10, rgb_12
                                      Enumeration of pixel formats
    colorSpace*             enum      Allowed:bt601, bt709, bt2020
                                      Enumeration of color spaces
    colorTcs                enum      Allowed:undefined, sdr, pq, hlg
                                      Enumeration of color transfer characteristic systems
    isIPv6Enabled*          boolean   Indicates whether IPv6 addressing is enabled for this stream.
    isCompressionEnabled*   boolean   DEFAULT:true
                                      Indicates whether compression is active for the current stream configuration.
    isRedundancyEnabled*    boolean   Indicates whether redundant streaming is active for this resource.
    isIPMXEnabled*          boolean   Indicates whether IPMX interoperability is enabled for the stream.
    srcIpAddress*           string    Source IP address used for the primary stream leg.
    dstIpAddress*           string    Destination IP address used for the primary stream leg.
    dstUdpPort*             number    Destination UDP port used for the primary stream leg.
    rtpSyncSourceId*        number    RTP synchronization source identifier (SSRC).
    rtpPayloadType*         number    RTP payload type value assigned to the stream.
    rtpTimeToLive*          number    Time-to-live applied to packets on the primary RTP stream.
    redundancySrcIpAddress* string    Source IP address used for the redundant leg.
    redundancyDstIpAddress* string    Destination IP address used for the redundant leg.
    redundancyDstUdpPort*   number    Destination UDP port used for the redundant leg.
    linkOffsetDelay         number    Additional latency in microseconds applied to align the redundant link.
  }
```

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

16.10 POST /device/settings/streams/video/{index}/manual

Set video stream manual settings

Applies advanced manual settings to the specified video stream.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
TX video stream advanced settings
  isIPv6Enabled*          boolean   Indicates whether IPv6 addressing is enabled for this stream.
  isRedundancyEnabled*    boolean   Indicates whether redundant streaming is active for this resource.
  isIPMXEnabled           boolean   Indicates whether IPMX interoperability is enabled for the stream.
  srcUdpPort*             number    Source UDP port used for the primary stream leg.
  dstIpAddress*           string    Destination IP address used for the primary stream leg.
  dstUdpPort*             number    Destination UDP port used for the primary stream leg.
```

```
  rtpSyncSourceId*          number   RTP synchronization source identifier (SSRC).
  rtpPayloadType*           number   RTP payload type value assigned to the stream.
  rtpTimeToLive*            number   Time-to-live applied to packets on the primary RTP stream.
  redundancySrcUdpPort*     number   Source UDP port used for the redundant leg.
  redundancyDstIpAddress*   string   Destination IP address used for the redundant leg.
  redundancyDstUdpPort*     number   Destination UDP port used for the redundant leg.
  payloadSize*              number   Payload size per packet in bytes.
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status   string
  code     integer
  message  string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
Response status on error.
  status   string   Status on error.
  code     integer  A non-null value indicates that the service encountered an error while processing the request.
  message  string   A human friendly error message.
}
```

16.11 POST /device/settings/streams/videosdp/{index}

Update video settings from SDP file

Updates the specified video stream by importing parameters from an SDP file.

Request

PATH PARAMETERS

Name	Type	Description
*index	integer	Stream index

Request Body - application/json

```
{
Object containing SDP file
  sdpContent*  string  SDP file content
}
```

Response

Status Code - 200: Successful operation

Status Code - 401: Authentication required (user not logged in)

Response Model - application/json

```
{
  status  string
  code    integer
  message string
}
```

Status Code - default: Error response

Response Model - application/json

```
{
```

Response status on error.

status	string	Status on error.
code	integer	A non-null value indicates that the service encountered an error while processing the request.
message	string	A human friendly error message.

```
}
```