OnePlus 8T (KB2005) – Android 13 – crDroid 9.9 – NetHunter – External WiFi Adapter Working

⚙ 1. Reset to Stock Firmware using MSM Tool

Use this to restore stock and prepare for ROM install.

1. Power off the phone.
2. Hold VOL+ & VOL- (⚠ do not press Power).
3. Connect to PC.

MSM Tool: wait for ENUM → Start (screen stays black). This rolls back to Android 11.

Do not update firmware after this.

2. Unlock Bootloader

Unlocks the phone for custom ROM flashing.

```
./adb devices
./adb reboot bootloader
./fastboot flashing unlock
```

Confirm on phone → Wipe data → Reboot and complete setup.

3. Flash Custom ROM (crDroid 9.9 – Android 13)

Enable USB debugging → Reboot to bootloader:

```
./adb reboot bootloader
```

Files to place in platform-tools folder:

- crDroidAndroid-13.0-20230929-kebab-v9.9.zip
- NikGapps-core-arm64-13-20250716-signed.zip
- vbmeta.img
- vbmeta_system.img
- recovery.img

Flash vbmeta and vbmeta_system (disable verity first):

```
./fastboot --disable-verity --disable-verification flash vbmeta vbmeta.img
./fastboot --disable-verity --disable-verification flash vbmeta_system vbmeta_system.img
```

OnePlus 8T (KB2005) – Android 13 – crDroid 9.9 – NetHunter – External WiFi Adapter Working

Reboot to recovery:

```
./fastboot boot recovery.img
```

Install ROM:

```
./adb sideload crDroidAndroid-13.0-20230929-kebab-v9.9.zip
```

(47% stop is normal). Then sideload GApps:

```
./adb sideload NikGapps-core-arm64-13-20250716-signed.zip
```

First boot may take several minutes.

4. Gain Root Access with Magisk

```
./adb reboot recovery
./adb sideload Magisk-v27.0.zip
```

Reboot → Install Magisk-v27.0.apk manually → Complete setup → Verify root.

5. Make System Partition Read/Write (RO2RW)

Copy to phone:

- RO2RW-StableBeta.v3.7.2.1.zip

- Termux APK

In Termux:

```
apt update && apt upgrade -y
```

Flash RO2RW ZIP in Magisk → Reboot → In Termux:

```
su
ro2rw
```

Responses:

1 → Install

1 → Max expansion

1 → Continue

2 → YES to DFE

(any key)

2 → NO REMOVE

2 → NO BACKUP

1 → Force Disable (fastboot/sparse)

```
./adb reboot bootloader
./fastboot flash super super-rw-sparse-fastboot-active-_b.img
./fastboot reboot recovery
```

On phone: Factory reset → Format data → Boot system.

Verify root and use ro2rw --check to confirm.

6. Install Kali NetHunter

Files:

- kali-nethunter-2025.3-oneplus8-oos-twelve-full.zip
- NetErnel_v1_opkona.zip
- NetErnel_modules_opkona.zip

⚠ Delete included kernel from NetHunter ZIP (do not unzip rest).

Flash NetHunter ZIP in Magisk → Wait 25 mins → Reboot → Open NetHunter App and run:

```
echo 'APT::Sandbox::User "root";' | sudo tee /etc/apt/apt.conf.d/01-android-nosandbox
apt install kali-linux-everything -y
apt update && apt upgrade -y
apt autoremove -y
```

⚡ 7. Flash Kernel

In SmartPack Kernel Manager:

Menu → Flash NetErnel_v1_opkona.zip → Reboot.

In Magisk → Modules → Install NetErnel_modules_opkona.zip → Reboot.

8. External WiFi Adapter Modules

In SmartPack Kernel Manager → Script Manager → (+) New Script → Name: external_wifi_driver_load

OnePlus 8T (KB2005) – Android 13 – crDroid 9.9 – NetHunter – External WiFi Adapter Working

Paste:

```
insmod /system/lib/modules/rtl_drivers/88XXau.ko
insmod /system/lib/modules/rtl_drivers/8188eu.ko
insmod /system/lib/modules/rtl_drivers/8192eu.ko
insmod /system/lib/modules/rtl_drivers/8192fu.ko
insmod /system/lib/modules/rtl_drivers/8814au.ko
```

Save → Enable On Boot → Reboot.

Setup Complete: OnePlus 8T (KB2005) now runs crDroid 9.9 (Android 13) with Magisk, RO2RW, Kali NetHunter, and full WiFi adapter support.

Final Step (Recommended Stability Fix)

After completing everything and confirming that your setup is working, run the following commands again from platform-tools to ensure system integrity and avoid crashes:

```
./fastboot --disable-verity --disable-verification flash vbmeta vbmeta.img
./fastboot --disable-verity --disable-verification flash vbmeta_system vbmeta_system.img
./fastboot reboot
```

Note: Running these again does NOT delete or wipe data. It simply refreshes vbmeta partitions with verification disabled to prevent dm-verity issues or bootloops after modification.
Once the device reboots successfully, your setup is fully stable.