



DPUKeyboardState

Outputs for every key of the keyboard whether the key is currently pressed or not. Please note that on most keyboards no more than two or three simultaneous key presses can be processed.

1. Outputs:

[keyname]

For every key of the keyboard an output is present. The output's value is 1, if the key is pressed, or 0, if the key is not pressed. A list of defined keys is following.

Keyname	Description	Keyname	Description
Back	← (delete; Backspace)	A	Keys with letters
Tab		B	
Return		C	
Shift	Both Shift keys	D	
LShift	Left Shift key	E	
RShift	Right Shift key	F	
Control	Both Ctrl keys	G	
LControl	Left Ctrl key	H	
RControl	Right Ctrl key	I	
Alt	Both Alt keys	J	
LAlt	Left Alt keys	K	
RAlt	Right Alt key	L	
Pause		M	
Capital		N	
Escape		O	
Space		P	
PageUp	Page up ↑	Q	
PageDown	Page down ↓	R	
End	End	S	
Home	Pos1	T	
Left	Cursor ←	U	
Up	Cursor ↑	V	
Right	Cursor →	W	
Down	Cursor ↓	X	
Print	Print	Y	



SILAB DRIVING SIMULATION

version Version 7.1 documentation

Snapshot		Z	
Insert	Insert (Ins)	AE	
Delete	Delete (Del)	OE	
Help		UE	
0	Numeric keys in the left part of the keyboard, above letters.	NumPad0	Numeric keys in the right part of the keyboard, Num pad.
1		NumPad1	
2		NumPad2	
3		NumPad3	
4		NumPad4	
5		NumPad5	
6		NumPad6	
7		NumPad7	
8		NumPad8	
9		NumPad9	
F1	Function Keys	NumPadMultiply	Calculation functions located at Num pad
F2		NumPadAdd	
F3		NumPadSubtract	
F4		NumPadDecimal	
F5		NumPadDivide	
F6		Add	Keys with special functions located on the left side of the keyboard, above letters.
F7		Subtract	
F8		Decimal	
F9		Comma	
F10		Number	
F11		Less	
F12		Greater	
NumLock		Roof	
Scroll	Scroll lock ↓	SZ	
		Accent	
		LWin	Left Windows key
		RWin	Right Windows key
		Context	Context menu key
		Separator	