

MfRDJ Installation & Setup Guide

MfRDJ Installation & Setup Guide

Overview

MfRDJ supports two setup modes:

Local Setup (Single PC)

All components run on one machine:

- MfRDJ
- Icecast
- Caddy

Use this for:

- Testing
 - Development
 - Private use
-

Server Setup (Network / Internet)

Icecast + Caddy run on a **server PC**, accessible by:

- Local network (LAN)
- Internet (public users)

Use this for:

- Radio stations
 - Public streaming
 - Multi-device access
-

Network Basics (IMPORTANT)

Situation	Host
Same PC	127.0.0.1

Situation	Host
Local Network	192.168.x.x
Internet	Domain or Public IP

Explanation

127.0.0.1

- Refers to **your own PC**
- Only works locally

192.168.x.x

- Local network address
- Works on devices in same network

Domain / Public IP

- Required for internet streaming
- Example:

factoryxradio.asuscomm.com

Icecast Setup

1. Extract:

```
..\MfPack\Samples\MfRdjJ\Binaries\icecast_win64_2.5.0.zip
```

2. Install Icecast

3. Replace config:

```
..\MfPack\Samples\MfRdjJ\Binaries\IceCast_defXML\icecast.xml
```

Caddy Setup (Web + PWA)

1. Extract:

```
..\MfPack\Samples\MfRdjJ\Binaries\Caddy_PWA.zip
```

2. Copy to:

```
C:\Caddy
```

Windows Firewall (SERVER PC)

Must allow:

Applications:

- `icecast.exe`
- `caddy.exe`

Ports:

Port	Purpose
8000	Stream
80	HTTP
443	HTTPS

Enable for:

- Private
 - Public
-

Router Setup (Internet Streaming)

Enable Port Forwarding:

External	Internal	IP
80	80	Server IP
443	443	Server IP

DDNS (Recommended)

Example (ASUS):

factoryxradio.asuscomm.com

Enable:

- DDNS
 - Let's Encrypt SSL
-

Server PC vs User Device

Server PC

Runs:

- MfRDJ
- Icecast
- Caddy

Must have:

- Firewall configured
 - Ports open
 - Correct IP/domain
-

User Device (*like smartphone or pc*)

Only:

- Opens webpage / PWA
- Plays stream

Note: No firewall setup needed

MfRDJ Project Setup

Install Components

- MfPack
- RDJ Controls

Add Search Paths

```
..\MfPack\src
..\MfPack\Samples\MfRdjJ\Controls
..\MfPack\Samples\MfComponents
```

Output

```
.\$(Platform)\$(Config)
```

▶ Running MfRDJ

First run:

- Creates INI
- Opens Setup dialog

General Settings

- Select Master Output
- Enable Headphones (Cue)
- Set buffer: **60 ms**

Microphone

- Enable input
- Select device

Audio Recorder

- Buffer: 60 ms
- Latency: 100 ms

Broadcast Setup

Local

Host: 127.0.0.1

LAN (Server)

Host: 192.168.x.x

Internet

Host: yourdomain.com

Common Settings

Port: 8000
Mount: /live

```
User: source
Password: your_password
```

Icecast Server Manager

Example:

```
Host: 127.0.0.1
Port: 8000
EXE: C:\Icecast\bin\icecast.exe
Config: C:\Icecast\icecast.xml
Working Dir: C:\Icecast
```

Caddy Setup

```
C:\Caddy
C:\Caddy\Caddyfile
C:\Caddy\nowplaying.json
```

Run:

```
caddy.exe run --config "C:\Caddy\Caddyfile"
```

Accessing the Stream

Same PC

```
http://127.0.0.1:8000/live
```

LAN

```
http://192.168.x.x:8000/live
```

Internet

```
https://yourdomain.com
```

Troubleshooting

Works on PC, not phone

Check:

- Firewall
 - Router ports
-

HTTPS not working

Check:

- Port 443
 - Caddy running
 - DDNS
-

Stream reconnects / unstable

Possible reasons:

- Buffer too small
 - Network issues
-

Final Checklist

Server PC

- ☐ Iccast running
 - ☐ Caddy running
 - ☐ Firewall open
 - ☐ Ports forwarded
 - ☐ Correct host
-

User Device

- ☐ Correct URL
 - ☐ Network access
-

Summary

Setup	Host
Local	127.0.0.1
LAN	192.168.x.x
Internet	Domain

-
- The server does all the work
 - A user only connects