

HART Communication Protocol in Industrial Process Automation: A Simulation-Based Study of Fault Detection in a Reactor Temperature Control Loop

Soaib Ferdous
BEng in Electronic Engineering
Hochschule Hamm-Lippstadt
Lippstadt, Germany

Md Arman Zaid Efty
BEng in Electronic Engineering
Hochschule Hamm-Lippstadt
Lippstadt, Germany

Md Zulkar Nain Sayeed
BEng in Electronic Engineering
Hochschule Hamm-Lippstadt
Lippstadt, Germany

Jamsadul Bari Fahad
BEng in Electronic Engineering
Hochschule Hamm-Lippstadt
Lippstadt, Germany

Abstract—The Highway Addressable Remote Transducer (HART) protocol superimposes bidirectional digital communication on the conventional 4–20 mA analog current loop, enabling rich device diagnostics while preserving legacy wiring [1], [2]. This paper investigates the fault-detection capability of HART within a simulated chemical-reactor temperature control loop comprising a temperature transmitter (TT-201), a flow transmitter (FT-202), and a smart valve positioner (FCV-203) integrated into a distributed-control-system (DCS) PID loop. Three representative fault scenarios are injected: sensor drift, loop failure, and valve sticking. The simulation shows that HART status bytes and diagnostic commands detect each fault, with detection latencies of 5.5 s, 1.0 s, and 0.0 s, respectively. The results illustrate that HART command-48 device status provides diagnostic depth unattainable with analog signalling alone, while the 1.2 kbit/s polling rate remains a limiting factor relative to fully digital fieldbuses [3].

Index Terms—HART protocol, industrial communication, fieldbus, process automation, fault detection, PID control, smart instrumentation.

I. INTRODUCTION

Modern process plants depend on the continuous exchange of measurement and command data between field instruments and a central control system [4]. For several decades, this exchange has been dominated by the 4–20 mA analog current loop, in which a single process variable is encoded as a proportional loop current [2]. Although robust and simple, the analog loop transmits only one variable per wire pair and conveys no information about the internal health of the device [1]. As process industries adopted microprocessor-based “smart” instruments, the need arose for a communication method capable of carrying diagnostic and configuration data without discarding the large installed base of analog wiring [5].

The HART protocol was developed to meet precisely this need by superimposing a frequency-shift-keyed (FSK) digital signal on the existing analog loop [2]. This hybrid approach

allows the analog value and the digital conversation to coexist on the same pair of wires [1]. HART has since become one of the most widely deployed field communication standards in the process industries [5]. Understanding how its digital diagnostic layer behaves under fault conditions is therefore of direct practical relevance to plant safety and maintenance [6].

Prior work has examined industrial communication networks from several perspectives. Galloway and Hancke surveyed the landscape of industrial control networks and the layered structure of common fieldbus standards [4]. Gungor and Hancke analysed the design principles and technical challenges of industrial sensor networks, including reliability and real-time constraints [7]. Devan *et al.* reviewed the adoption of WirelessHART in process monitoring, tracing the evolution of HART from its wired origins to the wireless standard [5]. On the control side, Isermann surveyed model-based fault-detection methods that exploit signal redundancy to identify faults [6], while the distributed nature of modern control execution has itself been the subject of network-timing analysis [8]. The present study complements this literature by examining, at the level of individual HART commands and status bytes, how three concrete device faults are surfaced within a single closed control loop.

This paper presents a simulation-based evaluation of HART fault detection in a reactor temperature control loop. The remainder of the paper is organised as follows. Section II reviews the HART protocol and its frame structure. Section III describes the simulated reactor, its instrumentation, and the PID control loop. Section IV analyses three fault scenarios and their detection. Section V compares HART with two fully digital fieldbuses, and Section VI concludes the study.

II. THE HART COMMUNICATION PROTOCOL

HART is a master–slave protocol residing at the application layer of the communication stack and is part of the IEC 61158 family of fieldbus standards [3]. The physical layer encodes digital bits as a Bell 202 FSK signal, representing a logic 1 by a 1.2 kHz tone and a logic 0 by a 2.2 kHz tone, transmitted at 1200 bit/s [2]. Because the average value of this sinusoidal signal is zero, it does not disturb the underlying 4–20 mA measurement, allowing simultaneous analog and digital communication on one wire pair [1].

A. Communication Model

In a HART network, the control system acts as the master and periodically polls each field device, which responds as a slave [1]. A point-to-point loop carries one analog value plus the digital channel, while a multidrop configuration can connect up to fifteen devices sharing the digital channel alone [5]. The master issues a command, the addressed slave replies, and the cycle repeats for the next device [2]. A minimum loop resistance is required so that the current-mode HART signal is converted into a voltage that the master can detect, and so that the loop power supply does not attenuate the digital signal [2]. This master–slave discipline makes the timing of fault detection deterministic, since each device is guaranteed to be addressed once per polling cycle [1].

B. Frame Structure and Commands

Each HART message is organised into a frame containing a preamble, a start delimiter, the device address, a command byte, a byte count, the data payload, and a checksum [1]. The trailing checksum is the longitudinal exclusive-OR of the preceding frame bytes and enables the receiver to detect transmission errors [2]. HART defines three classes of commands: universal commands supported by every device, common-practice commands, and device-specific commands [1].

Three commands are central to this study. Command 1 reads the primary variable; command 3 reads the dynamic variables together with the loop current; and command 48 reads additional device status, exposing detailed diagnostic information such as position deviation in valve positioners [1]. The response to each command includes two status bytes that flag communication errors and device malfunctions, providing the basis for the fault detection examined in this work [6].

Table I summarises the fields of a HART short-frame message in the order in which they are transmitted [1]. The preamble provides synchronisation, the delimiter distinguishes master requests from slave responses, and the address field identifies the polled device [2]. The command and byte-count fields are followed by the payload, and the frame terminates with the exclusive-OR checksum [1].

C. Diagnostics, Safety, and Modern Extensions

Beyond reading process variables, HART carries device-health information that enables a shift from reactive to predictive maintenance when the data is collected by an asset-management system [5]. Because the digital signal rides on

TABLE I
HART SHORT-FRAME FIELD STRUCTURE

Field	Bytes	Function
Preamble	5–20	FSK synchronisation (0xFF)
Delimiter	1	Frame type (request/response)
Address	1–5	Master and slave addressing
Command	1	Command number (e.g. 1, 3, 48)
Byte count	1	Number of payload bytes
Status	2	Response only: comm. and device status
Data	0–n	Payload (process and diagnostic data)
Checksum	1	Longitudinal XOR error check

the standard current loop, HART devices remain compatible with intrinsic-safety barriers and can be deployed in hazardous areas under the relevant explosion-protection standards [9]. More recent extensions of the protocol address its throughput limitation: WirelessHART provides a 2.4 GHz mesh network for hard-to-wire locations [10], and HART-IP transports HART payloads over Ethernet for high-bandwidth backhaul to the control system [11]. These extensions preserve the HART command and status model while relaxing the physical-layer constraints [5].

III. SYSTEM DESCRIPTION AND USE CASE

The simulated process is a chemical reactor, designated CR-101, whose internal temperature must be held at a defined setpoint to ensure correct reaction conditions [12]. Maintaining a process variable at a desired level against disturbances is the canonical task of feedback control [13]. Three HART field devices instrument the reactor, and a DCS executes the control algorithm.

A. Field Instrumentation

The temperature transmitter TT-201 (HART address 0x01) measures the reactor temperature over a span of 140–220 °C and is interrogated using command 3, which returns both the digital temperature and the analog loop current [1]. The flow transmitter FT-202 (HART address 0x02) measures inlet flow over 0–5 m³/h and is read using command 1 [2]. The smart valve positioner FCV-203 (HART address 0x03) actuates the inlet valve and reports commanded position, actual position, and position error through command 48 [1].

B. PID Control Loop

The DCS implements a discrete proportional–integral–derivative (PID) controller, the most widely used feedback control structure in process industries [13]. The controller computes the valve demand $u(t)$ from the temperature error $e(t) = SP - PV$ according to

$$u(t) = K_p e(t) + K_i \int_0^t e(\tau) d\tau + K_d \frac{de(t)}{dt}, \quad (1)$$

where K_p , K_i , and K_d are the proportional, integral, and derivative gains, respectively [13]. In this work the gains are set to $K_p = 0.8$, $K_i = 0.05$, and $K_d = 0.1$, and the loop is sampled every $\Delta t = 0.5$ s, matching the HART polling interval. The reactor thermal response is represented by a first-order model with a time constant of 20 s, a common approximation for self-regulating thermal processes [12]. The controller acts upon the temperature reported by TT-201 over HART, so the integrity of that digital value directly affects control quality [6].

Figure 1 shows the closed-loop behaviour over the full 300 s simulation. The process variable tracks the setpoint during normal operation, and the three shaded regions mark the intervals in which faults are active. The figure illustrates how a corrupted HART measurement propagates into the control action and ultimately into the true process temperature.

C. Polling Architecture and Timing

In a distributed control system, control functions are decentralised across networked controllers located close to the process, which improves reliability and responsiveness relative to a single central controller [8]. In the modelled loop, the DCS polls the three HART devices in a fixed rotation, issuing one command per device every 0.5 s, so that each device is addressed once per polling cycle. This polling period sets the granularity of fault detection: a fault can only be observed on the first poll that follows its onset, which directly determines the detection latencies reported in Section IV. The choice of a 0.5 s cycle reflects a balance between communication load on the 1.2 kbit/s digital channel and the responsiveness required for a thermal loop with a 20 s time constant [12].

D. Simulation Implementation

The control loop was implemented as a discrete-time simulation advancing in fixed steps of $\Delta t = 0.5$ s over a 300 s horizon, giving 600 iterations. At each step the controller reads the temperature reported by TT-201 over HART, computes the valve demand from the PID law, and applies the demand to the valve positioner [13]. The reactor temperature is then updated from the first-order thermal model driven by the actual valve position, and the flow transmitter is evaluated against the new flow condition [12]. Crucially, the controller acts on the HART-reported temperature rather than the true process temperature, so a fault in the reporting path propagates into the control action exactly as it would in a real installation [6]. Measurement noise was added to each variable to emulate realistic signal conditions, and an anti-windup limit was applied to the integral term to prevent the controller from saturating during the fault intervals [13].

The integral term of the PID law is bounded to keep the accumulated error within a fixed range, which prevents the large transient overshoot that would otherwise follow a prolonged fault [13]. Each device maintains its own status bytes, which are set whenever the corresponding fault condition is active, mirroring the response that a real HART device would return to the polling master [1]. The simulation records, at every




Fig. 1. PID temperature control loop for reactor CR-101 over the 300 s simulation. The actual process variable (black) tracks the setpoint (blue), while the HART-reported value from TT-201 (red) diverges during the sensor drift interval. Shaded regions indicate active faults; the right axis shows the FCV-203 valve position.

TABLE II
HART FAULT DETECTION SUMMARY

Device	Inject (s)	Latency (s)	Detection mechanism
TT-201	80.0	5.5	Analog/digital mismatch, CMD3 status byte
FT-202	160.0	1.0	Communication timeout, CMD1 no response
FCV-203	230.0	0.0	Position error > 5%, CMD48 status byte

step, the setpoint, the true and reported temperatures, the loop currents, the valve positions, and the status bytes, providing the time-series data from which the figures and the detection latencies in Table II were derived [6].

IV. FAULT SCENARIOS AND DETECTION

Three fault scenarios were injected sequentially to evaluate the diagnostic response of the HART layer. Model-based and signal-based fault detection relies on comparing observed signals against expected behaviour or redundant measurements [6]. HART provides exactly such redundancy by delivering a digital value alongside the analog loop current and by exposing internal device status [1]. The detection events for all three scenarios are summarised in Table II, and the corresponding signals are plotted in Fig. 2.

A. TT-201 Sensor Drift

In the first scenario the temperature transmitter develops a slowly increasing offset in its digital output while the analog loop current continues to reflect the true temperature [6]. Because HART delivers both quantities in the command 3 response, the control system can compare the digital value against the value implied by the loop current and flag a discrepancy [1]. The simulation raises the analog/digital mismatch indication once the offset exceeds a 2 °C threshold, which occurs 5.5 s after fault onset. During this interval the PID controller acts on the erroneous high reading and reduces the valve opening, causing the true reactor temperature to fall, as seen in Fig. 1. This illustrates that an undetected

measurement fault degrades control even when the actuator and controller operate correctly [13].

This scenario is representative of a broad class of sensor faults, including calibration drift, partial element failure, and signal-conditioning faults [6]. The key diagnostic mechanism is the redundancy between the analog and digital representations of the same measurement: because the two channels are generated by different parts of the device, a fault that affects only the digital path produces a divergence that neither channel alone would reveal [1]. The detection threshold embodies a trade-off, since a smaller threshold detects the drift earlier but is more susceptible to false alarms from measurement noise, whereas a larger threshold is more robust but permits a larger excursion before the alarm is raised [6].

B. FT-202 Loop Failure

In the second scenario the flow-transmitter loop fails, driving the loop current below the 3.6 mA fault threshold that lies beneath the valid 4 mA lower range [2]. The master issues command 1 but receives no valid response, and after three consecutive missed polls the communication timeout is declared, 1.0 s after onset. A conventional analog system can also detect an out-of-range current, but the HART communication status byte additionally distinguishes a communication failure from a genuine low-flow condition [1]. This diagnostic disambiguation reduces the risk of misinterpreting the loss of signal [6].

C. FCV-203 Valve Sticking

In the third scenario the inlet valve becomes mechanically stuck while the DCS continues to command a different position [12]. The smart positioner measures its actual stem position and reports the deviation from the commanded value through command 48 [1]. The simulation raises the position-deviation alarm immediately on the first poll after the fault, because the resulting error far exceeds the 5% alarm threshold. This fault is entirely invisible to an analog-only architecture, which transmits the commanded position but receives no independent confirmation of actual valve travel [5]. The command 48 diagnostic therefore provides information that has no analog equivalent [1].

Valve sticking, stiction, and actuator degradation are among the most common sources of poor control-loop performance in process plant, and they are difficult to diagnose without position feedback [12]. The smart positioner addresses this directly by closing the loop locally between the commanded and measured stem positions and exposing the residual error to the control system [1]. Because this error is reported as an explicit numerical value rather than inferred indirectly, detection is both immediate and unambiguous, which explains the zero detection latency observed in Table II [6]. This case most clearly demonstrates the diagnostic advantage of a bidirectional digital protocol over a unidirectional analog command [5].

Fig. 2 — HART Fault Detection Timeline (CR-101, Three Fault Scenarios)




Fig. 2. HART fault detection timeline for the three scenarios. Top: TT-201 sensor drift exceeding the mismatch threshold. Middle: FT-202 loop current collapsing below 3.6 mA. Bottom: FCV-203 position error exceeding the 5% alarm threshold. Vertical markers indicate the instant of detection.

D. Discussion

The three scenarios expose a clear ordering in detection latency that follows the nature of each fault. The valve-sticking fault is detected immediately because command 48 reports an explicit position error that crosses the alarm threshold on the first poll [1]. The loop failure is detected within one second, limited only by the requirement of three consecutive missed polls to distinguish a true failure from a single corrupted response [2]. The sensor drift is the slowest to detect, because the fault must accumulate until the analog/digital discrepancy exceeds the mismatch threshold [6]. This ordering illustrates a general principle of signal-based diagnosis: faults that produce an immediate, discrete indication are detected faster than those that manifest as a gradual parametric change [6]. The results also confirm that the diagnostic value of HART is greatest for the valve-positioner case, where the command 48 feedback has no analog counterpart and the fault would otherwise remain hidden from the control system [5].

E. Practical Implications

From an operational standpoint, the diagnostic data examined here is most valuable when it is collected continuously by an asset-management system, which allows a plant to move from reactive repair toward condition-based and predictive maintenance [5]. The status byte returned with every command response means that device health is available on each poll without additional communication overhead, so the diagnostic information is obtained as a by-product of normal process reads [1]. For a safety-related loop, the ability to distinguish a communication failure from a genuine process excursion is particularly important, because the two conditions call for different operator responses [6]. The fact that these diagnostics are delivered over the existing 4–20 mA wiring, and remain usable in hazardous areas through intrinsic-safety barriers, means that they can be adopted without re-engineering the




Fig. 3. Comparison of HART, Foundation Fieldbus H1, and PROFIBUS PA across four metrics: data rate, devices per segment, polling cycle, and installed base.

TABLE III
COMPARISON OF PROCESS FIELDBUS PROTOCOLS

Attribute	HART 7	FF H1	PROFIBUS PA
Physical layer	4–20 mA + FSK	MBP	MBP
Data rate (kbit/s)	1.2	31.25	31.25
Devices/segment	15	16	32
Communication	Master/slave	Pub./sub.	Master/slave
Analog channel	Yes	No	No
Retrofit support	High	Low	Low
Standard family	IEC 61158	IEC 61158	IEC 61158

installed infrastructure [9]. These properties help explain why HART has remained widely used even as faster, fully digital alternatives have become available [5].

V. PROTOCOL COMPARISON

To place these results in context, HART is compared with two fully digital process fieldbuses, Foundation Fieldbus H1 and PROFIBUS PA, both of which share the IEC 61158-2 physical layer [3]. The principal quantitative differences are summarised in Fig. 3 and listed in Table III.

The fully digital fieldbuses transmit at 31.25 kbit/s, more than an order of magnitude faster than the 1.2 kbit/s HART digital channel, and support scheduled communication to many devices per segment [14], [15]. Their higher throughput suits densely instrumented control strategies executed in the field [14]. HART, by contrast, retains the analog loop and therefore integrates directly with the existing 4–20 mA infrastructure, which is its principal advantage for retrofit and brownfield installations [2]. The very large installed base of HART devices reflects this compatibility [5]. For the single-loop reactor studied here, the 0.5 s polling cycle is sufficient to detect the injected faults within a few seconds, although the slower digital rate would become a constraint in larger multidrop networks [3].

A. Limitations of the Study

Several limitations should be noted when interpreting these results. The reactor is represented by a first-order thermal model, which captures the dominant dynamics but omits higher-order effects and measurement nonlinearity that occur

in real plant [12]. The fault thresholds and the three-poll timeout were fixed at representative values; in practice these are tuned to the noise characteristics of each loop and directly affect the detection latency [6]. The study also considers a single point-to-point loop, whereas the polling delay and channel contention that dominate dense multidrop or wireless networks were outside its scope [8]. Finally, the analysis addresses detection rather than isolation and recovery, which would require coordination between the diagnostic layer and the control strategy [6].

VI. CONCLUSION

This paper evaluated the fault-detection capability of the HART protocol in a simulated reactor temperature control loop instrumented with three smart field devices [1]. The simulation demonstrated that HART detected all three injected faults, with detection latencies of 5.5 s for sensor drift, 1.0 s for loop failure, and effectively immediate detection for valve sticking. The analog/digital comparison enabled by command 3 and the position diagnostics provided by command 48 deliver information that analog signalling alone cannot supply [6]. The study also confirmed that the principal limitation of HART is its 1.2 kbit/s polling rate, which is modest compared with fully digital fieldbuses [3].

Several directions follow naturally from these findings. Extending the model to a multidrop segment would expose the interaction between polling order and detection latency when several devices share the digital channel [8]. A WirelessHART configuration would introduce stochastic network delay and packet loss, whose effect on closed-loop diagnosis is an active research question [5]. Migrating the backhaul to HART-IP over Ethernet would raise the available bandwidth and allow the diagnostic data to feed a plant-wide asset-management system [11]. Finally, coupling the diagnostic layer to an automatic reconfiguration strategy would move the system from fault detection toward fault-tolerant control, in which a detected fault triggers a compensating control action rather than only an alarm [6].

REFERENCES

- [1] FieldComm Group, *HART Communication Protocol Specification, Revision 7.6*, FieldComm Group, Austin, TX, USA, 2012.
- [2] J. Wu, “A basic guide to the HART protocol,” Texas Instruments Inc., Dallas, TX, USA, Tech. Rep. Application Report SLAAEH0, 2022.
- [3] International Electrotechnical Commission, *IEC 61158-2:2019 Industrial Communication Networks — Fieldbus Specifications — Part 2: Physical Layer Specification and Service Definition*, IEC, Geneva, Switzerland, 2019.
- [4] B. Galloway and G. P. Hancke, “Introduction to industrial control networks,” *IEEE Communications Surveys & Tutorials*, vol. 15, no. 2, pp. 860–880, 2013.
- [5] P. A. M. Devan, F. A. Hussin, R. Ibrahim, K. Bingi, and F. A. Khanday, “A survey on the application of WirelessHART for industrial process monitoring and control,” *Sensors*, vol. 21, no. 15, p. 4951, 2021.
- [6] R. Isermann, “Model-based fault-detection and diagnosis — status and applications,” *Annual Reviews in Control*, vol. 29, no. 1, pp. 71–85, 2005.
- [7] V. C. Gungor and G. P. Hancke, “Industrial wireless sensor networks: Challenges, design principles, and technical approaches,” *IEEE Transactions on Industrial Electronics*, vol. 56, no. 10, pp. 4258–4265, 2009.

- [8] S. Wenzel, M. Riedl, and C. Diedrich, “Modeling network architecture and time behavior of distributed control systems in industrial plant automation,” in *Proc. 37th Annu. Conf. IEEE Ind. Electron. Soc. (IECON)*, 2011, pp. 3645–3650.
- [9] International Electrotechnical Commission, *IEC 60079-11:2011 Explosive Atmospheres — Part 11: Equipment Protection by Intrinsic Safety “i”*, IEC, Geneva, Switzerland, 2011.
- [10] —, *IEC 62591:2016 Industrial Networks — Wireless Communication Network and Communication Profiles — WirelessHART*, IEC, Geneva, Switzerland, 2016.
- [11] FieldComm Group, *HART-IP Technical Description*, FieldComm Group, Austin, TX, USA, 2020.
- [12] D. E. Seborg, T. F. Edgar, D. A. Mellichamp, and F. J. Doyle III, *Process Dynamics and Control*, 4th ed. Hoboken, NJ, USA: Wiley, 2017.
- [13] K. J. Åström and T. Hägglund, *Advanced PID Control*. Research Triangle Park, NC, USA: ISA — The Instrumentation, Systems, and Automation Society, 2006.
- [14] FieldComm Group, *Foundation Fieldbus — Technical Overview*, FieldComm Group, Austin, TX, USA, 2016.
- [15] PROFIBUS & PROFINET International, *PROFIBUS PA — User and Installation Guideline*, PI International, Karlsruhe, Germany, 2003, version 2.2.