

32 BIT RISC V PROCESSOR

Submitted By

Name: Gugulothu Gnana Sri Krishna Kowshik

Adm. No: 22JE0368

TABLE OF CONTENTS:

CONTENTS	PAGE NO
Abstract	4
Introduction	4
Objective	5
Tools used	5
Picorv32	6
Implementation: RTL - schematic	7
Synthesis (YOSYS)	8
Configuration files	9-10

Floorplan	11
Placement	12-13
Clock Tree	13
Routing	14-16
Final Layout	16-18
Timing Report	19-21
Power and Area Report	21-23
IR Drop	23-25
Routing Congestion Maps	26-27

Congestion Reports	27-29
Power Density	29-30
Placement Density	30-31
Pin Density	31-32
Comparision Graphs	32-34

ABSTRACT:

This report presents a comprehensive overview of the RTL-to-GDSII ASIC design flow for the PicoRV32 processor core using the OpenROAD-flowscripts framework. Covering the entire process from Register Transfer Level (RTL) Verilog description to the final generation of Graphic Data System II (GDSII) layout files, OpenROAD offers a fully open-source digital ASIC implementation platform. The report explores each stage of the digital backend flow including logic synthesis, floorplanning, placement, clock tree synthesis, and global and detailed routing. The PicoRV32, a minimal RISC-V RV32I processor core, is chosen for its simplicity and configurability, making it an ideal candidate for ASIC prototyping. This work highlights the capabilities and challenges of using open-source tools in ASIC workflows, focusing on design convergence, timing-driven placement, and layout generation.

INTRODUCTION:

With the increasing adoption of open-source IPs and tools in the hardware design industry, the development and prototyping of Application-Specific Integrated Circuits (ASICs) using fully open-source flows have gained significant traction. RISC-V, an open standard instruction set architecture (ISA), has become a cornerstone in this movement. Among its many implementations, PicoRV32 stands out as a compact, RV32I-compliant softcore processor optimized for resource-constrained environments. This project focuses on the ASIC design of the PicoRV32 core using OpenROAD-flowscripts, a fully automated RTL-to-GDSII flow built around the OpenROAD toolchain. Unlike traditional commercial EDA tools, OpenROAD enables a transparent and flexible environment for digital backend design. This implementation leverages PicoRV32's streamlined instruction set and compact architecture to explore the capabilities of the open-source flow.

OBJECTIVE:

The objective of this project is to design and implement a 32-bit RISC-V processor core PicoRV32 using the OpenROAD-flow-scripts RTL-to-GDSII digital design flow. The primary aim is to generate a GDSII layout from the RTL description of the processor while utilizing a fully open-source toolchain. Key goals include synthesizing the design for optimal area and performance, performing physical design steps such as floorplanning, placement, clock tree

synthesis, and routing, and achieving design closure without the inclusion of physical verification stages. This project intends to demonstrate a practical understanding of the digital backend flow using open-source ASIC tools, and to provide comprehensive documentation of the process, challenges encountered, and the resulting layout metrics.


TOOLS USED:

1. Xilinx Vivado
2. Yosys
3. OpenROAD
4. OpenROAD gui
5. Klayout

PICORV32:

PicoRV32 is a compact, open-source RISC-V processor core designed for minimal area and high configurability. It supports the RV32I instruction set with optional extensions like RV32M (multiply/divide) and RV32C (compressed instructions). Unlike traditional pipelined processors, PicoRV32 uses a finite state machine (FSM)-based, multi-cycle architecture, where each instruction is executed over several clock cycles. This simplifies control logic and reduces hardware resource usage, making it ideal for FPGA and low-power ASIC implementations. It also includes optional support for interrupts, coprocessor integration, and interfaces like AXI4-Lite and Wishbone.

IMPLEMENTATION:
RTL Analysis – Schematic:



Synthesis(YOSYS):

1.


```

=== design hierarchy ===

picorv32a                                1
  picorv32_pcpi_fast_mul                1

Number of wires:                        14477
Number of wire bits:                    18024
Number of public wires:                 202
Number of public wire bits:            2451
Number of memories:                     0
Number of memory bits:                  0
Number of processes:                    0
Number of cells:                        16482
  $_ANDNOT_                             3912
  $_AND_                                 1422
  $_DFFE_PP_                             957
  $_DFF_P_                               227
  $_MUX_                                 1885
  $_NAND_                                747
  $_NOR_                                 504
  $_NOT_                                 915
  $_ORNOT_                              228
  $_OR_                                 2315
  $_SDFFCE_PN0P_                         36
  $_SDFFCE_PP0P_                         9
  $_SDFFCE_PP1P_                         1
  $_SDFFE_PN0P_                          192
  $_SDFFE_PN1N_                           4
  $_SDFFE_PN1P_                          32
  $_SDFFE_PP0P_                           1
  $_SDFFE_PP1P_                           3
  $_SDFF_PN0_                            133
  $_SDFF_PP0_                             18
  $_XNOR_                                599
  $_XOR_                                2342

```

CONFIG files:

1. Clock period = 25 ns

```

export PLATFORM      = sky130hd
export DESIGN_NAME   = picorv32a
export VERILOG_FILES = $(sort $(wildcard ./designs/src/$(DESIGN_NICKNAME)/*.v))
export SDC_FILE       = ./designs/$(PLATFORM)/$(DESIGN_NICKNAME)/constraint.sdc

export CORE_UTILIZATION = 40
export PLACE_DENSITY    = 0.60

export TNS_END_PERCENT = 100

```

2. Clock period = 18 ns

```

export PLATFORM      = sky130hd
export DESIGN_NAME   = picorv32a
export VERILOG_FILES = $(sort $(wildcard ./designs/src/$(DESIGN_NICKNAME)/*.v))
export SDC_FILE       = ./designs/$(PLATFORM)/$(DESIGN_NICKNAME)/constraint.sdc

export CORE_UTILIZATION = 40
export PLACE_DENSITY    = 0.60

export TNS_END_PERCENT = 100

```

3. Clock period = 12 ns

```

export PLATFORM      = sky130hd
export DESIGN_NAME   = picorv32a
export VERILOG_FILES = $(sort $(wildcard ./designs/src/$(DESIGN_NICKNAME)/*.v))
export SDC_FILE       = ./designs/$(PLATFORM)/$(DESIGN_NICKNAME)/constraint.sdc

export CORE_UTILIZATION = 50
export PLACE_DENSITY    = 0.65

export TNS_END_PERCENT = 100

```

4. Clock period = 12 ns

```

export PLATFORM      = sky130hd
export DESIGN_NAME   = picorv32a
export VERILOG_FILES = $(sort $(wildcard ./designs/src/$(DESIGN_NICKNAME)/*.v))
export SDC_FILE      = ./designs/$(PLATFORM)/$(DESIGN_NICKNAME)/constraint.sdc

export CORE_UTILIZATION = 48
export PLACE_DENSITY    = 0.58

export TNS_END_PERCENT = 100

```

5. Clock period = 10 ns

```

export PLATFORM      = sky130hd
export DESIGN_NAME   = picorv32a
export VERILOG_FILES = $(sort $(wildcard ./designs/src/$(DESIGN_NICKNAME)/*.v))
export SDC_FILE      = ./designs/$(PLATFORM)/$(DESIGN_NICKNAME)/constraint.sdc


export CORE_UTILIZATION = 35
export PLACE_DENSITY    = 0.42
export CELL_PAD_IN_MICRON = 0.4
export SYNTH_BUFFERING = 1
export TNS_END_PERCENT = 100

```


Floorplan:

1.


2.





3.



4.




5.




Placement:

1.


2.




3.




4.




5.






CLOCK TREE:




ROUTING:


1.




2.




3.



4.




5.




Final:


1.




2.




3.



4.



5.



TIMING REPORT:

1.

```

=====
finish report_tns
-----
tns 0.00

=====
finish report_wns
-----
wns 0.00

=====
finish report_worst_slack
-----
worst slack 13.92

=====
finish report_clock_skew
-----
Clock core_clock
  0.84 source latency irq_mask[26]$_SDFFE_PN1P_/CLK ^
 -0.93 target latency count_instr[5]$_SDFFE_PN0P_/CLK ^
  0.00 CRPR
-----
 -0.10 setup skew

=====
finish report_checks -path_delay min

```

2.

```

=====
finish report_tns
-----
tns 0.00

=====
finish report_wns
-----
wns 0.00

=====
finish report_worst_slack
-----
worst slack 9.16

=====
finish report_clock_skew
-----
Clock core_clock
  0.86 source latency cpuregs[16][14]$_DFFE_PP_/CLK ^
 -0.94 target latency reg_out[14]$_DFF_P_/CLK ^
  0.00 CRPR
-----
 -0.08 setup skew

```

3.

```

=====
finish report_tns
-----
tns 0.00

=====
finish report_wns
-----
wns 0.00

=====
finish report_worst_slack
-----
worst slack 2.91

=====
finish report_clock_skew
-----
Clock core_clock
  0.88 source latency latched_stalu$_SDFFE_PN0P_/CLK ^
 -0.97 target latency cpuregs[4][12]$_DFFE_PP_/CLK ^
  0.00 CRPR
-----
 -0.10 setup skew

```

4.

```

=====
finish report_tns
-----
tns 0.00

=====
finish report_wns
-----
wns 0.00

=====
finish report_worst_slack
-----
worst slack 3.39

=====
finish report_clock_skew
-----
Clock core_clock
  0.98 source latency cpuregs[15][1]$_DFFE_PP_/CLK ^
 -0.87 target latency reg_op2[1]$_DFFE_PP_/CLK ^
  0.00 CRPR
-----
  0.11 setup skew

```

5.


```

=====
finish report_tns
-----
tns 0.00

=====
finish report_wns
-----
wns 0.00

=====
finish report_worst_slack
-----
worst slack 1.16

=====
finish report_clock_skew
-----
Clock core_clock
  0.95 source latency cpuregs[12][5]$_DFFE_PP_/CLK ^
 -0.82 target latency reg_op2[5]$_DFFE_PP_/CLK ^
  0.00 CRPR
-----
  0.13 setup skew

```

POWER AND AREA REPORT:

1.

```

>>> report_power

```

Group	Internal Power	Switching Power	Leakage Power	Total Power (Watts)	
Sequential	2.97e-03	2.35e-04	1.43e-08	3.21e-03	44.2%
Combinational	4.27e-04	8.75e-04	3.70e-08	1.30e-03	18.0%
Clock	1.57e-03	1.18e-03	2.93e-09	2.74e-03	37.8%
Macro	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Pad	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Total	4.96e-03	2.29e-03	5.42e-08	7.25e-03	100.0%
	68.5%	31.5%	0.0%		

```

>>> report_design_area
Design area 138574 u^2 48% utilization.

```

2.

```
>>> report_power
```

Group	Internal Power	Switching Power	Leakage Power	Total Power (Watts)	
Sequential	4.12e-03	2.86e-04	1.43e-08	4.41e-03	44.1%
Combinational	5.79e-04	1.18e-03	3.76e-08	1.76e-03	17.6%
Clock	2.18e-03	1.66e-03	2.90e-09	3.83e-03	38.3%
Macro	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Pad	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Total	6.88e-03 68.8%	3.12e-03 31.2%	5.48e-08 0.0%	1.00e-02	100.0%

```
>>> report_design_area
Design area 138852 u^2 48% utilization.
```

3.

```
>>> report_power
```

Group	Internal Power	Switching Power	Leakage Power	Total Power (Watts)	
Sequential	6.19e-03	4.07e-04	1.43e-08	6.59e-03	43.5%
Combinational	8.96e-04	1.87e-03	3.75e-08	2.76e-03	18.2%
Clock	3.28e-03	2.51e-03	2.93e-09	5.79e-03	38.2%
Macro	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Pad	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Total	1.04e-02 68.4%	4.78e-03 31.6%	5.47e-08 0.0%	1.51e-02	100.0%

```
>>> report_design_area
Design area 138662 u^2 60% utilization.
```

4.

```
>>> report_power
```

Group	Internal Power	Switching Power	Leakage Power	Total Power (Watts)	
Sequential	6.19e-03	4.53e-04	1.43e-08	6.64e-03	43.7%
Combinational	9.02e-04	1.91e-03	3.76e-08	2.81e-03	18.5%
Clock	3.17e-03	2.57e-03	2.91e-09	5.75e-03	37.8%
Macro	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Pad	0.00e+00	0.00e+00	0.00e+00	0.00e+00	0.0%
Total	1.03e-02 67.5%	4.93e-03 32.5%	5.48e-08 0.0%	1.52e-02	100.0%

```
>>> report_design_area
Design area 139199 u^2 52% utilization.
```


5.

```
>>> report_power
Group                Internal Power    Switching Power    Leakage Power    Total Power (Watts)
-----
Sequential           7.43e-03      4.90e-04      1.43e-08      7.92e-03      42.2%
Combinational        1.08e-03      2.15e-03      3.76e-08      3.23e-03      17.2%
Clock                4.45e-03      3.17e-03      3.31e-09      7.62e-03      40.6%
Macro                0.00e+00      0.00e+00      0.00e+00      0.00e+00      0.0%
Pad                  0.00e+00      0.00e+00      0.00e+00      0.00e+00      0.0%
-----
Total                1.30e-02      5.81e-03      5.52e-08      1.88e-02      100.0%
                        69.1%        30.9%        0.0%
```

```
>>> report_design_area
Design area 140697 u^2 43% utilization.
```


IR DROP:

1.



```
##### IR report #####
Net                : VDD
Corner             : default
Supply voltage    : 1.80e+00 V
Worstcase voltage : 1.80e+00 V
Average voltage   : 1.80e+00 V
Average IR drop   : 7.93e-05 V
Worstcase IR drop : 2.54e-04 V
Percentage drop   : 0.01 %
#####
[INFO PSM-0040] All shapes on net VSS are d
[INFO PSM-0073] Using bump pattern with x-p
x.
##### IR report #####
Net                : VSS
Corner             : default
Supply voltage    : 0.00e+00 V
Worstcase voltage : 2.24e-04 V
Average voltage   : 7.21e-05 V
Average IR drop   : 7.21e-05 V
Worstcase IR drop : 2.24e-04 V
Percentage drop   : 0.01 %
#####
```

2.




```

X.
##### IR report #####
Net          : VDD
Corner       : default
Supply voltage : 1.80e+00 V
Worstcase voltage: 1.80e+00 V
Average voltage : 1.80e+00 V
Average IR drop : 1.09e-04 V
Worstcase IR drop: 3.90e-04 V
Percentage drop : 0.02 %
#####
[INFO PSM-0040] All shapes on net VSS are c
[INFO PSM-0073] Using bump pattern with x-p
X.
##### IR report #####
Net          : VSS
Corner       : default
Supply voltage : 0.00e+00 V
Worstcase voltage: 3.52e-04 V
Average voltage : 9.85e-05 V
Average IR drop : 9.85e-05 V
Worstcase IR drop: 3.52e-04 V
Percentage drop : 0.02 %

```

3.




```

##### IR report #####
Net          : VDD
Corner       : default
Supply voltage : 1.80e+00 V
Worstcase voltage: 1.80e+00 V
Average voltage : 1.80e+00 V
Average IR drop : 2.88e-04 V
Worstcase IR drop: 7.58e-04 V
Percentage drop : 0.04 %
#####
[INFO PSM-0040] All shapes on net VSS are connected.
[INFO PSM-0073] Using bump pattern with x-pitch 140.8
X.
##### IR report #####
Net          : VSS
Corner       : default
Supply voltage : 0.00e+00 V
Worstcase voltage: 6.19e-04 V
Average voltage : 2.56e-04 V
Average IR drop : 2.56e-04 V
Worstcase IR drop: 6.19e-04 V
Percentage drop : 0.03 %
#####


```

4.



```
##### IR report #####
Net      : VDD
Corner   : default
Supply voltage : 1.80e+00 V
Worstcase voltage: 1.80e+00 V
Average voltage : 1.80e+00 V
Average IR drop : 1.78e-04 V
Worstcase IR drop: 6.73e-04 V
Percentage drop : 0.04 %
#####
[INFO PSM-0040] All shapes on net VSS are connected.
[INFO PSM-0073] Using bump pattern with x-pitch 140.0
x.
##### IR report #####
Net      : VSS
Corner   : default
Supply voltage : 0.00e+00 V
Worstcase voltage: 5.25e-04 V
Average voltage : 1.61e-04 V
Average IR drop : 1.61e-04 V
Worstcase IR drop: 5.25e-04 V
Percentage drop : 0.03 %
#####
```

5.




```
x.
##### IR report #####
Net      : VDD
Corner   : default
Supply voltage : 1.80e+00 V
Worstcase voltage: 1.80e+00 V
Average voltage : 1.80e+00 V
Average IR drop : 1.79e-04 V
Worstcase IR drop: 5.92e-04 V
Percentage drop : 0.03 %
#####
[INFO PSM-0040] All shapes on net VSS are c
[INFO PSM-0073] Using bump pattern with x-p
x.
##### IR report #####
Net      : VSS
Corner   : default
Supply voltage : 0.00e+00 V
Worstcase voltage: 4.98e-04 V
Average voltage : 1.71e-04 V
Average IR drop : 1.71e-04 V
Worstcase IR drop: 4.98e-04 V
Percentage drop : 0.03 %
#####
Cell type report: Co
```


ROUTING CONGESTION MAPS:

1.



2.




3.



4.





CONGESTION REPORTS:

1.

```
[INFO GRT-0096] Final congestion report:
```

Layer	Resource	Demand	Usage (%)	Max H / Max V / Total Overflow
li1	0	0	0.00%	0 / 0 / 0
met1	54620	25227	46.19%	0 / 0 / 0
met2	59675	32101	53.79%	0 / 0 / 0
met3	44185	13987	31.66%	0 / 0 / 0
met4	21329	8116	38.05%	0 / 0 / 0
met5	6006	755	12.57%	0 / 0 / 0
Total	185815	80186	43.15%	0 / 0 / 0

```
[INFO GRT-0018] Total wirelength: 785889 um
[INFO GRT-0014] Routed nets: 14059
```

2.

5.

```
[INFO GRT-0096] Final congestion report:
Layer          Resource      Demand      Usage (%)    Max H / Max V / Total Overflow
-----
li1             0           0           0.00%        0 / 0 / 0
met1          54318       25344       46.66%        0 / 0 / 0
met2          59675       31426       52.66%        0 / 0 / 0
met3          44185       13004       29.43%        0 / 0 / 0
met4          21329        7197       33.74%        0 / 0 / 0
met5           6006         489        8.14%        0 / 0 / 0
-----
Total         185513       77460       41.75%        0 / 0 / 0

[INFO GRT-0018] Total wirelength: 764595 um
[INFO GRT-0014] Routed nets: 14052
Perform buffer insertion and gate resizing...
```

3.

```
[INFO GRT-0096] Final congestion report:
Layer          Resource      Demand      Usage (%)    Max H / Max V / Total Overflow
-----
li1             0           0           0.00%        0 / 0 / 0
met1          40809       23053       56.49%        0 / 0 / 0
met2          47955       30543       63.69%        0 / 0 / 0
met3          35420       15291       43.17%        0 / 0 / 0
met4          17043        8247       48.39%        0 / 0 / 0
met5           4830        1104       22.86%        0 / 0 / 0
-----
Total         146057       78238       53.57%        0 / 0 / 0

[INFO GRT-0018] Total wirelength: 781080 um
[INFO GRT-0014] Routed nets: 14046
```

4.

```
[INFO GRT-0096] Final congestion report:
Layer          Resource      Demand      Usage (%)    Max H / Max V / Total Overflow
-----
li1             0           0           0.00%        0 / 0 / 0
met1          49557       25449       51.35%        0 / 0 / 0
met2          55426       33933       61.22%        0 / 0 / 0
met3          41015       14700       35.84%        0 / 0 / 0
met4          19832        8489       42.80%        0 / 0 / 0
met5           5624         605       10.76%        0 / 0 / 0
-----
Total         171454       83176       48.51%        0 / 0 / 0

[INFO GRT-0018] Total wirelength: 815524 um
[INFO GRT-0014] Routed nets: 14054
Perform buffer insertion and gate resizing...
repair_design
[INFO RSZ-0058] Using max wire length 2154um.
```

```


[INFO GRT-0096] Final congestion report:
Layer          Resource      Demand      Usage (%)    Max H / Max V / Total Overflow
-----
li1             0             0           0.00%        0 / 0 / 0
met1          63701         31418        49.32%        0 / 0 / 0
met2          67896         35341        52.05%        0 / 0 / 0
met3          50348         10976        21.80%        0 / 0 / 0
met4          24354          6316        25.93%        0 / 0 / 0
met5           6888           68          0.99%        0 / 0 / 0
-----
Total          213187        84119        39.46%        0 / 0 / 0

[INFO GRT-0018] Total wirelength: 812909 um
[INFO GRT-0014] Routed nets: 14077
Perform buffer insertion and gate resizing...
repair_design
[INFO RSZ-0058] Using max wire length 2154um.


```

POWER DENSITY:


1.




2.




3.



4.




5.




PLACEMENT DENSITY:


1.




2.




3.



4.




5.




PIN DENSITY:


1.




2.




3.




4.






5.



Comparison Graphs







Optimal clock period chosen is 12 ns. This is chosen because of Positive Skew and small Positive Slack.

According to Internal Power and Design Area ,clock period with 25 ns is best, but it does not meet timing requirements.