


LocoNet 16 input ports:

This device can send LocoNet messages. The circuit has 16 inputs that all have the same function. It has been decided to carry out the settings of function and address with DIP switches. No programming with a computer or central station is required. The function can be selected via DIP9 and DIP10. The address of input 1 is set via DIP ADDRESS1-8 (and optionally DIP11) in steps of 16 addresses per switch. The following 15 inputs have an ascending address with respect to input 1. The circuit provides several options for connections.

More information about the LocoNet opcodes can be found in "Personal Use Edition 1.0 SPECIFICATION" on the Digitrax website.



PCB LocoNet input device Version 1.
There will be an update later for the PCB
(version 2) where there are extra options for
connections.

Specific features of this circuit:

The circuit consumes very little power. The possibility is provided to take 5V via a voltage stabilizer 78L05 from pin 5 and 6 LocoNet cable. There is also a possibility to connect an external 5V with a connector 2.54mm or 5.08mm pin spacing. Then the 78L05 may not be present on the PCB!

The software filters out any interference signal from every input. A decision whether an input is high or low is made after 256 samples.

If the circuit is only used for occupancy feedback (DIP 9 and DIP10 = 'OFF') then it is not necessary to place DIP switches 9-11 on the PCB.

A resistor network of 4x22k is used on the PCB, this may not be replaced by a resistor network of a different value!

Indication LEDs on device:

LED1: 5V present. If 5V for device comes from LocoNet (via 78L05 voltage stabilizer) and the LED does not light up, there is a problem with the network.

LED2: Lights up (0.1s) when a message is read from LocoNet. All messages are read, including those coming from this device. Failure to illuminate this LED may indicate a problem with the network.


LED3: Lights up when this device has LocoNet commands in send buffer and goes out when all commands have been sent successfully. If this LED stays on, it may indicate that there is a problem with the network.

LED4: Lights up (0.2s) when a LocoNet command is placed in the sent buffer where DIR = '1'. This LED is useful to check whether the connected switches or detection are properly read, if not this may indicate a problem.

LED5: Lights up (0.2s) when a LocoNet command is placed in the sent buffer where DIR = '0'. This LED is useful to check whether the connected switches or detection are properly read, if not this may indicate a problem.


DIP 9 = 'OFF'
 DIP10 = 'OFF'
 DIP11 = XXX

Device give LocoNet command OPC_INPUT_REP with selected address. Sensor is high L='1' as switch is closed, and sensor is low L='0' where switch is opened.



For example, sensor can be mass-sensing or current-sensing when track is occupied

| | | | | | | | | | |
|--------------|------|---|---|---|---|---|---|---|--------|
| DIP ADDRESS: | 1 | 2 | 3 | 4 | 5 | 6 | 7 | 8 | |
| | 0 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | → 0 |
| 0='OFF' | 1 | 0 | 0 | 0 | 0 | 0 | 0 | 0 | → 16 |
| 1='ON' | 0 | 1 | 0 | 0 | 0 | 0 | 0 | 0 | → 32 |
| | | | | | | | | | |
| | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | → 4080 |




DIP 9 = 'ON'
DIP10 = 'OFF'
DIP11 = XXX

Device give LocoNet command OPC_SW_REQ with selected address, and DIR = '1' as switch is closed, and DIR = '0' where switch is opened.

↗ = Switch is closed
 ↖ = Switch is opened




| | | | | | | | | |
|--------------|---|---|---|---|---|---|---|--------|
| DIP ADDRESS: | 1 | 2 | 3 | 4 | 5 | 6 | 7 | |
| | 0 | 0 | 0 | 0 | 0 | 0 | 0 | → 0 |
| 0='OFF' | 1 | 0 | 0 | 0 | 0 | 0 | 0 | → 16 |
| 1='ON' | 0 | 1 | 0 | 0 | 0 | 0 | 0 | → 32 |
| | | | | | | | | |
| | 1 | 1 | 1 | 1 | 1 | 1 | 1 | → 2032 |



DIP 9 = 'OFF'
DIP10 = 'ON'
DIP11 = XXX


Device give LocoNet command OPC_SW_REQ with selected address, and DIR is alternating between '0' and '1' every time the button is pressed.
 The current DIR state is stored in EEPROM, so that it can be taken over after power-on.



DIP ADRESS: 1 2 3 4 5 6 7
 0000000 → 0
 0='OFF' 1000000 → 16
 1='ON' 0100000 → 32


 1111111 → 2032

Selected address is sum




DIP 9 = 'ON'
DIP10 = 'ON'
DIP11 = 'OFF' or 'ON'

Device give LocoNet command OPC_SW_REQ and two consecutive inputs with the same selected address. First input gives DIR='1' when button closed. Second input gives DIR='0' when button closed.



DIP ADDRESS: 1 2 3 4 5 6 7
 0000000 → 0
 1000000 → 16
 0100000 → 32

 1111111 → 2032



With this setting it is possible to make a switch panel like with Intellibox to move turnouts without having to change the address range. In combination with 'LocoNet 16 Output Ports' device you can also display the current position of the turnout on LEDs. With another 'LocoNet 16 Output Ports' device you can control the coils for the turnouts.