

TC53e / TC22 RFID SDK Sample - BSP Test (v3.4.1)

Author: Chuck

Date: 2026-06-18

Android sample app for Zebra handheld RFID devices including RFD40 support. The app connects to an available RFID reader, starts/stops inventory, and displays EPC + RSSI values in real time. This repository is maintained for BSP testing and validation.

Recent maintenance updates include explicit reader selection, Android 12+ permission-safe initialization, and batched UI refresh for high-frequency tag reads.

This branch also includes cleanup of unused scanner/test scaffolding, safer disconnect guards, and resource cleanup in `activity_main.xml`.

Project Summary

- **App ID:** `com.zebra.rfid.demo.sdksample`
- **Main screen:** `MainActivity`
- **RFID integration:** `RFIDHandler`
- **Target devices:** Zebra TC53e / TC22 class devices with supported RFID transport
- **SDK inputs:** Zebra `.aar` libraries under `app/libs`

Requirements

- macOS (or Linux/Windows with equivalent tools)
- Android SDK + platform/build tools installed
- `adb` available in terminal `PATH`
- **Java 17** for Android Gradle Plugin 8.13.x
 - This repo is configured to use Android Studio bundled JBR in VS Code task
- Connected Android device with Developer Options + USB debugging enabled

Build / Deploy / Run (Automated)

A VS Code task is included in `.vscode/tasks.json`:

- **Task label:** `Android: Build Deploy Run (Debug)`
- **What it does:**
 1. Builds debug APK
 2. Installs debug APK on connected device
 3. Launches `com.zebra.rfid.demo.sdksample/.MainActivity`

Run the task

- VS Code menu: **Terminal** → **Run Task...** → **Android: Build Deploy Run (Debug)**
- or Command Palette: **Tasks: Run Task**

Root one-click scripts

Project root also includes one-click scripts:

- `./runhh` (wrapper)
- `./runhh.sh` (main script)

They: 1. Set Java 17 (`JAVA_HOME`) for AGP compatibility 2. Verify `adb` and at least one connected device 3. Build + install debug APK 4. Launch `com.zebra.rfid.demo.sdksample/.MainActivity`




Figure 1: alt text

Manual Commands

If you prefer terminal commands:

```
export JAVA_HOME="/Applications/Android Studio.app/Contents/jbr/Contents/Home"
export PATH="$JAVA_HOME/bin:$PATH"
```

```
./gradlew :app:assembleDebug :app:installDebug
adb shell am start -n com.zebra.rfid.demo.sdksample/.MainActivity
```

App Usage

1. Launch app.
2. Grant Bluetooth permissions on Android 12+.
3. Use top-right menu:
 - **Connect** to initialize and connect reader
 - **Disconnect** to release reader
4. Tap **Start Inventory** to begin reading tags.
5. Tap **Stop Inventory** to stop reading.
6. Observe unique tag output in the on-screen list (**TAG_ID**, **RSSI**). The latest RSSI value is kept per tag and UI refreshes are batched to reduce churn during fast inventory reads.

Important Notes

- Build may show warnings about duplicate namespaces/permissions from vendor **.aar** files; these originate from bundled SDK artifacts.
- **Scan**/barcode path is scaffolded but currently not active in UI flow.
- Recent maintenance updates include:
 - **AsyncTask** migration to executor-based background processing in **RFIDHandler**
 - receiver lifecycle cleanup in **MainActivity** (**register/unregister**)
 - Android 12+ Bluetooth permission result validation for both **BLUETOOTH_SCAN** and **BLUETOOTH_CONNECT**
 - permission-safe RFID handler initialization/resume guards in **MainActivity**
 - explicit reader selection priority and logging in **RFIDHandler**
 - **DISCONNECTION_EVENT** auto-reconnect handling for BT/USB transport drops
 - unique-tag display with batched **ListView** refresh for smoother inventory UI
 - generic status toasts no longer clear tag results
 - removed disabled test button and unused scanner/test scaffolding
 - moved main layout text to **strings.xml** and switched left-only margins to start-aware margins

Repository Contents

- **app/src/main/java/com/zebra/rfid/demo/sdksample/MainActivity.java** (Application UI & USB state manager)
- **app/src/main/java/com/zebra/rfid/demo/sdksample/RFIDHandler.java** (Zebra RFID SDK connector)
- **app/libs/*.aar** (Zebra SDK dependencies)
- **.vscode/tasks.json** (automated build/deploy/run)
- **runhh** and **runhh.sh** (root automation scripts)
- **DESIGN.md** (architecture + review)
- **code.md** (interactive 11 runtime playbooks playbook)
- **USB-OTG.md** (USB, power connected, charging and pass-through policies review)

Change History

2026-06-18

- Version: **v3.4.1** (USB/OTG State Machine Implementation Update)
- Added active USB power broadcast and transport state monitors:
 - Subscribed receiver branches for `ACTION_USB_STATE`, `ACTION_POWER_CONNECTED`, and `ACTION_POWER_DISCONNECTED`
 - Parses system transport flag states (`mtp`, `ptp`, `mass_storage`, `adb`, `rndis`) in `updateUsbModeFromIntent`.
- Formulated mode-specific connection and disconnection policies:
 - **Power-Only (Charging adapter)**: Drops standard host-reader sessions gracefully via `rfidHandler.onPause()`, sets the host omission index (`skipTc53eReaderSelection` to `true`), and allows pass-through charging without interface selection conflicts.
 - **USB Data/File Transfer/Debug Mode**: Keeps RFID connections active until hardware physically detaches from the system to preserve debugging sessions.
 - **TC22R Gating**: Implemented `rfidHandler.isTC22R()` evaluation which ignores standard USB broadcast receiver blocks.
- Strengthened power-unplug debouncing:
 - Established a staggered reconnect schedule (500 ms → 1200 ms → 2500 ms) under `startPowerReconnectWindow()`.
 - Added busy checks (`rfidHandler.isConnectionBusy()`), automatic timeouts at 11,000 ms, and UI status suppression on intermediate errors to avoid status logs noise.
- Documented entire playbooks, sequence diagrams, and flowcharts in `code.md` and `USB-OTG.md`, compiling clean PDF references for both playbooks.

2026-06-17

- `RFIDHandler` code cleanup:
 - TAG changed to `private`
 - `Log.e` → `Log.d` in `getAvailableReader()`; removed redundant size log
 - Removed duplicate `connect()` hostname log
 - Removed `//Before///After` noise comments
 - Simplified `getAndroidDeviceSerialNumber()`: removed dead null check, unreachable try/catch, and unreachable Approach 4; removed unused `Settings` import
 - Removed redundant `reader = null` in `dispose()`
 - Collapsed `isTC22R()` to single-expression return
 - Removed `synchronized` from `beep()/beepAppear()`; corrected log messages
- Updated `DESIGN.md` code snippets to reflect `skipTc53eReaderSelection` and `POWER_CONNECTED_EVENT_DEBOUNCE_MS`

2026-06-15

- Version: **v3.4** (maintenance + automation update)
- Added robust build/deploy/run automation in `runhh.sh`:
 - `adb` discovery fallback for macOS SDK path
 - clear no-device / multi-device diagnostics
 - `--serial`, `--clean`, `--skip-build`, `--skip-install` options
 - app launch verification via PID check
- Updated `.vscode/tasks.json` to use `runhh.sh` tasks:
 - default debug build/deploy/run
 - prompt-driven device serial task
 - clean build variant
- Improved `RFIDHandler` lifecycle and reliability:
 - hardened connect/disconnect guards

- re-attach logic via `readersAttached` reset on disconnect
 - null-safe reader list handling during SDK init/discovery
 - reduced high-frequency tag logging overhead with debug sampling
 - deterministic eConnex reader matching (removed broad generic match)
 - app title now updates after connect to include SDK version (for example: TC53e v3.4.1 (SDK 2.0.5.238))
- Refreshed `DESIGN.md` with detailed implementation snippets for init, discovery, connect, disconnect, reconnect, and attach/detach behavior.

Troubleshooting

- **Error: AGP requires Java 17**
Ensure `JAVA_HOME` points to Java 17 (or run the provided VS Code task).
- **No reader found**
Verify hardware attachment/transport mode and that the device supports the configured reader transport.
- **Reader selection behavior**
The app selects readers in a deterministic order: RFD403 eConnex first, then RFD40 family Bluetooth sleds, and finally falls back to the first available reader with a visible warning.
- **adb not found**
Add Android SDK platform-tools to your shell `PATH`.