💡 Modulation is the art of transforming simple signals into complex forms!

UESTC 3018 - Communication Systems and Principles

Lecture 11 — Angle Modulation

Dr Hasan Abbas

Reflection 🤔

- Why Modulation?
- Amplitude Modulation (AM) is a linear process
- AM wave is a band limited signal
- AM is not resilient to noise

Today's Lecture 📅

- Angle Modulation
- Frequency Modulation (FM)
- Phase Modulation (PM)

First, AM ... 🎗

- For an AM signal, $m(t)\cos(2\pi f_c t)$
- The envelope changes along the real axis with $m(t)$
- Or $m(t)$ scales the carrier signal $\cos(2\pi f_c t)$



Now ... 🎗

- Include $m(t)$ as the **phase** of the carrier

$$2\cos\left(2\pi f_c t + km(t)\right) = e^{j(2\pi f_c t + km(t))} + e^{-j(2\pi f_c t + km(t))}$$



Angle Modulation

Angle Modulation 🔑

- Keep the modulated wave amplitude the same
- We can modulate a carrier by changing the **phase** and **frequency**
- Former is PM and latter is FM
- Angle Modulation is much more complex than AM
- A non-linear process
- We focus on FM

$$u(t) = A_c \cos(2\pi f_c t + \phi(t)).$$

Instantaneous Frequency 🥴

- 🧭 Remember instantaneous velocity from high school days
- Use of derivatives to describe the **instantaneous** phenomenon
- We can vary the *instantaneous frequency* of the signal through $m(t)$



Instantaneous Frequency (contd.) 😣

- At any time instant t_0, we can find the instantaneous frequency by taking the derivative



A Generalised Sinusoid

Lets look at,

$$\varphi(t) = A\cos\theta(t)$$

Here $\theta(t)$ is the generalised angle that can have any value

- For a true sinusoidal signal,

$$\theta(t) = \omega_c t + \theta_0$$

Finding the Instantaneous Frequency

- The derivative of the generalised angle,

$$\omega_i(t) = \frac{d\theta}{dt} = \theta'(t)$$

- The other way, phase is the integral of the instantaneous frequency,

$$\theta(t) = \int_{-\infty}^{t} \omega_i(u)du = \theta_0 + \int_{0}^{t} \omega_i(u)du$$

- We can modulate by either varying $\omega_i(t)$ or $\theta(t)$

Phase Modulation (PM)

- As the name suggests, we vary the phase $\theta(t)$ **linearly** with $m(t)$

$$\theta^{PM}(t) = \omega_c t + k_p m(t)$$

- The generalised or in fact the transmitted signal is thus,

$$\varphi^{\mathrm{PM}}(t) = A_c \cos(\omega_c t + k_p m(t))$$

We get the instantaneous frequency as,

$$\omega_i^{PM}(t) = \frac{d\theta}{dt} = \omega_c + k_p \dot{m}(t)$$

- 🔑 $\omega_i^{PM}(t)$ is proportional to the rate of change of $m(t)$
- Rapid changes in $m(t)$ results in higher value of $\dot{m}(t)$
- What about the bandwidth of the signal?

Frequency Modulation (FM)

- In FM we vary the frequency $\omega(t)$ **linearly** with $m(t)$,

$$\omega_i^{FM}(t) = \omega_c + k_f m(t)$$

- The phase θ^{FM} is,

$$\theta^{FM}(t) = \int_{-\infty}^{t} \omega_i^{FM}(u)du = \omega_c t + k_f \int_{-\infty}^{t} m(u)du$$

The transmitted signal is thus,

$$\varphi^{\mathrm{FM}}(t) = A_c \cos\left(\omega_c t + k_f \int_{-\infty}^{t} m(u)du\right)$$

Note the parameter k_f which along with $m(t)$ determines the bandwidth

- 🔑 $\theta^{FM}(t)$ to a phase modulator $\equiv \omega_i^{PM}(t)$ to a frequency modulator.

FM vs PM

Guess the 🟡, 🔴 and 🟢 signals




$m(t)$
FM Modulator
$m(t)$
Integrator
PM Modulator


$m(t)$
PM Modulator
$m(t)$
Differentiator
FM Modulator

Some Observations

- Regardless of PM or FM, angle modulation signal has constant amplitude
- Power of the signal remains the same irrespective of k_p or k_f.
- PM is a 90° shifted version of FM and vice versa.



An Example

- Given a signal $m(t)$, sketch the FM and PM waves.
- $k_f = 2\pi \times 10^5$, $k_p = 10\pi$ and $f_c = 100$ MHz.



Questions 🤔

- You can ask on Menti

Further Reading

- Section 4.5 - Angle Modulation
  Modern Digital and Analog Communication Systems, 5th Edition
- B P Lathi and Zhi Ding

Get in touch

Hasan.Abbas@glasgow.ac.uk