Noise-Rate-Activated Sensing

How changing noise strength changes the precision of an unknown frequency

Explanatory report

How accurately can we read a clock when both its speed and the action of its errors are unknown? In this report the clock is a quantum sensor. Its *phase* plays the role of a hand moving around a circle, and the frequency is the speed we want to measure. Noise interrupts that motion. We know the family of possible errors, but not which member of that family the device has. The same unknown error acts throughout the experiment.

The main result compares two versions of one specified device. The first has one fixed positive coupling to its noisy environment. The second may choose between two fixed positive couplings to that same environment. Neither setting turns the noise off. With only one coupling, the smallest achievable worst-case mean-square error has order $1/n$, where n is the number of interaction cells. With the two-setting menu it has order $1/n^2$. The clock interval, physical compensation and available boundary operations are otherwise the same. The frequency is initially unknown on a fixed nonzero interval, and the claim holds for every allowed error direction.

There are two different obligations in such a statement. To show that a precision is *attainable*, we must give a complete estimation procedure. To show that it is *optimal in order*, we must also rule out a better order for every permitted procedure, including clever feedback schemes. The report does both. Calibration, repeated trials, ambiguous phase readings and unsuccessful outcomes all count toward the same physical duration.

The mechanism in ordinary language. A protected reference lets us detect when an error flips the sensor without reading the phase we are trying to preserve. Two flips about the same unknown axis cancel each other. The signal accumulates with opposite signs between successive flips. Choosing the stronger coupling while the sensor is in the flipped sector makes its return more likely; choosing the weaker one in the unflipped sector helps retain a useful net signal. The complete error record then tells us how each possible frequency would have affected the surviving phase. Several progressively longer experiments locate the correct frequency. This is a description of the construction; a separate bound is needed to show why a single fixed coupling cannot achieve the same global precision order.

How to read the report. Section 1 introduces the language through small examples. Sections 2 and 3 establish the main finite-strength result. Sections 4 and 5 explain a separately proved continuous-time counterpart. Sections 6 and 7 ask what changes if a pulse can be applied during an interaction, and distinguish a known timing error from hidden random jitter. The final sections state the limitations and reassemble the physical conclusion. The prose explains the purpose of each calculation; the equations specify exactly what is being claimed and why it follows. No prior quantum mechanics or statistical estimation vocabulary is assumed. Basic algebra is useful; slopes, averages and accumulated changes are explained where their mathematical notation first appears.

1 The estimation problem

1.1 A two-level system can carry a phase

A qubit is a system with two distinguished basis states, written $|0\rangle$ and $|1\rangle$. The vertical bracket notation, called a ket, denotes a column vector:

$$|0\rangle = \begin{pmatrix} 1 \\ 0 \end{pmatrix}, \qquad |1\rangle = \begin{pmatrix} 0 \\ 1 \end{pmatrix}, \qquad |\psi\rangle = c_0|0\rangle + c_1|1\rangle, \qquad |c_0|^2 + |c_1|^2 = 1. \tag{1.1}$$

The coefficients c_0, c_1 are complex numbers called amplitudes. A measurement in this basis returns 0 with probability $|c_0|^2$ and 1 with probability $|c_1|^2$. The last equation says that these probabilities sum to one; this is what *normalized* means. The basis states are orthogonal: their inner product is zero, so this measurement can distinguish them perfectly.

A complex amplitude has a magnitude and an angle. We write an angle factor as $e^{i\vartheta} = \cos\vartheta + i\sin\vartheta$, where $i^2 = -1$. Multiplying the whole state by the same angle factor changes no measurement probability. Changing the angle of one amplitude relative to the other, however, changes what other measurements can reveal. That relative angle is the phase used for sensing. For example,

$$|\psi_\vartheta\rangle = \frac{|0\rangle + e^{i\vartheta}|1\rangle}{\sqrt{2}} \tag{1.2}$$

always gives equal probabilities in the 0/1 measurement, whatever ϑ is. A suitable different measurement can distinguish its phases.

Operations on these vectors are represented by matrices. The three Pauli matrices used throughout the report are

$$X = \begin{pmatrix} 0 & 1 \\ 1 & 0 \end{pmatrix}, \qquad Y = \begin{pmatrix} 0 & -i \\ i & 0 \end{pmatrix}, \qquad Z = \begin{pmatrix} 1 & 0 \\ 0 & -1 \end{pmatrix}. \tag{1.3}$$

Thus X swaps the two basis states, Z leaves $|0\rangle$ unchanged and changes the sign of $|1\rangle$, and Y swaps them with the phases i and $-i$. The symbol I is the identity matrix, which changes nothing. A dagger means transpose followed by complex conjugation; conjugation replaces i by $-i$. A bra $\langle\psi|$ is the row vector $|\psi\rangle^\dagger$. Hence $\langle\psi|\psi\rangle$ is the sum of the squared amplitude magnitudes.

For measurements, X, Y, Z also denote observables with outcomes $+1$ and -1. An observable is a Hermitian matrix, meaning $O^\dagger = O$; its eigenvalues are its possible outcomes. An eigenvector obeys $O|v\rangle = \lambda|v\rangle$ and gives outcome λ with certainty. For the state in Eq. (1.2),

$$\langle X\rangle = \cos\vartheta, \qquad \langle Y\rangle = \sin\vartheta, \qquad \langle Z\rangle = 0. \tag{1.4}$$

Angle brackets here denote the average measured outcome. Since the outcomes are ± 1, a mean m means probabilities $(1+m)/2$ and $(1-m)/2$. The X and Y measurements are therefore two ways of reading the cosine and sine of a phase. These are often called its two *quadratures*. They are performed on separately prepared systems; a single qubit does not give both readouts for free.

1.2 A density matrix keeps both phase and uncertainty

The density matrix of a pure state is $\rho = |\psi\rangle\langle\psi|$, a column times a row. If different states are prepared with ordinary probabilities p_j, the density matrix is their weighted average $\rho = \sum_j p_j |\psi_j\rangle\langle\psi_j|$. It has trace one, where Tr means the sum of the diagonal entries, and is positive:

$\langle v|\rho|v\rangle \geq 0$ for every vector $|v\rangle$. These properties ensure nonnegative measurement probabilities summing to one.

The difference between a quantum phase and an unrecorded random choice is visible in a simple example:

$$\rho_+ = \frac{1}{2}\begin{pmatrix} 1 & 1 \\ 1 & 1 \end{pmatrix}, \qquad \rho_{\text{mix}} = \frac{1}{2}\begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix}. \tag{1.5}$$

The first is the state $|+\rangle = (|0\rangle + |1\rangle)/\sqrt{2}$. The second is an equal random mixture of $|0\rangle$ and $|1\rangle$. Both give 0 and 1 equally often in the basis measurement. An X measurement always gives $+1$ for ρ_+, but gives both signs equally often for ρ_{mix}. The off-diagonal entries preserve the phase information that the mixture lacks.

In this notation, the mean outcome of observable O is $\text{Tr}(\rho O)$. The probability of one outcome is $\text{Tr}(\rho P)$, where P is the projector onto its outcome subspace. A projector keeps the component in that subspace and removes the perpendicular component. These statements are the *Born rule*. They let us calculate the probabilities of every experiment below, including experiments with partially lost phase information.

1.3 Frequency turns the phase, and long turns can be ambiguous

A Hamiltonian specifies how a quantum state changes in time. In units with $\hbar = 1$, evolution for time t under a constant Hamiltonian H is $U(t) = e^{-iHt}$. The matrix exponential is defined by the same power series as the ordinary exponential; it is a unitary matrix, $U^\dagger U = I$, so evolution preserves normalization. For $H = \omega Z/2$, its action on $|+\rangle$ is

$$e^{-i\omega t Z/2}|+\rangle = \frac{e^{-i\omega t/2}|0\rangle + e^{i\omega t/2}|1\rangle}{\sqrt{2}} \;\sim\; \frac{|0\rangle + e^{i\omega t}|1\rangle}{\sqrt{2}}. \tag{1.6}$$

The symbol $\sim$ here means equality up to an unobservable overall phase. The relative phase advances by ωt. Frequency and coupling strength have units of inverse time; phases are dimensionless and measured in radians.

A readout at known angle ζ uses $O_\zeta = \cos\zeta\, X + \sin\zeta\, Y$. Its two outcome probabilities are

$$\Pr\{y = \pm 1 \mid \omega, t, \zeta\} = \frac{1 \pm \cos(\omega t - \zeta)}{2}. \tag{1.7}$$

This adjustable phase-sensitive readout is called an equatorial measurement. An *interrogation* means allowing the sensor to evolve and then reading it. The displayed preparation, evolution and readout form a Ramsey experiment; no further meaning of that name is needed here.

A long interrogation makes small frequency changes produce large phase changes. But a full turn is 2π: at a fixed duration t, frequencies separated by $2\pi/t$ give exactly the same probabilities in Eq. (1.7), even if the readout angle is varied. The repeated oscillations of this probability are called fringes. A long experiment can therefore resolve a small shift within one fringe without identifying which fringe contains the true frequency. Shorter measurements must first remove that ambiguity.

The device below includes a fixed compensating frequency ω_0, leaving the residual frequency $\epsilon = \omega - \omega_0$. This is the known rotation already subtracted physically from the sensor's evolution. Updating a classical estimate of ϵ changes what we know. Choosing a different final readout angle changes what we measure. Neither action changes the compensating Hamiltonian.

1.4 Detect an error without reading the stored phase

The sensor S feels the signal and the noise. A protected ancillary qubit A acts as a reference and memory; it does not acquire an additional signal phase. Environmental qubits E interact with the sensor but are inaccessible. The symbol $\otimes$ combines system spaces: $|0_S 1_A\rangle$ means sensor state 0 and ancilla state 1. Operators with different subscripts act on the named systems. A partial trace removes one system from the mathematical description while preserving every measurement probability on those remaining. It does not make the removed system available to the controller.

The error family is

$$N_\phi = \cos\phi\, X + \sin\phi\, Y, \qquad N_\phi|0\rangle = e^{i\phi}|1\rangle, \quad N_\phi|1\rangle = e^{-i\phi}|0\rangle. \tag{1.8}$$

Every member swaps the two basis states, but leaves a different pair of phases. The angle ϕ specifies which error occurs; it is fixed but unknown throughout the experiment. We call it a transverse direction because it reverses the signal generator:

$$N_\phi^2 = I, \qquad N_\phi Z N_\phi = -Z. \tag{1.9}$$

Two identical flips cancel. The reduced error channel is unchanged by $\phi \mapsto \phi + \pi$, which changes only the sign of N_ϕ; its direction can therefore be taken modulo π.

Store a logical qubit in two physical qubits:

$$|0_L\rangle = |0_S 0_A\rangle, \quad |1_L\rangle = |1_S 1_A\rangle, \quad |\psi_L\rangle = c_0|0_L\rangle + c_1|1_L\rangle. \tag{1.10}$$

The subscript L denotes this encoded two-dimensional space. Both states have even parity, meaning that the two basis bits agree. The product observable $Z_S \otimes Z_A$ then gives $+1$. A sensor error produces

$$(N_\phi \otimes I_A)|\psi_L\rangle = c_0 e^{i\phi}|1_S 0_A\rangle + c_1 e^{-i\phi}|0_S 1_A\rangle, \tag{1.11}$$

which has odd parity: the bits disagree and the product observable gives -1. Measuring parity distinguishes agreement from disagreement without distinguishing the two amplitudes within either sector. It can reveal an error without reading the signal phase. This error indication is called a syndrome. It is obtained from the sensor and its reference, not from the bath.

A quantum *channel* is the rule taking an input density matrix to the accessible output. It can be written using Kraus operators as

$$\rho \longmapsto \sum_r K_r \rho K_r^\dagger, \qquad \sum_r K_r^\dagger K_r = I. \tag{1.12}$$

The individual terms describe possible alternatives. Their traces are their probabilities; the sum preserves total probability one. If a permitted measurement also identifies the alternative r, we have an *instrument*: keep that label, and divide $K_r \rho K_r^\dagger$ by its trace to obtain the conditional state. A Kraus label is not automatically observable. Below, parity makes the relevant alternatives observable. An unrecorded mixture and a collection of labelled conditional states are different experimental resources.

1.5 Error, probability and the resources we count

A strategy specifies preparation, allowed operations, decisions based on earlier observations, and the rule for turning the final record into an estimate $\widehat{\omega}$. Adaptivity means applying one prescribed rule to different observed histories. It does not give the controller the true parameters.

The complete record includes chosen settings, parity results, terminal measurements and failure flags.

For a random number W, its expectation $\mathbb{E}W$ is its probability-weighted average. Its variance is $\mathrm{Var}(W) = \mathbb{E}[(W - \mathbb{E}W)^2]$, the average squared fluctuation around that mean. For independent observations with the same variance, averaging N of them divides that variance by N. A conditional expectation $\mathbb{E}[W \mid R]$ uses only trials with the specified record R, or equivalently holds that record fixed in the probability model.

The mean-square frequency error of a strategy $\mathcal{P}$ is

$$\mathbb{E}^{\mathcal{P}}_{\omega,\phi}[(\widehat{\omega} - \omega)^2]. \tag{1.13}$$

It averages *all* its possible records, not only successful ones, and has units of inverse time squared. To require a guarantee across an interval, take the largest such error over its frequencies and all unknown directions. Then choose the permitted strategy with the smallest possible guarantee. This is the *minimax risk*, written R^*. In the formal definition, sup means the least upper bound (the largest value when one exists), and inf means the greatest lower bound. Estimates may be biased: their average need not equal the true frequency.

A fixed interval does not narrow as the experiment grows. A bound that is *uniform* over the interval and direction uses the same constant for all those unknown values. The order statement $R^*(n) = \Theta(n^{-a})$ means that positive constants bound $n^a R^*(n)$ above and below for sufficiently large n. $O(n^{-a})$ gives only an upper order bound, and $o(n^{-a})$ denotes a term whose ratio to n^{-a} tends to zero. The hardware is held fixed in these limits.

For orientation, a pure C/n mean-square law halves when the cell count doubles, while C/n^2 quarters. The corresponding root-mean-square orders are $n^{-1/2}$ and n^{-1}. Our theorem establishes these orders with hardware-dependent constants, not these exact finite-budget ratios or a particular numerical crossover between the two devices.

The cell duration is $h > 0$ and the full physical duration is $T = nh$. Ideal instruments have zero duration in this model, but their placement and number are constrained. Initial preparation and readout exactly at the deadline are free contacts. Earlier readouts, resets and interventions must fit the contact budget. Calibration cells, failed trials and repetitions all consume time. Storing an early estimate until the deadline creates no additional sensing time. These are assumptions of the comparison, not a claim that real laboratory control has no overhead.

1.6 Local sensitivity and an unknown nuisance

For a complete recorded outcome x, the likelihood $p(x \mid \omega, \phi)$ is the probability rule predicted at a candidate parameter pair. A derivative is a local slope: $f'(u)$ tells how much f changes per small change in u. A partial derivative ∂_ω varies ω while holding the other parameter fixed. An integral later sums a continuously changing contribution, such as elapsed signed time or an average over a frequency interval.

The logarithmic derivatives

$$\ell_\omega = \partial_\omega \log p, \qquad \ell_\phi = \partial_\phi \log p, \qquad J_{ij} = \mathbb{E}[\ell_i \ell_j] \tag{1.14}$$

are called scores and their Fisher information matrix. The logarithm is natural throughout the report. A score measures the fractional change in an outcome's probability. The matrix collects the size of those changes and how similarly the two unknowns change the data.

The direction ϕ is a nuisance parameter: it affects the observations but is not the quantity we wish to report. If a frequency change can be imitated by changing ϕ, its apparent sensitivity is

not all useful. The remaining local information is

$$\mathcal{I}_\omega = \min_c \mathbb{E}[(\ell_\omega + c\ell_\phi)^2] = J_{\omega\omega} - \frac{J_{\omega\phi}^2}{J_{\phi\phi}} \quad \text{if } J_{\phi\phi} > 0. \tag{1.15}$$

The minimization asks how small the observable change can be made by combining the frequency change with a direction change. It is a comparison of possible unknown parameters, not a controller action. The coefficient c has units of time. The minimization form remains meaningful when the division formula is unavailable. Trials sharing one direction must combine their full matrices before eliminating that same unknown direction.

Quantum Fisher information bounds the information obtainable by any measurement of a quantum state. This helps prove an impossibility result for all readouts. Both forms of Fisher information describe *local* distinguishability near a parameter value. The repeated-fringe example explains why large local information does not itself give a globally accurate estimate. The lower bounds below turn uniform information bounds into error bounds using a carefully chosen average over possible frequencies. The upper bounds instead construct actual estimators and charge every part of their operation.

2 A finite interaction device and its precision limit

The central comparison can be made without taking a weak-coupling or infinitely fast measurement limit. A sensor meets a sequence of fresh bath qubits. Each encounter lasts the same positive time h, and the coupling strength remains finite as the experiment grows. The controller may act between encounters. Its additional option in the more powerful design is to select one of two positive strengths for the next encounter.

The target frequency is ω, measured in inverse time. A fixed nominal compensation ω_0 leaves the residual frequency $\epsilon = \omega - \omega_0$. The unknown transverse direction is described by an angle ϕ, shared by every encounter, setting and repeated trial. On a sensor qubit, let X_S, Y_S, Z_S denote the Pauli matrices, and put

$$N_\phi = \cos\phi\, X_S + \sin\phi\, Y_S. \tag{2.1}$$

This operator obeys $N_\phi^2 = I$ and $N_\phi Z_S N_\phi = -Z_S$. An error about this direction reverses the sign of the signal generator; two such errors cancel. The difficulty is that the direction itself is unknown and continuously valued. For the reduced experiment, ϕ and $\phi + \pi$ describe the same noise axis.

2.1 What is fixed, what is controlled, and what is counted

During a cell with chosen coupling $g > 0$, the joint Hamiltonian is

$$H_g(\epsilon, \phi) = \frac{\epsilon}{2} Z_S \otimes I_E + g N_\phi \otimes X_E. \tag{2.2}$$

The subscript E denotes that cell's environmental qubit. Units are chosen so that $\hbar = 1$: H_g, g and ϵ have units of inverse time, whereas gh is dimensionless. All bath qubits start in $|0\rangle$ at time zero. Each is used once and retained afterward. The controller cannot measure or manipulate them. Thus a finite experiment uses a finite bath, whose size grows with the number of cells.

The controller has protected ancillary storage and ideal, instantaneous instruments at the boundaries. An instrument is an operation that can both change the quantum state and produce a classical outcome. Its subsequent choices may depend on the outcomes already recorded. The

control rule is fixed independently of the unknown parameters: learning from data is allowed, but the controller is not given the true values of ω or ϕ.

A budget of n cells has hard duration $T = nh$. Initial preparation and readout at T are free. There are at most $n-1$ nonterminal boundary contacts. Several consecutive operations at the same boundary count as one combined instrument: a parity measurement, a completed trial's readout, a fresh preparation and a choice of the next coupling can be combined there. A readout before T is a counted contact. Calibration, repetitions, rejected records and unsuccessful trials all consume their cells and contacts. An estimate obtained early can be held in protected storage until the deadline, but the charged duration remains nh.

There are no controls inside a cell, changes of cell duration, resets of the collision clock, or noise-free signal-bearing waiting periods. The physical compensation ω_0 stays fixed. A frequency estimate may change a later measurement basis; it does not change the Hamiltonian in Eq. (2.2).

Choose two specified couplings satisfying

$$0 < g_a < g_b, \qquad g_b h < \frac{\pi}{4}. \tag{2.3}$$

The fixed-device benchmark uses one specified $g \in \{g_a, g_b\}$ in every cell of every pooled trial. The two-setting device may choose g_a or g_b before each cell through classical recorded control. A recorded random choice between strengths is already access to the two-setting menu. Both classes have the same boundary-control and storage resources. Neither coupling decreases as n grows, and neither is zero.

2.2 The global statement

The frequency is promised to lie in a fixed interval $\Omega = [\omega_0 - E, \omega_0 + E]$, with $E > 0$ independent of n. Its sufficient size will be specified below. For a control protocol $\mathcal{P}$ and estimator $\widehat{\omega}$, the risk is the mean squared error, averaged over every recorded outcome. The optimal worst-case risk at one coupling is

$$R_g^*(n;\Omega) = \inf_{\mathcal{P},\widehat{\omega}} \sup_{\omega\in\Omega,\,\phi} \mathbb{E}^{\mathcal{P}}_{\omega,\phi}[(\widehat{\omega}-\omega)^2]. \tag{2.4}$$

The same definition with the two-setting control class gives $R^*_{\{g_a,g_b\}}(n;\Omega)$. The infimum includes biased estimators and all permitted adaptive strategies, not just the constructions described in this report. Squared frequency error has units of inverse time squared. Clipping any estimate to Ω cannot increase its risk.

Theorem 2.1 (Global finite-strength separation)**.** *For every fixed pair in Eq. (2.3), there is a fixed, nonzero bandwidth E on which, uniformly over the shared unknown transverse direction,*

$$\boxed{R_g^*(n;\Omega) = \Theta(n^{-1}) \quad (g = g_a \text{ or } g_b), \qquad R^*_{\{g_a,g_b\}}(n;\Omega) = \Theta(n^{-2}).} \tag{2.5}$$

The clock, strengths and compensation remain fixed throughout this comparison.

Here $\Theta(n^{-k})$ means that positive, finite constants bound the risk above and below by multiples of n^{-k} for all sufficiently large n. The constants may depend on the fixed hardware and interval. As h is fixed, the corresponding laws are inverse physical time and inverse physical time squared. This theorem establishes orders of risk; it does not identify the optimal global constants or the largest possible band.

Three ingredients establish the comparison. An exact one-cell experiment gives the inverse-n upper bound and provides paid coarse localization. A direction-changing comparison curve proves that every fixed-device strategy faces the inverse-n obstruction. Finally, the two-strength construction retains records whose accumulated phase is uniformly sensitive to frequency and resolves their ambiguity across several scales. The latter construction is developed in the next part of the report.

2.3 The exact instrument of one cell

We need both parts of a cell's output: what the parity measurement reports, and what happens to the stored phase after that report. An average noise channel alone would discard this distinction. The following calculation provides the probabilities and the conditional operations together.

The two terms in Eq. (2.2) anticommute: multiplying them in opposite orders changes the sign, so their cross terms cancel when the Hamiltonian is squared. Therefore $H_g^2 = R_g(\epsilon)^2 I$, where

$$R_g(\epsilon) = \sqrt{g^2 + \epsilon^2/4}, \qquad r_g = R_g(\epsilon)h. \tag{2.6}$$

The symbol $R_g(\epsilon)$ here is a frequency scale, distinguished by its argument and absence of a star from the risk $R_g^*(n;\Omega)$. Exponentiating the Hamiltonian gives the exact unitary

$$U_g = \cos r_g\, I - i\frac{\sin r_g}{R_g}\left(\frac{\epsilon}{2} Z_S \otimes I_E + g N_\phi \otimes X_E\right). \tag{2.7}$$

The operator norm, meaning the largest factor by which a matrix can stretch a vector, is $\|H_g\| = R_g(\epsilon)$. No short-time expansion has entered this formula.

Tracing out a bath input $|0\rangle$ produces a quantum channel $\rho \mapsto \sum_{r=0}^{1} K_r \rho K_r^\dagger$ with operators

$$K_0 = aI - ibZ_S, \qquad K_1 = -icN_\phi, \qquad a = \cos r_g, \quad b = \frac{\epsilon}{2R_g}\sin r_g, \quad c = \frac{g}{R_g}\sin r_g. \tag{2.8}$$

These real coefficient functions satisfy $a^2 + b^2 + c^2 = 1$. The term "Kraus operators" denotes this representation of an unobserved system–environment interaction; it does not imply environmental access.

One protected ancillary qubit makes the alternatives observable without reading out the stored phase. Encode $|0_L\rangle = |00\rangle$ and $|1_L\rangle = |11\rangle$, with the first qubit the sensor. The subscript L denotes this two-dimensional logical space. The first operator preserves the parity of the two qubits, while the second reverses it. A parity measurement distinguishes these cases without distinguishing $|0_L\rangle$ from $|1_L\rangle$. Because

$$K_1^\dagger K_1 = p_g I, \qquad K_0^\dagger K_0 = q_g I, \qquad p_g(\epsilon) = \frac{g^2}{R_g^2}\sin^2(R_g h), \quad q_g = 1 - p_g, \tag{2.9}$$

the flip and no-flip probabilities are independent of the logical state. They are also independent of ϕ, although generally dependent on ϵ.

On the band used below, the normalized no-flip branch is a phase rotation:

$$\frac{K_0}{\sqrt{q_g}} = \exp[-i\theta_g(\epsilon) Z_S/2], \qquad \theta_g(\epsilon) = 2\arctan\left[\frac{\epsilon}{2R_g}\tan(R_g h)\right]. \tag{2.10}$$

Here arctan is the inverse tangent taking values between $-\pi/2$ and $\pi/2$. This is the continuous phase branch with $\theta_g(0) = 0$. The flip branch is N_ϕ up to an irrelevant scalar phase. A phase is dimensionless; its derivative with respect to frequency has units of time. In particular,

$$d_j = \theta'_{g_j}(0) = \frac{\tan(g_j h)}{g_j}, \qquad j \in \{a, b\}. \tag{2.11}$$

A prime denotes differentiation with respect to residual frequency, not time. Although $d_j > h$, this conditional derivative is not a gain obtained without paying for failure: at compensation, $q_j d_j^2 = h^2 \sin^2(g_j h)/(g_j h)^2 \le h^2$.

2.4 One fixed band for calibration and coherent accumulation

The frequency promise must do three jobs. It must keep the one-cell response invertible, keep the flip probabilities positive and separated, and preserve the useful slope of long recorded phases. We now impose sufficient margins for all three jobs on the same interval. Their precise fractions are convenient proof choices; the physical point is that one positive-width interval works for every later budget. Choosing this interval does not require knowing the actual frequency within it.

Write $\chi_j = g_j h$ and choose $\chi_b < r_* < \pi/4$. Begin with

$$0 < E \le \frac{2}{h}\sqrt{r_*^2 - \chi_b^2}. \tag{2.12}$$

Then $R_{g_j}(\epsilon)h \le r_*$ for both settings and every $|\epsilon| \le E$. In particular the complete Hamiltonian is bounded by r_*/h, not just its coupling term. A specified hardware strength limit must cover this complete bound.

For brevity, set $p_j = p_{g_j}$, $q_j = q_{g_j}$ and $\theta_j = \theta_{g_j}$. Define the positive time scale

$$\mu_0 = \frac{p_b(0)q_a(0)d_a - p_a(0)q_b(0)d_b}{p_a(0) + p_b(0)}. \tag{2.13}$$

Its meaning will be the average sensitivity gained per cell when the strength is chosen from the observed parity. A "reward" below is this signed sensitivity score, not a payment or another physical resource. Its positivity can already be checked algebraically. In the trigonometric expressions below, $\tan x = \sin x/\cos x$, $\cot x = \cos x/\sin x$, and $\csc x = 1/\sin x$. At compensation,

$$\frac{q_j(0)d_j}{p_j(0)} = h\frac{\cot\chi_j}{\chi_j}, \qquad \frac{\mathrm{d}}{\mathrm{d}\chi}\frac{\cot\chi}{\chi} = -\frac{\chi\csc^2\chi + \cot\chi}{\chi^2} < 0. \tag{2.14}$$

Since $\chi_a < \chi_b$, the numerator in Eq. (2.13) is strictly positive.

At nonzero residual frequency define the frozen-derivative mean

$$\mu^0(\epsilon) = \frac{p_b(\epsilon)q_a(\epsilon)d_a - p_a(\epsilon)q_b(\epsilon)d_b}{p_a(\epsilon) + p_b(\epsilon)}. \tag{2.15}$$

The superscript 0 means that the rewards d_a, d_b are evaluated at zero, while the probabilities retain their actual frequency dependence. Shrink E, if necessary, until throughout the band

$$0 < p_a(\epsilon) < p_b(\epsilon) < \tfrac{1}{2}, \qquad \mu^0(\epsilon) \ge \tfrac{3}{4}\mu_0, \tag{2.16}$$

$$\max_{j\in\{a,b\}} |\theta_j'(\epsilon) - d_j| \le \tfrac{1}{4}\mu_0. \tag{2.17}$$

These are conditions on known smooth functions of one real variable. Their strict values at zero and continuity guarantee some positive bandwidth. Fix that bandwidth once. It is not narrowed as the cell budget grows. The conditions also explain why constants need not remain uniform if the two couplings approach one another: their positive drift then disappears.

2.5 Calibration that uses every outcome

Prepare $|+_L\rangle = (|00\rangle + |11\rangle)/\sqrt{2}$ for one cell. After measuring parity, measure the logical sine quadrature Y_L if parity is even. This is the Pauli Y measurement in the logical basis: its outcomes are ± 1, and their mean for a phase-rotated $|+_L\rangle$ is the sine of that phase. Record its outcome $z \in \{-1, +1\}$. If parity is odd, record $z = 0$. Lowercase z is a classical score, distinct from a Pauli operator. Equation (2.8) gives

$$\Pr\{z = 0\} = p_g(\epsilon), \qquad \Pr\{z = \pm 1\} = \frac{1}{2}(a \pm b)^2 = \frac{q_g(\epsilon) \pm F_g(\epsilon)}{2}, \tag{2.18}$$

where

$$F_g(\epsilon) = \mathbb{E}z = \frac{\epsilon \sin(2R_g h)}{2R_g}. \tag{2.19}$$

Every probability is independent of the unknown direction. The odd outcome is part of the experiment, not an event removed from its cost or likelihood. All three probabilities are strictly positive on the chosen band, because $|b| < \sin r_g < \cos r_g = a$ and $p_g > 0$.

For a concrete trial, take $gh = \pi/6$ and $\epsilon = 0$. Then $p_g = 1/4$, $a = \sqrt{3}/2$ and $b = 0$: the probabilities of $0, +1, -1$ are $1/4, 3/8, 3/8$. The mean score is zero for every unknown direction. A small positive residual frequency makes $+1$ more likely than -1; a negative one reverses the imbalance. Repetition measures this imbalance. The example illustrates the readout, not the two-strength advantage.

The response F_g is monotone with a uniform inverse. Differentiation shows

$$F_g'(\epsilon) = h\left[\frac{g^2}{R_g^2}\frac{\sin(2r_g)}{2r_g} + \frac{\epsilon^2}{4R_g^2}\cos(2r_g)\right]. \tag{2.20}$$

The two weights are nonnegative and add to one. For $0 < x < \pi/2$, $\sin x/x \geq \cos x$; indeed the derivative of $\sin x - x\cos x$ is $x \sin x \geq 0$, and its value at zero is zero. It follows that

$$\kappa \leq F_g'(\epsilon) \leq h, \qquad \kappa = h\cos(2r_*) > 0. \tag{2.21}$$

Thus distinct frequencies in the whole promised band give distinct mean scores, with a slope that never becomes arbitrarily small there.

Repeat this complete preparation and readout for N cells. Fresh bath partners and re-preparation make the scores independent. With $\overline{z} = N^{-1}\sum_{j=1}^{N} z_j$, define

$$\widehat{\omega} = \omega_0 + F_g^{-1}\Big(\mathrm{clip}_{[F_g(-E),F_g(E)]}(\overline{z})\Big). \tag{2.22}$$

Here clipping projects a number to the nearest point in the stated interval. It cannot increase its distance from the true mean. The variance $\mathrm{Var}(z)$ is the average squared deviation from that mean. Since $z \in [-1, 1]$, it is at most one. Independence makes the variance of the sample mean $\mathrm{Var}(z)/N$: cross terms from different centered scores average to zero. The inverse slope bound therefore yields

$$|\widehat{\omega} - \omega| \leq \kappa^{-1}|\overline{z} - F_g(\epsilon)|, \qquad \sup_{\omega\in\Omega,\phi} \mathbb{E}(\widehat{\omega} - \omega)^2 \leq \frac{1}{N\kappa^2}. \tag{2.23}$$

The same bounded scores give the uniform concentration bound

$$\Pr\{|\widehat{\omega} - \omega| \geq \delta\} \leq 2\exp[-N\kappa^2\delta^2/2], \qquad \delta > 0. \tag{2.24}$$

This bounds the probability that the frequency error exceeds a chosen tolerance δ. The bound decreases exponentially with the number of trials; it is stronger than a statement about average error alone. For confidence failure probability at most $\eta \in (0, 1)$, it is enough to take

$$N = \left\lceil \frac{2\log(2/\eta)}{\kappa^2\delta^2} \right\rceil. \tag{2.25}$$

The ceiling brackets mean rounding up to a whole number of cells. All logarithms here and below are natural unless explicitly stated otherwise. This is an ordinary concentration inequality applied to an exact microscopic likelihood; it is not a weak-coupling approximation.

As a stand-alone experiment, these N cells use $N - 1$ nonterminal contacts and terminal readout at Nh. As the prefix of a longer run, they use N counted contacts: the readout and next preparation at Nh are then before the final deadline. The prefix also costs time Nh, and its failure probability remains part of the later estimator's risk. Taking $N = n$ proves the fixed-device upper bound. Using a shorter, explicitly charged prefix supplies the coarse interval needed for the two-setting estimator.

2.6 Why arbitrary adaptation cannot beat the fixed-device order

The obstruction is not that the preceding calibration happens to use independent cells. It applies to every allowed boundary strategy, including strategies that try to learn ϕ while preserving quantum coherence in memory. To demonstrate this, consider a mathematical curve along which a frequency change is accompanied by a suitable change in the unknown direction. A worst-case guarantee over all (ω, ϕ) must also hold on this curve. No physical relationship between the two unknowns is imposed, and the curve is not supplied to the controller.

Fix one coupling g and use the coefficient functions a, b, c from Eq. (2.8). Put

$$p = c^2, \qquad q = a^2 + b^2, \qquad s = ab' - ba', \qquad \phi(\epsilon) = \phi_0 + \int_0^\epsilon \frac{s(u)}{p(u)}\,\mathrm{d}u. \tag{2.26}$$

The integral is well-defined because, on the entire band,

$$p \geq p_{\min,g} \equiv (gh)^2 \left(\frac{\sin r_*}{r_*}\right)^2 > 0. \tag{2.27}$$

This inequality follows from $p = (gh)^2(\sin r_g/r_g)^2$ and the decrease of $\sin r/r$ on the positive range in use. Angles in Eq. (2.26) can be read modulo π; the smooth real-valued expression is a convenient lift.

A dot now means the total derivative along this curve: both ϵ and $\phi(\epsilon)$ vary. Direct multiplication, using $N_\phi \partial_\phi N_\phi = iZ_S$, gives

$$\sum_{r=0}^{1} K_r^\dagger \dot{K}_r = i(-s + p\phi')Z_S = 0, \tag{2.28}$$

$$\sum_{r=0}^{1} \dot{K}_r^\dagger \dot{K}_r = A(\epsilon) I, \qquad A = a'^2 + b'^2 + c'^2 + \frac{s^2}{p}. \tag{2.29}$$

The first identity is the decisive cancellation. The direction changes at precisely the rate needed to remove the coherent accumulation of the channel derivative. Here is why this matters. If small changes produced by successive cells all point in the same direction in state space, their sizes can add before squaring, giving a term of order n^2. If the changes are perpendicular, their squared sizes add instead, giving order n. The zero-overlap identity enforces the latter behavior along the comparison curve, even when the controller uses the earlier record. Equivalently, $s = q\theta_g'/2$, and

$$4A = \frac{p'^2}{pq} + \frac{q\theta_g'^2}{p}. \tag{2.30}$$

The first term reflects changes in the branch probabilities; the second accounts for phase sensitivity and the direction variation. Dropping the probability term would not be a valid off-compensation calculation.

There is a simple uniform bound. At fixed ϕ, $\partial_\epsilon H_g = Z_S \otimes I_E/2$. Differentiating the unitary as an integral over the evolution gives $\|\partial_\epsilon U_g\| \leq h/2$. Applied to the bath input, this implies $A_0 = a'^2 + b'^2 + c'^2 \leq h^2/4$. The ordinary Cauchy–Schwarz inequality, which bounds the size of an inner product by the product of the two vector lengths, gives $s^2 \leq q(a'^2 + b'^2) \leq qA_0$. Therefore

$$4A \leq \frac{h^2}{p} \leq \frac{h^2}{p_{\min,g}}. \tag{2.31}$$

To see why the bound survives feedback, represent one cell by the isometry $V = \sum_r K_r \otimes |r\rangle$, where the extra orthogonal labels retain a mathematical purification of the discarded bath. An

isometry preserves vector lengths, so $V^\dagger V = I$. A purification enlarges the state space while reproducing the physical state when the extra registers are ignored. It can only increase the information available for an upper bound. Similarly purify boundary instruments and keep all classical records in orthogonal registers. The controller's instrument, including its conditional branches, has no explicit parameter derivative.

If $|\psi\rangle$ is the accumulated purified state, the derivative after a cell is $\dot{V}|\psi\rangle + V|\dot{\psi}\rangle$. Expanding its squared length gives

$$\|\dot{V}\psi + V\dot{\psi}\|^2 = \|\dot{V}\psi\|^2 + \|\dot{\psi}\|^2 + 2\,\mathrm{Re}\langle\dot{\psi}|V^\dagger\dot{V}|\psi\rangle. \tag{2.32}$$

Here Re takes the real part of a complex number. The last, cross term vanishes because $V^\dagger\dot{V} = 0$ from Eq. (2.28). Each cell consequently adds at most A to the derivative norm squared. Induction gives an upper bound nA. For a normalized pure state, the quantum Fisher information is $4(\langle\dot{\psi}|\dot{\psi}\rangle - |\langle\psi|\dot{\psi}\rangle|^2)$, which is at most four times the first term. Every actual final measurement has classical Fisher information J_ϵ no larger than this. Hence

$$J_\epsilon \le F_\epsilon^{\mathrm{out}} \le 4nA(\epsilon) \le \frac{nh^2}{p_{\min,g}}. \tag{2.33}$$

The classical information is the mean squared likelihood score, $J_\epsilon = \mathbb{E}[(\partial_\epsilon \log p(x|\epsilon))^2]$; $F_\epsilon^{\mathrm{out}}$ denotes the corresponding maximal quantum information before final measurement. The variable x is the complete outcome, including any flags, settings and stopping decisions.

This proof charges the whole adaptive experiment and keeps failures. Resetting the sensor, learning the direction, branching on earlier data or storing a result early does not remove the derivative cancellation. A separate curve is allowed for each fixed coupling. The two-setting comparison does not assume that a common cancelling curve exists for both settings.

2.7 Turning an information bound into a global error bound

A local information bound by itself is not a global risk theorem. In particular, the reciprocal of information is not automatically an attainable mean squared error in a phase-estimation problem. Here the lower bound uses an integrated inequality that remains valid for biased estimators.

The largest error over a band is at least any weighted average of errors within it. We can therefore choose convenient weights for a lower-bound proof, even though the actual experiment makes no probabilistic assumption about its unknown frequency. Such a weighting is called a prior. We choose one that goes smoothly to zero at the endpoints so that integration by parts has no boundary contribution.

Use the frequency-coordinate density

$$\pi_E(u) = \frac{1}{E}\cos^2\!\left(\frac{\pi u}{2E}\right), \qquad -E < u < E, \qquad I(\pi_E) = \int \frac{\pi_E'(u)^2}{\pi_E(u)}\,\mathrm{d}u = \frac{\pi^2}{E^2}. \tag{2.34}$$

This prior is a lower-bound device supported inside the promised band, not a distribution assumed of the physical frequency. On the nuisance curve take $\omega = \omega_0 + u$. For a fixed protocol with full outcome likelihood $p(x|u)$, the joint score is $S = \partial_u \log[p(x|u)\pi_E(u)]$. The density vanishes at both endpoints, so integration by parts gives

$$\mathbb{E}[(\widehat{\omega} - \omega_0 - u)S] = 1. \tag{2.35}$$

For a fixed observed outcome, the estimator has no explicit dependence on the unknown u, whereas the true frequency has derivative one. The derivative of their difference is therefore -1,

which produces the one on the right after integration by parts. The conditional likelihood score has mean zero because differentiating the total outcome probability, which is one, gives zero. Thus $\mathbb{E}S^2 = \mathbb{E}_{\pi_E} J_u + I(\pi_E)$, and another application of Cauchy–Schwarz yields

$$\sup_{\omega\in\Omega,\phi} \mathbb{E}(\widehat{\omega} - \omega)^2 \geq \frac{1}{\mathbb{E}_{\pi_E} J_u + I(\pi_E)}. \tag{2.36}$$

No unbiasedness condition appears. This derivation is the scalar integrated information inequality; the project-specific ingredient is the curve and the uniform channel bound used within it.

Substitution of Eq. (2.33), together with the calibration upper bound, proves the explicit fixed-device comparison

$$\boxed{\frac{1}{nh^2/p_{\min,g} + \pi^2/E^2} \leq R_g^*(n;\Omega) \leq \frac{1}{n\kappa^2}.} \tag{2.37}$$

Both denominators have units of time squared, as required. These finite bounds hold for every integer $n \geq 1$.

For a two-setting lower bound, use a different comparison path: keep ϕ fixed. In every selected cell the frequency derivative of the Hamiltonian remains $Z_S \otimes I_E/2$. Its integrated generator has norm at most $h/2$. Across n cells, the triangle inequality bounds the complete purified generator by $nh/2$, including classical selection and parameter-independent controls. Therefore $J_u \leq (nh)^2$. Using the same prior gives

$$R^*_{\{g_a,g_b\}}(n;\Omega) \geq \frac{1}{(nh)^2 + \pi^2/E^2}. \tag{2.38}$$

The next construction supplies an upper bound C/n^2, where C is a finite constant depending only on the fixed design. An enlarged C handles the finitely many small budgets by using the interval midpoint. Together these statements prove Theorem 2.1.

2.8 The scope of the adaptive and limiting claims

The argument above first covers finite adaptive instruments and their parameter-independent mixtures. It also extends to the controlled operational limits included in the model. The global extension rests on bounded loss, rather than an assumption that Fisher information is continuous under arbitrary convergence.

The idea can be stated without taking limits of information quantities. Round each possible estimate to one of finitely many nearby values. The rounded estimator depends only on which of finitely many outcome bins occurred. If the probability of each bin converges, its average squared error converges too. Finally make the rounding finer. Because all estimates and true frequencies stay in a bounded interval, this last change has a uniformly small effect on error.

Fix a budget, a comparison curve and its prior. Suppose the full outcome laws $P_{r,u}$ of finite controllers converge to P_u on one common measurable output space: for every event and every u on the prior support, its probability converges. The index r labels an approximating controller, not an extra resource. Take any measurable estimator f for the limiting experiment and clip it to Ω. Round its values to a finite grid in Ω, obtaining f_η with $|f_\eta - f| \leq \eta$. The grid inverse images form one fixed finite partition of the output space. Event-probability convergence gives pointwise convergence of the risk of f_η.

All such losses are bounded by $4E^2$. Dominated convergence therefore passes the same finite-controller Bayes lower bound to f_η under the fixed prior. Finally,

$$|(f_\eta - \omega)^2 - (f - \omega)^2| \leq 4E\eta \qquad (\omega \in \Omega). \tag{2.39}$$

Sending η to zero proves the lower bound for f itself. The finite rounding is classical postprocessing and requires no additional system contact. This explains exactly which limiting claim is used; agreement of experiments at a single parameter value would not suffice.

The fixed band remains a substantive physical qualification. A collision clock can have resonant frequency pairs that give identical complete boundary-controlled experiments. The theorem promises a suitable identifiable interval, not uniform consistency at every possible frequency. Likewise, an instrument placed inside a collision changes the resource class. Neither an added temporal access resource nor a retuned compensation is covered by the fixed-device obstruction just proved.

3 Turning retained records into a global frequency estimate

The remaining task is constructive. Two coupling strengths must do more than produce a large phase derivative at the compensated frequency: they must give an estimator that works throughout the promised interval, including when the frequency is initially unknown. A long interrogation alone cannot do this. Its phase may pass through many full turns, so a precise phase reading need not identify a unique frequency. Moreover, a parity record is random, its probability depends on frequency, and different records produce different phase functions.

The construction addresses these difficulties in three steps. First, an even-ending record removes the unknown noise direction exactly. Second, a gate computed from the record selects a fixed positive fraction of blocks whose phase functions have a uniformly positive slope. Third, a sequence of shorter and longer interrogations identifies the correct phase branch and refines the frequency estimate. Every attempted block is charged, whether or not the gate accepts it.

A *block* is a run of L consecutive cells, followed by a logical readout and a reset before the next block. The gate is a calculation on the recorded outcomes, not an additional physical pulse. The record determines a recipe for calculating the phase at any candidate frequency. Knowing that recipe is different from knowing its value at the still-unknown true frequency.

Throughout this section, write $u = \omega - \omega_0$ for residual frequency and $J = [-E, E]$ for the fixed promised interval. The variable $v \in J$ will denote a candidate frequency used in a classical calculation; it is not another physical setting. The interval and the hardware are held fixed as the available number n of collision cells increases.

3.1 An exact phase attached to an observed path

Use the two settings a and b for the couplings $g_a < g_b$. Start each block with the even-parity state $|+_L\rangle$, and measure parity at each cell boundary. Let $\sigma_i \in \{+1, -1\}$ be the parity after cell i, with $\sigma_0 = +1$. Choose setting a when the preceding parity is even and setting b when it is odd. There is no recovery operation after a flip.

The exact single-cell instrument has two normalized branches. A parity preserving result applies

$$D_j(u) = \exp[-i\theta_j(u) Z_S/2] \quad \text{with probability } q_j(u), \tag{3.1}$$

and a parity flip applies N_ϕ up to an irrelevant scalar phase, with probability $p_j(u) = 1 - q_j(u)$. These probabilities are independent of the logical input state and of ϕ. The label $j \in \{a, b\}$ is known from the preceding observed parity. In particular, the bath need not be measured: parity distinguishes the two Kraus branches without revealing the logical amplitudes.

Two elementary identities determine a whole block:

$$N_\phi^2 = I, \qquad N_\phi D_j(u) = D_j(u)^{-1} N_\phi. \tag{3.2}$$

The second identity follows from $N_\phi Z_S N_\phi = -Z_S$: moving a phase rotation past a flip reverses its sign. Move the flip factors together in the ordered product for an observed record $\mathcal{R} = (\sigma_0, \ldots, \sigma_L)$. If the record ends even, the number of flips is even, all factors of N_ϕ cancel in pairs, and the logical output is exactly

$$|\psi_{\mathcal{R}}(u)\rangle = \exp[-i\Phi_{\mathcal{R}}(u)Z_L/2]|+_L\rangle, \tag{3.3}$$

$$\Phi_{\mathcal{R}}(u) = \sum_{i=1}^{L} \sigma_{i-1}\mathbf{1}_{\{\sigma_i=\sigma_{i-1}\}}\theta_{j(\sigma_{i-1})}(u), \qquad j(+1) = a, \quad j(-1) = b. \tag{3.4}$$

Here $\mathbf{1}_A$ equals one when event A occurs and zero otherwise. Z_L is the logical Pauli operator. Equation (3.3) is a statement about each normalized conditional state. The probability of that state is still part of the complete experiment.

The unknown direction disappears for every even-ending record and for every u in the band. This cancellation is algebraic. It neither estimates ϕ nor implements an unknown physical operation N_ϕ as a control. The flips in (3.2) are the recorded noise itself.

For example, consider the five-cell path in Table 1. Its phase is $2\theta_a(u) - \theta_b(u)$ and its probability is $q_a(u)^2 p_a(u) q_b(u) p_b(u)$. The two flips remove the unknown direction, but they do not remove the frequency dependence of the record probability. This small example demonstrates the exact cancellation. By itself it does not guarantee that a long record has a useful slope.

Table 1: One even-ending record. A stay adds a signed signal phase; a flip changes the sign for subsequent stays.

Cell	Setting	Result	Final parity	Phase contribution
1	a	stay	even	$+\theta_a(u)$
2	a	flip	odd	0
3	b	stay	odd	$-\theta_b(u)$
4	b	flip	even	0
5	a	stay	even	$+\theta_a(u)$

3.2 Why two settings give a positive phase drift

At zero residual frequency, define

$$d_j = \theta_j'(0) = \frac{\tan\chi_j}{g_j}, \qquad \chi_j = g_j h, \qquad D_L^0 = \sum_{i=1}^{L} \sigma_{i-1}\mathbf{1}_{\{\sigma_i=\sigma_{i-1}\}} d_{j(\sigma_{i-1})}. \tag{3.5}$$

A prime means differentiation with respect to residual frequency. Thus each d_j, and D_L^0, has units of time, while θ_j is a dimensionless angle. For an even-ending record, $D_L^0 = \Phi_{\mathcal{R}}'(0)$. The superscript 0 means that the known derivatives are evaluated at zero; the actual record can have been generated at any unknown $u \in J$. We call each signed contribution a *reward* only as bookkeeping: positive contributions increase the phase slope, negative ones decrease it. "Frozen" means that these coefficients are calculated once at the known reference point. It does not mean that the experiment is assumed to be operating there.

At a fixed actual frequency, the observed parity is a two-state Markov chain with transition matrix

$$P(u) = \begin{pmatrix} q_a(u) & p_a(u) \\ p_b(u) & q_b(u) \end{pmatrix}. \tag{3.6}$$

Here "Markov chain" means that, at this fixed frequency, the probability of the next parity depends only on the present parity. The row labels are the preceding parity, even then odd;

the column labels are the subsequent parity in the same order. The *stationary fractions* are the long-run proportions of cells in each parity. In equilibrium the probability flowing from even to odd equals the reverse flow: $\pi_+ p_a = \pi_- p_b$. Together with $\pi_+ + \pi_- = 1$, this gives $\pi_+ = p_b/(p_a + p_b)$ and $\pi_- = p_a/(p_a + p_b)$. For example, $p_a = 0.1$ and $p_b = 0.3$ give an even fraction of 3/4: the system leaves the odd sector more readily. This example explains the balance calculation; the actual phase sensitivity also depends on d_a, d_b. Consequently the stationary mean frozen reward per cell is

$$\mu^0(u) = \frac{p_b(u)q_a(u)d_a - p_a(u)q_b(u)d_b}{p_a(u) + p_b(u)}. \tag{3.7}$$

The positive term counts stays in even parity; the negative term counts stays in odd parity. Increasing the coupling while the system is odd increases its chance of returning to the even sector. The exact expression also includes the different conditional phase responses of the two settings.

At $u = 0$, let $\mu_0 = \mu^0(0)$. Since

$$\frac{q_j(0)d_j}{p_j(0)} = h\frac{\cot\chi_j}{\chi_j}, \qquad \frac{\mathrm{d}}{\mathrm{d}\chi}\frac{\cot\chi}{\chi} = -\frac{\chi\csc^2\chi + \cot\chi}{\chi^2} < 0, \tag{3.8}$$

the strict ordering $0 < \chi_a < \chi_b < \pi/4$ implies $\mu_0 > 0$. With identical couplings this stationary reward instead vanishes. This particular comparison explains the construction's mechanism; the converse in the preceding section is what excludes all other fixed-coupling strategies from achieving a better global order.

The fixed band is chosen so that, for every $u \in J$,

$$0 < p_a(u) < p_b(u) < \tfrac{1}{2}, \qquad \mu^0(u) \geq \tfrac{3}{4}\mu_0, \tag{3.9}$$

$$\max_{j\in\{a,b\}} \sup_{v\in J} |\theta_j'(v) - d_j| \leq \tfrac{1}{4}\mu_0. \tag{3.10}$$

The functions involved are known and continuous. Their values at zero give strict margins for these inequalities, so some interval of positive width satisfies them. Once chosen, that interval is fixed. This argument does not supply a maximal bandwidth or constants uniform as $g_b - g_a$ tends to zero.

3.3 A record gate that certifies an entire phase curve

An even endpoint alone is insufficient: signed contributions can largely cancel on some paths. Accept a record for phase estimation precisely when

$$\sigma_L = +1 \quad \text{and} \quad D_L^0 \geq \frac{\mu_0 L}{2}. \tag{3.11}$$

The controller computes this predicate from the observed path and the known constants d_a, d_b, μ_0. It does not use the unknown actual frequency or direction. A rejected block is retained as a flagged outcome and costs the same L cells as an accepted block.

Two claims are needed: sufficiently long blocks pass the gate with a uniformly positive probability, and every accepted record has a useful phase slope throughout the whole band. An average slope alone would prove neither claim.

The next calculation separates the average from its fluctuations. The mean score grows proportionally to L, whereas its standard deviation grows at most proportionally to $\sqrt{L}$. Thus the relative fluctuation becomes small in long blocks. The proof also accounts for the initial even state, which need not be sampled from the long-run proportions.

Acceptance probability, including the initial transient. Set

$$M = \max(d_a, d_b), \qquad \rho = 1 - \inf_{u \in J}(p_a(u) + p_b(u)) < 1, \qquad V = M^2\left(1 + \frac{2}{1-\rho}\right). \tag{3.12}$$

For a fixed actual u, suppress its argument and write $\lambda = 1 - p_a - p_b$. The band conditions imply $0 < \lambda \le \rho < 1$. Starting from even parity, the exact two-state recursion gives

$$\Pr\{\sigma_i = +1\} = \pi_+ + \pi_-\lambda^i \ge \tfrac{1}{2}. \tag{3.13}$$

Define the conditional mean one-cell rewards $f_+ = q_a d_a$ and $f_- = -q_b d_b$. Summing their means yields

$$\mathbb{E}_u D_L^0 = L\mu^0(u) + \pi_-(f_+ - f_-)\sum_{i=0}^{L-1}\lambda^i \ge \tfrac{3}{4}\mu_0 L. \tag{3.14}$$

The correction for starting in even parity is nonnegative. No stationary initial state has been assumed.

For completeness, the fluctuations also admit a bound uniform over the band. Write X_i for the ith summand of D_L^0. Each X_i lies in $[-M, M]$. For $i < j$, its conditional prediction at the later cell is

$$\mathbb{E}[X_j \mid \sigma_0, \ldots, \sigma_i] = (P^{j-i-1}f)(\sigma_i). \tag{3.15}$$

The two possible values on the right differ by at most $2M\rho^{j-i-1}$, because a two-state chain contracts this difference by λ at each transition. A random variable in an interval of length a has variance at most $a^2/4$; applying the covariance inequality to the two bounded variables therefore gives

$$|\operatorname{Cov}(X_i, X_j)| \le M^2\rho^{j-i-1}, \qquad \operatorname{Var}(D_L^0) \le VL. \tag{3.16}$$

The second inequality follows by summing the geometric covariance bound and the L individual variances. It includes the nonstationary start. Covariance measures whether two rewards fluctuate together. The geometric factor says that distant cells remember less about each other's parity, so their correlations have a finite total contribution per cell. The bound on the variance is what turns a positive average into a useful probability of passing the gate.

An observed reward below $\mu_0 L/2$ lies at least $\mu_0 L/4$ below its mean. The variance bound thus implies

$$\Pr\{D_L^0 < \mu_0 L/2\} \le \frac{16V}{\mu_0^2 L}. \tag{3.17}$$

Subtract this probability from the lower bound $1/2$ for an even endpoint. The result is

$$\Pr\{\mathcal{R} \text{ accepted}\} \ge \frac{1}{2} - \frac{16V}{\mu_0^2 L} \ge \frac{1}{4} \quad \text{for } L \ge L_0, \tag{3.18}$$

where one sufficient integer is

$$L_0 = \max\left\{1, \left\lceil \frac{64V}{\mu_0^2} \right\rceil\right\}. \tag{3.19}$$

This subtraction is a union bound; the final parity and the reward need not be independent. The value of L_0 is a sufficient proof constant and can be large. No claim of practical optimality is attached to it.

Sensitivity of each accepted record. For any candidate $v \in J$, equation (3.10) gives the deterministic bound

$$|\Phi'_{\mathcal{R}}(v) - D^0_L| \le \tfrac{1}{4}\mu_0 L. \tag{3.20}$$

The gate therefore ensures

$$\alpha L \le \Phi'_{\mathcal{R}}(v) \le \beta L \quad \text{for every } v \in J, \qquad \alpha = \frac{\mu_0}{4}, \quad \beta = \max_{j\in\{a,b\}} \sup_{v\in J} |\theta'_j(v)|. \tag{3.21}$$

Both α and β have units of time. The record certifies a known, strictly increasing phase function over the whole frequency band, with a slope proportional to its length. The probability of receiving such a certificate is at least $p_0 = 1/4$, independently of the unknown frequency and direction.

3.4 Resolving the phase ambiguity one scale at a time

The rest of the argument uses only the exact conditional state (3.3), acceptance probability at least $p_0 > 0$, and derivative bounds (3.21). It therefore also explains what another recorded instrument would have to supply for the same estimation method to apply. The needed repetitions use fresh bath cells and a full reset to $|+_L\rangle$ between blocks.

Before specifying the proof constants, the procedure is:

1. Use short, paid trials to find a coarse frequency interval.
2. Double the block length and predict each accepted record's phase at the midpoint of that interval.
3. Measure relative to that prediction, compare the outcomes with the recorded response functions, and obtain a refined estimate.
4. Intersect a narrower window around the estimate with the old interval, then repeat at the next length.

Long blocks give sharper readings, while the preceding shorter blocks tell us which phase turn we are on. Intersection keeps all later estimates inside the earlier interval, even if a later refinement fails. The constants below are one sufficient way to make both the failure probabilities and the total cost precise.

The paid one-cell calibration experiment supplies an estimator $\widehat{u}_N \in J$ with

$$\sup_{u\in J,\phi} \Pr\{|\widehat{u}_N - u| \ge \delta\} \le 2\exp[-N\kappa^2\delta^2/2], \qquad \delta > 0. \tag{3.22}$$

Here $\kappa > 0$ is the uniform derivative lower bound for the one-cell calibration response, with units of time. A fixed initial localization accuracy will suffice, but its failure probability must become smaller as the final experiment becomes longer.

Choose a final scale $K \ge 1$ and define

$$s = \frac{\pi}{8\beta}, \qquad L_k = 2^k L_0, \qquad \gamma = \min\left\{\frac{p_0^2}{2}, \frac{p_0\alpha^2 s^2}{8}\right\} > 0. \tag{3.23}$$

L_k counts cells, s has units of frequency, and γ is dimensionless. The symbol π in this equation is the usual circle constant. All logarithms below are natural logarithms.

First use

$$N_0(K) = \left\lceil \frac{2L_0^2}{\kappa^2 s^2}(K\log 8 + \log 2) \right\rceil \tag{3.24}$$

one-cell calibration trials and form

$$C_0 = J \cap [\widehat{u}_0 - s/L_0, \widehat{u}_0 + s/L_0]. \tag{3.25}$$

The estimate $\widehat{u}_0$ is clipped to J, so C_0 is always nonempty. Its diameter is at most $2s/L_0$, and $\Pr\{u \notin C_0\} \le 8^{-K}$. This initial step costs only a number of cells proportional to K, despite the increasingly small failure probability, because its target width stays fixed.

At scale $k = 1, \dots, K$, let c be the midpoint of the current interval C_{k-1}. Hold that center and the block policy fixed throughout this stage, and attempt

$$r_k = \left\lceil \frac{(K-k)\log 8 + \log 12}{\gamma} \right\rceil \tag{3.26}$$

independent blocks of length L_k. Earlier stages may determine c. Earlier terminal measurement outcomes within this same stage do not change the later block policies. This restriction is part of the explicit attaining strategy and will make its conditional independence transparent.

For each accepted record $\mathcal{R}_i$, measure the logical equatorial observable

$$B_i(c) = \cos(\Phi_{\mathcal{R}_i}(c)) Y_L - \sin(\Phi_{\mathcal{R}_i}(c)) X_L. \tag{3.27}$$

Here X_L, Y_L are the logical Pauli operators. The outcome $Y_i \in \{-1, +1\}$ is a classical number; the subscript distinguishes it from the operator Y_L. The conditional mean is exactly

$$\mathbb{E}_u[Y_i \mid \mathcal{R}_i] = \sin(\Phi_{\mathcal{R}_i}(u) - \Phi_{\mathcal{R}_i}(c)). \tag{3.28}$$

This centers the readout at the phase predicted by the current interval center. It changes a terminal measurement basis only. The compensation, cell duration and interaction Hamiltonian remain fixed.

Let G be the number of accepted blocks in the stage. If $G < p_0 r_k/2$, take $\widetilde{u}_k = c$. Otherwise, compute from the actual accepted records the known function

$$H_k(v) = \frac{1}{G} \sum_{i:\, \mathcal{R}_i \text{ accepted}} \sin(\Phi_{\mathcal{R}_i}(v) - \Phi_{\mathcal{R}_i}(c)), \qquad v \in C_{k-1}. \tag{3.29}$$

Average the corresponding measured Y_i, clip that average to the image interval $H_k(C_{k-1})$, and invert H_k to obtain $\widetilde{u}_k$. The clipping prevents a fluctuation from requesting an inverse outside the current candidate interval. Finally set

$$C_k = C_{k-1} \cap [\widetilde{u}_k - s/L_k, \widetilde{u}_k + s/L_k]. \tag{3.30}$$

Every interval remains nonempty and nested, even when a statistical failure has occurred: $\widetilde{u}_k$ belongs to the preceding interval and to the new window. If an interval has already collapsed to a point, that point is the estimate and no inversion is needed.

Why is the inverse unique? The preceding interval has diameter at most $2s/L_{k-1}$, so every $v \in C_{k-1}$ obeys $|v - c| \le s/L_{k-1}$. For every accepted record,

$$|\Phi_{\mathcal{R}_i}(v) - \Phi_{\mathcal{R}_i}(c)| \le \beta L_k \frac{s}{L_{k-1}} = \frac{\pi}{4}. \tag{3.31}$$

All candidate phases therefore lie on a single increasing branch of the sine function. Combining its derivative with (3.21) gives

$$H_k'(v) \ge \frac{\alpha L_k}{\sqrt{2}}. \tag{3.32}$$

The full phase $\Phi_{\mathcal{R}_i}(v)$ may have wound around the circle many times. What is small is its difference across the candidate interval, made small by the earlier paid localization. This is how the construction resolves phase ambiguity instead of assuming it away.

3.5 Conditioning on the record, without freezing its law

For example, if two records are accepted, their prediction is the average of their two separate sine responses,

$$H_k(v) = \tfrac{1}{2}\big[\sin(\Phi_1(v) - \Phi_1(c)) + \sin(\Phi_2(v) - \Phi_2(c))\big]. \tag{3.33}$$

The record fixes which functions appear here. After fixing it, the remaining randomness is in the final $+1/-1$ measurements. A concentration bound says that their measured average is unlikely to differ greatly from this predicted average. Because the bound holds for every accepted collection of functions, it can then be averaged over their actual frequency-dependent occurrence probabilities. No average phase is substituted inside the sine. The two-record example illustrates the prediction rule, not a sufficient number of repetitions for a precise estimate.

The law of $\mathcal{R}_i$ depends on u through $p_a(u)$ and $p_b(u)$. This dependence does not invalidate (3.29). For the fixed unknown value u, first condition on all earlier stages. The fresh blocks have independent acceptance indicators and each succeeds with probability at least p_0. Bounded-variable concentration gives

$$\Pr\{G < p_0 r_k/2\} \le \exp[-p_0^2 r_k/2]. \tag{3.34}$$

Next condition on all the records of this stage. Because the policy was held fixed and the blocks used fresh bath cells, the terminal outcomes of the accepted blocks are conditionally independent. They need not have the same conditional mean; their average conditional mean is exactly $H_k(u)$.

When $u \in C_{k-1}$, clipping and (3.32) imply that an estimation error exceeding s/L_k requires the sample mean to differ from $H_k(u)$ by more than $\alpha s/\sqrt{2}$. Independent variables in $[-1,1]$ obey the tail bound $2\exp(-Gt^2/2)$ for a deviation t of their average from its mean. Consequently, on $G \ge p_0 r_k/2$,

$$\Pr\{|\widetilde{u}_k - u| > s/L_k \mid \mathcal{R}_1, \dots, \mathcal{R}_{r_k}\} \le 2\exp[-G\alpha^2 s^2/4] \le 2\exp[-p_0 r_k \alpha^2 s^2/8]. \tag{3.35}$$

Average this inequality over the actual record law and add the low-count event. Uniformly over earlier observations for which $u \in C_{k-1}$,

$$\Pr\{u \notin C_k \mid \text{earlier observations}\} \le 3e^{-\gamma r_k} \le \frac{1}{4}\,8^{-(K-k)}. \tag{3.36}$$

No derivative of the record distribution was taken, and no record probability was replaced by its compensated value. In particular, H_k is the average of the phase responses for the records actually seen, not the expectation of a phase under a guessed parameter-independent law. Classical information in record probabilities could also be used, but is not needed for this attainable bound.

3.6 Worst-case error with a hard cell budget

Return the midpoint $\widehat{u}$ of C_K. If the coarse localization and every refinement succeed, then $|\widehat{u}-u| \le s/L_K$. If the first failed refinement is stage k, the true frequency and every later estimate still belong to C_{k-1}. Thus their final separation is at most its diameter, $2s/L_{k-1} = 4s/L_k$. If the coarse step fails, both the true value and the final estimate still lie in J, giving the bound $2E$.

These three alternatives give an unconditional, worst-case mean-square error bound:

$$\begin{aligned}\sup_{u\in J,\phi} \mathbb{E}[(\widehat{u}-u)^2] &\le \frac{s^2}{L_K^2} + 4E^2\,8^{-K} + \sum_{k=1}^{K} \frac{16s^2}{L_k^2}\,\frac{1}{4}\,8^{-(K-k)} \\ &\le \frac{9s^2 + 4E^2 L_0^2}{L_K^2}.\end{aligned} \tag{3.37}$$

The last step is a geometric sum: after multiplication by L_K^2, the refinement terms are bounded by $4s^2 \sum_{j=0}^{K-1} 2^{-j} \le 8s^2$. The coarse term uses $4^K 8^{-K} \le 1$. This proof includes failed branches instead of reporting only the precision conditional on success.

The total number of cells is the deterministic number

$$B_K = N_0(K) + \sum_{k=1}^{K} r_k L_k. \tag{3.38}$$

The repetition count is largest at the short scales, where a failure could cause the largest final error. Long, costly blocks require fewer repetitions because a late failure can move the estimate only within an already narrow interval. In particular,

$$\sum_{k=1}^{K} L_k \le 2L_K, \qquad \sum_{k=1}^{K} (K-k) L_k \le 2L_K. \tag{3.39}$$

Since $N_0(K) = O(K+1)$ and $K+1 \le 2^K$ for $K \ge 1$, there is a fixed finite constant C_*, depending only on the hardware and chosen band, with

$$L_K \le B_K \le C_* L_K. \tag{3.40}$$

There is no extra logarithmic factor in the total cost. The decreasing repetition schedule is essential to this conclusion; requiring the same small failure probability at every scale would waste resources.

For a prescribed hard budget n, select the largest feasible K. Then $n < B_{K+1} \le 2C_* L_K$, so (3.37) becomes

$$\sup_{\omega \in [\omega_0 - E, \omega_0 + E], \phi} \mathbb{E}[(\widehat{\omega} - \omega)^2] = O(n^{-2}), \qquad \widehat{\omega} = \omega_0 + \widehat{u}. \tag{3.41}$$

The finitely many budgets too small for the first scale use the interval midpoint; increasing the fixed upper-bound constant covers them. The matching inverse-square lower bound in the preceding section therefore establishes the two-coupling minimax order. This construction does not determine the optimal global risk coefficient.

Contacts and duration. Each block has its prescribed length even when its record fails the gate. At a cell boundary, parity extraction, a completed block's logical readout, the next preparation and a coupling choice can be consecutive parts of one allowed instrument. Scheduling all used cells consecutively within the n-cell allocation therefore uses at most $n-1$ nonterminal boundary contacts, with the final readout at nh free under the stated convention. If a complete estimate is produced earlier, that readout is a counted contact and the classical result is retained through the remaining charged cells. The physical duration remains nh.

Calibration, failed gates, resets, repetitions and premature terminal readouts have all appeared in the same accounting. At no point does a classical frequency estimate alter the physical compensation. The quadratic precision comes from exact noise-direction cancellation and usable recorded phase functions, combined with paid ambiguity resolution. An unrecorded mixture, a phase known only through its derivative at zero, or an unknown timing perturbation would require a new argument.

4 The continuous-time counterpart

The finite-collision result has a related continuous-time statement. Its importance is conceptual: the obstruction caused by an unknown error direction does not depend on a weak-collision

approximation. The continuous model also admits an especially transparent way to convert noise into an exact, useful interrogation. It is a separate model, with ideal continuous syndrome monitoring. We do not obtain its theorems by silently replacing the finite collision clock by arbitrarily fast access inside a collision.

4.1 What changes, and what remains the same

The sensor is a qubit, the auxiliary memory is noiseless, and the target frequency is ω. A noise rate γ_j has a direct operational meaning: during a short time $\mathrm{d}t$, a flip occurs with probability $\gamma_j \mathrm{d}t$ up to terms smaller than $\mathrm{d}t$. Between flips, the signal rotates the state. At a fixed setting, the probability of a flip in the next short interval does not depend on how long the system has already waited. This is the memoryless, or Markovian, assumption in this model. Averaging the flip and no-flip alternatives gives the equation below. In a selected setting j, the reduced sensor state obeys

$$\frac{\mathrm{d}\rho}{\mathrm{d}t} = -i\left[\frac{s_j\omega}{2}Z, \rho\right] + \gamma_j(N_\phi \rho N_\phi - \rho), \qquad N_\phi = \cos\phi\, X + \sin\phi\, Y. \tag{4.1}$$

Here ρ is a density matrix, $[A, B] = AB - BA$, the known real number s_j is a dimensionless signal multiplier, and the known rate $\gamma_j > 0$ has units of inverse time. The angle ϕ is unknown, continuous, fixed throughout the experiment, and shared by every setting. Its physical period in this dissipator is π, because changing the sign of N_ϕ leaves (4.1) unchanged. In the main comparison $s_j = 1$: we change the noise rate while preserving the signal Hamiltonian. One device offers a single rate γ; the other offers two fixed rates $0 < a < b$.

The resource T is a hard physical exposure time for one sensor. Preparation, parameter-independent sensor–memory controls, monitoring, recovery pulses, classical feedback and protected storage are ideal. These idealizations are common to both sides of the comparison. They do not provide direct bath access. Rate selection means a classical choice of the scalar multiplying the same unknown noise operator. It does not mean a coherent superposition of baths or coherent access to N_ϕ as an extra Hamiltonian.

Use the two-qubit code $|0_L\rangle = |00\rangle$ and $|1_L\rangle = |11\rangle$, with the sensor first. The signal preserves parity; an error N_ϕ changes it. Ideal parity monitoring therefore identifies errors without measuring the encoded amplitudes. The jump operator is $L_j = \sqrt{\gamma_j} N_\phi$, so $L_j^\dagger L_j = \gamma_j I$. Consequently the jump rate is independent of the logical state, ω and ϕ. For a constant setting the observed jump count is Poisson with mean $\gamma_j t$: explicitly, $\Pr\{N = k\} = e^{-\gamma_j t}(\gamma_j t)^k/k!$ for $k = 0, 1, \ldots$. Here $k!$ is the product of the positive integers up to k, with $0! = 1$. Both the mean and variance of this count equal $\gamma_j t$. Thus the typical count is proportional to elapsed time, with fluctuations of order its square root. Between jumps, normalized evolution is just the signal rotation. These facts make the complete measurement record tractable; none permits discarding the time spent on an unsuccessful run.

4.2 Why a large frequency entry in an information matrix is insufficient

For an outcome distribution $p(x \mid \omega, \phi)$, its Fisher matrix has entries $J_{uv} = \mathbb{E}[(\partial_u \log p)(\partial_v \log p)]$, where $u, v \in \{\omega, \phi\}$. A nuisance direction can imitate a target change. The information that remains after allowing that imitation is

$$\mathcal{I}_\omega(J) = \inf_{c\in\mathbb{R}} (1, c) J (1, c)^{\mathsf{T}} = J_{\omega\omega} - \frac{J_{\omega\phi}^2}{J_{\phi\phi}} \quad \text{when } J_{\phi\phi} > 0. \tag{4.2}$$

The infimum definition also handles a zero or singular nuisance block. The superscript T denotes transpose. Frequency information has units of time squared. Its reciprocal bounds the variance

of a regular locally unbiased frequency estimator, with zero first-order response to ϕ. This is a local statement about a specified parameter point. It is not yet a global risk bound for an initially unknown frequency.

An elementary exact example shows what is at stake. Apply the fixed sensor recovery X after every detected error. Since $XN_\phi = e^{i\phi Z}$, an interrogation of duration t and observed count N has phase

$$\Theta = \omega t - 2\phi N, \qquad N \sim \text{Poisson}(\gamma t). \tag{4.3}$$

For a typical long run, N is near γt, so the phase's leading time-proportional part is $(\omega - 2\gamma\phi)t$. Count fluctuations supply the remaining distinction. A change in frequency can therefore be largely imitated by a change in the unknown direction. Two rates produce different combinations of the same two unknowns; this is the statistical reason that rate diversity can help. Prepare the logical X eigenstate and measure at a uniformly random, recorded equatorial angle ξ. The two probabilities are $[1 \pm \cos(\Theta - \xi)]/2$. This measurement has unit information about Θ except at isolated angles, which have probability zero under the recorded continuous randomization. The count likelihood itself contains no information about ω or ϕ.

More generally, a recorded phase $\omega D - 2\phi M$, with a parameter-independent distribution of the real variables (D, M), gives

$$J = \begin{pmatrix} \mathbb{E}D^2 & -2\mathbb{E}(DM) \\ -2\mathbb{E}(DM) & 4\mathbb{E}M^2 \end{pmatrix}. \tag{4.4}$$

For (4.3), $D = t$, $\mathbb{E}N = \gamma t$ and $\mathbb{E}N^2 = (\gamma t)^2 + \gamma t$. Substitution in (4.2) gives

$$\mathcal{I}_\omega(t) = \frac{t^2}{1 + \gamma t}. \tag{4.5}$$

The entry $J_{\omega\omega} = t^2$ is large, but its leading part is indistinguishable from an angle change. Only linear growth remains at long times. All counts and readout labels are retained in this calculation.

4.3 A converse for every adaptive control strategy

The limitation is not specific to that recovery. Restrict the two unknown parameters to a mathematical comparison path $\omega(u) = \omega_c + u$, $\phi(u) = \phi_c + cu$. The real parameter u has frequency units, and c has time units. The controller is held fixed along this path. Outcome probabilities may change; the control rule does not acquire knowledge of the unknown u.

We use a general information-growth inequality for a Markovian channel with arbitrary parameter-independent controls. If $F(t)$ is the output quantum Fisher information along the path, including the classical record, then

$$\frac{\mathrm{d}F}{\mathrm{d}t} \le 4(\|A\| + \|B\|\sqrt{F}), \tag{4.6}$$
$$A = (\partial_u L)^\dagger \partial_u L, \qquad B = \partial_u H - \frac{i}{2}((\partial_u L)^\dagger L - L^\dagger \partial_u L).$$

The operator norm $\|A\|$ is the largest factor by which A can stretch a vector. Quantum Fisher information bounds the classical Fisher information of every final measurement. The inequality is an information-theoretic ingredient; the following choice of nuisance path is its application to this physical model. The two terms have different roles. The A term allows information to increase at most at a bounded rate, giving a linear ceiling if $B = 0$. The term containing B permits coherent accumulation: because its size increases with $\sqrt{F}$, it can support quadratic

growth. We look for a nuisance path that cancels this second contribution. One rate admits such a cancellation; two different rates generally do not admit the same cancelling path. For adaptive setting selection, include the controller and recorded branches as orthogonal blocks and take the largest norms over the permitted settings. These blocks simply keep mutually distinguishable classical records in separate labels of the mathematical description. Measurements, resets and feedback remain parameter-independent channels. This is why the bound includes learning the angle during the experiment.

The Pauli identities $(\partial_\phi N_\phi)N_\phi = -iZ$ and $N_\phi(\partial_\phi N_\phi) = iZ$ give, in setting j,

$$A_j = c^2\gamma_j I, \qquad B_j = \left(\frac{s_j}{2} - c\gamma_j\right) Z. \tag{4.7}$$

For one unit-strength setting, $c = 1/(2\gamma)$ cancels B exactly. Starting from a parameter-independent preparation, $F(0) = 0$, so $F(T) \le T/\gamma$. The path $c = 0$ separately gives $F(T) \le T^2$. Together with (4.5), this proves

$$\mathcal{I}^*_{\omega,\gamma}(T) \le \min\{T^2, T/\gamma\}, \qquad \lim_{T\to\infty} \frac{\mathcal{I}^*_{\omega,\gamma}(T)}{T} = \frac{1}{\gamma}. \tag{4.8}$$

The star denotes optimization over all permitted controls and measurements. The mathematical path does not assert that noise physically encodes frequency; it selects difficult pairs inside the allowed two-parameter family.

For two rates define the dimensionless contrast

$$r = \frac{b-a}{b+a} \in (0,1). \tag{4.9}$$

Choosing $c = 1/(a+b)$ leaves $\|B\| \le r/2$ in either setting and $\|A\| \le b/(a+b)^2$. Thus

$$F'(t) \le C + 2r\sqrt{F(t)}, \qquad C = \frac{4b}{(a+b)^2}. \tag{4.10}$$

Here and below $F'(t)$ is a time derivative. Integrating the scalar comparison equation gives $\sqrt{F(t)} \le rt + O(t_c \log(1 + t/t_c))$ at large t, where $t_c = 1/(a+b)$ and the rates are fixed; hence the leading information coefficient is at most r^2. The comparison integral is $t = y/r - [C/(2r^2)]\log(1 + 2ry/C)$, where $y = \sqrt{F}$ and the logarithm is natural. This also explains why the term linear in time cannot change the leading quadratic coefficient.

4.4 Rate diversity can remove the leading statistical ambiguity

Two simple constructions attain that coefficient without adapting the bath rate to the syndrome. They still use syndrome-triggered recovery pulses.

First, use rate a for time t_a, rate b for time t_b, with $t_a + t_b = T$. Insert and later undo a logical X pulse so that the two block phases subtract. With independent Poisson counts N_a, N_b,

$$\Theta = \omega D - 2\phi M, \quad D = t_a - t_b, \quad M = N_a - N_b, \quad \mu = at_a - bt_b, \quad V = at_a + bt_b. \tag{4.11}$$

Since $\mathbb{E}M = \mu$ and $\mathbb{E}M^2 = V + \mu^2$,

$$\mathcal{I}_{\text{echo}} = \frac{D^2 V}{V + \mu^2}. \tag{4.12}$$

The choice $t_a = bT/(a+b)$, $t_b = aT/(a+b)$ makes $\mu = 0$ and $D = rT$. It achieves $\mathcal{I}_{\text{echo}} = r^2T^2$ exactly at every T. The nuisance remains in individual output states, but its score is statistically orthogonal to the frequency score after the complete records are pooled.

This design has a specific calibration sensitivity. Put $t_a = fT$ and define $q = af - b(1-f)$, $v = af + b(1-f)$. Then

$$\mathcal{I}_{\text{echo}} = \frac{(2f-1)^2 T^2}{1 + (q^2/v)T}. \tag{4.13}$$

A fixed nonzero imbalance q eventually restores linear information growth. The dimensionless quantity q^2T/v must stay bounded to retain a nonzero quadratic coefficient. This is a restriction of this particular balanced echo, not a universal accuracy requirement for rate-diverse sensing.

Second, choose rate a with probability p and b otherwise at the start of an interrogation. Retain the choice and use it throughout duration T. Define $\bar{\gamma} = pa + (1-p)b$, $g_2 = pa^2 + (1-p)b^2$ and $\sigma_\gamma^2 = p(1-p)(b-a)^2$. Pooling the full Fisher matrices before eliminating their *shared* nuisance gives

$$\mathcal{I}_p(T) = T^2 \frac{\sigma_\gamma^2 + \bar{\gamma}/T}{g_2 + \bar{\gamma}/T}, \qquad \lim_{T\to\infty} \frac{\mathcal{I}_p(T)}{T^2} = \frac{p(1-p)(b-a)^2}{pa^2 + (1-p)b^2}. \tag{4.14}$$

The maximizing probability is $p_* = b/(a+b)$ and the maximum is r^2. A fixed error in p changes this coefficient continuously; it does not incur the time-amplified penalty in (4.13). A fair choice $p = 1/2$ needs no numerical rate calibration in its design and retains the fraction $(a+b)^2/[2(a^2+b^2)] > 1/2$ of the optimal local coefficient. For example, $b = 3a$ gives $r^2 = 1/4$; the fair design retains four fifths of that coefficient.

Unknown numerical rates can be included as additional nuisance parameters in these likelihoods. With fixed durations and selection probabilities, the phase likelihood conditional on counts depends on (ω, ϕ), while the rate score comes from the count likelihood. Their cross-information is zero because the conditional phase score has mean zero. The displayed efficient information therefore survives elimination of the rate parameters. This fact is not free calibration: inference uses the recorded counts, and a precisely balanced echo still needs its design ratio. Nor does one labelled interrogation establish global estimation at an unknown frequency. Repeating it ν times costs νT.

There is a structural extension. For finitely many selectable pairs (s_j, γ_j), the optimal leading local coefficient is v_*^2, where

$$v_* = \max_{i,j} \frac{|s_i\gamma_j - s_j\gamma_i|}{\gamma_i + \gamma_j}. \tag{4.15}$$

Indeed the converse minimizes $\max_j |s_j - 2c\gamma_j|$. Requiring this maximum to be at most v says that the intervals $[(s_j - v)/(2\gamma_j), (s_j + v)/(2\gamma_j)]$ have a common intersection. Their endpoint inequalities give precisely (4.15). A recorded random choice of a maximizing pair, with probabilities proportional to the other member's rate, attains it by (4.4). If all ratios s_j/γ_j coincide, one nuisance path cancels every B_j, and the stronger bound $\mathcal{I}_\omega^*(T) \le T \max_j(s_j^2/\gamma_j)$ holds. Speeding up signal and noise in the same proportion therefore does not remove the obstruction. If each setting has an independently unknown direction, one can instead choose a separate cancelling nuisance slope for each setting; the same linear bound returns. A stable shared direction is essential.

5 Exact stopped sensing and a globally unknown frequency

Local information identifies a promising resource, but it does not resolve the multiple fringes of a long phase measurement. A different construction supplies a direction-independent channel on every completed run and makes the global precision theorem possible.

5.1 Use errors in pairs, and stop a signed clock

Again monitor parity, but apply no recovery after an error. Let $n(t)$ be the detected jump count and define the signed interrogation time

$$D(t) = \int_0^t (-1)^{n(u)}\,\mathrm{d}u. \tag{5.1}$$

It advances at unit speed in even parity and retreats at unit speed in odd parity. For example, a trajectory spending 0.9 time units even, 0.25 odd, and another 0.85 even has physical duration 2 but signed duration $0.9 - 0.25 + 0.85 = 1.5$. The negative interval subtracts signal phase rather than physical cost. Since $N_\phi Z = -ZN_\phi$, moving errors through the intervening signal rotations gives the exact trajectory unitary

$$U(t) = N_\phi^{n(t)} \exp[-i\omega D(t)Z/2]. \tag{5.2}$$

Use rate a when parity is even and b when it is odd. The positive state lasts longer on average, so the signed clock has positive long-time drift r. For a prescribed $d > 0$, stop at its first arrival at d:

$$\tau_d = \inf\{t \geq 0 : D(t) = d\}. \tag{5.3}$$

An upward arrival is in even parity, so the number of errors is even and $N_\phi^{n(\tau_d)} = I$. The completed logical operation is exactly

$$\rho_L \longmapsto e^{-i\omega d Z_L/2}\rho_L e^{i\omega d Z_L/2}. \tag{5.4}$$

It is correct for every logical input, frequency and direction. The stopping rule requires neither ϕ nor the numerical rates. Rates determine its cost, and rate knowledge enters the performance guarantees below. The stopping-time record is independent of ω and ϕ.

5.2 The cost of waiting is part of the result

The time needed to reach the prescribed signed duration is random. Its mean alone cannot enforce a deadline: rare runs might last much longer. We therefore describe its distribution through weighted averages of the form $\mathbb{E}e^{-q\tau_d}$. For $q > 0$, this gives less weight to longer runs. As q varies, these averages form the *Laplace transform* of the waiting time. Its first derivative at zero, with a minus sign, gives the mean; the second derivative of its logarithm gives the variance. Positive exponential weights $e^{\theta\tau_d}$ instead emphasize unusually long runs and will control deadline failures.

Write $\delta = (b - a)/2$. For a Laplace variable $q \geq 0$, with units of inverse time, the exact first-passage transform is

$$\mathbb{E}e^{-q\tau_d} = e^{-dk(q)}, \qquad k(q) = \sqrt{q^2 + (a + b)q + \delta^2} - \delta. \tag{5.5}$$

To see where it comes from, let $f_\pm(x)$ be the transform of the remaining time to d when the signed clock is at $x < d$ in even or odd parity. Conditioning on the next infinitesimal step gives

$$\begin{aligned} \partial_x f_+ + a(f_- - f_+) &= qf_+, \\ -\partial_x f_- + b(f_+ - f_-) &= qf_-. \end{aligned} \tag{5.6}$$

The form $f_\pm(x) = v_\pm e^{-k(d-x)}$ gives $k^2 + (b - a)k - q(q + a + b) = 0$. The outgoing boundary is $v_+ = 1$; the incoming value $f_-(d^-)$ is not assigned that same boundary condition. The root bounded towards $x = -\infty$ gives (5.5) for the initial state $x = 0$, even parity.

At $q = 0$ the transform equals one, establishing almost-sure completion, meaning completion with probability one. Differentiating its logarithm at zero gives

$$\mathbb{E}\tau_d = \frac{d}{r}, \qquad \mathrm{Var}(\tau_d) = \frac{8ab\,d}{(b-a)^3}. \tag{5.7}$$

The transform also has a finite positive exponential-moment domain:

$$\mathbb{E}e^{\theta\tau_d} = e^{-dk(-\theta)}, \qquad 0 < \theta < \frac{(\sqrt{b}-\sqrt{a})^2}{2}. \tag{5.8}$$

Finiteness can be established before continuation of the transform. For a real tilt z with inverse-time units, exponential moments of $D(t)$ are governed by the two-state matrix

$$G_z = \begin{pmatrix} z-a & a \\ b & -z-b \end{pmatrix}, \qquad \lambda(z) = -\frac{a+b}{2} + \sqrt{(z+\delta)^2 + ab}. \tag{5.9}$$

The quantity $\lambda(z)$ is its largest eigenvalue. At $z = -\delta < 0$ it equals $-(\sqrt{b}-\sqrt{a})^2/2$. For fixed rates, the corresponding matrix exponential bounds $\mathbb{E}e^{-\delta D(t)}$ by a constant times $e^{\lambda(-\delta)t}$. Since $\tau_d > t$ implies $D(t) < d$, the exponential Markov inequality bounds its probability by a constant times $e^{\delta d + \lambda(-\delta)t}$. Thus positive exponential moments of τ_d are finite throughout the domain in (5.8). Continuing (5.5) within that domain yields the stated formula.

The strict inequality $a < b$ matters. If $a = b = \gamma$, the transform becomes $\exp[-d\sqrt{q(q+2\gamma)}]$. Completion remains almost sure, but its mean is infinite: increasingly rare but increasingly long waits make the average diverge. An eventual noiseless output alone therefore supplies no finite-cost precision advantage.

Under a deadline T, retain both success and failure flags. Transfer completed logical outputs to protected memory; on failure assign a parameter-independent output. With $p_T = \Pr(\tau_d \le T)$, the experiment has local information $p_T d^2$. For instance, choose $t_c = 1/(a+b)$ and $d = r[T - t_c(T/t_c)^{2/3}]$ at large T. The mean duration falls short of T by the stated margin, while its variance is $O(T)$. The failure probability is $O(T^{-1/3})$ by the variance bound, and $p_T d^2/T^2 \to r^2$. Thus stopped sensing also attains the optimal local coefficient with every failed run charged. This margin is an explicit construction, not a claim about the best finite-time stopping design.

5.3 The same global risk criterion on both sides

Fix a closed frequency interval Ω of width $W > 0$, independent of T. For the permitted control menu $\mathcal{A}$, define

$$R_{\mathcal{A}}(T;\Omega) = \inf_{\mathcal{P},\widehat{\omega}} \sup_{\omega\in\Omega,\,\phi} \mathbb{E}^{\mathcal{P}}_{\omega,\phi}(\widehat{\omega}-\omega)^2. \tag{5.10}$$

The infimum includes adaptive protocols $\mathcal{P}$ and arbitrary estimators; no unbiasedness condition is imposed. Calibration, repetitions, waiting and failures all share the same deadline. Clipping an estimate to Ω cannot increase its squared error. In this model,

$$R_\gamma(T;\Omega) = \Theta(T^{-1}), \qquad R_{\{a,b\}}(T;\Omega) = \Theta(T^{-2}). \tag{5.11}$$

Here Θ means upper and lower bounds by fixed positive multiples for sufficiently large T; the constants carry the required units and depend on the fixed rates and interval. We next connect this statement to both a converse for biased estimators and an explicit construction.

The use of a prior below does not change the estimation task into one in which the frequency is drawn from a known distribution. If an estimator worked well at every allowed frequency and direction, it would also work well on average under any weighting of those possibilities. Exhibiting one difficult weighted average is therefore enough to lower-bound its worst-case error.

Choose an interior half-width $w > 0$ and center ω_c with $[\omega_c - w, \omega_c + w] \subseteq \Omega$. On a nuisance path use the prior

$$\pi_w(u) = \frac{1}{w}\cos^2\left(\frac{\pi u}{2w}\right), \qquad -w < u < w, \qquad I(\pi_w) = \frac{\pi^2}{w^2}. \tag{5.12}$$

This is a proof device inside the worst-case parameter family, not information supplied to the controller. For the joint score $S = \partial_u \log[p(x \mid u)\pi_w(u)]$, integration by parts yields $\mathbb{E}[(\widehat{\omega} - \omega_c - u)S] = 1$; the endpoint term vanishes because the prior density does. The likelihood score has conditional mean zero, so $\mathbb{E}S^2 = \mathbb{E}_{\pi_w} J_u + \pi^2/w^2$. The Cauchy–Schwarz inequality therefore gives prior-average squared error at least $1/(\mathbb{E}_{\pi_w} J_u + \pi^2/w^2)$, without an unbiasedness assumption. Worst-case risk is at least this average.

The single-rate cancelling path gives

$$R_\gamma(T;\Omega) \geq \frac{1}{T/\gamma + \pi^2/w^2}. \tag{5.13}$$

For two rates a supersolution of (4.10) is $B(T) = (rT + \sqrt{CT})^2$: its derivative exceeds $C + 2r\sqrt{B(T)}$ by $r\sqrt{CT} \geq 0$. Thus

$$R_{\{a,b\}}(T;\Omega) \geq \frac{1}{(rT + \sqrt{CT})^2 + \pi^2/w^2}. \tag{5.14}$$

In particular the asymptotic global constants obey

$$\liminf_{T\to\infty} T R_\gamma \geq \gamma, \qquad \liminf_{T\to\infty} T^2 R_{\{a,b\}} \geq \frac{1}{r^2}. \tag{5.15}$$

These are lower bounds, not claims that the locally optimal coefficients have globally attainable reciprocals.

For the matching single-rate upper scaling, compensate only the known interval center and repeat trials of fixed duration $\tau = \min\{1/\gamma, \pi/(2W)\}$. A trial with no error has probability $p_0 = e^{-\gamma\tau}$ and produces phase $(\omega - \omega_c)\tau$ independently of ϕ. Every trial costs τ, including those with errors. Among $M = \lfloor T/\tau \rfloor$ attempts, let K be the number with no error; K is binomial with parameters (M, p_0). On those useful trials measure the sine quadrature. Clip the sample mean to the possible sine range and invert it. Since $W\tau/2 \leq \pi/4$, the inverse has Lipschitz constant at most $\sqrt{2}/\tau$, and conditional risk is at most $2/(K\tau^2)$ for $K > 0$. Use the midpoint if $K = 0$. The identities

$$\mathbb{E}\frac{1}{K+1} = \frac{1 - (1-p_0)^{M+1}}{(M+1)p_0}, \qquad \frac{\mathbf{1}_{K>0}}{K} \leq \frac{2}{K+1} \tag{5.16}$$

then give the uniform bound

$$R_\gamma(T;\Omega) \leq \frac{4}{\tau^2(M+1)p_0} + \frac{W^2}{4}(1-p_0)^M = O(T^{-1}). \tag{5.17}$$

This rejection scheme establishes a rate, not an optimal constant. Its resource count uses attempted trials, so the successful records are not free.

5.4 Resolve phase ambiguity, then charge the whole random schedule

There are now two distinct ways an experiment can fail: the measurements can select the wrong phase turn, or the physical schedule can remain unfinished at the deadline. The next construction bounds both. Its short interrogations locate the turn; its long ones refine the position within it. The physical duration is charged for the complete sequence of attempts.

For two rates, use (5.4) to implement exact Ramsey experiments at effective durations $d_k = 2^k d_0$, $k = 0, \dots, K$, where $W d_0 \le \pi/2$. A known center rotation removes $\omega_c d_k$ from the readout. At each stage measure both sine and cosine, each on n_k fresh logical probes. All repetitions are physical experiments. Bounded-outcome concentration gives

$$\Pr(\text{stage } k \text{ is inaccurate}) \le 4e^{-n_k/128} \tag{5.18}$$

when inaccuracy means either quadrature mean differs by more than $1/8$. Otherwise the inferred phase error is less than $\pi/6$. Choose

$$n_k = \lceil 128[(K-k)\log 8 + \log 16] \rceil . \tag{5.19}$$

The brackets contain natural logarithms. Earlier stages receive more repetitions because an incorrect coarse fringe is more costly.

Choose at each stage the frequency representative nearest the preceding estimate. On consecutive accurate stages, a phase error below $\pi/6$ is small enough to select the correct representative when the duration doubles. The starting stage is unambiguous on the prescribed band. If the first inaccurate stage is k, the final frequency error is nevertheless $O(2^{-k}/d_0)$: each subsequent nearest-representative update moves by at most π/d_ℓ, and those movements have a bounded geometric sum. Final clipping reduces risk. The stage failure probabilities from (5.19) are at most $8^{-(K-k)}/4$. Therefore

$$\sup_{\omega,\phi} \mathbb{E}(\widehat{\omega} - \omega)^2 \le O(4^{-K}) + O\left(\sum_{k=0}^{K} 4^{-k} 8^{-(K-k)} \right) = O(4^{-K}), \tag{5.20}$$

where fixed powers of d_0 are contained in the constants. The total prescribed effective exposure is

$$S_K = 2 \sum_{k=0}^{K} n_k d_k = \Theta(2^K). \tag{5.21}$$

The factor two pays for both quadratures. The taper avoids an extra logarithmic factor in the total cost: long interrogations require fewer repetitions than short, coarse ones.

Effective exposure is not yet physical time. Replace each Ramsey operation in this schedule by a fresh stopped experiment. Its duration law is independent of phase, direction and readout. Multiplying their transforms in (5.5) gives, for the total physical duration,

$$\mathbb{E} e^{-q\tau_{\text{total}}} = e^{-S_K k(q)}. \tag{5.22}$$

Choose a fixed $0 < \alpha < 1$ and the largest K for which $S_K \le \alpha r T$. The sequence (5.21) grows geometrically, so this still gives $S_K = \Theta(T)$. For sufficiently small fixed $\theta > 0$, the exponential-moment bound gives

$$\Pr(\tau_{\text{total}} > T) \le \exp[-\theta T - S_K k(-\theta)] \le e^{-cT} \tag{5.23}$$

for some fixed $c > 0$ with inverse-time units. Indeed $-k(-\theta) = \theta/r + O(\theta^2)$, and the strict margin $\alpha < 1$ makes the leading exponent negative. Terminate the experiment at T and use a bounded fallback estimate if incomplete. This contributes at most $W^2 e^{-cT}$ to risk. On completed schedules, the quadrature statistics are unaffected by conditioning on duration, because completed channels are exact and duration records are parameter-independent. Equation (5.20) contributes $O(T^{-2})$.

This completes the global upper bound and hence (5.11). The argument pays for every repeated probe, every waiting period and every unfinished schedule. It uses a fixed frequency band, resolves its phase ambiguity explicitly and does not promote a local Fisher matrix into a global estimator. Its role beside the finite-collision theorem is to expose the same resource distinction through an exact continuous-time mechanism, with its stronger ideal monitoring assumption kept visible.

6 What changes when contacts resolve a collision?

The coupling comparison fixes when the controller can act: only at collision boundaries. That restriction has physical content. A bath qubit becomes correlated with the sensor during its collision, and a sensor pulse applied before that collision ends changes their subsequent joint evolution. An endpoint noise channel does not specify this response to an intervening pulse. We now keep just one coupling and change temporal access. This is a supporting comparison, with its own estimation proof; it is not a consequence of the boundary-only coupling theorem.

Fix $g, h > 0$ with $\chi = gh \in (0, \pi/4)$, and retain the same Hamiltonian, shared direction, protected memory and fixed compensation. The horizon is $T = nh$. There are at most $n-1$ nonterminal system–memory contacts in total, of which at most m occur strictly inside cells, where $0 \le m \le n-1$. These are hard bounds on every possible classical history. Boundary contacts consume the total allowance too. Initial preparation and readout exactly at nh are free; an earlier readout is a contact and does not shorten the charged horizon. The permitted controllers may adapt their classical contact times and instruments, but cannot access the bath or retune the Hamiltonian.

On a sufficiently small fixed band $\Omega = [\omega_0 - E, \omega_0 + E]$, the optimal worst-case frequency error obeys

$$R^*_{n,m}(\Omega) = \Theta_{\chi,Eh}\left(\frac{1}{h^2(n+m^2)}\right). \tag{6.1}$$

The constants are independent of n, m and the unknown direction. The factor h^{-2} supplies the units of squared frequency; χ and Eh are dimensionless. Thus m of order $\sqrt{n}$ marks the crossover in order, and m proportional to n permits inverse-square risk. This does not give an optimal numerical constant or the largest usable band.

The two terms describe two usable resources. Repeated ordinary one-cell measurements give the n term. Interior contacts permit a coherent interrogation whose useful length grows with m, giving the m^2 term. The construction below chooses the better of these designs; it need not combine their information in one experiment. If m grows much more slowly than $\sqrt{n}$, the interior contacts do not change the asymptotic order. If m is proportional to n, they do.

6.1 An exact temporal menu at one strength

There are two cell settings: leave a cell untouched, or apply one sensor Z_S pulse at its midpoint. This is an echo: the pulse reverses the noisy interaction, since $Z_S N_\phi Z_S = -N_\phi$, while leaving the signal term unchanged, since $Z_S Z_S Z_S = Z_S$. At zero residual frequency the second half exactly undoes the first half's noisy evolution. Away from zero, we must calculate the complete evolution rather than assume perfect cancellation. An additional known boundary operation removes the extra rotation introduced by the pulse itself; this is the frame correction mentioned below. Let $R = (g^2 + \epsilon^2/4)^{1/2}$ and $r = Rh$. The corrected echoed propagator, meaning the unitary for the complete cell, is

$$V = e^{-iH_- h/2} e^{-iH_+ h/2}, \qquad H_\pm = \frac{\epsilon}{2} Z_S \otimes I_E \pm g N_\phi \otimes X_E. \tag{6.2}$$

Multiplication gives the parity branches

$$\begin{aligned} K_{0,e} &= uI - ivZ_S, & K_{1,e} &= -ixN'_\phi, \\ u &= \cos r + \frac{g^2}{R^2}(1 - \cos r), & v &= \frac{\epsilon}{2R}\sin r, \\ x &= \frac{\epsilon g}{2R^2}(1 - \cos r), & N'_\phi &= \partial_\phi N_\phi. \end{aligned} \tag{6.3}$$

Here u, v, x are dimensionless real numbers and $u^2 + v^2 + x^2 = 1$. On an odd result, an additional known Z_S within that same boundary instrument uses $Z_S N'_\phi = -iN_\phi$ to make the flip operator proportional to N_ϕ. The frame correction, parity measurement, conditional correction and next preparation are components of one instrument at one time; the midpoint pulse is a separate contact.

Both settings consequently have the same unknown normalized flip, while their no-flip phases differ. Denote the untouched setting by p and the echoed setting by e. Their transition probabilities and phase derivatives at compensation are

$$p_e(0) = 0, \quad p_p(0) = \sin^2 \chi, \qquad \theta'_e(0) = A := \frac{\sin \chi}{g}, \quad \theta'_p(0) = d_p := \frac{\tan \chi}{g}. \tag{6.4}$$

Primes on scalar cell functions mean differentiation with respect to the residual frequency ϵ; N'_ϕ retains its explicit meaning $\partial_\phi N_\phi$. Thus A and d_p have units of time. The zero value of p_e holds at compensation only. Away from it, $p_e = x^2$ is usually positive.

Use an echoed cell after an even parity result and a plain cell after an odd result. Every record ending even again has exact cancellation of ϕ and a known signed sum of the no-flip phases. To verify usable sensitivity, freeze the two phase rewards at A and d_p. Their stationary signed mean is

$$\mu^0(\epsilon) = \frac{p_p(1 - p_e)A - p_e(1 - p_p)d_p}{p_e + p_p}, \qquad \mu^0(0) = A > 0. \tag{6.5}$$

Continuity supplies one fixed band on which $\mu^0 \geq 3A/4$, $p_e < p_p < 1/2$, and each actual derivative differs from its frozen value by at most $A/4$. Also $p_e + p_p$ stays bounded below, uniformly controlling how rapidly dependence between well-separated parity outcomes decays. The record gate already developed for the coupling menu then accepts at least one quarter of sufficiently long blocks and gives, on every accepted record of length L,

$$AL/4 \leq \Phi'_{\mathcal{R}}(v) \leq \beta L \quad (|v| \leq E) \tag{6.6}$$

for a fixed finite time constant β. A positive lower bound on p_e is unnecessary: at compensation the process never leaves its initial even sector. Plain one-cell trials provide the paid initial localization. The same conditional inversion and multiscale schedule therefore give risk $C_1/(h^2Q^2)$ with at most Q used cells, including calibration, repetitions and rejected records.

For $n \geq 3$ and $m \geq 1$, choose

$$Q = \min\left\{m, \left\lfloor \frac{n-1}{2} \right\rfloor\right\}. \tag{6.7}$$

The whole estimator uses at most Q midpoint pulses and Q boundary instruments. Its last readout is counted because it occurs before nh. Thus $2Q \leq n - 1$ and $Q \leq m$. Store the resulting classical estimate through the remaining charged cells. For example, $n = 101, m = 20$ permits $Q = 20$, uses at most 40 contacts, and still pays for all 101 cells. It does not receive another 101 cells for calibration.

Since $Q \geq m/3$, this construction has risk at most $9C_1/(h^2m^2)$. A separate design uses all n cells for plain-cell calibration and has risk at most $C_0/(h^2n)$ with $n - 1$ boundary contacts. Choose the better design from the known budgets. The elementary inequality

$$\min\left\{\frac{C_0}{n}, \frac{9C_1}{m^2}\right\} \leq \frac{C_0 + 9C_1}{n + m^2} \tag{6.8}$$

proves the upper order in (6.1); the plain design covers $m = 0$ and the small values of n.

6.2 Why adaptivity does not evade the contact bound

The proof uses the geometry of small changes in a quantum state. Represent the response to a small parameter change by a vector. Contributions from untouched cells are perpendicular in this mathematical state space, so their squared lengths add, as in Pythagoras' theorem. Contributions from contacted cells may instead align, so their lengths can add. This is the origin of the two scales $\sqrt{n}$ and m in the information bound.

Use the plain-cell nuisance curve $\phi' = q_p\theta'_p/(2p_p)$ from the fixed-coupling converse. It is a mathematical subfamily used to lower-bound worst-case error, not information supplied to the controller. Put

$$p_{\min} = \chi^2\left(\frac{\sin r_*}{r_*}\right)^2, \quad K = \sup_{|\epsilon|\le E}|\phi'(\epsilon)|, \quad a_0 = \frac{h}{2\sqrt{p_{\min}}}, \quad b_0 = h\sqrt{\frac{1}{4}+g^2K^2}, \tag{6.9}$$

where $r_* = (\chi^2 + (Eh/2)^2)^{1/2} < \pi/4$ bounds Rh on the band. Both a_0, b_0 have units of time. A cell with no interior contact has zero derivative overlap and derivative norm at most a_0 in the chosen purification. A cell with interior contacts instead has derivative norm at most b_0, because along the same curve

$$\dot{H} = \tfrac{1}{2}Z_S \otimes I_E + g\phi' N'_\phi \otimes X_E, \qquad \|\dot{H}\| = \sqrt{\tfrac{1}{4} + g^2(\phi')^2}. \tag{6.10}$$

The norm is the operator norm, the largest vector-stretching factor. The equality uses anticommutation. Integrating the unitary derivative over the cell's physical duration h gives the bound even with intermediate adaptive instruments.

The hard history constraint is essential to the rest of the argument. Dilate the instruments—represent them as unitary operations on a larger state space—keeping a mathematical archive of which cells contained an interior contact. This archive is not a new observation available to the controller. Derivative contributions from untouched cells are mutually orthogonal, so their total norm is at most $a_0\sqrt{n}$. For contacted cells, let D_j be the vector contribution from cell j. The projector Q_z selects the part associated with one archived activity history z, where $z_j = 1$ marks a contacted cell. Every history contains at most m active cells. Cauchy–Schwarz within each history gives

$$\left\|\sum_j D_j\right\|^2 = \sum_z \left\|\sum_{j:z_j=1} Q_z D_j\right\|^2 \le m\sum_j \|D_j\|^2 \le m^2 b_0^2. \tag{6.11}$$

The last step charges the expected number of active cells by the hard bound m. Merely summing square roots of separate activity probabilities would lose this dependence. The entrance activity flags are legitimate because operations on protected memory alone commute with the cell evolution; they can be moved before it until the first actual system contact.

Consequently the complete accessible information along the curve obeys

$$J_\epsilon \le 4(a_0\sqrt{n} + b_0 m)^2 \le 4(a_0^2 + b_0^2)(n + m^2). \tag{6.12}$$

A fixed cosine-squared prior of half-width E yields the global bound

$$R^*_{n,m}(\Omega) \ge \frac{1}{4(a_0^2 + b_0^2)(n + m^2) + \pi^2/E^2}. \tag{6.13}$$

This applies to biased estimators and all retained branches. Clipping and finite quantization transfer the bounded-loss statement to the stated operational limits; continuity of Fisher information is not assumed. The converse may grant extra boundary operations as a relaxation, but never relaxes the hard interior budget. Together with the construction it proves (6.1).

7 Timing knowledge changes the experiment

A pulse being displaced by a known amount and a pulse having an unobserved random displacement are different statistical experiments, even at the same error magnitude. A simple timing example makes the distinction concrete. Divide a cell into 100 equal clock ticks, so that its midpoint is tick 50:

Timing information	What the controller knows
Known fixed offset	Every pulse arrives at tick 55, and this fact is supplied.
Unknown fixed offset	Every pulse has the same displacement, but its value must be learned. This calibration problem is not solved here.
Hidden random jitter	Each pulse independently arrives at tick 45 or 55; the probabilities are known, but the realized choice is never reported.

The ticks are only an illustration, not an additional measurement available to the controller. To isolate the timing question, keep one coupling and permit only plain cells or cells with one Z_S pulse. A displaced pulse occurs at $h/2+\delta$, with $|\delta| < h/2$; there is no further interior contact in that cell. Its corrected propagator is

$$V_\delta = e^{-iH_-(h/2-\delta)} e^{-iH_+(h/2+\delta)}. \tag{7.1}$$

Its known pulse frame is included in the counted endpoint instrument. The exact branch coefficients are

$$\begin{aligned} D &= \cos(2R\delta) - \cos(Rh), & u &= \cos(Rh) + \frac{g^2}{R^2} D, \\ v &= \frac{\epsilon}{2R} \sin(Rh), & w &= \frac{g}{R} \sin(2R\delta), \\ x &= \frac{\epsilon g}{2R^2} D, \end{aligned} \tag{7.2}$$

with

$$K_0 = uI - ivZ_S, \qquad K_1 = -i(wN_\phi + xN'_\phi), \qquad u^2+v^2+w^2+x^2 = 1. \tag{7.3}$$

Each branch is proportional to a unitary because N_ϕ and N'_ϕ anticommute. The odd branch has a frequency-dependent axis, but for a supplied known δ that dependence is known.

7.1 A supplied fixed displacement preserves a usable phase

Fix $0 < |\delta| < h/2$ throughout the experiment and suppose its value is part of the device specification. Near compensation, w has fixed nonzero sign. Absorb that sign into an irrelevant scalar phase and define

$$\theta_e = 2\arctan(v/u), \qquad \zeta_e = \arctan(x/w). \tag{7.4}$$

The normalized odd branch is then $N_{\phi+\zeta_e}$ up to a scalar phase. For a plain cell, $\zeta_p = 0$. Using pulsed cells in the even sector and plain cells in the odd sector gives the exact final-even phase

$$\Phi_{\mathcal{R}}(\epsilon) = \sum_i \sigma_{i-1} \left[\mathbf{1}_{\text{stay}} \theta_{j_i}(\epsilon) - 2\mathbf{1}_{\text{flip}} \zeta_{j_i}(\epsilon) \right]. \tag{7.5}$$

The extra flip-axis terms must be retained. They are known functions of frequency, while the common unknown angle still cancels in pairs.

For a direct sensitivity check, set $z = 2g\delta$, so $0 < |z| < \chi$. At zero residual frequency,

$$\begin{aligned} p_e &= \sin^2 z, & p_p &= \sin^2 \chi, \\ d_e &= \theta_e'(0) = \frac{\sin \chi}{g \cos z}, & z_e &= \zeta_e'(0) = \frac{\cos z - \cos \chi}{2g \sin z}. \end{aligned} \tag{7.6}$$

Put $f_e = (1 - p_e)d_e - 2p_e z_e$ and $f_p = (1 - p_p)\tan \chi / g$. The exact contrast is

$$\frac{f_e}{p_e} - \frac{f_p}{p_p} = \frac{(\sin \chi - \sin z)\sin(\chi + z)}{g \sin \chi \, \sin^2 z} > 0. \tag{7.7}$$

All factors determining the sign are positive for $-\chi < z < \chi$ except at the excluded zero. Thus the stationary derivative drift $(p_p f_e - p_e f_p)/(p_e + p_p)$ is strictly positive; denote it by μ_δ. The record score must now include the new flip contributions:

$$D_L^0 = \sum_{i=1}^{L} \sigma_{i-1} \left[\mathbf{1}_{\text{stay}} \theta_{j_i}'(0) - 2\mathbf{1}_{\text{flip}} \zeta_{j_i}'(0) \right]. \tag{7.8}$$

It is computed from the observed record and the supplied displacement. Its stationary mean is μ_δ. Accept even-ending records with $D_L^0 \geq \mu_\delta L/2$. All these one-cell rewards are bounded for the fixed nonzero displacement. The same two-state mean and variance argument therefore gives a positive acceptance probability for sufficiently long blocks. Continuity on a sufficiently small fixed band keeps each derivative close to its frozen value, certifying a whole-band positive phase slope. The same conditional estimator then gives inverse-square risk. The band and constants may depend on the supplied displacement. Using (6.7) charges at most Q interior and Q boundary contacts, so this yields the quadratic global order when $m = \Theta(n)$. The ideal $\delta = 0$ case is already covered by the midpoint construction.

This argument does not need to retime the pulse. If calibrated retiming is allowed, shifting the command by $-\delta$ restores the midpoint instead. Neither statement supplies a method for learning an unknown δ. Such learning would need its own identifiable likelihood, accuracy analysis and charged calibration cost.

7.2 Hidden independent jitter mixes the odd branch

Now let each pulsed cell independently have $\delta = +d$ or $-d$ with equal probability, where the amplitude $0 < d < h/2$ is known but its realized signs are never reported. The signs are independent of the unknown parameters, prior records and controls. At cell entrance the controller can choose plain or jittered, but has no further pulse-position menu, extra interior pulse, coupling choice or physical compensation change.

Only w in (7.2) changes sign. Averaging the two physical channels gives three Kraus operators, evaluated at $\delta = d$:

$$L_0 = uI - ivZ_S, \qquad L_1 = -iwN_\phi, \qquad L_2 = -ixN_\phi'. \tag{7.9}$$

Parity distinguishes L_0 from the combined odd branch. It does not reveal which odd operator acted. A putative record identifying L_1 or L_2 would supply information absent from this experiment.

For input state ρ, the normalized state after an odd result is

$$\rho_{\text{odd}} = \frac{w^2 N_\phi \rho N_\phi + x^2 N_\phi' \rho N_\phi'}{w^2 + x^2}. \tag{7.10}$$

Two alternatives remain unresolved. In general this is a mixture, not one known unitary rotation whose phase can be calculated from the record. That explains why the earlier estimator does not directly apply. A separate converse is still needed to rule out other permitted strategies.

For every fixed $d > 0$, this restricted menu has

$$R^*_{n,m}(d;\Omega) = \Theta(n^{-1}), \qquad 0 \le m \le n-1, \tag{7.11}$$

on a fixed identifiable band, uniformly over the shared direction. Constants may depend on g, h, E, d. The upper bound simply uses plain-cell calibration; it fits every m and costs all nh. The limitation requires a new converse, because good local sensitivity at compensation still survives.

Choose a fixed compact residual-frequency interval strictly inside $(0, E)$. Use the plain-cell nuisance curve $\phi' = k(\epsilon)$ from the earlier converse. For the jittered cell write $p = w^2 + x^2$ and $a = uv' - vu'$. Along this curve,

$$i\sum_j L_j^\dagger \dot{L}_j = (a - pk)Z_S, \qquad L_1^\dagger L_2 = iwxZ_S. \tag{7.12}$$

On the chosen positive interval $w, x > 0$. The same accessible channel has several equivalent descriptions using inaccessible environmental labels. Changing that description leaves every accessible measurement probability unchanged. We choose one convenient description to prove a bound; this choice is called an environment gauge and grants no control over the physical bath. Its smooth unitary change of basis has a Hermitian derivative generator G, a 3×3 matrix acting on the three Kraus labels, with entries

$$G_{12} = i\eta_G, \qquad G_{21} = -i\eta_G, \qquad \eta_G = \frac{a - pk}{2wx}, \tag{7.13}$$

and all other entries zero. The entries of G have units of time because the derivative is with respect to frequency. In the derivative convention $\widetilde{\dot{L}} = \dot{L} - iGL$, L denotes the column of three Kraus operators. This choice cancels the overlap exactly:

$$\begin{aligned} i\sum_j L_j^\dagger \widetilde{\dot{L}}_j &= 0, \\ \sum_j \widetilde{\dot{L}}_j^\dagger \widetilde{\dot{L}}_j &= [(u')^2 + (v')^2 + (w')^2 + (x')^2 \\ &\qquad + (wk + \eta_G x)^2 + (xk + \eta_G w)^2]I. \end{aligned} \tag{7.14}$$

For completeness the unitary basis change exists by solving $U_E' = -iU_E G$ on that interval. It is an analytical freedom in a purification, not bath access granted to the experimenter. The scalar in (7.14), and the corresponding plain-cell scalar, have one finite bound A_* on this compact interval.

Both selectable cells now have zero overlap on the same nuisance curve. Successive derivative contributions are therefore orthogonal even with adaptive setting choices, arbitrary protected memory and all branches retained. The complete information is at most $4nA_*$. A cosine-squared prior of fixed half-width ℓ contained in the positive interval gives

$$R^*_{n,m}(d;\Omega) \ge \frac{1}{4nA_* + \pi^2/\ell^2}. \tag{7.15}$$

The prior is deliberately away from compensation, where $x = 0$ and the chosen gauge would be singular. A worst-case risk over the entire band is at least this fixed-prior average. Thus the singularity at zero does not invalidate the global limitation, and the proof makes no pointwise risk claim at every frequency. The bounded-loss limit argument again extends the result to the allowed operational limits.

7.3 Local information and a necessary accuracy scale

At compensation the third Kraus operator in (7.9) vanishes. Near zero it has the form $L_2(\epsilon) = \epsilon B + O(\epsilon^2)$ for a fixed operator B with units of time. Its contribution to the state is consequently $\epsilon^2 B\rho B^\dagger + O(\epsilon^3)$: it does not affect the first derivative exactly at zero, although it matters away from zero. The first-order instrument therefore still permits a positive phase drift. Put $z_d = 2gd$, $A = \sin\chi/g$, $p_e = \sin^2 z_d$ and $p_p = \sin^2\chi$. The even-jittered/odd-plain protocol has local signed-phase drift per physical time

$$v_d = \frac{A[\sin^2\chi\cos z_d - \sin^2 z_d\cos\chi]}{h(p_p + p_e)} > 0. \tag{7.16}$$

Positivity follows from the strict increase of $\sin^2 z/\cos z$ on $(0, \pi/4)$ and $0 < z_d < \chi$. Here is the finishing operation used for the local claim. For a sufficiently large allocation of N cells, put $q_p = 1 - \sin^2\chi < 1$ and reserve $k_N = \lceil 3\log N/(-\log q_p)\rceil$ of those cells. Run the parity policy for the first $N - k_N$ cells. If parity is even, read out immediately; if it is odd, use plain cells until it first becomes even or the allocation ends. At an even endpoint measure Y_L, retain the record and store the result. An unfinished trial retains a failure flag. The return failure probability at compensation is at most $q_p^{k_N} \le N^{-3}$. The reserved number is only $O(\log N)$, so it does not change the leading accumulated phase derivative. The complete record with this readout has pointwise classical score information $v_d^2(Nh)^2 + o(N^2)$ for N used cells. Allocating $N = \min\{m, \lfloor(n-1)/2\rfloor\}$ pays the early readout and fits the original contact budget. If $m = \Theta(n)$, quadratic local information and the global inverse-linear law (7.11) therefore coexist. A particularly sensitive readout at one special frequency need not work uniformly well across an interval. Here the local statement concerns the classical outcome probabilities of a specified readout, not an assumption that quantum Fisher information remains continuous when a noise branch vanishes.

The same away-from-zero gauge supplies a necessary condition when jitter shrinks with the budget. Fix $d_{\max} < h/2$ and put $\xi = d/h$. Uniformly for $0 < d \le d_{\max}$ on the fixed prior interval, w is bounded below by a constant times ξ, while x stays bounded below by a positive constant. The gauged derivative cost is consequently at most Ch^2/ξ^2 per pulsed cell and Ch^2 per plain cell. Charging at most m pulsed cells gives, with a fixed constant C,

$$R^*_{n,m}(d;\Omega) \ge \max\left\{\frac{1}{n^2h^2 + \pi^2/\ell^2},\ \frac{1}{Ch^2(n + m/\xi^2) + \pi^2/\ell^2}\right\}. \tag{7.17}$$

The first term is the independent signal-generator limitation. For $m = \Theta(n)$, the second denominator can grow quadratically only if $1/\xi^2$ grows at least linearly. Risk of order n^{-2} would therefore require

$$d = O(h/\sqrt{n}). \tag{7.18}$$

The reference scale $h/\sqrt{n}$ halves when n quadruples. This illustrates the necessary asymptotic order, not an exact finite-budget tolerance. Meeting that scale alone does not establish a working estimator: necessity rules out inadequate accuracy, whereas sufficiency would require a construction that succeeds. This is not an optimized joint law in n, m, d, and does not cover recorded timing errors, arbitrary pulse sequences, finite-duration controls or additional coupling settings.

8 Which idealizations carry the conclusion?

The shared transverse direction is essential. Two applications of the same error cancel, and the same unknown angle constrains the nuisance curve in both settings. If a continuous-time

setting j has an independent unknown angle ϕ_j, signal coefficient s_j and positive rate γ_j, the path $\phi'_j = s_j/(2\gamma_j)$ cancels the coherent contribution separately in every setting. It gives the all-strategy ceiling

$$\mathcal{I}^*_\omega(T) \le T \max_j \frac{s_j^2}{\gamma_j}. \tag{8.1}$$

Known angular offsets between settings are not independently unknown axes. Likewise a rate knob must have its stated signal response. If setting j adds an unconstrained unknown frequency offset δ_j, then $(s_j\omega + \delta_j)Z/2$ is invariant under $\omega \mapsto \omega + u$ and $\delta_j \mapsto \delta_j - s_j u$. The target is then unidentifiable without an additional constraint.

An uncorrectable parallel noise component gives a second sharp boundary. In the continuous model add the independent unobserved operator $L_z = \sqrt{\kappa}Z$, with known $\kappa > 0$. Its contribution is $\kappa(Z\rho Z - \rho)$, so off-diagonal coherence decays as $e^{-2\kappa T}$. Parity does not identify these errors. The signal lies in the same operator direction as this noise, and a channel gauge coupling the identity to L_z with coefficient $-1/(4\sqrt{\kappa})$ gives

$$\mathcal{I}^*_\omega(T) \le \frac{T}{4\kappa}. \tag{8.2}$$

This familiar channel-bound mechanism applies even if the transverse axis is known. Hence the strict quadratic asymptotic claim is not protection against arbitrary added noise.

A finite advantage can nevertheless remain. For the prescribed fixed-duration random-rate readout with a recorded uniform equatorial measurement angle, parallel dephasing multiplies every entry of its frequency–direction Fisher matrix by

$$w(T) = 1 - \sqrt{1 - e^{-4\kappa T}}. \tag{8.3}$$

The nuisance-adjusted information is multiplied by the same factor. For $b = 3a$, lower-rate probability $3/4$, and $T = 10/a$, the ideal information is $200/(7a^2)$. At $\kappa/a = 0.01$ it becomes approximately $12.16635/a^2$, still above the universal ideal single-rate-a bound $T/a = 10/a^2$. This is a finite local-information comparison for a specified readout, not a global risk ratio or a general hardware error tolerance. The random physical duration of a stopped interrogation would require its own averaging; this fixed-duration formula cannot be transplanted to it.

Finite-rate monitoring also needs its own scope. In the continuous Markov model, parity checks separated by a fixed interval Δ miss pairs of jumps. Writing $p_\gamma = (1 - e^{-2\gamma\Delta})/2$, the even/odd rate policy has mean signed signal rate

$$v_\Delta = \frac{p_a p_b}{\Delta(p_a + p_b)} \left(\frac{1}{a} - \frac{1}{b}\right) > 0. \tag{8.4}$$

At compensation, a retained-even logical Y_L readout gives local information $v_\Delta^2 T^2 + o(T^2)$. Use the same kind of logarithmic finishing window within the allocated intervals, retaining the high rate in the odd sector until an even boundary result, and keep deadline failures as flags. Thus both the finishing time and failures are charged. Away from compensation, unobserved residence times form a mixture of phases. This local finite-cadence result does not prove the continuous-monitoring global risk theorem at finite cadence. The microscopic global theorem avoids this inference by analyzing its own exact recorded instrument.

Finally, the charged resource is exposure time under specified ideal control. Memory is protected, instruments and pulses are instantaneous, the bath cells are prepared as stated, and the shared axis is stable throughout the run. Control work, bath preparation expense, pulse duration, readout errors and unknown timing-offset calibration are not assigned free solutions. Exact conditional identities and analytic bounds establish the mathematical results in this resource model; finite numerical checks verify selected identities and examples. Neither those checks nor a completed exposition constitutes an independent experimental or expert certification.

9 What the comparison establishes

The question was how accurately to measure an initially unknown frequency when the same unknown transverse error keeps acting on the sensor. The quantity being optimized is mean-square error, including every experimental outcome, at the hardest frequency and direction in the promised set. The resource is the full physical duration nh, with the stated restrictions on when the controller can act. The frequency interval, collision duration, couplings and physical compensation are fixed as n grows.

With one positive coupling, a change in frequency can be partly hidden by a change in the unknown error direction. The proof chooses a whole curve of such difficult parameter pairs and shows that no allowed boundary-control strategy can distinguish them faster than a linear information law permits. A guarantee at every parameter pair must also hold on average over that curve, which turns the information limit into an inverse-linear lower bound on error. Repeated, fully charged one-cell calibration reaches that order. This is a limitation of all allowed strategies, not just a failure of one chosen recovery procedure.

With two distinct positive couplings, the construction uses the weaker one in the even sector and the stronger one in the odd sector. The unknown direction cancels on every even-ending record. Some such records have little useful phase left, so a computable rule accepts only those with a certified response throughout the frequency band. The retained path supplies a known prediction curve for every candidate frequency; it need not reveal the true frequency on its own.

The estimator then pays for a coarse estimate and uses progressively longer blocks to narrow the candidate interval. It compares measured outcomes with the curves from the paths actually observed. Early mistakes receive greater protection because they would cause larger errors; all rejected blocks still consume their full time. The resulting worst-case mean-square error has order $1/n^2$. A separate bound on the total signal response rules out a better order. Thus both sides of the main comparison have a matching construction and converse. Updating the estimate never retunes the physical compensation.

The continuous-time model reaches the same distinction under its own, stronger assumption of ideal continuous error monitoring. Its first explanation is statistical: two noise rates expose different combinations of the same unknown frequency and direction. Its second explanation pairs errors and stops when the signed signal clock reaches a chosen value. This makes an exact sensing operation, but the physical waiting time must still be charged. The finite-cell theorem does not depend on approximating its hardware by that continuous model. Sharp local information coefficients are not asserted to be optimal constants in the global estimation error.

Access during a collision is another resource. At one fixed coupling, the companion contact law combines an ordinary n scale with a coherent m^2 scale, where m bounds the allowed interior contacts. Both its construction and its limitation use the full contact budget. The same recorded-phase estimator is useful there, but the physical operation enabling it is different.

Finally, timing knowledge changes what the record tells us. A supplied fixed displacement can be included when calculating each path's phase. Hidden independent jitter can instead leave two unresolved operations after the same observed parity result. For the stated plain/one-pulse menu, a global lower bound then restores inverse-linear error at any fixed nonzero jitter amplitude. High sensitivity at the special compensation point does not contradict poor worst-case precision over a whole interval. The shrinking-jitter accuracy condition is necessary only: meeting it has not been shown sufficient.

The stable shared axis, protected memory, ideal permitted instruments and fixed band remain essential. Within that model, controlling noise strength changes the attainable order of global estimation error, with every trial and failure charged.