

CompTIA A+ Core 1 Playbook

IT Labs

Prepared by Garrick White

3.3.7 Install Triple Channel Memory

You work at a computer repair store. You are building a new computer for a customer. The computer has an Intel i7-960 processor, and you need to install memory in the computer.

In this lab, your task is to complete the following:

- Install a total of three memory modules.
- Configure the memory to run in triple channel mode.
For triple channel operation, memory should be installed in matched sets (same capacity and same speed).
- Select the largest and fastest memory supported by the motherboard.
- Install the memory according to the motherboard recommendations.
- After you install the memory, boot into the BIOS setup (press **F2**) and verify that the memory is running in triple channel mode.

Complete this lab as follows:

1. Identify the supported memory and installation procedures.
 1. Above the computer, switch to the motherboard view.
 2. Select the **motherboard**.
 3. From the Selected Item pane, select the **Item Details** button.
 4. Read the **documentation** to identify supported memory and installation procedures.

The motherboard supports modules up to 1600 MHz for one module per channel.
Installing faster modules would not make the memory operate above 1600 MHz.
 5. Close the documentation.
2. Install memory
 1. Under Inventory, expand **Memory Modules**.
 2. Drag a **DDR3 2 GB, DDR3 1600** memory module to the memory slot on the motherboard.

Based on the motherboard documentation, when using 1600 MHz modules, you should only install three modules, and you should use slots DIMM_A1, DIMM_B1, and DIMM_C1 (the three blue slots).
 3. Repeat step 2b to install the additional two memory modules.
3. Verify that the memory runs in triple channel mode.
 1. Switch to the front view of the computer.
 2. Select the **power** button on the computer and then press **F2** to enter the BIOS as the BIOS loads.
 3. Under System Information, verify that all the **memory** is recognized, that it runs at the correct speed, and that it is operating in triple channel mode.

