

FlipperHTTP LED Status Reference

ESP32-S3 / ESP32-C5 only • All other boards: single green LED (blink/on/off only)

LED	Behaviour	Meaning
	R → G → B → white flash, then 3× white blinks	Boot — ESP32 starting up <i>Always plays; ignores LED on/off setting</i>
	Steady on	Connecting to network (during WiFi join attempt)
	Steady on	Connected and ready (persists until next event)
	Steady on (blocks during scan)	WiFi scan in progress
	300 ms on → off	Scan complete — networks found
	600 ms on → off	Scan complete — no networks found
	400 ms on → off	Disconnected (link dropped)
	1 s on → off	Connection attempt failed

Timing key

-  Steady = LED held on until state changes (no timeout)
-  Timed = LED on for N ms, then automatically off
-  Green steady = idle/ready state after successful connect

Non-NeoPixel boards (WROOM, WROVER, C6, C3, Pico W, BW16 ...)
Only blink() and on()/off() are active. Status colours above do not apply.