Nama: Abdul Rozak A
NIM: 221344033
Kelas: 2B – TNK

UTS-LAB

Nomor 1

program

```
TITLE UTS LAB-1
.MODEL SMALL
.STACK 100H
.DATA
DAT DB 0,0,0,0,0,0,0,0,0,0,0,0,0,0,0,0
HASIL DW 0

.CODE

MAIN PROC
     MOV AX,@DATA
     MOV DS,AX

     MOV SI,0
     MOV DX,0

LUP: MOV [DAT+SI],DL

     INC SI
     ADD DL,5H
     MOV [DAT+SI],DL

     INC SI
     ADD DL,0AH

     CMP SI,10H
     JNZ LUP

      MOV CX,0
      MOV SI,0
LUUP: ADD CL,[DAT+SI]
      ADC CH,0
      INC SI
      CMP SI,10H
      JNZ LUUP


      MOV [HASIL],CX

     MOV AH,4CH
     INT 21H
MAIN ENDP
END MAIN
```

output



input ada di variable DAT



hasil ada di register CX

Nomor 2

Program

```
TITLE UTS LAB-2-COUNTER
.MODEL SMALL
.STACK 100H
.DATA
.CODE

MAIN PROC
     MOV AX,@DATA
     MOV DS,AX

     MOV DX,0
     MOV BX,0
     ADD CX,0
     JZ  SKIP
     MOV DX,CX

LUP: ADD BX,1H
     MOV AL,BL
     ADD AL,0
     DAA
     ADC BH,0
     MOV BL,AL
     MOV AL,BH
     ADD AL,0
     DAA
     MOV BH,AL

     SBB DX,1
         MOV AL,DL
         AND AL,0FH
         CMP AL,08H
         JB  SKIP0
         SUB DL,08H

SKIP0:   MOV AL,DL
         AND AL,0F0H
         CMP AL,80H
         JB  SKIP1
         SUB DL,80H

SKIP1:   MOV AL,DH
         AND AL,0FH
         CMP AL,08H
         JB  SKIP2
         SUB DH,08H


SKIP2:   MOV AL,DH
         AND AL,0F0H
         CMP AL,80H
         JB  SKIP3
         SUB DH,80H
SKIP3:
     CMP DX,0
     JNZ LUP

SKIP:MOV CX,DX

     MOV AH,4CH
     INT 21H
     MAIN ENDP
END MAIN
```

output



CX menyimpan input oktal 4 digit



BX menyimpan output desimal