



MIDDLE EAST TECHNICAL UNIVERSITY

ELECTRICAL AND ELECTRONICS ENGINEERING
DEPARTMENT

EE400 SUMMER PRACTICE REPORT

Student Name : Hamza Solmaz

Student ID: 2516904

Company Name: ASELSAN

Company Division: MEOS – Digital Design

Date: 07.07.2025 – 04.08.2025

Mentor Engineer: Ömer Bağcıgil

E-mail: obagcigil@aselsan.com

Phone Number: 0534 418 52 80

TABLE OF CONTENTS

1. DESCRIPTION OF THE COMPANY	4
1.1. General Information.....	4
1.2. Location	4
1.3. Fields of Activity	4
1.4. Organization and Workforce.....	4
1.5. My Division and Team	4
2. A BRIEF HISTORY OF THE COMPANY	5
3. INTRODUCTION	6
4. DIGITAL DESIGN PROJECT.....	7
4.1. MSP430.....	8
4.2. Communication Protocols.....	9
4.2.1. UART.....	9
4.2.2. I ² C	9
4.2.3. SPI.....	10
4.3. Digital Design Rules And Considerations	10
4.3.1. Datasheet.....	10
4.3.2. Voltage levels.....	10
4.3.3. Decoupling capacitors.....	11
4.3.4. Pull-up/ pull-down	11
4.3.5. Transmission lines	11
5. DIGITAL I/O VOLTAGE LEVEL STANDARDS	12
5.1. TTL	12
5.2. CMOS	13
5.3. LVDS	14

5.4. LVPECL	15
5.5. Others.....	16
5.5.1. HCSL (High-Speed Current Steering Logic).....	16
5.5.2. SSTL (Stub Series Terminated Logic).....	16
5.5.3. HSTL (High-Speed Transceiver Logic).....	16
5.6. Communication Between Different Standards	17
6. CONCLUSION.....	18
7. REFERENCES	19

1. DESCRIPTION OF THE COMPANY

1.1. General Information

ASELSAN is one of the largest defense electronics and technology companies in Turkey. It mainly operates in the fields of research and development, design, manufacturing, integration, and testing of advanced electronic systems. The company develops products and solutions for both military and civilian applications. Its customers include the Turkish Armed Forces, government institutions, and international clients.

1.2. Location

Address: Balıkhisar Mahallesi Koca Seyit Onbaşı Caddesi No: 1 Akyurt-Ankara P.K. 20 Akyurt, 06750 Ankara, Türkiye

Phone: +90 (312) 592 10 00

Website: <https://www.aselsan.com>

1.3. Fields of Activity

ASELSAN is specialized in communication systems, radar and electronic warfare, electro-optics, avionics, defense systems, transportation, and energy management. The end products are usually system-level solutions such as secure communication devices, radar units, command and control systems, and electronic subsystems for vehicles and aircrafts.

1.4. Organization and Workforce

ASELSAN has several divisions that focus on different engineering areas such as communication and information technologies (HBT), radar and electronic warfare (REHIS), defense systems technologies (SST), microelectronics and electro-optics (MEOS), avionics and guidance systems (AGS) and transportation, security, energy and healthcare systems (UGES). Organization schematic of ASELSAN is given in figure-1.

- a. The company employs thousands of people, including engineers, technicians, and administrative staff.
- b. A significant portion of the employees are engineers, mostly from Electrical and Electronics, Computer, and Mechanical Engineering backgrounds.
- c. The company structure is organized in the form of divisions, departments, and groups. Each division includes multiple departments that work on specific product lines and technologies.

1.5. My Division and Team

During my internship, I was part of the Digital Design team within the microelectronics and electro-optics (MEOS) division. Our team consisted mainly of Electrical and Electronics Engineers, supported by a few technicians for practical implementation and testing. The

engineers in the group specialized in digital logic design, embedded systems, and hardware development.




Figure 1 Organization Schematics of ASELSAN. The image is from [2]

2. A BRIEF HISTORY OF THE COMPANY

ASELSAN was founded in 1975 in Ankara, Turkey, with the main purpose of reducing foreign dependency in defense electronics. The company initially focused on secure communication systems for the Turkish Armed Forces. Over time, it expanded its expertise into areas such as radar, electronic warfare, avionics, electro-optics, and transportation technologies.

In the 1980s and 1990s, ASELSAN started to grow rapidly by introducing new product lines and strengthening its research and development capacity. Establishing strong ties with universities and research institutions also played an important role in its development. In the 2000s, the company became a leader in the national defense industry and increased its international presence by exporting systems to different countries.

Today, ASELSAN is recognized as one of the most innovative and reliable technology companies in Turkey. It plays a critical role in supporting national security, while also contributing to civilian sectors such as transportation, energy, and communication. Its success is mainly based on continuous investment in research and development, highly skilled engineers, and strong cooperation with both local and global partners.

3. INTRODUCTION

I completed my summer internship at ASELSAN, one of Turkey's leading defense and technology companies. ASELSAN is well known for designing and producing advanced electronic and communication systems that are used in both defense and civil fields. My internship lasted for four weeks, covering 20 working days, and was carried out in the digital design team.

The purpose of this internship was to gain practical experience in addition to my academic knowledge in Electrical and Electronics Engineering. During this period, I had the chance to observe the workflow of professional engineers, follow technical processes, and perform tasks that supported both my technical and personal development. It was also an opportunity to see how teamwork and project organization are carried out in a large engineering company.

My main studies focused on communication protocols such as I²C, UART, and SPI, and communication standards including RS232, RS422, and RS485. I also worked with the MSP430 microcontroller, which helped me better understand embedded systems and low-power applications. In addition, I learned to use Altium Designer for schematic and PCB layout design, and I practiced reading datasheets and connecting integrated circuits to microprocessors. At the end of the internship, I prepared a presentation on digital i/o voltage level standards, covering TTL, CMOS, LVDS, LVPECL etc. technologies.

Overall, this internship provided me with valuable technical knowledge and improved my ability to apply theoretical concepts to real projects. In this report, I will first introduce the company briefly, then explain the tasks I performed and the methods I used, and finally present the results and experiences I gained from the internship.

4. DIGITAL DESIGN PROJECT

In my first project, I worked on a digital design that involved both hardware design and microcontroller integration. The project aimed to build a circuit using the MSP430 microcontroller together with several integrated circuits (ICs) that communicate through different communication protocols. The schematic design of the circuit was prepared using Altium Designer, and the corresponding layouts can be seen in Figure 2 and Figure 3.

During this project, I designed the schematic connections between the microcontroller and other ICs according to their datasheets. Each component had specific voltage levels, pin configurations, and communication interfaces that needed to be properly matched. I also paid attention to rules that I will mention later during the schematic design process.

This project allowed me to understand the practical aspects of digital circuit design and how different devices communicate within an embedded system. I also became more familiar with Altium Designer and learned how to convert theoretical circuit diagrams into professional schematic drawings.




Figure 2 Altium schematic of MSP430 and JTAG connection.




Figure 3 Altium schematic that contains ICs of the card.

4.1. MSP430

The MSP430 is a low-power 16-bit microcontroller family developed by Texas Instruments. It is widely used in embedded systems that require low energy consumption, high precision, and reliable performance. MSP430 devices are suitable for applications such as sensor systems, portable measurement devices, and industrial control systems. They combine analog and digital peripherals on a single chip, making them very efficient for mixed-signal designs.[1]

In this project, I used the MSP430F249MPMEP microcontroller. The letters and numbers in its name represent specific characteristics of the device:

- MSP430 indicates the family name, which is known for ultra-low power operation.
- F refers to the type of memory, meaning that the device includes Flash memory, which allows the program to be re-written multiple times.
- 249 identifies the specific model within the MSP430 family, defining its internal memory size, pin count, and peripheral features.
- MPMEP is a package and reliability code, describing the physical package type and extended temperature range for military or industrial-grade use.

To program and debug the microcontroller, I established a four-wire JTAG (Joint Test Action Group) connection. JTAG is a standard serial communication interface used to test, program, and debug microcontrollers and digital circuits. It allows direct access to the internal registers and memory of the device, enabling step-by-step debugging and code verification. The four

wires typically used in JTAG are TDI (Test Data In), TDO (Test Data Out), TMS (Test Mode Select), and TCK (Test Clock).

Through this setup, the MSP430F249MPMEP will be able to programmed efficiently and verify the proper operation of the designed circuit. This step helped me understand how microcontrollers are programmed at the hardware level and how debugging tools communicate with embedded systems.

4.2. Communication Protocols

4.2.1. UART

UART (Universal Asynchronous Receiver/Transmitter) is one of the most common serial communication protocols used in embedded systems. It enables two devices to exchange data serially, bit by bit, without requiring a shared clock signal. Instead, both devices agree on a baud rate, which defines how fast the bits are transmitted. The UART interface uses two main data lines: TX (Transmit) and RX (Receive). The communication is asynchronous, meaning that start and stop bits are used to mark the beginning and end of each data frame. [7]

In this project, UART communication was used to transfer data between the MSP430 microcontroller and a computer. Since most modern computers use USB ports instead of serial ports, I needed to create a USB-to-UART interface to establish the connection.

For this purpose, I used the uUSB SM47589 connector to provide the USB interface. The signals coming from the USB port were then converted to UART format using the FT232RL integrated circuit. The FT232RL is a USB-to-serial converter IC developed by FTDI. It converts USB signals (D+ and D-) into TX and RX signals that can be understood by the microcontroller. This setup allowed the MSP430 to communicate with the computer as a virtual COM port, enabling data transfer, programming, and debugging through a simple USB connection.

4.2.2. I²C

I²C (Inter-Integrated Circuit) is a two-wire serial communication protocol commonly used to connect multiple integrated circuits on the same board. It was developed by Philips and is widely preferred for short-distance communication between sensors, memory devices, and microcontrollers. The I²C protocol uses two main lines: SDA (Serial Data) and SCL (Serial Clock). These lines are shared among all devices on the bus, allowing multiple components to communicate with the same microcontroller using unique addresses. [8]

In this project, I used the TMP101 temperature sensor, which communicates through the I²C protocol. The TMP101 has an ADD0 pin that determines the address of the device on the I²C bus. By changing the logic level of this pin (for example, connecting it to GND, VCC, or leaving it floating), different addresses can be assigned to each sensor. This feature allows up to three TMP101 sensors to be connected to the same SDA and SCL pins of the microcontroller without any signal conflict.

Working with the I²C protocol helped me understand how multiple devices can share the same communication lines while maintaining individual data exchange through addressing. It also

demonstrated the importance of bus configuration and address management in complex embedded systems.

4.2.3. SPI

SPI (Serial Peripheral Interface) is a high-speed, full-duplex serial communication protocol commonly used for short-distance data exchange between a microcontroller and one or more peripheral devices such as sensors, memory chips, or displays. It operates using four main lines: MOSI (Master Out Slave In), MISO (Master In Slave Out), SCLK (Serial Clock), and SS (Slave Select).

In SPI communication, the master device (in this case, the MSP430) generates the clock signal and controls the communication, while slave devices respond based on the clock provided. The MOSI line transfers data from the master to the slave, while MISO sends data back from the slave to the master. The SS line allows the master to select which slave it wants to communicate with when multiple devices are connected on the same bus.

In my project, SPI was not used but I research about it to understand differences between protocols.

4.3. Digital Design Rules And Considerations

During my internship, there was an educational document prepared by the company for interns to guide us through the basic principles of digital design. I followed the tasks and answered the questions provided in this document. While sketching and reviewing my schematics, I also applied several design rules that I personally observed from the engineers I worked with. I received useful feedback from them during the process, which helped me better understand professional design practices. The following points summarize the important rules and observations that should be considered while performing digital design to ensure reliable and efficient circuit operation.

4.3.1. Datasheet

In digital design, datasheets are very important because they give all the key information about a component. A datasheet shows things like pin names, voltage limits, communication types, and timing details. Before connecting or using any part, checking its datasheet helps to avoid mistakes.

If we don't follow what the datasheet says, the circuit may not work correctly or some parts may even get damaged. In my project, I often used datasheets to learn how to connect pins and set the right voltage or protocol settings. Understanding datasheets is one of the most important steps to design a working and safe circuit.

4.3.2. Voltage levels

In digital design, voltage levels are very important because different devices may work with different logic voltages such as 1.8V, 3.3V, or 5V. If we connect two devices with different voltage levels directly, one of them can be damaged or the signal may not be read correctly.

To solve this problem, we use voltage level shifters. In my schematic, I used the SN74LVC2T45 level shifter. This IC can safely transfer data between two circuits that operate at different voltage levels. It supports bidirectional communication, meaning data can move in both directions. Using such components helps to ensure signal integrity and protects microcontrollers and ICs from voltage mismatches.

4.3.3. Decoupling capacitors

Decoupling capacitors are very important in digital and analog circuits. They are usually placed close to the power pins of ICs. Their main job is to filter noise and stabilize the supply voltage.

When a circuit switches quickly, it can cause small voltage drops or spikes on the power line. The decoupling capacitor provides a short burst of current during these moments, keeping the voltage stable. This helps the IC work correctly and prevents unwanted resets or malfunctions.

In short, decoupling capacitors make the power line cleaner and more stable, which is essential for reliable circuit operation.

4.3.4. Pull-up/ pull-down

Pull-up and pull-down resistors are used to define the default logic state of a signal line when no active device is driving it. Without these resistors, the input pin could “float,” meaning it might randomly read as HIGH or LOW, causing unstable or unpredictable behavior.

A pull-up resistor connects the pin to the supply voltage (V_{cc}), making the default state logic HIGH. A pull-down resistor connects the pin to ground (GND), making the default state logic LOW.

The resistor value is chosen to balance power consumption and signal reliability. If the resistor is too small, it will waste power because more current flows through it. If it is too large, the signal may respond too slowly or become noisy. Typical values are between 4.7 k Ω and 100 k Ω , depending on the circuit speed and voltage level.

In short, pull-up and pull-down resistors ensure stable logic levels and prevent floating inputs in digital circuits.

4.3.5. Transmission lines

Transmission line termination is a key concept in high-speed digital circuit design. When a digital signal travels through a PCB trace or a long wire, it can reflect back from the end of the line if the impedance of the line and the load do not match. These reflections can cause voltage overshoot, ringing, or noise, which may lead to false triggering or data errors in the system.

To avoid these problems and ensure clean signal transitions, engineers use termination techniques. The main goal of termination is to match the impedance of the transmission line to the load or source, so that the signal energy is absorbed instead of reflected.

There are five common types of terminations: Parallel, Thevenin, AC, Series, and Diode termination [9]

- Parallel termination connects a resistor directly between the signal line and ground or Vcc, providing a constant impedance.
- Thevenin termination uses two resistors as a voltage divider to create an equivalent resistance that matches the line.
- AC termination includes a capacitor in series with a resistor, reducing DC power loss.
- Series termination places a resistor in series with the source to slow down signal edges and minimize reflections.
- Diode termination uses diodes to clamp voltage spikes and protect the circuit.

In my project, I studied how these termination techniques improve signal quality and reduce noise. Some of these methods will be discussed further in the Digital I/O Voltage Level Standards section.

5. DIGITAL I/O VOLTAGE LEVEL STANDARDS

During my internship, I prepared a presentation about Digital I/O Voltage Level Standards, which play a crucial role in communication between components on an electronic board. These standards define how microprocessors, integrated circuits (ICs), and other digital devices interpret logical “1” and “0” levels. In other words, they can be considered as the languages of electronic components that enable them to communicate correctly.

An ideal I/O voltage standard should provide reliable communication, operate over a wide supply voltage range, maintain low power consumption, ensure high-speed data transfer, and remain cost-efficient. However, just like in many engineering problems, achieving all these characteristics at once is not possible—there are always trade-offs between speed, power, noise immunity, and compatibility.

In my research, I focused on four commonly used standards: TTL (Transistor-Transistor Logic), CMOS (Complementary Metal-Oxide-Semiconductor), LVDS (Low Voltage Differential Signalling), and LVPECL (Low Voltage Positive Emitter Coupled Logic). In addition to these, I also reviewed several less common standards that are used in specific applications requiring high-speed or low-noise performance.

In the following subsections, I will explain the main characteristics, advantages, and typical usage areas of these digital voltage level standards.

5.1. TTL

TTL (Transistor-Transistor Logic) is one of the oldest and most widely known digital voltage level standards. It was developed in the 1960s and is still used today in some communication interfaces such as UART, where the signal levels often follow TTL voltage ranges.

A standard TTL circuit operates with a 5V supply voltage. The logic levels are defined as follows:

- VIH (Input High Voltage): 2V (minimum recognized as logic HIGH)
- VIL (Input Low Voltage): 0.8V (maximum recognized as logic LOW)
- VOH (Output High Voltage): 2.4V (minimum output for logic HIGH)

- VOL (Output Low Voltage): 0.4V (maximum output for logic LOW)

In standard TTL, the propagation delay is around 10 ns, and the power consumption is approximately 10 mW per gate. The maximum operating speed can reach up to 10 Mbps, which was considered quite fast at the time of its development. [3]

Over time, several subtypes of TTL have been developed to improve performance in terms of speed and power efficiency:

- Low Power TTL (LPTTL): Consumes about 1 mW per gate with a 33 ns delay.
- High-Speed TTL (HSTTL): Provides faster operation with 6 ns delay but consumes 22 mW.
- Schottky TTL (STTL): Achieves a very low 3 ns delay and 19 mW consumption by using Schottky diodes to prevent transistor saturation.
- Low Power Schottky TTL (LSTTL): A balance between power and speed, with 9.5 ns delay and 2 mW power consumption.

Even though newer standards like CMOS have replaced TTL in most modern designs, TTL remains an important reference and is still used in low-speed, 5V-compatible systems due to its simplicity and robustness.

5.2. CMOS

CMOS (Complementary Metal-Oxide-Semiconductor) is one of the most common and versatile digital logic standards used in modern electronics. Unlike TTL, CMOS technology allows a wide supply voltage range, typically between 1.8V and 15V, making it suitable for various low-power and high-performance applications.

One of the main advantages of CMOS logic is its high noise margin, which provides better immunity against unwanted voltage fluctuations and interference. Compared to TTL, CMOS circuits also operate at higher speeds while consuming significantly less static power. However, the power consumption in CMOS circuits increases with frequency, since more current is drawn during switching events.

[4] CMOS voltage levels are commonly used in communication protocols such as I²C and SPI, which require reliable and low-power digital signaling. For a 5V supply voltage, the typical logic levels are:

- VIH (Input High Voltage): 3.5V
- VIL (Input Low Voltage): 1.5V
- VOH (Output High Voltage): 4.95V
- VOL (Output Low Voltage): 0.05V

These wide voltage differences between input and output states provide a much higher noise margin than TTL, making CMOS communication more stable and reliable, especially in electrically noisy environments.

Over time, several subtypes of CMOS have been developed to optimize performance for specific applications:

- LVC MOS (Low Voltage CMOS): Designed for operation at lower supply voltages such as 1.8V or 3.3V, providing reduced power consumption.
- Advanced CMOS (ACMOS): Offers improved switching speed and reduced propagation delay.
- Bipolar CMOS (BiCMOS): Combines CMOS's low power characteristics with the high speed and drive strength of bipolar transistors.
- HCMOS (High-speed CMOS): Provides higher performance and better noise immunity for high-speed applications.

Because of its flexibility, low power usage, and strong noise tolerance, CMOS has largely replaced TTL in modern digital circuit design.

5.3. LVDS

LVDS (Low Voltage Differential Signaling) is a high-speed digital signaling standard that uses differential data transmission to achieve fast and reliable communication with minimal power consumption and noise. In differential transmission, data is carried over two complementary signals, and the receiver detects the difference between them rather than the absolute voltage level. This method greatly reduces electromagnetic interference (EMI) and improves signal integrity, especially over long distances or at high frequencies.

LVDS circuits typically operate with a supply voltage between 2.4V and 3.3V, a common-mode voltage of 1.2V, and a voltage swing of around 0.4V. The drivers consume a constant current of approximately 3.5 mA, resulting in a low power consumption of around 8.75 mW per channel. Despite this low power use, LVDS supports very high data rates — up to 4 Gbps per lane, making it suitable for high-speed communication systems. [5]

Another advantage of LVDS is its simple and efficient output termination. It does not require any external DC biasing when connecting to an LVDS receiver. Typically, a single 100-ohm resistor is connected across the receiver input pins to provide impedance matching and reduce signal reflections. In some measurement setups, two 50-ohm series resistors are used instead for testing purposes. LVDS termination example is shown in figure 4.




Figure 4 LVDS termination circuit. The image is from [10]

LVDS signaling is widely used in applications that require fast and low-noise data transfer, such as Flat Panel Display Links (FPD-Link) and Gigabit Multimedia Serial Links (GMSL).

There are also several subtypes of LVDS developed for different use cases:

- Bus LVDS (BLVDS): Allows multiple receivers on the same differential pair, enabling bus-type topologies.
- SLVS (Scalable Low Voltage Signaling): Operates at even lower voltage levels (around 800 mV) for ultra-low-power applications.
- Mini-LVDS: Used mainly for short-distance, lower-speed display panel connections.

Overall, LVDS provides an excellent balance between speed, power efficiency, and signal reliability, which makes it one of the most preferred signaling standards in high-performance digital systems.

5.4. LVPECL

LVPECL (Low-Voltage Positive Emitter-Coupled Logic) is a high-speed differential signaling standard derived from ECL (Emitter-Coupled Logic) and its positive variant PECL. It is designed to operate at lower supply voltages, typically 3.3V, while maintaining the excellent speed and signal integrity characteristics of traditional ECL. [6]

Like LVDS, LVPECL uses differential pairs for data transmission, which helps reduce noise and improve timing accuracy. The common-mode voltage of LVPECL signals is approximately $V_{cc} - 2V$, and the voltage swing is around 800 mV. Thanks to its strong output drive capability, LVPECL can achieve data rates up to 10 Gbps, making it suitable for very high-speed digital communication systems.

However, LVPECL consumes more power than LVDS and has lower noise tolerance, meaning it requires careful PCB layout design and termination to maintain signal integrity. Proper termination is essential to prevent reflections and distortions in high-frequency signals.

There are several termination techniques used for LVPECL signals, including Parallel, Thevenin, Y, and AC termination. Each method is preferred for different circuit conditions or signal requirements. Among these, the Y-termination method is one of the simplest and widely used technic. It provides good impedance matching and stable biasing, as illustrated in the figure below. An example of Y-termination is given in figure 5.

LVPECL is commonly used in high-speed and precision communication systems such as Gigabit Ethernet, Fibre Channel, and Optical Communication equipment. Its ability to deliver fast edge rates and high signal integrity makes it ideal for clock distribution and other timing-critical applications, despite its higher power consumption.




Figure 5 Y-termination connection schematic. The image is from [10]

5.5. Others

Besides the commonly used voltage level standards such as TTL, CMOS, LVDS, and LVPECL, there are several other signaling standards designed for more specific or high-performance applications. These include HCSL, SSTL, and HSTL, each optimized for a different purpose in modern electronic systems.

5.5.1. HCSL (High-Speed Current Steering Logic)

HCSL is widely used for PCI Express (PCIe) reference clock and other high-speed serial interfaces. It provides low phase jitter, which is essential for maintaining timing accuracy in high-speed data communication. HCSL typically operates with a 3.3V supply and supports clock frequencies around 100 MHz. It uses current-steering drivers to achieve fast signal transitions and stable timing performance, making it ideal for high-speed clock distribution applications.

5.5.2. SSTL (Stub Series Terminated Logic)

SSTL uses a reference voltage, typically $V_{DD}/2$, and the signal swings symmetrically around this reference point. This balanced signaling method improves noise margins and reduces reflections on transmission lines. SSTL is commonly used in DDR SDRAM (Double Data Rate Synchronous DRAM) interfaces, where precise timing and stable signal levels are crucial for reliable high-speed data transfer.

5.5.3. HSTL (High-Speed Transceiver Logic)

HSTL is another high-speed signaling standard designed for inter-chip communication. It operates within a 0–1.5V signaling range, making it suitable for low-power systems. HSTL can be used in both single-ended and differential configurations, offering flexibility depending on system requirements. It supports frequencies beyond 180 MHz, which makes it ideal for high-speed data buses and advanced integrated circuit designs.

Although these standards are less common than TTL or CMOS, they are critical in high-speed and precision systems where performance, timing accuracy, and signal integrity are top priorities.

5.6. Communication Between Different Standards

In practical electronic systems, it is often necessary to establish communication between devices that operate at different voltage levels or signaling types. For example, one component may use CMOS 3.3V logic, while another operates at TTL 5V, or one may use differential signaling while the other uses single-ended signaling. To ensure proper communication between such devices, voltage level conversion is required.

The main differences that must be considered during conversion are:

- Single-ended vs. Differential signaling
- Voltage level compatibility
- Operating speed

There are several common techniques used to perform these conversions:

- Basic resistive voltage dividers: Simple and low-cost, but only suitable for low-speed and unidirectional signals.
- Dedicated level shifters or translators such as TXS0102: These integrated circuits are designed to safely convert between different logic levels while maintaining signal integrity.
- Microcontrollers or FPGAs (e.g., STM32): Some devices include multiple I/O banks that can operate at different voltage levels, allowing them to act as smart voltage translators.

To sum up, communication between different voltage level standards is possible, but it typically comes with performance limitations. The data transmission speed must be adjusted to match the lower-speed or limiting device, and even then, signal degradation, noise, or data loss may occur due to imperfect level conversion. Therefore, proper converter selection and careful design are crucial for maintaining reliable communication between systems that use different voltage standards.

6. CONCLUSION

During my internship at ASELSAN, I had the opportunity to strengthen both my technical knowledge and professional understanding of electronic system design. Throughout this internship, I worked on projects related to digital design, communication protocols (UART, I²C, SPI), and voltage level standards such as TTL, CMOS, LVDS, and LVPECL. I also studied additional standards like HCSL, SSTL, and HSTL, gaining a broader view of how modern digital communication systems operate. While working on these topics, I learned the importance of datasheets, voltage compatibility, termination techniques, decoupling capacitors, and pull-up/pull-down resistors, which are all essential in ensuring reliable and noise-free circuit operation.

In addition to technical tasks, I frequently assisted engineers in their ongoing projects and observed their workflow, which helped me understand how theoretical knowledge is applied in real industry environments. Some of the information and design details I learned are confidential, so I could not include them in this report. However, these experiences significantly contributed to my practical understanding of digital circuit design and communication systems.

My internship also provided a valuable networking opportunity. I met many engineers and managers, learned about their professional journeys, and received insightful advice about career development in the engineering field. I realized that sometimes, learning from experienced people and understanding how they approach problems can be even more valuable than performing tasks alone.

Overall, this internship was a highly educational and motivating experience for me. It helped me connect academic knowledge with real-world engineering applications, develop my technical and interpersonal skills, and gain a clearer vision for my future career in the field of electrical and electronics engineering.

7. REFERENCES

Datasheets:

[1] https://www.ti.com/lit/ds/symlink/msp430f249-ep.pdf?ts=1760179339585&ref_url=https%253A%252F%252F

Websites:

[2] *Organizational structure*. Aselsan. (n.d.).
<https://www.aselsan.com/en/about/organizational-structure>

[3] Bigelow, S. J. (2023, July 21). *Transistor-to-transistor logic (TTL)?*. TechTarget.
<https://www.techtarget.com/whatis/definition/transistor-to-transistor-logic-TTL>

[4] *Logic signal voltage levels | Logic Gates | Electronics textbook*. All About Circuits. (n.d.).
<https://www.allaboutcircuits.com/textbook/digital/chpt-3/logic-signal-voltage-levels/>

[5] Cadence PCB Solutions. (2023, November 9). *LVDS signals Crashcourse*. Cadence.
<https://resources.pcb.cadence.com/blog/2023-lvds-signals-crashcourse>

[6] *ECL vs PECL VS LVPECL: Understanding the differences*. RF Wireless World. (n.d.).
<https://www.rfwireless-world.com/terminology/ecl-vs-pecl-vs-lvpecl>

Documents:

[7] Laddha, N. R., & Thakare, A. P. (2013). A review on serial communication by UART. *International journal of advanced research in computer science and software engineering*, 3(1).

[8] Kalinsky, D., & Kalinsky, R. (2001). Introduction to I2C. *Embedded Systems Programming*, 14(8), 1101-1105.

[9] Brooks, D. (2002). Transmission Line Terminations. UltraCAD Design, Inc.

[10] Integrated Device Technology, Inc. (2012, January 31). LVPECL / LVDS Termination. California.