

SIGNALS AND SYSTEM EXP 4

4. SYSTEM ANALYSIS AND CLASSIFICATION

Experiment 4.1


Discrete -Time System

Program:

```
% Discrete-Time System
clc;
clear;
close all;
% Input sequence
n = 0:10;
x = [1 2 3 4 5 6 7 8 9 10 11];
% Discrete-Time System
y = filter([1 1],1,x);

% Display output
disp('Output Sequence:');
disp(y);
% Plotting
figure;
subplot(2,1,1);
stem(n,x,'filled');
grid on;
title('Input Sequence x(n)');
xlabel('n');
ylabel('Amplitude');
subplot(2,1,2);
stem(n,y,'filled');
grid on;
title('Output Sequence y(n)=x(n)+x(n-1)');
xlabel('n');
ylabel('Amplitude');
```

Output



Experiment 4.2

Causal/Non-Causal System

Program:

```
% Causal and Non-Causal Systems
clc;
clear;
close all;
% Input sequence
n = 0:10;
x = [1 2 3 4 5 6 7 8 9 10 11];
% Causal System:  $y(n)=x(n)+x(n-1)$ 
y_causal = filter([1 1],1,x);
% Non-Causal System:
 $y(n)=x(n)+x(n+1)$ 
y_noncausal = x + [x(2:end) 0];
% Plotting
figure;
subplot(3,1,1);
stem(n,x,'filled');
grid on;
title('Input Sequence  $x(n)$ ');
xlabel('n');
ylabel('Amplitude');
subplot(3,1,2);
stem(n,y_causal,'filled');
grid on;
title('Causal System Output  $y(n)=x(n)+x(n-1)$ ');
xlabel('n');
ylabel('Amplitude');
subplot(3,1,3);
stem(n,y_noncausal,'filled');
grid on;
title('Non-Causal System Output  $y(n)=x(n)+x(n+1)$ ');
xlabel('n');
ylabel('Amplitude');
```

Output:

