Go2 SDK Development Guide

Search article titles

About Go2
Remote Controller
SDK Concepts 3
Application Development 7
Software Interface Services 19
Motion Services Interface V2.0
DDS Services Interface
Avoidance Services Interface
VuiClient Interface
RobotStateClient Interface
Motion Switcher Service Interface
Sports Services Interface
AI motion Services interface
Basic Services Interface
LiDAR Services Interface
Multimedia Services Interface
UWB Services Interface
Fault Services Interface
SLAM and Navigation Services Interfa
Aruco Recharge Service Interface
Odometer Services Interface
D1 Mechanical Arm Services Interface
ROS2 Services Interface
Python Services Interface
Case reference 8
Debugging Specification
FAQ

Motion Switcher Service Interface

Last Updated On : 2025-11-21 11:19:44

Applicable Scope

This document's interface description is applicable to the **Go2 Edu model**.

- Should you have any other questions, you are welcome to **contact official technical support**.

Thank you for your support!

Motion Control Mode Name Description

Service Name	Motion Control Service Version
mcf	$\ge$1.1.6
ai=AI Mode, normal = Normal Mode, advanced = Advanced Mode	<1.1.6

MotionSwitcherClient Class

MotionSwitcherClient is the Client provided by the motion control switching service. Through MotionSwitcherClient, you can easily switch the Go2 motion control mode via RPC. It also provides interfaces to set or get whether Go2 is in a silent state (when Go2 is in a silent state, Go2's default motion controls are not started, and this setting remains effective after Go2 restarts).

Interface Error Code List

Error Number	Error Description	Notes
7001	Request parameter error.	Server response
7002	Switching service is busy, please try again later.	Server response
7004	Motion control mode name is not supported.	Server response
7005	Internal command execution error in motion control mode.	Server response
7006	Detection command execution error in motion control mode.	Server response
7007	Switching command execution error in motion control mode.	Server response
7008	Release command execution error in motion control mode.	Server response
7009	Custom configuration error.	Server response

Class and Interface Description

Class Name	Construction and Destruction
MotionSwitcherClient	explicit MotionSwitcherClient(); </BR> ~MotionSwitcherClient();

Function Name	CheckMode
Function Prototype	int32_t CheckMode(std::string& form, std::string& name)
Function Summary	Detects the current form and motion control mode.
Parameters	**form**: The current Go2 form. "0" for Standard Form; "1" for Wheel-Foot Form **name**: Motion control mode name. Please refer to "Motion Control Mode Name" above for details.
Return Value	Returns 0 if the call is successful, otherwise returns the relevant error code.
Notes	

Function Name	SelectMode
Function Prototype	int32_t SelectMode(const std::string& name)
Function Summary	Selects the motion control mode.
Parameters	**name**: Motion control mode name.
Return Value	Returns 0 if the call is successful, otherwise returns the relevant error code.
Notes	

Function Name	ReleaseMode
Function Prototype	int32_t ReleaseMode()
Function Summary	Releases the motion control mode.
Parameters	None
Return Value	Returns 0 if the call is successful, otherwise returns the relevant error code.
Notes	

Function Name	SetSilent
Function Prototype	int32_t SetSilent(bool silent)
Function Summary	Sets the silent state.
Parameters	**silent:** Whether to set the silent state
Return Value	Returns 0 if the call is successful, otherwise returns the relevant error code.
Notes	

This page contains content

Motion Control Mode Na...
MotionSwitcherClient Cla...
Interface Error Code List
Class and Interface Description

Helpful
Feedback

Function Name	GetSilent
Function Prototype	int32_t GetSilent(bool& silent)
Function Summary	Gets the silent setting.
Parameters	**silent:** Whether the silent state is set
Return Value	Returns 0 if the call is successful, otherwise returns the relevant error code.
Notes	

The PDF has been downloaded. Rate us: