Measure the insulation resistance between the two windings with a 500 V megger and record it in table 2, and the insulation value should be more than 1 MΩ

Testing after re-assembling

Apply good quality grease in correct quantity inside the bearing. Then assemble the motor in reverse order as dismantled. Now the air gap is measured by feeler gauge. Test run is to be done in the motor.

Result

AC three phase squirrel cage induction motor is dismantled by using proper tools. Insulation resistance is measured by megger and tabulated as above. Bearing are tested and grease is applied. Now the motor is running smoothly in good condition.

BEE_ENG_Pratical.indd 204 12/27/2019 10:54:36 AM