```
  for (int i=0; i<=150; i++) {
    analogWrite(backLight, i);
    delay(30);
  }
  for (int i=150; i>=0; i--) {
    analogWrite(backLight, i);
    delay(30);
  }
  lcd.clear();
}
```

# Source Code Summary

With that out of they way, we should have an Arduino connected to a breadboard through a slew of wires and … nothing actually happens. That is at least until we shake the thing or turn it upside down when an answer will illuminate briefly before fading away again. Now, let's see how it does that.

## Inclusions and Declarations

The first line enables the `LiquidCrystal` library that gives us some easy to use code for talking to LCDs:

```
#include <LiquidCrystal.h>
```

We'll get to libraries in more depth when we talk about `LiquidCrystal` among other hardware libraries in the next chapter. Following this line is the first of our declarations:

```
char* allAnswers[] = {
"  As I see it,  ",
"      yes       ",

"     It is      ",
"    certain     ",
.
.
.
"      Very      ",
"    doubtful    "   };
```

This page-long list of curious two-line answers is called a character array and contains all of the possible 20 answers that our Decision Machine might display. Each answer is spaced so that it will appear in the center of the LCD and some extra white space has been added to make each answer easier to read in code at the cost of extra paper. Each answer will be addressed by an index number elsewhere in our sketch. After defining our array of answers, we now need to set up the pins that we plan to use, as follows:

```
LiquidCrystal lcd(5, 6, 7, 8, 9, 10);
const int backlight = 11;
const int axisPin[] = {A0, A1, A2};
```