External sensors interfacing with Super Mini

Now let's interact with the physical world using our amazing Super Mini. First, let's have some fun with colourful LEDs creating interesting forward/backward/random movements. The code given below arranges red, yellow, green, blue, and white LEDs in a line. These light up in forward and backward motion and finally settle at a random LED light to represent the numbers 1 to 5. When more than one LED lights up it represents the number 6. In a nutshell, we are building an electronic dice game. Isn't that interesting and exciting?

```
#--- Start of chaseleds.
py ---

from machine import Pin,
soft_reset, Signal
from os import uname
from random import randint
from time import sleep

pfrm = uname()[-1].split()
[-1].replace('-','')
ahgh = True
tdly = 0.1

eleds = (
          Signal(Pin(0, Pin.
OUT), invert=not(ahgh)),
          Signal(Pin(1, Pin.
OUT), invert=not(ahgh)),
          Signal(Pin(2, Pin.
OUT), invert=not(ahgh)),
          Signal(Pin(3, Pin.
OUT), invert=not(ahgh)),
          Signal(Pin(4, Pin.
OUT), invert=not(ahgh)),
        )

def aledoff():
  eleds[0].off()
  eleds[1].off()
  eleds[2].off()
  eleds[3].off()
  eleds[4].off()

def aledon():
  eleds[0].on()
  eleds[1].on()
  eleds[2].on()
  eleds[3].on()
  eleds[4].on()

def rledon():
  eleds[0].on()
  eleds[1].off()
  eleds[2].off()
  eleds[3].off()
  eleds[4].off()

def yledon():
  eleds[0].off()
  eleds[1].on()
  eleds[2].off()
  eleds[3].off()
  eleds[4].off()

def gledon():
  eleds[0].off()
  eleds[1].off()
  eleds[2].on()
  eleds[3].off()
  eleds[4].off()

def bledon():
  eleds[0].off()
  eleds[1].off()
  eleds[2].off()
  eleds[3].on()
  eleds[4].off()

def wledon():
  eleds[0].off()
  eleds[1].off()
  eleds[2].off()
  eleds[3].off()
  eleds[4].on()

aledoff()

def chsrlinf(onet = False):
  i = 0
  try:
    while True:
      if i > 4:
        if onet:
          aledoff()
          break
        else:
          i = 0

      if i == 0:
        rledon()
      elif i == 1:
        yledon()
      elif i == 2:
        gledon()
      elif i == 3:
        bledon()
      elif i == 4:
        wledon()

      i += 1
      sleep(tdly)
  except:
    aledoff()
    if -1 == pfrm.
find('ESP32C3'):
      soft_reset()

def chsrlinb(onet = False):

  i = 0
  try:
    while True:
      if i > 4:
        if onet:
          aledoff()
          break
        else:
          i = 0

      if i == 0:
        wledon()
      elif i == 1:
        bledon()
      elif i == 2:
        gledon()
      elif i == 3:
        yledon()
      elif i == 4:
        rledon()

      i += 1
      sleep(tdly)
  except:
    aledoff()
    if -1 == pfrm.
find('ESP32C3'):
      soft_reset()

def chsrlinfb():

  try:
    while True:
      chsrlinf(True)
      sleep(tdly)
      chsrlinb(True)
  except:
    aledoff()
    if -1 == pfrm.
find('ESP32C3'):
      soft_reset()

def chsrand():


  try:
    while True:
      i = randint(0,4)

      if i == 0:
        rledon()
      elif i == 1:
        yledon()
      elif i == 2:
        gledon()
      elif i == 3:
        bledon()
      elif i == 4:
        wledon()

      sleep(tdly)
  except:
    aledoff()
    if -1 == pfrm.
find('ESP32C3'):
      soft_reset()

def randice(onet = False):

  try:
    while True:
      i = 0
      while i < 2:
```