



No LEDs

Well, this subheading is true for both the next step in the process and the lack of fancy LED lighting on the Mac mini M2. All you need to do, in order to disconnect the flex cable for the LED indicator light, is use the spudger to flip up the ZIF connector and remove the cable from the housing, where it has been held in place securely. The polyester film can then be removed to expose the power supply connector. That connector can in turn, be pulled away to disconnect the power supply of your device.



Logically important

We would not recommend tinkering much with the main/logic board of the device, but if you want to have a look at the brains of your device, you can do that! The first part to go in this process will be the speaker, held down by two T6 screws. After that, the two coax connectors for the Bluetooth antenna will need to be removed. Once they are out of the way, flip the board around and undo the ZIF connector, holding the power button. The I/O plate, once all the wires and connectors have been removed, can be undone by removing the five T6 Torx screws holding it in place. Again, flip the logic board to locate the four screws and two brackets holding the heatsink in place. And voila! You will now see the brains of your latest Mac mini M2.



Sliding away!

Once you have completed all the above steps, all you need to do now is pull out the mainboard from the aluminium housing. The main/logic board is held in place using 10 Torx T10 screws. After you have removed all the screws, you will be able to slide out the board from the housing with ease and grace.

