

LIST OF AVAILABLE ARDUINO™ BOARDS								
Arduino™ Variant	Microcontroller	Speed (MHz)	Analog In	Analog Out	Digital IO	PWM	Flash [KB]	Serial Port
Uno	ATMega328	16	6	0	14	6	32	1
Due*	AT91SAM3X8E	84	12	2	54	12	512	4
Leonardo	ATMega32u4	16	12	0	20	7	32	1
Mega 2560	ATMega2560	16	16	0	54	15	256	4
Mega ADK	ATMega2560	16	16	0	54	15	256	4
Micro	ATMega32u4	16	12	0	20	7	32	1
Nano	ATMega168 ATMega328	16	8	0	14	6	16 32	1
Arduino™BT	ATMega328	16	6	0	14	6	32	1
Fio	ATMega328P	8	8	0	14	6	32	1
Pro (168)	ATMega168	8	6	0	14	6	16	1
Pro (328)	ATMega328	16	6	0	14	6	32	1
Pro Mini	ATMega168	8	6	0	14	6	16	1
		16						
Mini	ATMega328	16	8	0	14	6	32	-
Ethernet	ATMega328	16	6	0	14	4	32	-
Esplora	ATMega32u4	16	-	-	-	-	32	-
LilyPad	ATMega168V ATMega328V	8	6	0	14	6	16	-
LilyPad USB	ATMega32u4	8	4	0	9	6	32	-
LilyPad								
Simple	ATMega328	8	4	0	9	4	32	-
LilyPad								
SimpleSnap	ATMega328	8	4	0	9	4	32	-

*The Arduino™ Due is based on a 32-bit ARM processor.

which one should you select for your project? Let's refer to the aforementioned list of devices in the table to pick one that fits our application. Many things must be kept in mind when choosing a board, such as aesthetics (especially for wearable technology). In the beginning stages of your project, however, it's always better to favour functionality over appearance, which can be concentrated on later.