

5. Run the following command to open the Arduino™ IDE:

- `./Arduino`

A PIECE OF ADVICE:

Plan ahead while selecting or changing boards. When in doubt, check the aforementioned guidelines.

Mac OS

1. To use Arduino™, Mac users must download the FTDI drivers from the FTDI website. Get it from the FTDI website: <http://dgit.in/ftdidriver>.
2. Install the FTDI drivers.
3. Download the Arduino™ IDE from <http://dgit.in/ardsoft>.
- a. The Arduino™ Yún and Arduino™ Due compatible IDE, Arduino™ 1.5.8 can be downloaded from <http://dgit.in/ardsoft> for your version of the OS.
4. Install the IDE and open it.

Sketches

A piece of code or program written in the Arduino™ IDE is called a ‘Sketch’. The name has been borrowed from Processing’s IDE – the software that inspired the Arduino™ IDE’s GUI. Also, since Arduino™ was originally aimed at designers, the name Sketch remained a natural choice among the developers.



Arduino™ Integrated Development Environment

The Arduino™ development environment is divided into the following parts, illustrated in the picture (These names are given for our convenience):

1. **Menu bar:** Contains the necessary functions and options to select the board you’re using and the port the board is connected to.
2. **Quick shortcuts:** Shortcuts (see table) are available for frequently used functions such as verifying the sketch and uploading it. Before using these options, ensure that you’ve selected the correct board from the ‘Tools’ menu.
3. **Sketch Name:** When a single project has many files, you can see each of them in tabs with the corresponding name on this bar.
4. **Sketch Editor:** All the code that’s flashed (written to the microcontroller’s EEPROM) is written in this part of the IDE.