

- `GPIO.output(4,True)`
- `time.sleep(1)`
- `GPIO.output(4,False)`
- `time.sleep(1)`

Code	Explanation
<code>import RPi.GPIO as GPIO</code> <code>import time</code>	The GPIO library allows use of GPIO pins. The Time library has the functionality of waiting for a specified amount of time.
<code>GPIO.setmode(GPIO.BCM)</code> <code>GPIO.setup(4, GPIO.OUT)</code>	Sets pin 4 on the Raspberry Pi as an output pin, since it will output a voltage that will switch the LED ON and OFF.
<code>while True:</code>	We want the LED blinking forever, so we use the 'while' loop with the condition to be 'True' – a hack used by the electronic device for running programs forever without halting.
<code>GPIO.output(4,True)</code>	This command switches ON the LED by giving a high voltage at pin 4.
<code>time.sleep(1)</code>	Waits for one second.
<code>GPIO.output(4,False)</code>	This command switches OFF the LED by giving a low voltage at pin 4.
<code>time.sleep(1)</code>	Waits for one second.

The code does the following things:

- ◆ Switches ON the LED
- ◆ Waits for 1 second
- ◆ Switches OFF the LED
- ◆ Waits for 1 second
- ◆ Repeats again from Step 1

Once the entire process is complete, the program will jump to the beginning of the 'while' loop and restarts the process from the 'GPIO.output(4,True)' command.

Code 2: This code reads the input from the switch connected at pin 22 and switches the LED ON and OFF accordingly.