

ence, our default values are `-j 4` and `-c`. The `-j 4` part means that there will be four simultaneous threads/connections. If you experience problems syncing, you can lower this to `-j 3` or `-j 2`. On the other hand, `-c` will ask repo to pull in only the current branch instead of all branches that are available on GitHub.

Prepare the device-specific code

After the source downloads, ensure you're in the root of the source code (`cd ~/android/lineage`), then type:

- `source build/envsetup.sh`
- `breakfast oneplus2`

This will download your device's device specific configuration and kernel.

IMPORTANT

Some devices require a vendor directory to be populated before breakfast will succeed. If you receive an error here about vendor makefiles, jump down to Extract proprietary blobs. The first portion of breakfast should have succeeded, and after completing you can rerun breakfast

Extract proprietary blobs

Now ensure your 2 is connected to your computer via the USB cable, with ADB and root enabled, and that you are in the `~/android/lineage/device/oneplus/oneplus2` folder. Then run the `extract-files.sh` script:

- `./extract-files.sh`

The blobs should be pulled into the `~/android/lineage/vendor/oneplus` folder. If you see "command not found" errors, adb may need to be placed in `~/bin`.

Turn on caching to speed up build

Make use of `ccache` if you want to speed up subsequent builds by running:

- `export USE_CCACHE=1`

and adding that line to your `~/bashrc` file. Then, specify the maximum amount of disk space you want `ccache` to use by typing this:

- `ccache -M 50G`

Here 50G stands for the 50GB of cache. This only needs to run once. Any option between 25GB to 100GB will result in conspicuously increased build speed. Although, if you're plan includes building your ROM for multiple