

COMPONENTS				
Symbol	Pcs	Component	Equivalent**	Emergency solution***
U1	1	MAX232	Other manufacturer's equivalent substitute (possibly all "232" chips are not equivalent with MAX232)	MAX3232, requires pull-up to pin 10, smaller capacitors and zener diode. V+ must not exceed 7 volts.
	1	16 pin IC socket		
D1,D4	2	1N5819	Any schottky diode	1N4148
D3	1	4.7V 400mW zener	Any 4,7 volt zener with higher power rating	78L05-based linear regulator circuit
C1,C2,C3	3	1μF 16V	Any 1μF capacitor with higher voltage rating	
R1	1	47 ohm		
J1	1	DB9 female	DB25 female (different pin arrangement, see chapter 2.3)	
J2	1	Phone connector		
		Copper-stripped circuit board 11 x 10 holes		

Your data on memory card is safe, but since you are backing up your phone memory, it will be safer to spend few extra minutes taking backup of your memory card as well, just in case you need it later. Also, it is recommended to delete system folders (sys, private, resource) from your memory card by connecting your phone in 'Mass Storage' mode. Though we went ahead without doing it, it may or may not cause bugs after new firmware is installed. Once you've backed up your data, you are ready to flash your phone without risk of losing it permanently.

Flashing ... 5% ... 25% ... BRICKED!!!!

If you do manage to brick your phone, don't worry get your hands on Phoenix and flash your phone while keeping in mind the following.

1. Remove the USB cable and turn your phone off. Remove and insert the battery if necessary.
2. Run Phoenix Service Software and Select "NO CONNECTION" as connection type.
3. Select "Open Product" option in "File" menu. Then select the RM-xxx number of your mobile phone.
4. Select "Firmware Update" option in "Flashing" menu. Then click on