



KNOW HOW

Jetking®
Presents



Q I run a Squid Proxy Server Version 2.6 on CentOS. In Squid, the access.log does not show the time and date like in the cache.log. Please suggest how I can configure Squid logs so that I can check the time of access also.

—Hema Singh, Ahmedabad

You can do this by changing the log format in the squid.conf. To do this, open the squid.conf in any text editor, search for the line that starts with logformat and change '%ts.%03tu' to '%tg' for GMT time. If you need local time, change it to '%tg'. The complete format is mentioned below:

```
logformat squid %ts.%03tu %6tr %>a  
%Ss/%03Hs %cst %rm %ru %un %Sh/%<A %mt
```

Change it to:

```
logformat squid %tl %6tr %>a %Ss/%03Hs  
%cst %rm %ru %un %Sh/%<A %mt
```

This is for access logs showing local time.

You can read up on the complete details about customising your logs in the squid.conf.default files.

Q I am facing a problem with one of the our Web applications.

It has been running on the LAMP stack for the past several months. After a reboot owing to a power failure, it started giving the following error: "Unable to connect to the database". After searching around a lot, I came to know that some table in the database, has been corrupted. Please help me to fix this issue using phpMyAdmin commands or any other method. I do not have the back-up of the database.

—Masoom Ali Raza, Delhi

It is clear from your report that the problem must have occurred due to the sudden reboot after the power failure. It seems the undesirable reboot rendered your database corrupt, making it inaccessible. It is a good idea to always back up your database to avoid such situations from occurring. You can try the following steps to repair the table of the database, using phpMyAdmin:

Step 1: Open phpMyAdmin and log in.
Step 2: Select the database that is to be repaired.

Step 3: After selecting the database, you can see the list of all tables on the screen. Select the table that is corrupt.

Step 4: Select 'Repair Table' from the drop down menu at the bottom of the current page.

The above steps will repair the corrupted table and let you access your Web application. However, in the future, it would be good if you remember to take the back-ups of your database at regular intervals.

Q I have been a regular reader of your magazine for the last two years. I have installed many of the distros, shipped along with the

magazine, onto my desktop. Of late, I have been using OpenSUSE for my day to day computing needs. Last month, I purchased a new Compaq Presario CQ42 laptop and installed OpenSUSE 11.2 on it. But I am not able to use it properly as the wireless function is not working on it, for some reason. Can you please help me configure the wireless feature on it?

—Dinesh Chandra, Chennai

Your laptop has a RTL8191SEvA wireless LAN device. You need to install the driver for it. Given below are the steps to do this:

1. Connect your laptop to the Internet, using a wired interface and log in as the 'root' on the terminal.
2. Add the repository as stated below:

```
#zypper ar http://download.opensuse.org/repositories/driver:/wireless/openSUSE_11.2 wireless
```

3. Get the kernel name by using the 'uname -r' command.
4. Now install the driver.

```
#zypper install rtl8192se-kmp-KNAME
```

where KNAME is the currently used kernel name.

5. After installation is complete, reboot your system.
Now, cross-check if the module for your hardware is loaded or not.

```
#lsmod | grep 8192
```

The output of the above command will confirm the status. Now, you can use the network manager or traditional method to configure your wireless network. 