

Mihalis' Cisco 877W router (cisco) Cisco Router

Host: Graph Types:

[*Edit this Host](#)
[*Create New Host](#)

Graph Templates

Graph Template Name

Create: Cisco - CPU Usage

Create:

Data Query [SNMP - Interface Statistics]

Index	Status	Description	Name (IF-MIB)	Alias (IF-MIB)	Type	Speed	High Speed	Hardware Address	IP Address
1	Down	FastEthernet0	Fast0		ethernetCsmacd(6)	100000000	100	00:10:A2:C2:65:97	
2	Up	FastEthernet1	Fast1		ethernetCsmacd(6)	100000000	100	00:10:A2:C2:65:98	
3	Down	FastEthernet2	Fast2		ethernetCsmacd(6)	100000000	100	00:10:A2:C2:65:99	
4	Down	FastEthernet3	Fast3		ethernetCsmacd(6)	100000000	100	00:10:A2:C2:65:9A	
5	Up	Dsl1Kad00	D00		ieee80211(7)	34000000	34	00:10:A2:E7:3F:80	192.168.2.1
6	Up	AT00	AT0		atds(94)	510000	1		
7	Up	Nu00	Nu0		other(1)	4294967295	10000		
8	Up	AT00-aim layer	AT00-aim layer		aim(37)	0	0		
9	Up	AT00-0-aim subif	AT00-0-aim subif		atmSubInterface(134)	510000	1		
10	Up	AT00-aal5 layer	AT00-aal5 layer		aal5(49)	0	0		
11	Up	AT00-0-aal5 layer	AT00-0-aal5 layer		aal5(49)	510000	1		
12	Up	AT00-actl	AT00-actl		actl(94)	510000	0		
13	Up	Vl001	Vl1		ethernetCsmacd(6)	100000000	100	00:10:A2:C2:65:97	192.168.1.1
14	Testing	Dn001	Dl1		ppp(23)	56000	0		97.202.33.229
15	Up	VlSub-Access1	Vl1		ppp(23)	510000	1		

Select a graph type:

Figure 3: The available Cisco 877W interfaces

is '300' seconds, with a maximum of a '300' second Cron, but 1656 seconds have passed since the last poll!

```
06/28/2012 11:56:08 AM - SYSTEM STATS: Time:0.1121
Method:cmd.php Processes:1 Threads:N/A Hosts:2
HostsPerProcess:2 DataSources:0 RRDsProcessed:0
```

- If everything is OK, *Poller* should be added to *cron* in order to run automatically. I needed to put it in the *www* user's *crontab* because, on my machine, Apache runs as a process that is owned by the *www* user. You can do it as follows:

```
$ sudo -u www crontab -e
*/5 * * * * /usr/bin/php /opt/local/share/cacti/poller.php >
/dev/null 2>&1
```

Installation is over and done with but, as you can see, the installation of Cacti is a little tricky; so you should be very careful during the process.

Configuring Cacti

Now it is time to configure Cacti. I opened the URL <http://localhost/cacti/install/index.php>. The default password is *admin/admin*. When asked, I used the following information (change the full path of your commands if needed):

```
snmpwalk path: /usr/bin/snmpwalk
snmpget path: /usr/bin/snmpget
RRDtool path: /opt/local/bin/rrdtool
PHP binary path: /usr/bin/php
```

When asked for the type of installation, select 'New Install' and click 'Next >>'. Correct the path of the RRDTool, do not change any other value, check that the PHP executable path is correct and click 'Finish'. You are now ready to use Cacti via the URL <http://localhost/cacti/index.php>. The first thing Cacti asks you to do is to change the password for the admin user. After successfully setting the new password, you will see Cacti's console tab (Figure 1).

Running Cacti

After installing and configuring Cacti, you are ready to add devices and graphs to it. Feel free to view the *cacti.log* file, which (for my installation) is located inside */opt/local/share/cacti/log* for error messages.

Monitoring a Cisco 877W router

What you need to know in advance in order to monitor your Cisco router with Cacti is the name of the SNMP community (*CactiCom*), and the hostname or the IP address of the router (*cisco*).