

```

        DelayMs(1000);

        goto known;
    }
    else
    {
        count=0;

        ConvertAndDisplay(count,"Thanks for Visit");
        DelayMs(1000);

        goto known;
    }
}

if(S1==0)
{
    while(S1==0);
    for(i=0;i<12;i++)
    {
        c[i]=0xFF;
    }

    while(RI==0);

    for(i=0;i<12;i++)
    //command to recv data
    {
        j=0;
        while(RI==0)
        {
            if(j>=1000)
                goto timeout;
            DelayMs(1);
            j++;
        }
        c[i]=SBUF;
        RI=0;
    }
    timeout:
    i=strncmp(c,d,10);
    if(result==0 && count<10)
    {
        lcdinit();

        Welcome("VERICAL1 Amount ", "Detect-ed:100");
        DelayMs(1000);
        amount2--100;
        if(amount2>0)
        {
            ConvertAndDisplay(amount2,"Balance Amount");
            dcMotor();
        }
        else
        {
            amount2=0;
            Welcome("VERICAL1 Amount ", "BALANCE NIL");
            buzzer(500);
            Welcome("Recharge Your","Card Please");
            while(rc1==1&&rc2==1)
            {
                if(rc1==0)
                {
                    while(rc1==0);
                    amount2=900;
                    Welcome("Card is recharged","with amount 900");
                }
                if(rc2==0)
                {
                    while(rc2==0);
                    amount2=500;
                    Welcome("Card is recharged","with amount 500");
                }
            }
        }
        if(amount2==400)
        {
            Welcome("VERICAL1 Amount ", "BALANCE LOW");
            buzzer(200);
        }
    }
}

DelayMs(1000);
count++;
lcdcmd(0x01);
DelayMs(10);
ConvertAndDisplay(count,"Number of Cars");
goto known;
}
else
{
    Welcome("Parking is Full","Sorry for Inconvenience");
    buzzer(500);
    DelayMs(1000);
    goto known;
}
}
}

void Welcome(unsigned char c[], unsigned char d[])
{
    unsigned int i=0;

    lcdcmd(0x01);
    DelayMs(10);
    lcdcmd(0x80);
    DelayMs(10);

    i=0;
    while(c[i]!='\0')
    {
        lcdData(c[i]);
        i++;
    }

    lcdcmd(0xc0);
    DelayMs(10);

    i=0;
    while(d[i]!='\0')
    {
        lcdData(d[i]);
        i++;
    }
}

void ConvertAndDisplay(unsigned int value, unsigned char c[])
{
    unsigned int i,a=0,j;
    unsigned char d1,d2,d3;
    for(i=0;i<value;i++)
    {
        a++;
        lcdcmd(0x01);
        DelayMs(10);
        lcdcmd(0x80);
        DelayMs(10);
    }

    j=0;
    while(c[j]!='\0')
    {
        lcdData(c[j]);
        j++;
    }
    d1=a/10; //digits before desible point
    a=a/10;
    d2=a/10;
    a=a/10;
    d3=a/10;

    lcdcmd(0xc0);
    DelayMs(10);
    display(d1,d2,d3);
}

//-----
// Lcd initialization subroutine
//-----
void lcdinit(void)
{
    lcdcmd(0x38);
    DelayMs(250);
    lcdcmd(0x0E);
    DelayMs(250);
    lcdcmd(0x01);
    DelayMs(250);
    lcdcmd(0x06);
    DelayMs(250);

    lcdcmd(0x80);
    DelayMs(250);
}

//-----
// Lcd data display
//-----
void lcdData(unsigned char l)
{
    P2=1;
    RS=1;
    EN=1;
    DelayMs(1);
    EN=0;
    return;
}

//-----
// Lcd command
//-----
void lcdcmd(unsigned char k)
{
    P2=k;
    RS=0;
    EN=1;
    DelayMs(1);
    EN=0;
    return;
}

//-----
// Delay mS function
//-----
void DelayMs(unsigned int count)
{
    // mSec Delay 11.0592 Mhz
    unsigned int i; // Keil v7.5a
    while(count)
    {
        i = 115;
        exact value
        while(i>0)
        {
            i--;
            count--;
        }
    }
}

void dcMotor()
{
    START_POINT=1;
    TERMINATE_POINT=0;
    DelayMs(400);
    START_POINT=0;
    TERMINATE_POINT=0;
    DelayMs(2000);
    START_POINT=0;
    TERMINATE_POINT=1;
    DelayMs(400);
    START_POINT=0;
    TERMINATE_POINT=0;
}

void display(unsigned char s,t,u)
{
    a=s*0x30; // convert each digit to equivalent ASCII value
    t=t*0x30;
    u=u*0x30;

    //Move the cursor to position 5 on LCD
    DelayMs(50);

    lcdData(u);
    Display the digits one by one on LCD
    DelayMs(50);
    lcdData(t);
    DelayMs(50);
    lcdData(s);
    DelayMs(50);
}

void buzzer(unsigned int time)
{
    BUZZPORT=1;
    DelayMs(time);
    BUZZPORT=0;
}

```